Go to www.vtechphones.com to register your product for enhanced warranty support and the latest VTech product news.

vtech

Quick start quide

VM5263 VM5263-2

Full Color Pan and Tilt Video Monitor









requency control





Parent unit power adapter: Output: 5V DC ⊚ 1A

ower requirements	Parent unit: 3.8V Li-lon battery
effective range	Maximum power allowed by FCC and IC. Actual operating range may vary according to environmental conditions at the time of use.
d:	S" Color LCD (WGVGA 480x272 pixel)
sjauueu	32
4	Parent unit: 2405 - 2475 MHz

TECHNICAL SPECIFICATIONS

Press @ to zoom in or out.

IMPORTANT SAFFTY INSTRUCTIONS

- hen using your equipment, basic safety precautions ould always be followed to reduce the risk of fire, eleo ock and injury, including the following: Follow all warnings and instructions marked on the
- Adult setup is required.

 CAUTION: Do not install the baby unit at a height above
- Z meters.
 This product is intended as an aid. It is not a substitute for proposition and propose adult rupposition and should not be
- responsible and proper adult supervision and should used as such. This product is not intended for use as a medical

Power adapter inf VTech Telecommunicati Model: VTDSFLISDS100

unit output: 5V DC 1A.

- Model: VTUstuscus.

 A III Rechargeable battery inform Li-ion battery, 3.8V2100mAh Zhongshan Tianmao Battery Co., Ltd. Model Number: 8P1763
- Model Number: 8P1763 The power adapters are intended to be correctly oriente in a vertical or floor mount position. The prongs are not designed to hold the plug in place if it is plugged into a ceiling unfor-the-table or calingt outlet.

- Do not allow anything to rest on the power cords. Do not install this product where the cords may be walked on or
- crimped.

 This product should be operated only from the type of power source indicated on the marking label. If you are not sure of the type of power supply in your home, consult your dealer or local power company.

 Do not exclude your dealer or local power company.

- on the united of thronic varies on two components.

 There is a very low tax of privacy (case when using certain electronic devices, such as tably monitors, condess privacy (case the condess of the cond

SAVE THESE INSTRUCTIONS


Precautions for users of implanted cardiac pacemakers Cardiac pacemakers (applies only to digital cordiess devi-Wireless Technology Research, LLC (WTR), an independe research entity. Jed a multidisciplinary evaluation of the

maker patients nould keep wireless devices at least six inches from the

Electromagnetic fields (FMF)

his VTech product complies with all standards regarding electromagnetic fields (EMF). If handled properly and according to the instructions in this user's manual, the pro-

WHAT'S IN THE BOX




CONNECT THE BABY MONITOR


- The rechargeable battery in the parent unit is built-in Use only the power adapters supplied with this product
- Make sure the baby monitor is not connected to a switch-controlled electric outlet.
- Connect the power adapters in a vertical or floor mount position only. The adapters' prongs are not designed to hold the weight of baby monitor, so do not connect them to any ceiling, under-the-lable, or cabined outlets. Otherwise, the adapters may not prosperly connect to the outlets.
- Make sure the parent unit, the baby units and the power adapter cords are out of reach of children



Power on or off the baby monitor



POSITIONING THE BABY MONITOR



4 STATUS CHECK

baby unit and parent unit, your parent unit displays image from the baby unit, and the LINK LED light turns on.

The ON LED light of baby unit turns on.





BASIC OPERATION - PARENT UNIT

Crystal controlled PLL synthesizer

Adjust speaker volume

Press ● vol. / vol. ● to adjust your parent unit



Talk to your baby unit Press and hold TALK and speak to your

parent unit. Your voice is transmitted to the baby unit. Release TALK when finish talking and hear your baby again



Turn off the screen Press and hold LCD ON/OFF to switch off

the screen. You can still hear sound from the




· Press any keys on the parent unit to turn on

Use the menu


Press METALET to enter the menu, choose a menu item, or save a setting. You can use the parent unit for advanced settings or operations, such as to play or stop the baby unit lullaby, or to adjust the baby



- Press MENU to select an item, or to save a setting. Press ∧ or ∨ to scroll among the sub-menus,
- without changing the current setting.
- Press ①, /EXIT to return to live video.




OVERVIEW - PARENT UNIT



- LCD display Microphone
- POWER
- TALK
- Arrow keys
- 8 Volume •
- O VIEW /I CD ON/OEE

- 11 Antenna 12 RESET 13 Stand 14 Power lack

Overview - Baby unit




8 - O Night light on/off key

10 Slots for wall mounting

0 Poweriack

- Camera lens
- Microphone
- Night light
- On/Off switch 6 On/Off LED light
- On when the baby unit is turned on and is paired to the parent unit.
- Flashes when the baby unit is not being viewed; or when the link to the parent unit is lost.
- NEED HELP?





Scan the QR code on the right. Launch the camera app or QR code scanne app on your smarrphone or tablet. Hold the device's camera up to the QR code and frame it. Tap the notification to trigger the redirection of the

 If the QR code is not clearly displayed, adjust your camera's focus by moving your device closer or further away until it is clear. You can also call our Customer Support at 1 (800) 595-9511 [in US] or 1 (800) 267-7377 [in Canadal for help.

VM5263

VM5263-2

PARENT UNIT ICONS

Main menu icons

Main Sub-menu Adjust the parent unit's LCD brightness. -**D**-

Camera setting **Q Q**₁₁|

Monitoring mode (For VM5263-2 only)

Split mode

Lullaby J









Baby unit speaker volume Adjust the baby unit's speake

• Patrol mode

 \approx

≋1 ≋2 ≋3 ≋4

11 11 2 11 3 11 4 11 5

60min 45min 30min 15min Set timer to stop playing the selected melody or soothing sound.

Main Sub-menu menu Night light ON/OFF Turn on/off night light

\$\\ \partial 1 \\ \partial 2 \\ \partial 3 \\ \partial 4 \\ \partial 5 \\ \partial 6 \\ \partial 7 Select one of the night light colors. Change to all seven colors in cycles.

60min 30min 15min

Set timer to turn the night light off. Select to set the night light to always on.

AUTO
Set to auto turn on the night light when baby unit detects sound. It will turn off after 15 minutes of no sound detection. You can set VOX sensitivity level to detect sounds that exceed certain levels. See Sound sensitivity and sound activation section.

ON/OFF Turn on/off the adaptive night light feature. When this feature is on, the teature. When this teature is on, the baby unit detects the ambience light. If the room is bright, the night light adjusts itself to be brighter; if the room is dim, the night light adjusts itself to be less bright.

Temperature

Turn on/off temperature alert tone Set the parent unit to beeps whene the room temperature detected by the baby unit falls outside of the set

· Set the maximum temperature.

Set temperature display in Fahrenheit (°F) or Celsius (°C)

Main Sub-menu menu Alort topor Set the parent unit to beep when the battery is low (!/

- Set the parent unit to beep when the link between the parent unit and the baby unit is lost
- Set the confirmation tone on or off wher selecting an option in the menus.
- Set the parent unit to beep when the baby unit detects sounds while in Split mode (For VM5263-2 only).

Sound activation - screen and audio

ON/OFF Turn on/off sound activation Set sound activation on or off.

When it is on, and the baby unit detects no sound, the parent unit screen stays of

no sound, me parent unit screen says on to save power. Once a sound is detected, the parent unit screen and speaker turns on automatically, and you can see and hear your baby. The parent unit will then turn off again after 50 seconds of no sound detection.

 Nore
 When the parent unit screen is off and it receives alerts, for example, link lost between parent unit and baby unit, or battery is low, the parent unit screen and speaker will turn on for 10 seconds. VOX (Voice Activated Alert) Sensitivity







(V)

PARENT UNIT ICONS (CONT'D)

Status icons Connection status

- Till Strong signal strength. Til - Moderate signal
- strength. Ti - Low signal strength
- T Weak signal strength.





("For VM5263-2 only) Current view status

- . The haby unit number that is
- Single CAM mode Patrol mode (*For VM5263-2 only)
- (*For VM5263-2 only)





 \blacksquare

옏

Q1 or

<u>@</u>2

(

П

Lullaby - On



Night light - Auto-on Color icon indicates the night light is set to auto-on, and is currently turned on by sound activation. Gray icon indicates the night

light is currently off but is set to auto-on. Night light will turn on when sound is detected by the haby uni

Status icons

°F or °C Real-time temperature Real-time temperature Real-time temperature detected by the baby unit in Fahrenheit (°F) or Celsius (°C) (e.g. 57 °F or 14 °C).

- Temperature alert tone On
- 9-level sound indicator
 - indicates low sound level detected by the baby unit.

 - indicates high sound level detected by the baby unit.

 - Mute alert

 Displays when the parent unit speaker volume is set to off.

 Displays when the parent unit is talking to the baby unit.
 - Battery status
 - . > animates when the battery is charging. - battery is fully charged
 - battery is low and

Alert icons

1.4 Displays when parent unit's battery is low and needs charging.



A

A

- Displays when connection between parent unit and baby unit is lost.
- Displays when sound is detected at a baby unit when in Split view. (*For VM5263-2 only)
- Raby unit detects temperature reaches or exceeds the set maximum.

Baby unit detects temperature is at or is lower than the set minimum.

Sound sensitivity and sound activation

Adjust sound detection sensitivity You can turn on Sound activation and adjust


the VOX sensitivity to detect sounds and turn on the parent unit while its screen is switched off or dimmed

When the baby unit detects sounds that screen will turn on and the baby unit starts transmitting the sounds to the parent unit, and you can see and hear your baby. If you nave turned on the Night light Auto-on feature, it will turn on automatically to sooth

If you turn off Sound activation, you will be a sounds from the baby unit all the time, even when the parent unit screen is switched off.

NIGHT VISION

If you have turned on sound alert, the parent unit beeps when the baby unit detect sour while in **Split** mode ("For **VM5263-2** only).



Sound activated screen and audio

When Sound activation is on, the parent unit screen stays off to save power when the baby unit detects no sound. Once the baby unit detects sounds that are louder than the chosen sound sensitivity level, the parent unit screen and speaker turn on automatically. The parent unit will then turn off again after 50 seconds of no sound detection. MNOTE

If you have muted the parent unit speaker, only the parent unit









allow you to see your baby clearly at night or in a dark room. When the baby unit being viewed detects low light levels, the infrared LEDs are switched on automatically. The images from the baby unit are in black and white, and appears on the screen.

Notes It is normal if you see a short white glare or

- your parent unit screen as the baby unit is adapting to the dark environment. When the infrared LEDs are on, the images are in black and white. This is normal.
- Depending on the surroundings and othe
- interfering factors, like lightings, objects, colors and backgrounds, the video quality may vary. Adjust the baby unit's angle or place the baby unit at a higher level to prevent glare and blurry display

DIM MODE

The parent unit display will dim to conserve energy after 10 minutes of inactivity, in which there is neither key pressed nor alert received from the baby unit









- If you power on only one baby unit, you may see the parent unit displaying $\overline{\mathbb{X}}$ and then $\ref{initial}$, and

Press VIEW in Single CAM or Patrol mode to switch to the baby unit you have powered on

Change different views - Single CAM





Change different views - Patrol

For VM5263-2 ONLY

Status check - Two baby units

If you are viewing baby unit 2, the

turns on. As baby unit 2 is not being

POWER LED light of baby unit @ A

viewed, its POWER LED light flashes.

the LINK LED light flashing.

of baby units 🔯 🌡

Notes



Select **Patrol** as your monitoring mode to atternately view the image from baby units



Change different views - Split





MOUNT THE BABY UNIT ON DRY WALL (OPTIONAL)

□Notes

- Check for reception strength and camera angle before drilling the holes
- The types of screws and anchors you need depend on the composition of the wall. You may need to purchase screws and anchors separately to moun vour camera units.

3. Align the wall mount bracket and screws with

the holes in the wall as shown. Tighten the screv

in the middle hole first, so that the wall mount

bracket position is fixed. You can tighten the other screw in the top hole.

4. Place the camera unit on the wall mount

bracket, and then slide it forward until it locks into place. Connect the power

adapter to the camera unit and a power

supply not controlled by a wall switch

1. Place the wall mount bracket on a wall and then use a pencil to mark two holes in parallel. Remove the wall mount bracket and drill two holes in the wall (7/32 inch drill bit).



OR


- 2. If you drill the holes into a stud, go to step 3.
- If you drill the holes into an object other than a stud. insert the wall anchors into the holes Tap gently on the ends with a hammer until the wall anchors are flush with the wall.



3 Insert the screws into the holes and tighten the screws until only 1/4 inch of the screws are exposed.



4. Place the camera unit on the wall mount bracket, and then slide it forward until it locks into place. Align the holes on the wall mount bracke with the screws on the wall, and slide the wall mount bracket down until it



5. You can maximize your camera unit's viewing angles by tilting the wall mount bracket. Hold the camera unit, and then rotate the knob in anticlockwise direction. This will loosen the joint of the wall mount bracket. Tilt your camera unit up or down to adjust to your preferred angle. Then, rotate the knob in clockwise direction to tighten the



THE RBRC SEAL

participating in an industry program to collect and recycle thes when taken out of service within the United States and Canada.

when taken out of service within the United States and Canada.

The program provides a convenient alternative to placing used lithium-inor batteries into the trash or
municipal waste, which may be illegal in your area.

Is participation makes it says for you to drop of the speen battery at local retailers participating in the program
rised Viled products revice content. Please call 1609/9 BATTERY for information on illihum-in-oblattery recyclematics.

When the product is the product in the program is part of the commitment to protect
movement and convenienting instant resource. Novement in this programs part of the commitment to protect
movement and convenienting instant resource.

The RBRC Seal and 1 (800) 8 BATTERY® are registered trademarks of Cali2recycle, In

FCC AND IC REGULATIONS

FCC Part 1S

This equipment has been tested and found to comply with the requirements for a Class 8 digital device under Part 1S of the sequence of the communications (Commission) (FCC) rules. These requirements are intended to provide reasonable protection against a result and intendence in a continual relations to the sequence repeated in the provide reasonable protection against and intendence of the sequence repeated in the sequence of the sequence repeated by the sequence of the seque

**Vocable in the cases or adjustment of the capture of the capture

indesired operation.

o muse safety of users, the FCC has established criteria for the amount of radio frequency energy that can be safely abox by a user or bystander according to the intended usage of the product. This product has been tested and found to compile here or the product has been tested and found to compile here or the product has been tested and found to compile here or the product has been tested and found to compile here or the product has been the product and a distance and a distance are of the product and that but he held at least 1 in (2.5 only from y and a distance are the product and that but held at least 1 in (2.5 only from y and a distance are the product and that but held at least 1 in (2.5 only from y and a distance are the product and that but held at least 1 in (2.5 only from y and a distance are the product and that but held at least 1 in (2.5 only from y and a distance are the product a

This Class B digital apparatus complies with Canadian requirement: CAN ICFS-3 (RI/NMR-3/R)

Industry Canada

device.

The term "IC." before the certification/registration number only signifies that the Industry Canada technical specifications were

RE radiation exposure statement

Nr Fadamon exposure statement. The baby unit of the baby

CALIFORNIA ENERGY COMMISSION BATTERY CHARGING TESTING MODE

This baby monitor meets the California Energy Commission (CEC) regulations for energy consumption. Your baby monitor is set up to comply with the energy conserving standard: right out of the box. Follow the instructions to institlal and charge the battery. The CEC battery charging testing mode is activated while charging. Even if the parent unit is paired to baby units, the CEC battery charging reting mode is activated while it is prevened of and charged on the charge of th

FOR CETL COMPLIANCE ONLY

Mesures de sécurité importantes La plaque signalétique appliquée est située au bas du socie de l'unité du bébé. suivent :
Observez toutes les instructions et mises en garde inscrites sur l'appareil.

- rappareil. L'installation par un adulte est requise. MISE EN GARDE: N'installez pas l'unité du bébé à une hauteur
- supernoure a z metres.

 Ce produit a été conçu pour être un dispositif d'appoint
 seulement a li n'est pas le remplacement d'une supervision
 responsable et adéquate par un adulte et ne devrait pas être
- utilisé comme talle. Ce produit n'est pas conçu pour être utilisé en tant que moniteur médical.
- The process of the Borrous pools are unions with Stiff questions. Writilises pass cell apparell period of Foxus in die topic autre source of humidistit, par eximple, prês d'une balagoniez et al sexteu, évire de cuisine, dans un sous-sol humidis ni prês d'une pischne, dans un soussol humidis ni prês d'une pischne, dans un soussol humidis ou une douché. Se pour qu'il yet un risque d'orgonolom à un maurais type de pile est utilisé pour l'unifie du parent. La pile ne pole pas d'est soumies à des temperatures avoirmes et la pile ne pole pas d'est soumies à des temperatures eximènes et la topo expect of titles good Praint de parent. It gibb e es basis errocción melhorique a hauta dilliga paredar i praint de la companio de la companio de la companio de plas datas i les jos delar su finor rivale, ou en decarant ou periodos. Laster si les es un en enricon entral si empleada-portifica de la companio de la companio de la companio de entrale del la companio del la companio del la companio del participa del la companio del la la companio del la companio del la companio del la companio del la la companio del la

mettric votre sicurité en péril.

L'aliant les adaptateurs électriques
Adaptateur de l'unité du parent : Sortie : 5V CC 1A
Vicch felecommunications Ltd.
Modéle : VIDES USSUIO
Adaptateur de l'unité du bébé : Sortie : 5V CC 1A
Vicch felecommunications Ltd.

Adaptateur de l'unité du bébé : Sortie : 5V CC 1A
Vicch felecommunications Ltd.

VTech Tolecommunications Ltd.
Modele: VTOSEUSOSIOD

Lilon battery, 3.8V 2100mAh
Zhongdhan Tianmao Battery Co., Ltd.
Modell Numbers: 892763

- Pour les PRODUITS à BRANCHER À UNE PRISE DE CLUISSE by prise de courant doit être installée prés du produit, afin d'assurer une accessibilité sécuritaire à la prisé de courant. Débranchez ce produit de la prise de courant avent de procéder au notioyage, N'utilisse pas de nettoyants en aérosisi. Utilise un chiffrie humide pour le nettoyants en aérosisi. Utilise un chiffrie humide pour le nettoyants en aérosisi. Utilise un chiffrie humide pour le nettoyant. Na coupaz pas les cordone d'alimentation pour reimplace.
- Out from findjale is excused in a containt of animalities. We failed from findjale failed from cere dispagnished. Si your find confidence for a findjale failed from findjale failed from findjale failed from findjaled from findjaled
- support de montrage in table chancelaris. Les trous et ouvertures du boîtier, situés à l'arrière de l'appareil ou sous celui-ci, servent à aèrer l'appareil. Pour l'empêcher de surchauffer, ne bloques sous aucun prétente ces ouvertures et n'empéchez pas l'aération adéquate de l'appareil en le plaçant sur un lit, divan, tapis ou toute autre surface si De même, ne le positionnez pas à proximité ni au-de

pair l'appareil dans un endroit avant de vous assurer qu'il y alt lune bohne circulation d'air.

N'anfonces pinnai d'objets à travers les ouvertures de cet appareil, car ils pourraisent entirer en contact avec des points de lemsion disappreus ou causer des courts-circult qui pouvent dépénders en incondes ou en réquise criter qui pouvent dépénders en incondes ou en réquise produit. Une leménde paine de liquide étaire de produit.

- - que contient cet appareil, à l'exception de l'accès autorisé à certaines portes ou ouvertures, risque de vous exposer à des points de tension dangereux ou d'autres dangèrs. Un remontage incorrect peut par la suite présenter des risque
- l'appareil en fonction. Examinez les composantes afin de vérifier si celles-ci ne sont pas endommagées. Il existe un très faible risque de perte de confidentialité
 - avec certains appareits électroniques (autres écoute-bébés, téléphones sans fils etc.). Pour l'éviter, s'assurer que le produ r's jamais été utilisé avant l'achat, réinitialiser l'unité de façon périodique, ételindre l'écoute-bébé quand il n'est pas en pour d'utilitation.
- 20. Les enfinite dornalent être supervists afin de vous assurer qui fin ne jouent pas avec l'appareil.

 qu'ils ne present pas avec l'appareil.

 qu'ils ne present pas avec l'appareil privipèque, se nendrailes commandes.

 qu'ils ne propriété pas avec l'appareil pas avec l'appareil pas avec l'appareil pas une personne responsable de laur sécurité, conserve L'appareil par une personne responsable de laur sécurité, conserve L'appareil par une personne responsable de laur sécurité, avec l'appareil par une personne responsable de laur sécurité, avec l'appareil par une personne responsable de laur sécurité.

Miss en garde
1. Utilize et entreposez le pecdud à run et température entre 0 ° C (32° f) et 40° C (104° f).
2. You et 40° C (104° f).
2. Hong et 40° C (104° f).
3. You et 40° C (104° f).
4. Hong et 40° C (104° f).
5. Hong et 40° C (104 pas près d'une source de chauffage. Le bloc-piles ne doit pas être exposé à la chaleur excessive telle que la lumière du soleil ou au feu.

 A. List Avertissement - Risque de strangulation - Les enfants se sont ÉTRANGLÉS dans des cordons. Gardez ce cordon hars de portée des enfants la plus de 0,9 ml. N'enfevez pas cotte étiquette.

Ne jamais placer le moniteur à l'intérieur du berceau ou cluper autre placer le moniteur à l'intérieur du berceau ou cluper autre de la comment de la comm

fil. Stimulateurs cardiaques implantés dans l'organisme Les simulateurs cardiaques (ne s'applique qu'aux dispositifs numériques sans fil): numentation sains in): L'organisme Wireless Technology Research, LLC (WTR), une firme de recherche indépendante, a mené une évaluation pluridisciplinaire des interférences entre les téléphones sans fil

qui unissent asposints sans fra a proximite du ceux-ci.

Champa (électromagnéfiques (EMF)

Co produit de VTech est conforme à toutes les normes se
rapportant aux champs dilectromen à froutes (EMP) standard. Si voi

le manipulez correctiment en suivant les instructions de ce guide,

son utilisation ser sécuritaire pendant de nombreuses années,

solon les meilleures évidences scientifiques dont nous disposons

aulourd'hui.

LIMITED WARRANTY

holder of a valid proof of purchase ("Consumer" or "you" that the Product and all accessories provided in the sales that the Product and all accessories provided in the sale package ("Product") are free from defects in material and workmanship, pursuant to the following terms and conditions, when installed and used normally and in

concurions, when installed and used normally and in accordance with the Product operating instructions. This limited warranty extends only to the Consumer for Productions and used in the United States of America and Canada. What will VTech do if the Product is not free from defects

1 800) 3x3-777.

MOTE Before calling for service, please review the user's manual - a check of the Product's controls and features may reput service a check of the Product's controls and features may reput as service a graphical less vary, summar the or risk of loss or changing change of the product under the proposable for clearing service or harding change is control in the expensible for self-under or harding change is control in the will than repaired or replaced Product under this limited will reput the control of the change of the control of the change of the control of the change of the control of the similar of the limited will reput to produce of the change of the change

description of the maturation or amiculity; and 2. Include a "valid proof of purchase" (sales receipt) identifying the Product purchased (Product model) and the date of purchase or receipt; and 3. Provide your name, complete and correct mailing address, and telephone number.

Other limitations
This warranty is the complete and exclusive agreement between you and Virech. It apperades all other written or concurrent existed to the first bound. Virech provide or communications related to the first bound. Virech providely describes all of Virech's responsibilities regarding the product. These are on other express warrante. No one is authorised to make modifications to this limited warranty and you should not lay on any such modification. State Provincia. State Provincia. You may such a work on any such and collection. State Provincia. You may such or such as the such as the such as the province to province to province to province to province.

What is not covered by this limited warrantly?

It is limited warrantly boto and covere:

I. Product that has been subjected on misses, accident, happings or other played damage, improper traditation, files, water or other liquid intrinsion, or illustrations, files, water or other liquid intrinsion; or illustration, files, water or other liquid intrinsion; or modification by simple enhanced the manufacture or modification by simple enhanced them as suchostical or modification by simple enhanced them as suchostical Product in the section that the problem engineerized is caused by signal conditions, network reliability, or cable or interest spikence. antenna systems, or
A Product to the extent that the problem is caused by use
with non-VTech accessories, or
Product whose warranhy-(quality stickers, product serial
number plates or electronic serial numbers have been
removed, altered or rendered ellegible; or
A Product purchased, used, serviced, or shipped for repair
from outside the United States of America or Canada, or used for commercial or institutional purposes (including but not limited to Products used for rental purposes); or

Please retain your original sales receipt as proof

what will vect do in the Floduc is not nee in didects in materials and workmanship during the limited warranty period ("Materially Defective Product")? During the limited warranty period, VTech's authorized service representative will repair or replace at VTech's option,

service expresentative will repair or replace at VIEdr5 option without change, a Materially Defective Product. If we repair the Product, we may use now or refurbished replacement parts. If we choose to replace the Product, we may replace parts. If we choose to replace the Product, we may replace parts. If we choose to replace the Product, we may replace similar design. We will retain defective parts, modules, or equipment. Repair or replacement of the Product, at VIEdr5 option, is your exclusive remedy. VIEdrs will return the repaired or replacement Products by you in working condition. You should require the repair or replacement to the approximation of the product of the option of the product of the

How long is the limited warranty period? The limited warranty period for the Product extends for ONE (1) YEAR from the date of purchase. If VTech repairs or replaces a Materially Defective Product under the terms of

What is not covered by this limited warranty?

What does this limited warranty cover? How do you get warranty service? ufacturer of this VTech Product warrants to th To obtain warranty service in the USA, please visit our website at www.vtechphones.com or call 1 (800) 595-9511. In Canada, go to www.vtechcanada.com or call 1 (800) 267-7377.

What must you return with the Product to get warranty service?

Return the entire original package and contents includ the Product to the VTech service location along with a description of the malfunction or difficulty; and

Other limitations