

NOTICE OF COMPLETION

2021-02-24



Ms. Aranjit Sangha
ENPHASE ENERGY INC
1420 N McDowell Blvd
Petaluma, CA, 94954-6515, US

Our Reference: File E341165, Vol 7

Order: 13616861
Project: 4789745763

Your Reference: Ensemble 1.0 UL 1741 CRD on PCS
Project Scope: Evaluation of Enphase Ensemble for Power Control System functionality.

Dear Ms. Sangha

Congratulations! UL's investigation of your product has been completed under the above Reference Number and the product was determined to comply with the applicable requirements of the UL 1741 CRD on Power Control Systems, issued on March 8, 2019, including working draft revisions to UL 1741 which specifically address the management, control and limitation of power exchange between Energy Storage Systems and AC utility systems. The PCS evaluation was conducted on a representative Enphase Ensemble System and the certification applies to the following products which were part of the tested system:

ESS operating modes: Import Only

UL (Listed), Enphase IQ7 series micro-inverters

- Models IQ7-60, IQ7PLUS-72, IQ7X-96, IQ7XS-96, may be f/b -2, -5 or -E, may be f/b -ACM, f/b -US, may be f/b -NM, may be f/b -RMA, may be f/b -&, where "&" designates additional characters.
- Models IQ7A, may be f/b S, may be f/b -66 or -72, may be f/b -2, -5, or -E, may be f/b -ACM, f/b -US, may be f/b -NM, may be f/b -RMA, may be f/b -&, where "&" designates additional characters.
- Model IQ7PD-72-2-US, may be f/b -&, where "&" designates additional characters.
- Model IQ7PD-84-2-US may be f/b -&, where "&" designates additional characters.

UL (Listed), Enphase Encharge Battery system

- Model numbers: ENCHARGE-3-1P-NA, ENCHARGE-3T-1P-NA , ENCHARGE-10T-1P-NA and ENCHARGE-10-1P-NA

When used in combination with the following accessories:

- UL (Listed), Enphase Enpower smart switch, model number: EP200G101-M240US00, and
- UL (Listed), Enphase Envoy communications gateway, model numbers: ENV-IQ-AM3-3P, ENV-IQ-AM1-240, ENV-S-AM1-120, X-IQ-AM1-240-3C, X-IQ-AM1-240-3, X-IQ-AM1-240-3-ES, X-IQ-AM1-240-3C-ES, X-IQ-AM1-240-2, X-IQ-AM1-240-B, , XAM1-120-B, or XAM1-120
- UL (Listed), Current Transformers, Enphase Model CT-200-SPLIT (Needs 2 units)
- UL (Listed), Current Transformers, Enphase Model CT-200-SOLID (Included with Envoy)

NOTICE OF COMPLETION

2021-02-24



The completed system was evaluated for its' ability to control export levels to the AC line (grid connection) when connected to all the above sources. The export current settings for the system are adjustable and range from 0 Amps to 64 Amps (0 Watts to 15,360 Watts @ 240 Vac).

Export levels and power output from the energy storage sub-system and PV were monitored to verify that when system load levels or available power from the PV source were subjected to step changes in levels, the ESS and PV output levels were adjusted by the control system to ensure that the output to the AC line (grid connection) returned to it's pre-set level and that at steady state levels, power output from the PV source was the principal source of export power to the AC utility system.

Maximum (Peak) Overshoot (Combined PV/ESS)	Steady state value at set level		
	100%	50%	0%
31,150 Watts	15,182 Watts	7659 Watts	110 Watts

The maximum open loop response time (OLRT) for the system evaluated in under this investigation was less than 30 seconds. In all trials the output to the AC utility system was reduced to the set level before the open loop response time had expired. The table below summarizes the maximum OLRT as well as the average OLRT for each level measured.

Measured Open Loop Response Time (OLRT) in Seconds				
Variable load settings		PCS Output control limit settings		
		L1-L2 loaded		
Trials		100%	50%	0%
100%	OLRT 1	9	6	6
	OLRT 2	8	9	7
	OLRT 3	9	8	6
	AVERAGE	8.67	7.67	6.33
66%	OLRT 1	6	6	6
	OLRT 2	9	6	7
	OLRT 3	9	5	8
	AVERAGE	8	5.67	7
33%	OLRT 1	0*	4	5
	OLRT 2	0*	3	5
	OLRT 3	0*	3.5	7
	AVERAGE	N/A	3.5	5.67

*No overshoot during transition.

A UL certification is a valuable marketing tool meaning your product or company has successfully met stringent requirements. We encourage you to use your product certification in your marketing activities. You can find information on how to accurately promote your UL certification at <https://www.ul.com/marketing>.

If you have any questions, please contact me or any of our customer service representatives. And, congratulations again on your achievement!

Sincerely,
 David Koll
 Senior Project Engineer
 UL LLC
 David.Koll@ul.com

John Carr
 Senior Staff Engineer
 UL LLC
 John.W.Carr@ul.com

This is an electronically generated letter. Signatures are not required for this document to be valid.