

Control Commands

Model No. PT-RQ50K
PT-SRQ50KC



- Please refer to the Operating Instructions for the serial command format, limitations, connection and other details.
- シリアルコマンドのフォーマット、制限事項、接続方法およびその他詳細につきましては、各モデルの取扱説明書をご覧ください。
- 有关串行控制命令的格式、限制事项、连接方法以及其他详情、请参阅各机型的使用说明书。

Panasonic

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
BASIC OPERATIO N REMOTE CONTROL	POWER	ON		PON	QPW	001	✓
		OFF (STANDBY)		POF		000	✓
	INPUT SELECT	DIGITAL LINK		IIS:DL1	QIN	DL1	✓
	INPUT SELECT (DIGITAL LINK)	COMPUTER1		IIS:DL1:PC1	QIN	DL1:PC1	✓
		COMPUTER2		IIS:DL1:PC2		DL1:PC2	✓
		VIDEO		IIS:DL1:VID		DL1:VID	✓
		HDMI1		IIS:DL1:HD1		DL1:HD1	✓
		HDMI2		IIS:DL1:HD2		DL1:HD2	✓
		S-VIDEO		IIS:DL1:SVD		DL1:SVD	✓
	INPUT SELECT (SLOT)	SLOT1 : SDI1		IIS:AU1,SD1	QIN	AU1,SD1	✓
		SLOT1 : SDI2		IIS:AU1,SD2		AU1,SD2	✓
		SLOT1 : SDI3		IIS:AU1,SD3		AU1,SD3	✓
		SLOT1 : SDI4		IIS:AU1,SD4		AU1,SD4	✓
		SLOT2 : SDI1		IIS:AU2,SD1		AU2,SD1	✓
		SLOT2 : SDI2		IIS:AU2,SD2		AU2,SD2	✓
		SLOT2 : SDI3		IIS:AU2,SD3		AU2,SD3	✓
		SLOT2 : SDI4		IIS:AU2,SD4		AU2,SD4	✓
		SLOT1 : HDMI1		IIS:AU1,HD1		AU1,HD1	✓
		SLOT1 : HDMI2		IIS:AU1,HD2		AU1,HD2	✓
		SLOT2 : HDMI3		IIS:AU2,HD3		AU2,HD3	✓
		SLOT2 : HDMI4		IIS:AU2,HD4		AU2,HD4	✓
		SLOT1 : DVI1		IIS:AU1,DV1		AU1,DV1	✓
		SLOT1 : DVI2		IIS:AU1,DV2		AU1,DV2	✓
		SLOT2 : DVI3		IIS:AU2,DV3		AU2,DV3	✓
		SLOT2 : DVI4		IIS:AU2,DV4		AU2,DV4	✓
		SLOT1 : DisplayPort1		IIS:AU1,DP1		AU1,DP1	✓
		SLOT1 : DisplayPort2		IIS:AU1,DP2		AU1,DP2	✓
		SLOT2 : DisplayPort3		IIS:AU2,DP3		AU2,DP3	✓
		SLOT2 : DisplayPort4		IIS:AU2,DP4		AU2,DP4	✓
	FREEZE	OFF		OFZ:0	QFZ	0	✓
		ON		OFZ:1		1	✓
	MENU KEY			OMN			✓
	ENTER KEY			OEN			✓
	UP KEY			OCU			✓
	DOWN KEY			OCD			✓
	LEFT KEY			OCL			✓
	RIGHT KEY			OCR			✓
	DEFAULT KEY			OST			✓
	AUTO SETUP KEY			OAS			✓
	SHUTTER	OFF		OSH:0	QSH	0	✓
		ON		OSH:1		1	✓
	SHUTTER(Toggle)	OFF		OSH	QSH	0	✓
		ON				1	✓
	FUNCTION KEY			FC1			✓
	SYSTEM SELCTOR KEY			OSL			✓
	ASPECT KEY			VS1			✓
	NUMERIC KEY	0		ONK:0			✓
		1		ONK:1			✓
		2		ONK:2			✓
		3		ONK:3			✓
		4		ONK:4			✓
		5		ONK:5			✓
		6		ONK:6			✓
		7		ONK:7			✓
		8		ONK:8			✓
		9		ONK:9			✓
	LENS HOME POSITION	EXECUTE		VXX:LNSI1=+00001			✓
	ACTIVE FOCUS OPTIMIZER-ACTIVE FOCUS	OFF		VXX:AF0I1=+00000	QVX:AF0I1	AF0I1=+00000	✓
		ON		VXX:AF0I1=+00001		AF0I1=+00001	✓
	ACTIVE FOCUS OPTIMIZER-FOCUS OFFSET BRIGHT	-00099		VXX:F0BI1=-00099	QVX:F0BI1	F0BI1=-00099	✓
		+00099		VXX:F0BI1=+00099		F0BI1=+00099	✓
	ACTIVE FOCUS OPTIMIZER-FOCUS OFFSET DARK	-00099		VXX:F0BI2=-00099	QVX:F0BI2	F0BI2=-00099	✓
		+00099		VXX:F0BI2=+00099		F0BI2=+00099	✓
	ACTIVE FOCUS OPTIMIZER-INITILIZE	EXECUTE		VXX:F0II1=+00001			✓
	LENS SHIFT-HORIZONTAL	SLOW+		VXX:LNSI2=+00000			✓
		SLOW-		VXX:LNSI2=+00001			✓
		NORMAL+		VXX:LNSI2=+00100			✓
		NORMAL-		VXX:LNSI2=+00101			✓
		FAST+		VXX:LNSI2=+00200			✓
		FAST-		VXX:LNSI2=+00201			✓
	LENS SHIFT-VERTICAL	SLOW+		VXX:LNSI3=+00000			✓
		SLOW-		VXX:LNSI3=+00001			✓
		NORMAL+		VXX:LNSI3=+00100			✓
		NORMAL-		VXX:LNSI3=+00101			✓
		FAST+		VXX:LNSI3=+00200			✓
		FAST-		VXX:LNSI3=+00201			✓
	LENS FOCUS	SLOW+		VXX:LNSI4=+00000			✓
		SLOW-		VXX:LNSI4=+00001			✓
		NORMAL+		VXX:LNSI4=+00100			✓
		NORMAL-		VXX:LNSI4=+00101			✓
		FAST+		VXX:LNSI4=+00200			✓
		FAST-		VXX:LNSI4=+00201			✓
	LENS ZOOM	SLOW+		VXX:LNSI5=+00000			✓
		SLOW-		VXX:LNSI5=+00001			✓
		NORMAL+		VXX:LNSI5=+00100			✓
		NORMAL-		VXX:LNSI5=+00101			✓
		FAST+		VXX:LNSI5=+00200			✓
		FAST-		VXX:LNSI5=+00201			✓
	LENS POSITION HORIZONTAL	-02480		VXX:LNSI7=-02480	QVX:LNSI7	LNSI7=-02480	✓
		+02480		VXX:LNSI7=+02480		LNSI7=+02480	✓
	LENS POSITION VERTICAL	-03200		VXX:LNSI8=-03200	QVX:LNSI8	LNSI8=-03200	✓
		+03200		VXX:LNSI8=+03200		LNSI8=+03200	✓
	LENS POSITION FOCUS	+00000		VXX:LNSI9=+00000	QVX:LNSI9	LNSI9=+00000	✓
		+02560		VXX:LNSI9=+02560		LNSI9=+02560	✓
	LENS POSITION H/V	-02480/-03200		VXX:LNSSB=-02480-03200	QVX:LNSSB	LNSSB=-02480-03200	✓
		+02480/+03200		VXX:LNSSB=+02480+03200		LNSSB=+02480+03200	✓
	LENS POSITION H/V FOCUS	-02480/-03200/+00000		VXX:LNSSC=-02480-03200+00000	QVX:LNSSC	LNSSC=-02480-03200+00000	✓
		+02480/+03200/+02560		VXX:LNSSC=+02480+03200+02560		LNSSC=+02480+03200+02560	✓
	STATUS KEY			STS			✓
	LENS FOCUS KEY			OLF			✓
	LENS SHIFT KEY			OLH			✓
	LENS ZOOM KEY			OLZ			✓
	DIGITAL LINK KEY			DLK			✓
	INPUT MENU KEY			IPT			✓
	SELF DIAGNOSIS				QVX:ERRS1 QVX:ERRS2	ERRS1=*****	✓
						ERRS2=*****	✓
	PICTURE MODE	DYNAMIC		VPM:DYN	QPM	DYN	✓
		NATURAL		VPM:NAT		NAT	✓
		STANDARD		VPM:STD		STD	✓
		CINEMA		VPM:CIN		CIN	✓
		GRAPHIC		VPM:GRA		GRA	✓
		DICOM SIM.		VPM:DIC		DIC	✓
		USER		VPM:USR		USR	✓
	PICTURE MODE-NAME SETTING USER	PICTUREMODE		VXX:NCGS0=PICTUREMODE	QVX:NCGS0	NCGS0=PICTUREMODE	✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
PICTURE	PICTURE MODE-NAME CLEAR USER	PICTUREMODE		VXX:NCLI0=+00000			✓
	CONTRAST	+1		VCN:001	QVR	001	✓
		+63		VCN:063		063	✓
	BRIGHTNESS	+1		VBR:001	QVB	001	✓
		+63		VBR:063		063	✓
	COLOR	+1		VCO:001	QVC	001	✓
		+63		VCO:063		063	✓
	TINT	+1		VTN:001	QVT	001	✓
		+63		VTN:063		063	✓
	SHARPNESS	0		VSR:000	QVS	000	✓
		15		VSR:015		015	✓
	COLOR TEMPERATURE	USER1(USER)		OTE:04	QTE	4	✓
		USER2		OTE:09		9	✓
		DEFAULT		OTE:10		10	✓
		3200K		OTE:3200		3200	✓
		3300K		OTE:3300		3300	✓
		9200K		OTE:9200		9200	✓
		9300K		OTE:9300		9300	✓
		9400K		OTE:9400		9400	✓
		12900K		OTE:12900		12900	✓
		13000K		OTE:13000		13000	✓
	COLOR TEMP-NAME SETTING USER1	COLORTEMP1		VXX:NCGS1=COLORTEMP1	QVX:NCGS1	NCGS1=COLORTEMP1	✓
	COLOR TEMP-NAME SETTING USER2	COLORTEMP2		VXX:NCGS3=COLORTEMP2	QVX:NCGS3	NCGS3=COLORTEMP2	✓
	COLOR TEMP-NAME CLEAR USER1	COLORTEMP1		VXX:NCLI1=+00000			✓
	COLOR TEMP-NAME CLEAR USER2	COLORTEMP2		VXX:NCLI3=+00000			✓
	WHITE BALANCE LOW-RED	-127		VOR:001	QOR	001	✓
		+127		VOR:255		255	✓
	WHITE BALANCE LOW-GREEN	-127		VOG:001	QOG	001	✓
		+127		VOG:255		255	✓
	WHITE BALANCE LOW-BLUE	-127		VOB:001	QOB	001	✓
		+127		VOB:255		255	✓
	WHITE BALANCE HIGH-RED	0		VHR:000	QHR	000	✓
		+255		VHR:255		255	✓
	WHITE BALANCE HIGH-GREEN	0		VHG:000	QHG	000	✓
		+255		VHG:255		255	✓
	WHITE BALANCE HIGH-BLUE	0		VHB:000	QHB	000	✓
		+255		VHB:255		255	✓
	GAMMA	1.0		VGA:1.0	QGA	1.0	✓
		1.8		VGA:1.8		1.8	✓
		2.0		VGA:2.0		2.0	✓
		2.1		VGA:2.1		2.1	✓
		2.2		VGA:2.2		2.2	✓
		2.3		VGA:2.3		2.3	✓
		2.4		VGA:2.4		2.4	✓
		2.5		VGA:2.5		2.5	✓
		2.6		VGA:2.6		2.6	✓
		2.7		VGA:2.7		2.7	✓
		2.8		VGA:2.8		2.8	✓
		USER1		VGA:US1		US1	✓
		USER2		VGA:US2		US2	✓
		DICOM		VGA:DIC		DIC	✓
		HDR HLG		VGA:HD1		HD1	✓
		HDR ST2048-500		VGA:HD2		HD2	✓
		HDR ST2048-1000		VGA:HD3		HD3	✓
		DEFAULT		VGA:DEF		DEF	✓
	GAMMA-HDR HLG SYSTEM GAMMA	min.	(0.1step)	VXX:HLGS1=+1.00	QVX:HLGS1	HLGS1=1.00	✓
		max.		VXX:HLGS1=+1.62		HLGS1=1.62	✓
	GAMMA-NAME SETTING USER1	GAMMAUSER1		VXX:NCGS2=GAMMAUSER1	QVX:NCGS2	NCGS2=GAMMAUSER1	✓
	GAMMA-NAME SETTING USER2	GAMMAUSER2		VXX:NCGS4=GAMMAUSER2	QVX:NCGS4	NCGS4=GAMMAUSER2	✓
	GAMMA-NAME CLEAR USER1	GAMMAUSER1		VXX:NCLI2=+00000			✓
	GAMMA-NAME CLEAR USER2	GAMMAUSER2		VXX:NCLI4=+00000			✓
	DAYLIGHT VIEW FRONT INSTALL	OFF		VXX:DLVI0=+00000	QVX:DLVI0	DLVI0=+00000	✓
		AUTO(1)		VXX:DLVI0=+00001		DLVI0=+00001	✓
		ON(2)		VXX:DLVI0=+00002		DLVI0=+00002	✓
		ON(3)		VXX:DLVI0=+00003		DLVI0=+00003	✓
		4		VXX:DLVI0=+00004		DLVI0=+00004	✓
		5		VXX:DLVI0=+00005		DLVI0=+00005	✓
		6		VXX:DLVI0=+00006		DLVI0=+00006	✓
	NOISE REDUCTION	OFF		VNS:0	QNS	0	✓
		1		VNS:1		1	✓
		2		VNS:2		2	✓
		3		VNS:3		3	✓
		4		VNS:4		4	✓
		5		VNS:5		5	✓
		6		VNS:6		6	✓
	DYNAMIC CONTRAST/IRIS	OFF		OAI:0	QAI	0	✓
		1		OAI:1		1	✓
		2		OAI:2		2	✓
		3		OAI:3		3	✓
		USER		OAI:4		4	✓
	DYNAMIC CONTRAST/AUTO IRIS (AUTO CONTRAST)	OFF		OAI:A000	QAI:A	000	✓
		1		OAI:A001		001	✓
		255		OAI:A255		255	✓
							✓
	DYNAMIC CONTRAST (BRIGHT SIGNAL LEVEL)	6%		VXX:DYCI1=+00006	QVX:DYCI1	00006	✓
		50%		VXX:DYCI1=+00050		00050	✓
	DYNAMIC CONTRAST (LIGHTS OUT TIMER)	DISABLE		VXX:DYCS2=OFF	QVX:DYCS2	OFF	✓
		0.0s		VXX:DYCS2=0.0		0.0	✓
		10.0s		VXX:DYCS2=10.0		10.0	✓
	DYNAMIC CONTRAST (LIGHTS OUT SIGNAL LEVEL)	0		VXX:DYCI3=+00000	QVX:DYCI3	00000	✓
		5		VXX:DYCI3=+00005		00005	✓
	DYNAMIC CONTRAST (LIGHTS OUT FADE-IN)	0.0s(OFF)		VXX:DYCS4=0.0	QVX:DYCS4	DYCS4=0.0	✓
		0.5s		VXX:DYCS4=0.5		DYCS4=0.5	✓
		1.0s		VXX:DYCS4=1.0		DYCS4=1.0	✓
		1.5s		VXX:DYCS4=1.5		DYCS4=1.5	✓
		2.0s		VXX:DYCS4=2.0		DYCS4=2.0	✓
		2.5s		VXX:DYCS4=2.5		DYCS4=2.5	✓
		3.0s		VXX:DYCS4=3.0		DYCS4=3.0	✓
		3.5s		VXX:DYCS4=3.5		DYCS4=3.5	✓
		4.0s		VXX:DYCS4=4.0		DYCS4=4.0	✓
		5.0s		VXX:DYCS4=5.0		DYCS4=5.0	✓
		7.0s		VXX:DYCS4=7.0		DYCS4=7.0	✓
		10.0s		VXX:DYCS4=10.0		DYCS4=10.0	✓
	DYNAMIC CONTRAST (LIGHTS OUT FADE-OUT)	0.0s(OFF)		VXX:DYCS5=0.0	QVX:DYCS5	DYCS5=0.0	✓
		0.5s		VXX:DYCS5=0.5		DYCS5=0.5	✓
		1.0s		VXX:DYCS5=1.0		DYCS5=1.0	✓
		1.5s		VXX:DYCS5=1.5		DYCS5=1.5	✓
		2.0s		VXX:DYCS5=2.0		DYCS5=2.0	✓
		2.5s		VXX:DYCS5=2.5		DYCS5=2.5	✓
		3.0s		VXX:DYCS5=3.0		DYCS5=3.0	✓
		3.5s		VXX:DYCS5=3.5		DYCS5=3.5	✓
		4.0s		VXX:DYCS5=4.0		DYCS5=4.0	✓
		5.0s		VXX:DYCS5=5.0		DYCS5=5.0	✓
		7.0s		VXX:DYCS5=7.0		DYCS5=7.0	✓
		10.0s		VXX:DYCS5=10.0		DYCS5=10.0	✓
							✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
	DYNAMIC CONTRAST/MANUAL IRIS (MANUAL INTENSITY)	OFF		OAI:M000	QAI:M	000	✓
		1		OAI:M001		001	✓
		255		OAI:M255		255	✓
	DYNAMIC CONTRAST (DYNAMIC GAMMA)	OFF		OAI:D0	QAI:D	0	✓
		1		OAI:D1		1	✓
		2		OAI:D2		2	✓
		3		OAI:D3		3	✓
	COLOR SPACE	NATIVE		VXX:CSPI1=+00000	QVX:CSPI1	CSPI1=+00000	✓
		ITU-709		VXX:CSPI1=+00001		CSPI1=+00001	✓
		DCI-P3		VXX:CSPI1=+00002		CSPI1=+00002	✓
		ITU2020		VXX:CSPI1=+00003		CSPI1=+00003	✓
	SYSTEM SELECTOR RGB(VGA/480P)	VGA60		ORF:0	QRF	0	✓
		480P(YCbCr)		ORF:1		1	✓
		480p(RGB)		ORF:3		3	✓
	SYSTEM SELECTOR RGB(Other)/DVI/SLOT-DVI	RGB		ORF:0	QRF	0	✓
		YPbPr		ORF:1		1	✓
	SYSTEM SELECTOR HDMI/DIGITAL LINK/SLOT-HDMI	RGB		ORF:0	QRF	0	✓
		YPbPr		ORF:1		1	✓
		AUTO		ORF:2		2	✓
	GEOMETRY	OFF		VXX:GMMI0=+00000	QVX:GMMI0	GMMI0=+00000	✓
		KEYSTONE		VXX:GMMI0=+00001		GMMI0=+00001	✓
		CURVED		VXX:GMMI0=+00002		GMMI0=+00002	✓
		PC-1		VXX:GMMI0=+00003		GMMI0=+00003	✓
		PC-2		VXX:GMMI0=+00004		GMMI0=+00004	✓
		PC-3		VXX:GMMI0=+00005		GMMI0=+00005	✓
		CORNER-CORRECTION		VXX:GMMI0=+00010		GMMI0=+00010	✓
	GEOMETRY-KEYSTONE-LENS THROW RATIO	0.7	0.1 step	VXX:GMKS0=+00.7	QVX:GMKS0	GMKS0=+00.7	✓
		16.5		VXX:GMKS0=+16.5		GMKS0=+16.5	✓
POSITION	GEOMETRY-KEYSTONE-VERTICAL BALANCE	-60		VXX:GMKI4=-00060	QVX:GMKI4	GMKI4=-00060	✓
		+60		VXX:GMKI4=+00060		GMKI4=+00060	✓
	GEOMETRY-KEYSTONE-HORIZONTAL BALANCE	-30		VXX:GMKI7=-00030	QVX:GMKI7	GMKI7=-00030	✓
		+30		VXX:GMKI7=+00030		GMKI7=+00030	✓
	GEOMETRY-KEYSTONE-VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX:GMKS8=-40.0	QVX:GMKS8	GMKS8=-40.0	✓
		+40.0 (+45.0)*		VXX:GMKS8=+40.0		GMKS8=+40.0	✓
	GEOMETRY-KEYSTONE-HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX:GMKS9=-15.0	QVX:GMKS9	GMKS9=-15.0	✓
		+15.0 (+40.0)*		VXX:GMKS9=+15.0		GMKS9=+15.0	✓
	GEOMETRY-CURVED-LENS THROW RATIO	0.7	0.1 step	VXX:GMCS0=+00.7	QVX:GMCS0	GMCS0=+00.7	✓
		16.5		VXX:GMCS0=+16.5		GMCS0=+16.5	✓
	GEOMETRY-CURVED-VERTICAL ARC	-50 (-100)*		VXX:GMCI3=-00050	QVX:GMCI3	GMCI3=-00050	✓
		+50 (+100)*		VXX:GMCI3=+00050		GMCI3=+00050	✓
	GEOMETRY-CURVED-HORIZONTAL ARC	-50 (-100)*		VXX:GMCI7=-00050	QVX:GMCI7	GMCI7=-00050	✓
		+50 (+100)*		VXX:GMCI7=+00050		GMCI7=+00050	✓
	GEOMETRY-CURVED-VERTICAL BALANCE	-60		VXX:GMCI2=-00060	QVX:GMCI2	GMCI2=-00060	✓
		+60		VXX:GMCI2=+00060		GMCI2=+00060	✓
	GEOMETRY-CURVED-HORIZONTAL BALANCE	-30		VXX:GMCI6=-00030	QVX:GMCI6	GMCI6=-00030	✓
		+30		VXX:GMCI6=+00030		GMCI6=+00030	✓
	GEOMETRY-CURVED-VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX:GMCS8=-40.0	QVX:GMCS8	GMCS8=-40.0	✓
		+40.0 (+45.0)*		VXX:GMCS8=+40.0		GMCS8=+40.0	✓
	GEOMETRY-CURVED-HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX:GMCS9=-15.0	QVX:GMCS9	GMCS9=-15.0	✓
		+15.0 (+40.0)*		VXX:GMCS9=+15.0		GMCS9=+15.0	✓
	GEOMETRY-CURVED-MAINTAIN ASPECT RATIO	OFF		VXX:GMCIA=+00000	QVX:GMCIA	GMCIA=+00000	✓
		ON		VXX:GMCIA=+00001		GMCIA=+00001	✓
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(V)	min.		VXX:GMFI1=+00000	QVX:GMFI1	GMFI1=+00000	0
		max.		VXX:GMFI1=+00300		GMFI1=+00300	+300
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(V)	min.		VXX:GMFI2=+00000	QVX:GMFI2	GMFI2=+00000	0
		max.		VXX:GMFI2=+00300		GMFI2=+00300	+300
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(V)	min.		VXX:GMFI3=-00300	QVX:GMFI3	GMFI3=-00300	-300
		max.		VXX:GMFI3=+00000		GMFI3=+00000	0
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(V)	min.		VXX:GMFI4=-00300	QVX:GMFI4	GMFI4=-00300	-300
		max.		VXX:GMFI4=+00000		GMFI4=+00000	0
	GEOMETRY-CORNER CORRECTION-LINEARITY(V)	min.		VXX:GMFI5=-00127	QVX:GMFI5	GMFI5=-00127	-127
		max.		VXX:GMFI5=+00127		GMFI5=+00127	+127
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(H)	min.		VXX:GMFI6=+00000	QVX:GMFI6	GMFI6=+00000	0
		max.		VXX:GMFI6=+00480		GMFI6=+00480	+480
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(H)	min.		VXX:GMFI7=-00480	QVX:GMFI7	GMFI7=-00480	-480
		max.		VXX:GMFI7=+00000		GMFI7=+00000	0
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(H)	min.		VXX:GMFI8=+00000	QVX:GMFI8	GMFI8=+00000	0
		max.		VXX:GMFI8=+00480		GMFI8=+00480	+480
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(H)	min.		VXX:GMFI9=-00480	QVX:GMFI9	GMFI9=-00480	-480
		max.		VXX:GMFI9=+00000		GMFI9=+00000	0
	GEOMETRY-CORNER CORRECTION-LINEARITY(H)	min.		VXX:GMFIA=-00127	QVX:GMFIA	GMFIA=-00127	-127
		max.		VXX:GMFIA=+00127		GMFIA=+00127	+127
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION UPPER	min.		VXX:GMFIB=-00100	QVX:GMFIB	GMFIB=-00100	✓
		max.		VXX:GMFIB=+00100		GMFIB=+00100	✓
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION LOWER	min.		VXX:GMFIC=-00100	QVX:GMFIC	GMFIC=-00100	✓
		max.		VXX:GMFIC=+00100		GMFIC=+00100	✓
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION LEFT	min.		VXX:GMFID=-00100	QVX:GMFID	GMFID=-00100	✓
		max.		VXX:GMFID=+00100		GMFID=+00100	✓
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION RIGHT	min.		VXX:GMFIE=-00100	QVX:GMFIE	GMFIE=-00100	✓
		max.		VXX:GMFIE=+00100		GMFIE=+00100	✓
	GEOMETRY-CORNER/PINCUSHION-LINEARITY	AUTO		VXX:GMFIF=+00000	QVX:GMFIF	GMFIF=+00000	✓
		MANUAL		VXX:GMFIF=+00001		GMFIF=+00001	✓
	GEOMETRY - FREE GRID(ON/OFF)	OFF		VXX:GMGI1=+00000	QVX:GMGI1	GMGI1=+00000	✓
		ON		VXX:GMGI1=+00001		GMGI1=+00001	✓
	GEOMETRY - FREE GRID - INITIALIZE			VXX:GMGI2=+00001			✓
	GEOMETRY - FREE GRID - GRID RESOLUTION	2x2		VXX:GMGI3=+00002	QVX:GMGI3	GMGI3=+00002	✓
		3x3		VXX:GMGI3=+00003		GMGI3=+00003	✓
		5x5		VXX:GMGI3=+00005		GMGI3=+00005	✓
		9x9		VXX:GMGI3=+00009		GMGI3=+00009	✓
		17x17		VXX:GMGI3=+00017		GMGI3=+00017	✓
	GEOMETRY - FREE GRID - GRID COLOR	OFF		VXX:GMGI4=+00000	QVX:GMGI4	GMGI4=+00000	✓
		WHITE		VXX:GMGI4=+00001		GMGI4=+00001	✓
		BLACK		VXX:GMGI4=+00002		GMGI4=+00002	✓
		RED		VXX:GMGI4=+00003		GMGI4=+00003	✓
		GREEN		VXX:GMGI4=+00004		GMGI4=+00004	✓
		BLUE		VXX:GMGI4=+00005		GMGI4=+00005	✓
		CYAN		VXX:GMGI4=+00006		GMGI4=+00006	✓
		MAGENTA		VXX:GMGI4=+00007		GMGI4=+00007	✓
		YELLOW		VXX:GMGI4=+00008		GMGI4=+00008	✓
	GEOMETRY - FREE GRID - CONTROL POINTS	POINT		VXX:GMGI5=+00000	QVX:GMGI5	GMGI5=+00000	✓
		HORIZONTAL LINE		VXX:GMGI5=+00001		GMGI5=+00001	✓
		VERTICAL LINE		VXX:GMGI5=+00002		GMGI5=+00002	✓
	GEOMETRY - FREE GRID - GRID WIDTH	1		VXX:GMGI7=+00001	QVX:GMGI7	GMGI7=+00001	✓
		10		VXX:GMGI7=+00010		GMGI7=+00010	✓
	GEOMETRY - FREE GRID - CONTROL POINTS COLOR	WHITE		VXX:GMGI8=+00001	QVX:GMGI8	GMGI8=+00001	✓
		BLACK		VXX:GMGI8=+00002		GMGI8=+00002	✓
		RED		VXX:GMGI8=+00003		GMGI8=+00003	✓
		GREEN		VXX:GMGI8=+00004		GMGI8=+00004	✓
		BLUE		VXX:GMGI8=+00005		GMGI8=+00005	✓
		CYAN		VXX:GMGI8=+00006		GMGI8=+00006	✓
		MAGENTA		VXX:GMGI8=+00007		GMGI8=+00007	✓
		YELLOW		VXX:GMGI8=+00008		GMGI8=+00008	✓
	CONVERGENCE	OFF		VXX:CNVI1=+00000	QVX:CNVI1	CNVI1=+00000	✓
		ON		VXX:CNVI1=+00001		CNVI1=+00001	✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
	CONVERGENCE - UPPER LEFT VERTICAL			VXX:CNVS2=*:*****	QVX:CNVS2	CNVS2=*:*****	✓
				VXX:CNVS2=R:*****		CNVS2=R:*****	✓
				VXX:CNVS2=G:*****		CNVS2=G:*****	✓
				VXX:CNVS2=B:*****		CNVS2=B:*****	✓
				VXX:CNVS2=*:+00.00		CNVS2=*:+00.00	✓
				VXX:CNVS2=*:+03.75		CNVS2=*:+03.75	✓
	CONVERGENCE - UPPER LEFT HORIZONTAL			VXX:CNVS3=*:*****	QVX:CNVS3	CNVS3=*:*****	✓
				VXX:CNVS3=R:*****		CNVS3=R:*****	✓
				VXX:CNVS3=G:*****		CNVS3=G:*****	✓
				VXX:CNVS3=B:*****		CNVS3=B:*****	✓
				VXX:CNVS3=*:+00.00		CNVS3=*:+00.00	✓
				VXX:CNVS3=*:+03.75		CNVS3=*:+03.75	✓
	CONVERGENCE - UPPER RIGHT VERTICAL			VXX:CNVS4=*:*****	QVX:CNVS4	CNVS4=*:*****	✓
				VXX:CNVS4=R:*****		CNVS4=R:*****	✓
				VXX:CNVS4=G:*****		CNVS4=G:*****	✓
				VXX:CNVS4=B:*****		CNVS4=B:*****	✓
				VXX:CNVS4=*:+00.00		CNVS4=*:+00.00	✓
				VXX:CNVS4=*:+03.75		CNVS4=*:+03.75	✓
	CONVERGENCE - UPPER RIGHT HORIZONTAL			VXX:CNVS5=*:*****	QVX:CNVS5	CNVS5=*:*****	✓
				VXX:CNVS5=R:*****		CNVS5=R:*****	✓
				VXX:CNVS5=G:*****		CNVS5=G:*****	✓
				VXX:CNVS5=B:*****		CNVS5=B:*****	✓
				VXX:CNVS5=*:-03.75		CNVS5=*:-03.75	✓
				VXX:CNVS5=*:+00.00		CNVS5=*:+00.00	✓
	CONVERGENCE - LOWER LEFT VERTICAL			VXX:CNVS6=*:*****	QVX:CNVS6	CNVS6=*:*****	✓
				VXX:CNVS6=R:*****		CNVS6=R:*****	✓
				VXX:CNVS6=G:*****		CNVS6=G:*****	✓
				VXX:CNVS6=B:*****		CNVS6=B:*****	✓
				VXX:CNVS6=*:+00.00		CNVS6=*:+00.00	✓
				VXX:CNVS6=*:+03.75		CNVS6=*:+03.75	✓
	CONVERGENCE - LOWER LEFT HORIZONTAL			VXX:CNVS7=*:*****	QVX:CNVS7	CNVS7=*:*****	✓
				VXX:CNVS7=R:*****		CNVS7=R:*****	✓
				VXX:CNVS7=G:*****		CNVS7=G:*****	✓
				VXX:CNVS7=B:*****		CNVS7=B:*****	✓
				VXX:CNVS7=*:-03.75		CNVS7=*:-03.75	✓
				VXX:CNVS7=*:+00.00		CNVS7=*:+00.00	✓
	CONVERGENCE - LOWER RIGHT VERTICAL			VXX:CNVS8=*:*****	QVX:CNVS8	CNVS8=*:*****	✓
				VXX:CNVS8=R:*****		CNVS8=R:*****	✓
				VXX:CNVS8=G:*****		CNVS8=G:*****	✓
				VXX:CNVS8=B:*****		CNVS8=B:*****	✓
				VXX:CNVS8=*:-03.75		CNVS8=*:-03.75	✓
				VXX:CNVS8=*:+00.00		CNVS8=*:+00.00	✓
	CONVERGENCE - LOWER RIGHT HORIZONTAL			VXX:CNVS9=*:*****	QVX:CNVS9	CNVS9=*:*****	✓
				VXX:CNVS9=R:*****		CNVS9=R:*****	✓
				VXX:CNVS9=G:*****		CNVS9=G:*****	✓
				VXX:CNVS9=B:*****		CNVS9=B:*****	✓
				VXX:CNVS9=*:-03.75		CNVS9=*:-03.75	✓
				VXX:CNVS9=*:+00.00		CNVS9=*:+00.00	✓
	SHIFT-HORIZONTAL	0		VTH:0000	QTH	0000	✓
		+4095		VTH:4095		4095	✓
	SHIFT-VERTICAL	0		VTV:0000	QTV	0000	✓
		+4094		VTV:4094		4094	✓
	ASPECT	AUTO/VID AUTO/DEFAULT		VSE:0	QSE	0	✓
		NORMAL(4:3)		VSE:1		1	✓
		WIDE(16:9)		VSE:2		2	✓
		NATIVE(through)		VSE:5		5	✓
		FULL(HV FIT)		VSE:6		6	✓
		H-FIT		VSE:9		9	✓
		V-FIT		VSE:10		10	✓
	ZOOM-HORIZONTAL	50		OZH:050	QZH	050	✓
		999		OZH:999		999	✓
	ZOOM-VERTICAL	50		OZV:050	QZV	050	✓
		999		OZV:999		999	✓
	ZOOM-BOTH	50		OZO:050	QZO	050	✓
		999		OZO:999		999	✓
	ZOOM-INTERLOCKED	OFF		OZS:0	QZS	0	✓
		ON		OZS:1		1	✓
	ZOOM-MODE	INTERNAL		OZT:0	QZT	0	✓
		FULL		OZT:1		1	✓
	DIGITAL CINEMA REALITY	AUTO		OPD:0	QPD	0	✓
		OFF		OPD:1		1	✓
		30p/25p FIXED		OPD:2		2	✓
	BLANKING-UPPER	min.		DBU:000	QLU	000	0
		max.		DBU:2398		2398	2398
	BLANKING-LOWER	min.		DBB:000	QLB	000	0
		max.		DBB:2398		2398	2398
	BLANKING-RIGHT	min.		DBR:000	QLR	000	0
		max.		DBR:3838		3838	3838
	BLANKING-LEFT	min.		DBL:000	QLL	000	0
		max.		DBL:3838		3838	3838
	EDGE BLENDING	OFF		VXX:EDBI0=+00000	QVX:EDBI0	EDBI0=+00000	✓
		ON		VXX:EDBI0=+00001		EDBI0=+00001	✓
		USER		VXX:EDBI0=+00002		EDBI0=+00002	✓
	EDGE BLENDING-UPPER ON/OFF	OFF		VGU:0	QGU	0	✓
		ON		VGU:1		1	✓
	EDGE BLENDING-LOWER ON/OFF	OFF		VGB:0	QGB	0	✓
		ON		VGB:1		1	✓
	EDGE BLENDING-LEFT ON/OFF	OFF		VGL:0	QGL	0	✓
		ON		VGL:1		1	✓
	EDGE BLENDING-RIGHT ON/OFF	OFF		VGR:0	QGR	0	✓
		ON		VGR:1		1	✓
	EDGE BLENDING-START-UPPER	min.		VEU:0000	QEU	0000	0
		max.		VEU:2272		2272	2272
	EDGE BLENDING-START-LOWER	min.		VEB:0000	QEB	0000	0
		max.		VEB:2272		2272	2272
	EDGE BLENDING-START-LEFT	min.		VEL:0000	QEL	0000	0
		max.		VEL:3712		3712	3712
	EDGE BLENDING-START-RIGHT	min.		VER:0000	QER	0000	0
		max.		VER:3712		3712	3712
	EDGE BLENDING-WIDTH-UPPER	min.		VXX:EUIW0=+00000	QVX:EUIW0	EUIW0=+00000	0
		max.		VXX:EUIW0=+02272		EUIW0=+02272	2272
	EDGE BLENDING-WIDTH-LOWER	min.		VXX:EBWI0=+00000	QVX:EBWI0	EBWI0=+00000	0
		max.		VXX:EBWI0=+02272		EBWI0=+02272	2272
	EDGE BLENDING-WIDTH-LEFT	min.		VXX:ELWI0=+00000	QVX:ELWI0	ELWI0=+00000	0
		max.		VXX:ELWI0=+03712		ELWI0=+03712	3712
	EDGE BLENDING-WIDTH-RIGHT	min.		VXX:ERWI0=+00000	QVX:ERWI0	ERWI0=+00000	0
		max.		VXX:ERWI0=+03712		ERWI0=+03712	3712
	EDGE BLENDING-MARKER-ON/OFF	OFF		VGM:0	QGM	0	✓
		ON		VGM:1		1	✓
	EDGE BLENDING-NON- OVERLAPPED BLACK LEVEL	0 (W,R,G,B)		VJI:000.000.000.000	QJI	000.000.000.000	✓
		255 (W,R,G,B)		VJI:255.255.255.255		255.255.255.255	✓
	EDGE BLENDING-NON- OVERLAPPED BLACK LEVEL-	OFF		VXX:EBII1=+00000	QVX:EBII1	EBII1=+00000	✓
		ON		VXX:EBII1=+00001		EBII1=+00001	✓
	EDGE BLENDING-BLACK BORDER	0 (W,R,G,B)		VJO:000,000,000,000	QJO	000.000.000.000	✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
ADVANCED	LEVEL	255 (W,R,G,B)		VJ0:255,255,255,255		255.255.255.255	✓
	EDGE BLENDING-BLACK BORDER LEVEL-INTERLOCKED	OFF ON		VXX:EBII2=-00000 VXX:EBII2=+00001	QVX:EBII2	EBII2=-00000 EBII2=+00001	✓ ✓
	EDGE BLENDING-BLACK BORDER WIDTH-UPPER	min. max.		VJU:0000 VJU:2272	QJU	0000 2272	0 2272
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER	min. max.		VJB:0000 VJB:2272	QJB	0000 2272	0 2272
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT	min. max.		VJL:0000 VJL:3712	QJL	0000 3712	0 3712
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT	min. max.		VJR:0000 VJR:3712	QJR	0000 3712	0 3712
	EDGE BLENDING-BLACK BORDER WIDTH-UPPER KEYSTONE AREA	min. max.		VXX:EBBI4=-02272 VXX:EBBI4=+02272	QVX:EBBI4	EBBI4=-02272 EBBI4=+02272	-2272 2272
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER KEYSTONE AREA	min. max.		VXX:EBBI5=-02272 VXX:EBBI5=+02272	QVX:EBBI5	EBBI5=-02272 EBBI5=+02272	-2272 2272
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT KEYSTONE AREA	min. max.		VXX:EBBI6=-03712 VXX:EBBI6=+03712	QVX:EBBI6	EBBI6=-03712 EBBI6=+03712	-3712 3712
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT KEYSTONE AREA	min. max.		VXX:EBBI7=-03712 VXX:EBBI7=+03712	QVX:EBBI7	EBBI7=-03712 EBBI7=+03712	-3712 3712
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS0=000,000,000,000 VXX:EBBS0=255,255,255,255	QVX:EBBS0	EBBS0=000,000,000,000 EBBS0=255,255,255,255	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS1=000,000,000,000 VXX:EBBS1=255,255,255,255	QVX:EBBS1	EBBS1=000,000,000,000 EBBS1=255,255,255,255	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS2=000,000,000,000 VXX:EBBS2=255,255,255,255	QVX:EBBS2	EBBS2=000,000,000,000 EBBS2=255,255,255,255	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS3=000,000,000,000 VXX:EBBS3=255,255,255,255	QVX:EBBS3	EBBS3=000,000,000,000 EBBS3=255,255,255,255	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER INTERLOCKED	OFF ON		VXX:EBII3=-00000 VXX:EBII3=+00001	QVX:EBII3	EBII3=-00000 EBII3=+00001	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	OFF ON		VXX:EBII4=-00000 VXX:EBII4=+00001	QVX:EBII4	EBII4=-00000 EBII4=+00001	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT INTERLOCKED	OFF ON		VXX:EBII5=-00000 VXX:EBII5=+00001	QVX:EBII5	EBII5=-00000 EBII5=+00001	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT INTERLOCKED	OFF ON		VXX:EBII6=-00000 VXX:EBII6=+00001	QVX:EBII6	EBII6=-00000 EBII6=+00001	✓ ✓
	EDGE BLENDING-AUTO TESTPATTERN	OFF ON		VXX:EATII1=-00000 VXX:EATII1=+00001	QVX:EATII1	EATII1=-00000 EATII1=+00001	✓ ✓
	FRAME RESPONSE	NORMAL FAST FIXED		VXX:FDYI0=-00000 VXX:FDYI0=+00001 VXX:FDYI0=+00005	QVX:FDYI0	FDYI0=-00000 FDYI0=+00001 FDYI0=+00005	✓ ✓ ✓
	FRAME DELAY	0.00 100.00		VXX:FDYS1=+0.00 VXX:FDYS1=+100.00	QVX:FDYS1	FDYS1=+0.00 FDYS1=+100.00	✓ ✓
	FILM DETECTION	OFF ON		VXX:FDTI1=-00000 VXX:FDTI1=+00001	QVX:FDTI1	FDTI1=-00000 FDTI1=+00001	✓ ✓
	RASTER POSITION-HORIZONTAL	-2048 +2047		VRH:2952 VRH:7047	QRH	2952 7047	✓ ✓
	RASTER POSITION-VERTICAL	-2048 +2047		VRV:2952 VRV:7047	QRV	2952 7047	✓ ✓
DISPLAY LANGUAGE	LANGUAGE	English German French Spanish Italian Japanese Chinese Russian Korea Portuguse		OLG:ENG OLG:DEU OLG:FRA OLG:ESP OLG:ITL OLG:JPN OLG:CHI OLG:RUS OLG:KOR OLG:POR	QLG	ENG DEU FRA ESP ITL JPN CHI RUS KOR POR	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	COLOR MATCHING	OFF 3COLORS 7COLORS MEASURED		VXX:CMAI0=-00000 VXX:CMAI0=+00001 VXX:CMAI0=+00002 VXX:CMAI0=+00004	QVX:CMAI0	CMAI0=-00000 CMAI0=+00001 CMAI0=+00002 CMAI0=+00004	✓ ✓ ✓ ✓
	COLOR MATCHING-RESET MODE	NATIVE PICTURE		VXX:CRMI1=-00000 VXX:CRMI1=+00001	QVX:CRMI1	CRMI1=-00000 CRMI1=+00001	✓ ✓
	COLOR MATCHING-3COLORS-RED	0 (R,G,B) 2048,2048,2048(R,G,B)		VMR:0000,0000,0000 VMR:2048,2048,2048	QMR	0000,0000,0000 2048,2048,2048	✓ ✓
	COLOR MATCHING-3COLORS-GREEN	0 (R,G,B) 2048,2048,2048(R,G,B)		VMG:0000,0000,0000 VMG:2048,2048,2048	QMG	0000,0000,0000 2048,2048,2048	✓ ✓
	COLOR MATCHING-3COLORS-BLUE	0 (R,G,B) 2048,2048,2048(R,G,B)		VMB:0000,0000,0000 VMB:2048,2048,2048	QMB	0000,0000,0000 2048,2048,2048	✓ ✓
	COLOR MATCHING-3COLORS-AUTO TESTPATTERN	OFF ON		VXX:CATI0=-00000 VXX:CATI0=+00001	QVX:CATI0	CATI0=-00000 CATI0=+00001	✓ ✓
	COLOR MATCHING-3COLORS-RESET	EXECUTE		VXX:CREI1=-00001			✓
	COLOR MATCHING-7COLORS-RED	0 (R,G,B) 2048(R,G,B)		VXX:C7CS0=0000,0000,0000 VXX:C7CS0=2048,2048,2048	QVX:C7CS0	C7CS0=0000,0000,0000 C7CS0=2048,2048,2048	✓ ✓
	COLOR MATCHING-7COLORS-GREEN	0 (R,G,B) 2048(R,G,B)		VXX:C7CS1=0000,0000,0000 VXX:C7CS1=2048,2048,2048	QVX:C7CS1	C7CS1=0000,0000,0000 C7CS1=2048,2048,2048	✓ ✓
	COLOR MATCHING-7COLORS-BLUE	0 (R,G,B) 2048(R,G,B)		VXX:C7CS2=0000,0000,0000 VXX:C7CS2=2048,2048,2048	QVX:C7CS2	C7CS2=0000,0000,0000 C7CS2=2048,2048,2048	✓ ✓
	COLOR MATCHING-7COLORS-CYAN	0 (R,G,B) 2048(R,G,B)		VXX:C7CS3=0000,0000,0000 VXX:C7CS3=2048,2048,2048	QVX:C7CS3	C7CS3=0000,0000,0000 C7CS3=2048,2048,2048	✓ ✓
	COLOR MATCHING-7COLORS-MAGE	0 (R,G,B) 2048(R,G,B)		VXX:C7CS4=0000,0000,0000 VXX:C7CS4=2048,2048,2048	QVX:C7CS4	C7CS4=0000,0000,0000 C7CS4=2048,2048,2048	✓ ✓
	COLOR MATCHING-7COLORS-YELLO	0 (R,G,B) 2048(R,G,B)		VXX:C7CS5=0000,0000,0000 VXX:C7CS5=2048,2048,2048	QVX:C7CS5	C7CS5=0000,0000,0000 C7CS5=2048,2048,2048	✓ ✓
	COLOR MATCHING-7COLORS-WHITE	0 (R,G,B) 2048(R,G,B)		VXX:C7CS6=0000,0000,0000 VXX:C7CS6=2048,2048,2048	QVX:C7CS6	C7CS6=0000,0000,0000 C7CS6=2048,2048,2048	✓ ✓
	COLOR MATCHING-7COLORS-AUTO TESTPATTERN	OFF ON		VXX:CATI1=-00000 VXX:CATI1=+00001	QVX:CATI1	CATI1=-00000 CATI1=+00001	✓ ✓
	COLOR MATCHING-7COLORS-RESET	EXECUTE		VXX:CREI2=-00001			✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLACK	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS0=00000,0001,0001 VXX:CMMS0=65535,0999,0999	QVX:CMMS0	CMMS0=00000,0001,0001 CMMS0=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS1=00000,0001,0001 VXX:CMMS1=65535,0999,0999	QVX:CMMS1	CMMS1=00000,0001,0001 CMMS1=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS2=00000,0001,0001 VXX:CMMS2=65535,0999,0999	QVX:CMMS2	CMMS2=00000,0001,0001 CMMS2=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS3=00000,0001,0001 VXX:CMMS3=65535,0999,0999	QVX:CMMS3	CMMS3=00000,0001,0001 CMMS3=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS4=00000,0001,0001 VXX:CMMS4=65535,0999,0999	QVX:CMMS4	CMMS4=00000,0001,0001 CMMS4=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS0=00000,0001,0001 VXX:CMTS0=65535,0999,0999	QVX:CMTS0	CMTS0=00000,0001,0001 CMTS0=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS1=00000,0001,0001 VXX:CMTS1=65535,0999,0999	QVX:CMTS1	CMTS1=00000,0001,0001 CMTS1=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS2=00000,0001,0001 VXX:CMTS2=65535,0999,0999	QVX:CMTS2	CMTS2=00000,0001,0001 CMTS2=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA CYAN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS3=00000,0001,0001 VXX:CMTS3=65535,0999,0999	QVX:CMTS3	CMTS3=00000,0001,0001 CMTS3=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA MAGENTA	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS4=00000,0001,0001 VXX:CMTS4=65535,0999,0999	QVX:CMTS4	CMTS4=00000,0001,0001 CMTS4=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA YELLOW	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS5=00000,0001,0001 VXX:CMTS5=65535,0999,0999	QVX:CMTS5	CMTS5=00000,0001,0001 CMTS5=65535,0999,0999	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS6=00000,0001,0001 VXX:CMTS6=65535,0999,0999	QVX:CMTS6	CMTS6=00000,0001,0001 CMTS6=65535,0999,0999	✓ ✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
	COLOR MATCHING-MEASURED MODE-AUTO TESTPATTERN	OFF		VXX:CATI3=+00000	QVX:CATI3	CATI3=+00000	✓
		ON		VXX:CATI3=+00001		CATI3=+00001	✓
	COLOR MATCHING-MEASURED MODE-RESET	EXECUTE		VXX:CREI3=+00001			✓
	AUTO SIGNAL	OFF		VXX:AASI0=+00000	QVX:AASI0	AASI0=+00000	✓
		ON		VXX:AASI0=+00001		AASI0=+00001	✓
	AUTO SETUP -POSITION ADJ.	OFF		VXX:APAI0=+00000	QVX:APAI0	APAI0=+00000	✓
		ON		VXX:APAI0=+00001		APAI0=+00001	✓
	AUTO SETUP -SIGNAL LEVEL ADJ.	OFF		VXX:ASLI0=+00000	QVX:ASLI0	ASLI0=+00000	✓
		ON		VXX:ASLI0=+00001		ASLI0=+00001	✓
	BACKUP INPUT SETTING-BACKUP INPUT	PRIMARY		VXX:BACI1=+00001	QVX:BACI1	BACI1=+00001	✓
		SECONDARY		VXX:BACI1=+00002		BACI1=+00002	✓
		TOGGLE		VXX:BACI1=+00010		BACI1=+00010	✓
	BACKUP INPUT SETTING-BACKUP INPUT MODE (OPTION SLOT)	OFF		VXX:BACI6=+00000	QVX:BACI6	BACI6=+00000	✓
		HDMI1 (SLOT1) / HDMI2 (SLOT1)		VXX:BACI6=+00012		BACI6=+00012	✓
		DVI1 (SLOT1) / DVI2 (SLOT1)		VXX:BACI6=+00013		BACI6=+00013	✓
		SDI1 (SLOT1) / SDI3 (SLOT1)		VXX:BACI6=+00014		BACI6=+00014	✓
		HDMI3 (SLOT2) / HDMI4 (SLOT2)		VXX:BACI6=+00022		BACI6=+00022	✓
		DVI3 (SLOT2) / DVI4 (SLOT2)		VXX:BACI6=+00023		BACI6=+00023	✓
		SDI1 (SLOT2) / SDI3 (SLOT2)		VXX:BACI6=+00024		BACI6=+00024	✓
		SDI1-3 (SLOT1) / SDI1-3 (SLOT2)		VXX:BACI6=+00104		BACI6=+00104	✓
		SDI1-2-3-4 (SLOT1) / SDI1-2-3-4 (SLOT2)		VXX:BACI6=+01003		BACI6=+01003	✓
	BACKUP INPUT SETTING- AUTOMATIC SWITCHING	DISABLE		VXX:BACI3=+00001	QVX:BACI3	BACI3=+00001	✓
		ENABLE		VXX:BACI3=+00002		BACI3=+00002	✓
	BACKUP INPUT SETTING-BACKUP INPUT STATUS	INACTIVE			QVX:BACI4	BACI4=+00000	✓
		ACTIVE				BACI4=+00001	✓
	SIMUL INPUT SETTING - SLOT IN (SDI In/Slot In 対応)	OFF		VXX:SMLI2=+00000	QVX:SMLI2	SMLI2=+00000	✓
		AUTO (x2 speed)		VXX:SMLI2=+00011		SMLI2=+00011	✓
	DIGITAL LINK-SIGNAL LEVEL	AUTO		VXX:DKLI1=+00000	QVX:DKLI1	DKLI1=+00000	✓
		0-1023		VXX:DKLI1=+00001		DKLI1=+00001	✓
		64-940		VXX:DKLI1=+00002		DKLI1=+00002	✓
	DIGITAL LINK-AUTO GAMMA SELECT	DISABLE		VXX:LAGI1=+00000	QVX:LAGI1	LAGI1=+00000	✓
		ENABLE		VXX:LAGI1=+00001		LAGI1=+00001	✓
	DIGITAL LINK- AUTO COLOR SPACE SELECT	DISABLE		VXX:LACI1=+00000	QVX:LACI1	LACI1=+00000	✓
		ENABLE		VXX:LACI1=+00001		LACI2=+00001	✓
	DIGITAL LINK-EDID SELECT (SINGLE LINK)	EDID1:4K/60p		VXX:LESI1=+00000	QVX:LESI1	LESI1=+00000	✓
		EDID2:4K/30p		VXX:LESI1=+00001		LESI1=+00001	✓
		EDID3:2K		VXX:LESI1=+00002		LESI1=+00002	✓
		EDID4:4K/30p/HDR		VXX:LESI1=+00011		LESI1=+00011	✓
	DIGITAL LINK-EDID MODE	DEFAULT		VXX:EDMI4=+00000	QVX:EDMI4	EDMI4=+00000	✓
		USER		VXX:EDMI4=+00010		EDMI4=+00010	✓
	DIGITAL LINK-EDID RESOLUTION	1024x768p		VXX:EDRS4=1024:0768:p	QVX:EDRS4	EDRS4=1024:0768:p	✓
		1280x720p		VXX:EDRS4=1280:0720:p		EDRS4=1280:0720:p	✓
		1280x768p		VXX:EDRS4=1280:0768:p		EDRS4=1280:0768:p	✓
		1280x800p		VXX:EDRS4=1280:0800:p		EDRS4=1280:0800:p	✓
		1280x1024p		VXX:EDRS4=1280:1024:p		EDRS4=1280:1024:p	✓
		1366x768p		VXX:EDRS4=1366:0768:p		EDRS4=1366:0768:p	✓
		1400x1050p		VXX:EDRS4=1400:1050:p		EDRS4=1400:1050:p	✓
		1440x900p		VXX:EDRS4=1440:0900:p		EDRS4=1440:0900:p	✓
		1600x900p		VXX:EDRS4=1600:0900:p		EDRS4=1600:0900:p	✓
		1600x1200p		VXX:EDRS4=1600:1200:p		EDRS4=1600:1200:p	✓
		1680x1050p		VXX:EDRS4=1680:1050:p		EDRS4=1680:1050:p	✓
		1920x1080p		VXX:EDRS4=1920:1080:p		EDRS4=1920:1080:p	✓
		1920x1080i		VXX:EDRS4=1920:1080:i		EDRS4=1920:1080:i	✓
		1920x1200p		VXX:EDRS4=1920:1200:p		EDRS4=1920:1200:p	✓
		2048x1080p		VXX:EDRS4=2048:1080:p		EDRS4=2048:1080:p	✓
		2560x1600p		VXX:EDRS4=2560:1600:p		EDRS4=2560:1600:p	✓
		3840x2400p		VXX:EDRS4=3840:2400:p		EDRS4=3840:2400:p	✓
	DIGITAL LINK-EDID VERTICAL SCAN FREQUENCY	60Hz		VXX:EDVI4=+06000	QVX:EDVI4	EDVI4=+06000	✓
		50Hz		VXX:EDVI4=+05000		EDVI4=+05000	✓
		48Hz		VXX:EDVI4=+04800		EDVI4=+04800	✓
		30Hz		VXX:EDVI4=+03000		EDVI4=+03000	✓
		25Hz		VXX:EDVI4=+02500		EDVI4=+02500	✓
		24Hz		VXX:EDVI4=+02400		EDVI4=+02400	✓
	DIGITAL LINK-EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:EDLS1=*****:*:****	QVX:EDLS1	EDLS1=*****:*:****	✓
			1024x768	VXX:EDLS1=1024:0768:*:****		EDLS1=1024:0768:*:****	✓
			1280x720	VXX:EDLS1=1280:0720:*:****		EDLS1=1280:0720:*:****	✓
			1280x768	VXX:EDLS1=1280:0768:*:****		EDLS1=1280:0768:*:****	✓
			1280x800	VXX:EDLS1=1280:0800:*:****		EDLS1=1280:0800:*:****	✓
			1280x1024	VXX:EDLS1=1280:1024:*:****		EDLS1=1280:1024:*:****	✓
			1366x768	VXX:EDLS1=1366:0768:*:****		EDLS1=1366:0768:*:****	✓
			1400x1050	VXX:EDLS1=1400:1050:*:****		EDLS1=1400:1050:*:****	✓
			1440x900	VXX:EDLS1=1440:0900:*:****		EDLS1=1440:0900:*:****	✓
			1600x900	VXX:EDLS1=1600:0900:*:****		EDLS1=1600:0900:*:****	✓
			1600x1200	VXX:EDLS1=1600:1200:*:****		EDLS1=1600:1200:*:****	✓
			1680x1050	VXX:EDLS1=1680:1050:*:****		EDLS1=1680:1050:*:****	✓
			1920x1080	VXX:EDLS1=1920:1080:*:****		EDLS1=1920:1080:*:****	✓
			1920x1200	VXX:EDLS1=1920:1200:*:****		EDLS1=1920:1200:*:****	✓
			2048x1080	VXX:EDLS1=2048:1080:*:****		EDLS1=2048:1080:*:****	✓
			2560x1600	VXX:EDLS1=2560:1600:*:****		EDLS1=2560:1600:*:****	✓
			3840x2400	VXX:EDLS1=3840:2400:*:****		EDLS1=3840:2400:*:****	✓
		* PARAMETER2	Progressive	VXX:EDLS1=*****:p:****		EDLS1=*****:p:****	✓
			Interlace	VXX:EDLS1=*****:i:****		EDLS1=*****:i:****	✓
		* PARAMETER3	60Hz	VXX:EDLS1=*****:*:6000		EDLS1=*****:*:6000	✓
			50Hz	VXX:EDLS1=*****:*:5000		EDLS1=*****:*:5000	✓
			48Hz	VXX:EDLS1=*****:*:4800		EDLS1=*****:*:4800	✓
			30Hz	VXX:EDLS1=*****:*:3000		EDLS1=*****:*:3000	✓
			25Hz	VXX:EDLS1=*****:*:2500		EDLS1=*****:*:2500	✓
			24Hz	VXX:EDLS1=*****:*:2400		EDLS1=*****:*:2400	✓
	DIGITAL LINK-EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX:ESLS1	ESLS1=*****:*:****	✓
			1024x768			ESLS1=1024:0768:*:****	✓
			1280x720			ESLS1=1280:0720:*:****	✓
			1280x768			ESLS1=1280:0768:*:****	✓
			1280x800			ESLS1=1280:0800:*:****	✓
			1280x1024			ESLS1=1280:1024:*:****	✓
			1366x768			ESLS1=1366:0768:*:****	✓
			1400x1050			ESLS1=1400:1050:*:****	✓
			1440x900			ESLS1=1440:0900:*:****	✓
			1600x900			ESLS1=1600:0900:*:****	✓
			1600x1200			ESLS1=1600:1200:*:****	✓
			1680x1050			ESLS1=1680:1050:*:****	✓
			1920x1080			ESLS1=1920:1080:*:****	✓
			1920x1200			ESLS1=1920:1200:*:****	✓
			2048x1080			ESLS1=2048:1080:*:****	✓
			2560x1600			ESLS1=2560:1600:*:****	✓
			3840x2400			ESLS1=3840:2400:*:****	✓
		* PARAMETER2	Progressive			ESLS1=*****:p:****	✓
			Interlace			ESLS1=*****:i:****	✓
		* PARAMETER3	60Hz			ESLS1=*****:*:6000	✓
			50Hz			ESLS1=*****:*:5000	✓
			48Hz			ESLS1=*****:*:4800	✓
			30Hz			ESLS1=*****:*:3000	✓
			25Hz			ESLS1=*****:*:2500	✓
			24Hz			ESLS1=*****:*:2400	✓
	SDI IN - SDI MODE(ET-MDN12G10)	* PARAMETER		VXX:*****=VXX:*****+*****	QVX:*****=QVX:*****	*****=*****+*****	✓

				CONTROL		QUERY	RQ50K SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC	
		* PARAMETER1, 2	SLOT1	VXX:SLSS1=VXX:SM0I1=+*****		SLSS1=SM0I1=+*****	✓	
			SLOT2	VXX:SLSS2=VXX:SM0I1=+*****		SLSS2=SM0I1=+*****	✓	
		* PARAMETER3	INPUT	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	
			OUTPUT	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	
	SDI IN - SDI LINK	SINGLE LINK		VXX:SLKI1=+00000	QVX:SLKI1	SLKI1=+00000	✓	
		DUAL LINK		VXX:SLKI1=+00001		SLKI1=+00001	✓	
		QUAD		VXX:SLKI1=+00002		SLKI1=+00002	✓	
		AUTO		VXX:SLKI1=+00010		SLKI1=+00010	✓	
		DUAL / DUAL		VXX:SLKI1=+00100		SLKI1=+00100	✓	
		DUAL / SINGLE		VXX:SLKI1=+00101		SLKI1=+00101	✓	
		SINGLE / DUAL		VXX:SLKI1=+00102		SLKI1=+00102	✓	
	SLOT - SDI IN - SDI LINK(ET-MDN12G10)	* PARAMETER		VXX:*****=VXX:*****=+00000		*****=*****=+*****	✓	
		* PARAMETER1, 2	SLOT1	VXX:SLSS1=VXX:SLKI3=+*****		SLSS1=SLKI3=+*****	✓	
			SLOT2	VXX:SLSS2=VXX:SLKI3=+*****		SLSS2=SLKI3=+*****	✓	
		* PARAMETER3	SNGL E LINK	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	
			DUAL LINK	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	
			QUAD LINK	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	
	SLOT - HDMI IN - HDMI LINK		AUTO	VXX:*****=VXX:*****=+00010		*****=*****=+00010	✓	
		SINGLE LINK		VXX:HLKI1=+00000	QVX:HLKI1	HLKI1=+00000	✓	
		QUAD LINK		VXX:HLKI1=+00002		HLKI1=+00002	✓	
	SLOT - DVI IN - DVI LINK		AUTO	VXX:HLKI1=+00010		HLKI1=+00010	✓	
		SINGLE LINK		VXX:DLKI1=+00000	QVX:DLKI1	DLKI1=+00000	✓	
		QUAD LINK		VXX:DLKI1=+00002		DLKI1=+00002	✓	
	SLOT : SDI RESOLUTION		AUTO	VXX:DLKI1=+00010		DLKI1=+00010	✓	
		* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	
		* PARAMETER1, 2	SDI1	VXX:SLSS1=VXX:SRSI1=+*****		SLSS1=SRSI1=+*****	✓	
	SDI2		VXX:SLSS1=VXX:SRSI2=+*****		SLSS1=SRSI2=+*****	✓		
	SDI3		VXX:SLSS2=VXX:SRSI1=+*****		SLSS2=SRSI1=+*****	✓		
	SDI4		VXX:SLSS2=VXX:SRSI2=+*****		SLSS2=SRSI2=+*****	✓		
	DUAL LINK 1(SDI1+2)		VXX:SLSS1=VXX:SRDI1=+*****		SLSS1=SRDI1=+*****	✓		
	DUAL LINK 2(SDI3+4)		VXX:SLSS2=VXX:SRDI1=+*****		SLSS2=SRDI1=+*****	✓		
	* PARAMETER1, 2 (ET-MDN12G10)		SLOT1:SDI1	VXX:SLSS1=VXX:SRSI1=+*****		SLSS1=SRSI1=+*****	✓	
			SLOT1:SDI2	VXX:SLSS1=VXX:SRSI2=+*****		SLSS1=SRSI2=+*****	✓	
			SLOT1:SDI3	VXX:SLSS1=VXX:SRSI3=+*****		SLSS1=SRSI3=+*****	✓	
			SLOT1:SDI4	VXX:SLSS1=VXX:SRSI4=+*****		SLSS1=SRSI4=+*****	✓	
			SLOT2:SDI1	VXX:SLSS2=VXX:SRSI1=+*****		SLSS2=SRSI1=+*****	✓	
			SLOT2:SDI2	VXX:SLSS2=VXX:SRSI2=+*****		SLSS2=SRSI2=+*****	✓	
		SLOT2:SDI3	VXX:SLSS2=VXX:SRSI3=+*****		SLSS2=SRSI3=+*****	✓		
		SLOT2:SDI4	VXX:SLSS2=VXX:SRSI4=+*****		SLSS2=SRSI4=+*****	✓		
		DUAL LINK(SLOT1:SDI1+3)	VXX:SLSS1=VXX:SRDI1=+*****		SLSS1=SRDI1=+*****	✓		
		DUAL LINK(SLOT2:SDI1+3)	VXX:SLSS2=VXX:SRDI1=+*****		SLSS2=SRDI1=+*****	✓		
		QUAD LINK(SLOT1:SDI1+2+3+4)	VXX:SLSS1=VXX:SRQI1=+*****		SLSS1=SRQI1=+*****	✓		
		QUAD LINK(SLOT2:SDI1+2+3+4)	VXX:SLSS2=VXX:SRQI1=+*****		SLSS2=SRQI1=+*****	✓		
	* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓		
		1280x720p	VXX:*****=VXX:*****=+00003		*****=*****=+00003	✓		
		1920x1080i	VXX:*****=VXX:*****=+00005		*****=*****=+00005	✓		
		1920x1080p	VXX:*****=VXX:*****=+00006		*****=*****=+00006	✓		
		1920x1080sF	VXX:*****=VXX:*****=+00007		*****=*****=+00007	✓		
		2048x1080p	VXX:*****=VXX:*****=+00009		*****=*****=+00009	✓		
		3840x2160p	VXX:*****=VXX:*****=+00011		*****=*****=+00011	✓		
		4096x2160p	VXX:*****=VXX:*****=+00013		*****=*****=+00013	✓		
		SLOT : SDI : SDI 4K DIVISION	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓
			* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SKSI1=+*****		SLSS1=SKSI1=+*****	✓
	SINGLE LINK(SLOT1:SDI3)			VXX:SLSS1=VXX:SKSI3=+*****		SLSS1=SKSI3=+*****	✓	
	SINGLE LINK(SLOT2:SDI1)			VXX:SLSS2=VXX:SKSI1=+*****		SLSS2=SKSI1=+*****	✓	
	SINGLE LINK(SLOT2:SDI3)			VXX:SLSS2=VXX:SKSI3=+*****		SLSS2=SKSI3=+*****	✓	
	DUAL LINK(SLOT1:SDI1+3)			VXX:SLSS1=VXX:SKDI1=+*****		SLSS1=SKDI1=+*****	✓	
	DUAL LINK(SLOT2:SDI1+3)			VXX:SLSS2=VXX:SKDI1=+*****		SLSS2=SKDI1=+*****	✓	
	* PARAMETER3		QUAD LINK(SLOT1:SDI1+2+3+4)	VXX:SLSS1=VXX:SKQI1=+*****		SLSS1=SKQI1=+*****	✓	
			QUAD LINK(SLOT2:SDI1+2+3+4)	VXX:SLSS2=VXX:SKQI1=+*****		SLSS2=SKQI1=+*****	✓	
			AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	
			SQUARE	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	
			INTERLEAVE	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	
		SLOT : SDI : SDI 3G-SDI MAPPING	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓
	* PARAMETER1, 2 (ET-MDN12G10)		SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SGMI1=+*****		SLSS1=SGMI1=+*****	✓	
			SINGLE LINK(SLOT1:SDI2)	VXX:SLSS1=VXX:SGMI2=+*****		SLSS1=SGMI2=+*****	✓	
			SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SGMI3=+*****		SLSS1=SGMI3=+*****	✓	
			SINGLE LINK(SLOT1:SDI4)	VXX:SLSS1=VXX:SGMI4=+*****		SLSS1=SGMI4=+*****	✓	
			SINGLE LINK(SLOT2:SDI1)	VXX:SLSS2=VXX:SGMI1=+*****		SLSS2=SGMI1=+*****	✓	
			SINGLE LINK(SLOT2:SDI2)	VXX:SLSS2=VXX:SGMI2=+*****		SLSS2=SGMI2=+*****	✓	
			SINGLE LINK(SLOT2:SDI3)	VXX:SLSS2=VXX:SGMI3=+*****		SLSS2=SGMI3=+*****	✓	
			SINGLE LINK(SLOT2:SDI4)	VXX:SLSS2=VXX:SGMI4=+*****		SLSS2=SGMI4=+*****	✓	
			DUAL LINK(SLOT1:SDI1+3)	VXX:SLSS1=VXX:DGMI1=+*****		SLSS1=DGMI1=+*****	✓	
			DUAL LINK(SLOT2:SDI1+3)	VXX:SLSS2=VXX:DGMI1=+*****		SLSS2=DGMI1=+*****	✓	
			QUAD LINK(SLOT1:SDI1+2+3+4)	VXX:SLSS1=VXX:QGMI1=+*****		SLSS1=QGMI1=+*****	✓	
			QUAD LINK(SLOT2:SDI1+2+3+4)	VXX:SLSS2=VXX:QGMI1=+*****		SLSS2=QGMI1=+*****	✓	
	* PARAMETER3		AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	
			LEVEL A	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	
			LEVEL B	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	
	* PARAMETER3 (ET-MDN12G10)		AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	
			TYPE1/LEVEL A	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	
			TYPE2/LEVEL B	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	
	SLOT : SDI : SDI SYSTEM SELECTOR	* PARAMETER		VXX:*****=VXX:*****=*,*****:*****	QVX:*****=QVX:*****=*,*****:*****	*****=*****=*,*****:*****	✓	
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SYSS1=1:1:****	QVX:SLSS1=QVX:SYSS1=1:1	SLSS1=SYSS1=1:1:****	✓	
			SINGLE LINK(SLOT1:SDI2)	VXX:SLSS1=VXX:SYSS1=1:2:****	QVX:SLSS1=QVX:SYSS1=1:2	SLSS1=SYSS1=1:2:****	✓	
			SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SYSS1=1:3:****	QVX:SLSS1=QVX:SYSS1=1:3	SLSS1=SYSS1=1:3:****	✓	
			SINGLE LINK(SLOT1:SDI4)	VXX:SLSS1=VXX:SYSS1=1:4:****	QVX:SLSS1=QVX:SYSS1=1:4	SLSS1=SYSS1=1:4:****	✓	
			SINGLE LINK(SLOT2:SDI1)	VXX:SLSS2=VXX:SYSS1=1:1:****	QVX:SLSS2=QVX:SYSS1=1:1	SLSS2=SYSS1=1:1:****	✓	
			SINGLE LINK(SLOT2:SDI2)	VXX:SLSS2=VXX:SYSS1=1:2:****	QVX:SLSS2=QVX:SYSS1=1:2	SLSS2=SYSS1=1:2:****	✓	
			SINGLE LINK(SLOT2:SDI3)	VXX:SLSS2=VXX:SYSS1=1:3:****	QVX:SLSS2=QVX:SYSS1=1:3	SLSS2=SYSS1=1:3:****	✓	
			SINGLE LINK(SLOT2:SDI4)	VXX:SLSS2=VXX:SYSS1=1:4:****	QVX:SLSS2=QVX:SYSS1=1:4	SLSS2=SYSS1=1:4:****	✓	
			DUAL LINK(SLOT1:SDI1+3)	VXX:SLSS1=VXX:SYSS1=2:13:****	QVX:SLSS1=QVX:SYSS1=2:13	SLSS1=SYSS1=2:13:****	✓	
			DUAL LINK(SLOT2:SDI1+3)	VXX:SLSS2=VXX:SYSS1=2:13:****	QVX:SLSS2=QVX:SYSS1=2:13	SLSS2=SYSS1=2:13:****	✓	
			QUAD LINK(SLOT1:SDI1+2+3+4)	VXX:SLSS1=VXX:SYSS1=4:1234:****	QVX:SLSS1=QVX:SYSS1=4:1234	SLSS1=SYSS1=4:1234:****	✓	
			QUAD LINK(SLOT2:SDI1+2+3+4)	VXX:SLSS2=VXX:SYSS1=4:1234:****	QVX:SLSS2=QVX:SYSS1=4:1234	SLSS2=SYSS1=4:1234:****	✓	
		* PARAMETER3	AUTO	VXX:*****=VXX:SYSS1=*,*****:00000		*****=SYSS1=*,*****:00000	✓	
			RGB	VXX:*****=VXX:SYSS1=*,*****:00001		*****=SYSS1=*,*****:00001	✓	
			YPbPr4:4:4	VXX:*****=VXX:SYSS1=*,*****:00002		*****=SYSS1=*,*****:00002	✓	
			YPbPr4:2:2	VXX:*****=VXX:SYSS1=*,*****:00003		*****=SYSS1=*,*****:00003	✓	
			SLOT : SDI : BIT DEPTH	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****
* PARAMETER1, 2 (ET-MDN12G10)				SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SBTI1=+*****		SLSS1=SBTI1=+*****	✓
	SINGLE LINK(SLOT1:SDI2)	VXX:SLSS1=VXX:SBTI2=+*****			SLSS1=SBTI2=+*****	✓		
	SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SBTI4=+*****			SLSS1=SBTI4=+*****	✓		
	SINGLE LINK(SLOT1:SDI4)	VXX:SLSS1=VXX:SBTI5=+*****			SLSS1=SBTI5=+*****	✓		
	SINGLE LINK(SLOT2:SDI1)	VXX:SLSS2=VXX:SBTI1=+*****			SLSS2=SBTI1=+*****	✓		
	SINGLE LINK(SLOT2:SDI2)	VXX:SLSS2=VXX:SBTI2=+*****			SLSS2=SBTI2=+*****	✓		
	SINGLE LINK(SLOT2:SDI3)	VXX:SLSS2=VXX:SBTI4=+*****			SLSS2=SBTI4=+*****	✓		
	SINGLE LINK(SLOT2:SDI4)	VXX:SLSS2=VXX:SBTI5=+*****			SLSS2=SBTI5=+*****	✓		
	DUAL LINK(SDI1+3)	VXX:SLSS1=VXX:SBTI3=+*****			SLSS1=SBTI3=+*****	✓		
	DUAL LINK(SDI1+3)	VXX:SLSS2=VXX:SBTI3=+*****			SLSS2=SBTI3=+*****	✓		
	QUAD LINK (SDI1+2+3+4)	VXX:SLSS1=VXX:SBTI7=+*****			SLSS1=SBTI7=+*****	✓		
	QUAD LINK (SDI1+2+3+4)	VXX:SLSS2=VXX:SBTI7=+*****		SLSS2=SBTI7=+*****	✓			
* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓			
	12-bit	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓			

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ50K SERIES
				COMMANDS	COMMANDS	CALL BACK	
DISPLAY OPTION	SLOT : SDI : SIGNAL LEVEL	* PARAMETER	10-bit	VXX: *****=VXX: *****=+00002 VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+00002 *****=*****=+*****	✓ ✓
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX: SLSS1=VXX: SSLI1=+*****		SLSS1=SSLI1=+*****	✓
			SINGLE LINK(SLOT1:SDI2)	VXX: SLSS1=VXX: SSLI2=+*****		SLSS1=SSLI2=+*****	✓
			SINGLE LINK(SLOT1:SDI3)	VXX: SLSS1=VXX: SSLI4=+*****		SLSS1=SSLI4=+*****	✓
			SINGLE LINK(SLOT1:SDI4)	VXX: SLSS1=VXX: SSLI5=+*****		SLSS1=SSLI5=+*****	✓
			SINGLE LINK(SLOT2:SDI1)	VXX: SLSS2=VXX: SSLI1=+*****		SLSS2=SSLI1=+*****	✓
			SINGLE LINK(SLOT2:SDI2)	VXX: SLSS2=VXX: SSLI2=+*****		SLSS2=SSLI2=+*****	✓
			SINGLE LINK(SLOT2:SDI3)	VXX: SLSS2=VXX: SSLI4=+*****		SLSS2=SSLI4=+*****	✓
			SINGLE LINK(SLOT2:SDI4)	VXX: SLSS2=VXX: SSLI5=+*****		SLSS2=SSLI5=+*****	✓
			DUAL LINK(SDI1+3)	VXX: SLSS1=VXX: SSLI3=+*****		SLSS1=SSLI3=+*****	✓
			DUAL LINK(SDI1+3)	VXX: SLSS2=VXX: SSLI3=+*****		SLSS2=SSLI3=+*****	✓
		* PARAMETER3	QUAD LINK (SDI1+2+3+4)	VXX: SLSS1=VXX: SSLI7=+*****		SLSS1=SSLI7=+*****	✓
			QUAD LINK (SDI1+2+3+4)	VXX: SLSS2=VXX: SSLI7=+*****		SLSS2=SSLI7=+*****	✓
			64-940	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			4-1019	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓
	SLOT : HDMI : SIGNAL LEVEL	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: HSLI1=+*****		SLSS1=HSLI1=+*****	✓
			HDMI2	VXX: SLSS1=VXX: HSLI2=+*****		SLSS1=HSLI2=+*****	✓
			HDMI3	VXX: SLSS2=VXX: HSLI1=+*****		SLSS2=HSLI1=+*****	✓
			HDMI4	VXX: SLSS2=VXX: HSLI2=+*****		SLSS2=HSLI2=+*****	✓
			QUAD LINK (HDMI1+2+3+4)	VXX: SLDS1=VXX: HSQI1=+*****		SLDS1=HSQI1=+*****	✓
		* PARAMETER3	0-1023	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			64-940	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓
			AUTO	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓
	SLOT : HDMI : AUTO GAMMA SELECT	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: HAGI1=+*****		SLSS1=HAGI1=+*****	✓
			HDMI2	VXX: SLSS1=VXX: HAGI2=+*****		SLSS1=HAGI2=+*****	✓
			HDMI3	VXX: SLSS2=VXX: HAGI1=+*****		SLSS2=HAGI1=+*****	✓
			HDMI4	VXX: SLSS2=VXX: HAGI2=+*****		SLSS2=HAGI2=+*****	✓
		* PARAMETER3	DISABLE	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			ENABLE	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓
	SLOT : HDMI : AUTO COLOR SPACE SELECT	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: HACI1=+*****		SLSS1=HACI1=+*****	✓
			HDMI2	VXX: SLSS1=VXX: HACI2=+*****		SLSS1=HACI2=+*****	✓
			HDMI3	VXX: SLSS2=VXX: HACI1=+*****		SLSS2=HACI1=+*****	✓
			HDMI4	VXX: SLSS2=VXX: HACI2=+*****		SLSS2=HACI2=+*****	✓
		* PARAMETER3	DISABLE	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			ENABLE	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓
	SLOT : HDMI : EDID SELECT	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: HESI1=+*****		SLSS1=HESI1=+*****	✓
			HDMI2	VXX: SLSS1=VXX: HESI2=+*****		SLSS1=HESI2=+*****	✓
			HDMI3	VXX: SLSS2=VXX: HESI1=+*****		SLSS2=HESI1=+*****	✓
			HDMI4	VXX: SLSS2=VXX: HESI2=+*****		SLSS2=HESI2=+*****	✓
		* PARAMETER3	4K/60p/SDR	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			4K/30p	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓
			2K	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓
			4K/60p/HDR	VXX: *****=VXX: *****=+00010		*****=*****=+00010	✓
	SLOT : HDMI : EDID MODE	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: EDMI3=+*****		SLSS1=EDMI3=+*****	✓
			HDMI2	VXX: SLSS1=VXX: EDMI6=+*****		SLSS1=EDMI6=+*****	✓
			HDMI3	VXX: SLSS2=VXX: EDMI3=+*****		SLSS2=EDMI3=+*****	✓
			HDMI4	VXX: SLSS2=VXX: EDMI6=+*****		SLSS2=EDMI6=+*****	✓
		* PARAMETER3	DEFAULT	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			USER	VXX: *****=VXX: *****=+00010		*****=*****=+00010	✓
	SLOT : HDMI : EDID RESOLUTION	* PARAMETER		VXX: *****=VXX: *****=*****.*	QVX: *****=QVX: *****	*****=*****=*****.*	✓
		* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: EDRS3=*****.*		SLSS1=EDRS3=*****.*	✓
			HDMI2	VXX: SLSS1=VXX: EDRS6=*****.*		SLSS1=EDRS6=*****.*	✓
			HDMI3	VXX: SLSS2=VXX: EDRS3=*****.*		SLSS2=EDRS3=*****.*	✓
			HDMI4	VXX: SLSS2=VXX: EDRS6=*****.*		SLSS2=EDRS6=*****.*	✓
		* PARAMETER3	1024x768	VXX: *****=VXX: *****=1024:0768.*		*****=*****=1024:0768.*	✓
			1280x720	VXX: *****=VXX: *****=1280:0720.*		*****=*****=1280:0720.*	✓
			1280x768	VXX: *****=VXX: *****=1280:0768.*		*****=*****=1280:0768.*	✓
			1280x800	VXX: *****=VXX: *****=1280:0800.*		*****=*****=1280:0800.*	✓
			1280x1024	VXX: *****=VXX: *****=1280:1024.*		*****=*****=1280:1024.*	✓
			1366x768	VXX: *****=VXX: *****=1366:0768.*		*****=*****=1366:0768.*	✓
			1400x1050	VXX: *****=VXX: *****=1400:1050.*		*****=*****=1400:1050.*	✓
			1440x900	VXX: *****=VXX: *****=1440:0900.*		*****=*****=1440:0900.*	✓
			1600x900	VXX: *****=VXX: *****=1600:0900.*		*****=*****=1600:0900.*	✓
			1600x1200	VXX: *****=VXX: *****=1600:1200.*		*****=*****=1600:1200.*	✓
			1680x1050	VXX: *****=VXX: *****=1680:1050.*		*****=*****=1680:1050.*	✓
			1920x1080	VXX: *****=VXX: *****=1920:1080.*		*****=*****=1920:1080.*	✓
			1920x1200	VXX: *****=VXX: *****=1920:1200.*		*****=*****=1920:1200.*	✓
			1920x2160	VXX: *****=VXX: *****=1920:2160.*		*****=*****=1920:2160.*	✓
			2048x1080	VXX: *****=VXX: *****=2048:1080.*		*****=*****=2048:1080.*	✓
			2048x2160	VXX: *****=VXX: *****=2048:2160.*		*****=*****=2048:2160.*	✓
			2560x1600	VXX: *****=VXX: *****=2560:1600.*		*****=*****=2560:1600.*	✓
			3840x2400	VXX: *****=VXX: *****=3840:2400.*		*****=*****=3840:2400.*	✓
		* PARAMETER4	Progressive	VXX: *****=VXX: *****=*****.*:p		*****=*****=*****.*:p	✓
			Interlace	VXX: *****=VXX: *****=*****.*:i		*****=*****=*****.*:i	✓
	SLOT : HDMI : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: EDVI3=+*****		SLSS1=EDVI3=+*****	✓
			HDMI2	VXX: SLSS1=VXX: EDVI6=+*****		SLSS1=EDVI6=+*****	✓
			HDMI3	VXX: SLSS2=VXX: EDVI3=+*****		SLSS2=EDVI3=+*****	✓
			HDMI4	VXX: SLSS2=VXX: EDVI6=+*****		SLSS2=EDVI6=+*****	✓
		* PARAMETER3	60Hz	VXX: *****=VXX: *****=+06000		*****=*****=+06000	✓
			50Hz	VXX: *****=VXX: *****=+05000		*****=*****=+05000	✓
			48Hz	VXX: *****=VXX: *****=+04800		*****=*****=+04800	✓
			30Hz	VXX: *****=VXX: *****=+03000		*****=*****=+03000	✓
			25Hz	VXX: *****=VXX: *****=+02500		*****=*****=+02500	✓
			24Hz	VXX: *****=VXX: *****=+02400		*****=*****=+02400	✓
		* PARAMETER4	Progressive	VXX: *****=VXX: *****=*****.*:p		*****=*****=*****.*:p	✓
			Interlace	VXX: *****=VXX: *****=*****.*:i		*****=*****=*****.*:i	✓
	SLOT : HDMI : EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: *****=VXX: *****=*****.*:*****	QVX: *****=QVX: *****	*****=*****=*****.*:*****	✓
		* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: EDHS1=*****.*:*****		SLSS1=EDHS1=*****.*:*****	✓
			HDMI2	VXX: SLSS1=VXX: EDHS2=*****.*:*****		SLSS1=EDHS2=*****.*:*****	✓
			HDMI3	VXX: SLSS2=VXX: EDHS1=*****.*:*****		SLSS2=EDHS1=*****.*:*****	✓
			HDMI4	VXX: SLSS2=VXX: EDHS2=*****.*:*****		SLSS2=EDHS2=*****.*:*****	✓
		* PARAMETER3	1024x768	VXX: *****=VXX: *****=1024:0768.*:*****		*****=*****=1024:0768.*:*****	✓
			1280x720	VXX: *****=VXX: *****=1280:0720.*:*****		*****=*****=1280:0720.*:*****	✓
			1280x768	VXX: *****=VXX: *****=1280:0768.*:*****		*****=*****=1280:0768.*:*****	✓
			1280x800	VXX: *****=VXX: *****=1280:0800.*:*****		*****=*****=1280:0800.*:*****	✓
			1280x1024	VXX: *****=VXX: *****=1280:1024.*:*****		*****=*****=1280:1024.*:*****	✓
			1366x768	VXX: *****=VXX: *****=1366:0768.*:*****		*****=*****=1366:0768.*:*****	✓
			1400x1050	VXX: *****=VXX: *****=1400:1050.*:*****		*****=*****=1400:1050.*:*****	✓
			1440x900	VXX: *****=VXX: *****=1440:0900.*:*****		*****=*****=1440:0900.*:*****	✓
			1600x900	VXX: *****=VXX: *****=1600:0900.*:*****		*****=*****=1600:0900.*:*****	✓
			1600x1200	VXX: *****=VXX: *****=1600:1200.*:*****		*****=*****=1600:1200.*:*****	✓
			1680x1050	VXX: *****=VXX: *****=1680:1050.*:*****		*****=*****=1680:1050.*:*****	✓
			1920x1080	VXX: *****=VXX: *****=1920:1080.*:*****		*****=*****=1920:1080.*:*****	✓
			1920x1200	VXX: *****=VXX: *****=1920:1200.*:*****		*****=*****=1920:1200.*:*****	✓
			1920x2160	VXX: *****=VXX: *****=1920:2160.*:*****		*****=*****=1920:2160.*:*****	✓
			2048x1080	VXX: *****=VXX: *****=2048:1080.*:*****		*****=*****=2048:1080.*:*****	✓
			2048x2160	VXX: *****=VXX: *****=2048:2160.*:*****		*****=*****=2048:2160.*:*****	✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
		* PARAMETER4	2560x1600	VXX: *****=VXX: *****=2560:1600: *: ****		*****=*****=2560:1600: *: ****	✓
			3840x2400	VXX: *****=VXX: *****=3840:2400: *: ****		*****=*****=3840:2400: *: ****	✓
			Progressive	VXX: *****=VXX: *****=*****: p		*****=*****=*****: p	✓
			Interlace	VXX: *****=VXX: *****=*****: i		*****=*****=*****: i	✓
		* PARAMETERS5	60Hz	VXX: *****=VXX: *****=*****: *: 6000		*****=*****=*****: *: 6000	✓
			50Hz	VXX: *****=VXX: *****=*****: *: 5000		*****=*****=*****: *: 5000	✓
			48Hz	VXX: *****=VXX: *****=*****: *: 4800		*****=*****=*****: *: 4800	✓
			30Hz	VXX: *****=VXX: *****=*****: *: 3000		*****=*****=*****: *: 3000	✓
			25Hz	VXX: *****=VXX: *****=*****: *: 2500		*****=*****=*****: *: 2500	✓
			24Hz	VXX: *****=VXX: *****=*****: *: 2400		*****=*****=*****: *: 2400	✓
		* PARAMETER			QVX: *****=QVX: *****	*****=*****=*****: *: ****	✓
		* PARAMETER1, 2	HDMI1			SLSS1=ESHS1=*****: *: ****	✓
			HDMI2			SLSS1=ESHS2=*****: *: ****	✓
			HDMI3			SLSS2=ESHS1=*****: *: ****	✓
			HDMI4			SLSS2=ESHS2=*****: *: ****	✓
		* PARAMETER3	1024x768			*****=*****=1024:0768: *: ****	✓
			1280x720			*****=*****=1280:0720: *: ****	✓
			1280x768			*****=*****=1280:0768: *: ****	✓
			1280x800			*****=*****=1280:0800: *: ****	✓
			1280x1024			*****=*****=1280:1024: *: ****	✓
			1366x768			*****=*****=1366:0768: *: ****	✓
			1400x1050			*****=*****=1400:1050: *: ****	✓
			1440x900			*****=*****=1440:0900: *: ****	✓
			1600x900			*****=*****=1600:0900: *: ****	✓
			1600x1200			*****=*****=1600:1200: *: ****	✓
			1680x1050			*****=*****=1680:1050: *: ****	✓
			1920x1080			*****=*****=1920:1080: *: ****	✓
			1920x1200			*****=*****=1920:1200: *: ****	✓
			1920x2160			*****=*****=1920:2160: *: ****	✓
			2048x1080			*****=*****=2048:1080: *: ****	✓
			2048x2160			*****=*****=2048:2160: *: ****	✓
			2560x1600			*****=*****=2560:1600: *: ****	✓
			3840x2400			*****=*****=3840:2400: *: ****	✓
		* PARAMETER4	Progressive			*****=*****=*****: p: ****	✓
			Interlace			*****=*****=*****: i: ****	✓
		* PARAMETERS5	60Hz			*****=*****=*****: *: 6000	✓
			50Hz			*****=*****=*****: *: 5000	✓
			48Hz			*****=*****=*****: *: 4800	✓
			30Hz			*****=*****=*****: *: 3000	✓
			25Hz			*****=*****=*****: *: 2500	✓
			24Hz			*****=*****=*****: *: 2400	✓
	SLOT : DVI : SIGNAL LEVEL	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	DVI1	VXX: SLSS1=VXX: DVII0=+*****		SLSS1=DVII0=+*****	✓
			DVI2	VXX: SLSS1=VXX: DVII2=+*****		SLSS1=DVII2=+*****	✓
			DVI3	VXX: SLSS2=VXX: DVII0=+*****		SLSS2=DVII0=+*****	✓
			DVI4	VXX: SLSS2=VXX: DVII2=+*****		SLSS2=DVII2=+*****	✓
			QUAD LINK (DVI1+2+3+4)	VXX: SLDS1=VXX: DVQI1=+*****		SLDS1=DVQI1=+*****	✓
		* PARAMETER3	0-255(PC)	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			16-235	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓
			AUTO	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓
		* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
	SLOT : DVI : EDID SELECT	* PARAMETER1, 2	DVI1	VXX: SLSS1=VXX: DSLI1=+*****		SLSS1=DSLI1=+*****	✓
			DVI2	VXX: SLSS1=VXX: DSLI2=+*****		SLSS1=DSLI2=+*****	✓
			DVI3	VXX: SLSS2=VXX: DSLI1=+*****		SLSS2=DSLI1=+*****	✓
			DVI4	VXX: SLSS2=VXX: DSLI2=+*****		SLSS2=DSLI2=+*****	✓
		* PARAMETER3	EDID1:4K/60p	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			EDID2:4K/30p	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓
			EDID3:2K	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓
		* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
	SLOT : DVI : EDID MODE	* PARAMETER1, 2	DVI1	VXX: SLSS1=VXX: EDMI2=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
			DVI2	VXX: SLSS1=VXX: EDMI5=+*****		SLSS1=EDMI5=+*****	✓
			DVI3	VXX: SLSS2=VXX: EDMI2=+*****		SLSS2=EDMI2=+*****	✓
			DVI4	VXX: SLSS2=VXX: EDMI5=+*****		SLSS2=EDMI5=+*****	✓
		* PARAMETER3	DEFAULT	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			USER	VXX: *****=VXX: *****=+00010		*****=*****=+00010	✓
	SLOT : DVI : EDID RESOLUTION	* PARAMETER		VXX: *****=VXX: *****=*****: *	QVX: *****=QVX: *****	*****=*****=*****: *	✓
		* PARAMETER1, 2	DVI1	VXX: SLSS1=VXX: EDRS2=*****: *		SLSS1=EDRS2=*****: *	✓
			DVI2	VXX: SLSS1=VXX: EDRS5=*****: *		SLSS1=EDRS5=*****: *	✓
			DVI3	VXX: SLSS2=VXX: EDRS2=*****: *		SLSS2=EDRS2=*****: *	✓
			DVI4	VXX: SLSS2=VXX: EDRS5=*****: *		SLSS2=EDRS5=*****: *	✓
		* PARAMETER3	1024x768	VXX: *****=VXX: *****=1024:0768: *		*****=*****=1024:0768: *	✓
			1280x720	VXX: *****=VXX: *****=1280:0720: *		*****=*****=1280:0720: *	✓
			1280x768	VXX: *****=VXX: *****=1280:0768: *		*****=*****=1280:0768: *	✓
			1280x800	VXX: *****=VXX: *****=1280:0800: *		*****=*****=1280:0800: *	✓
			1280x1024	VXX: *****=VXX: *****=1280:1024: *		*****=*****=1280:1024: *	✓
			1366x768	VXX: *****=VXX: *****=1366:0768: *		*****=*****=1366:0768: *	✓
			1400x1050	VXX: *****=VXX: *****=1400:1050: *		*****=*****=1400:1050: *	✓
			1440x900	VXX: *****=VXX: *****=1440:0900: *		*****=*****=1440:0900: *	✓
			1600x900	VXX: *****=VXX: *****=1600:0900: *		*****=*****=1600:0900: *	✓
			1600x1200	VXX: *****=VXX: *****=1600:1200: *		*****=*****=1600:1200: *	✓
			1680x1050	VXX: *****=VXX: *****=1680:1050: *		*****=*****=1680:1050: *	✓
			1920x1080	VXX: *****=VXX: *****=1920:1080: *		*****=*****=1920:1080: *	✓
			1920x1200	VXX: *****=VXX: *****=1920:1200: *		*****=*****=1920:1200: *	✓
			1920x2160	VXX: *****=VXX: *****=1920:2160: *		*****=*****=1920:2160: *	✓
			2048x1080	VXX: *****=VXX: *****=2048:1080: *		*****=*****=2048:1080: *	✓
			2048x2160	VXX: *****=VXX: *****=2048:2160: *		*****=*****=2048:2160: *	✓
		* PARAMETER4	Progressive	VXX: *****=VXX: *****=*****: p		*****=*****=*****: p	✓
			Interlace	VXX: *****=VXX: *****=*****: i		*****=*****=*****: i	✓
	SLOT : DVI : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	DVI1	VXX: SLSS1=VXX: EDVI2=+*****		SLSS1=EDVI2=+*****	✓
			DVI2	VXX: SLSS1=VXX: EDVI5=+*****		SLSS1=EDVI5=+*****	✓
			DVI3	VXX: SLSS2=VXX: EDVI2=+*****		SLSS2=EDVI2=+*****	✓
			DVI4	VXX: SLSS2=VXX: EDVI5=+*****		SLSS2=EDVI5=+*****	✓
		* PARAMETER3	60Hz	VXX: *****=VXX: *****=+06000		*****=*****=+06000	✓
			50Hz	VXX: *****=VXX: *****=+05000		*****=*****=+05000	✓
			48Hz	VXX: *****=VXX: *****=+04800		*****=*****=+04800	✓
			30Hz	VXX: *****=VXX: *****=+03000		*****=*****=+03000	✓
			25Hz	VXX: *****=VXX: *****=+02500		*****=*****=+02500	✓
			24Hz	VXX: *****=VXX: *****=+02400		*****=*****=+02400	✓
		* PARAMETER4	Progressive	VXX: *****=VXX: *****=*****: p		*****=*****=*****: p	✓
			Interlace	VXX: *****=VXX: *****=*****: i		*****=*****=*****: i	✓
	SLOT : DVI : EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: *****=VXX: *****=*****: *: ****	QVX: *****=QVX: *****	*****=*****=*****: *: ****	✓
		* PARAMETER1, 2	DVI1	VXX: SLSS1=VXX: EDDS1=*****: *: ****		SLSS1=EDDS1=*****: *: ****	✓
			DVI2	VXX: SLSS1=VXX: EDDS2=*****: *: ****		SLSS1=EDDS2=*****: *: ****	✓
			DVI3	VXX: SLSS2=VXX: EDDS1=*****: *: ****		SLSS2=EDDS1=*****: *: ****	✓
			DVI4	VXX: SLSS2=VXX: EDDS2=*****: *: ****		SLSS2=EDDS2=*****: *: ****	✓
		* PARAMETER3	1024x768	VXX: *****=VXX: *****=1024:0768: *: ****		*****=*****=1024:0768: *: ****	✓
			1280x720	VXX: *****=VXX: *****=1280:0720: *: ****		*****=*****=1280:0720: *: ****	✓
			1280x768	VXX: *****=VXX: *****=1280:0768: *: ****		*****=*****=1280:0768: *: ****	✓
			1280x800	VXX: *****=VXX: *****=1280:0800: *: ****		*****=*****=1280:0800: *: ****	✓
			1280x1024	VXX: *****=VXX: *****=1280:1024: *: ****		*****=*****=1280:1024: *: ****	✓
			1366x768	VXX: *****=VXX: *****=1366:0768: *: ****		*****=*****=1366:0768: *: ****	✓
			1400x1050	VXX: *****=VXX: *****=1400:1050: *: ****		*****=*****=1400:1050: *: ****	✓
			1440x900	VXX: *****=VXX: *****=1440:0900: *: ****		*****=*****=1440:0900: *: ****	✓
		* PARAMETER4					
		* PARAMETER1, 2	DVI1	VXX: SLSS1=VXX: EDDS1=*****: *: ****		SLSS1=EDDS1=*****: *: ****	✓
			DVI2	VXX: SLSS1=VXX: EDDS2=*****: *: ****		SLSS1=EDDS2=*****: *: ****	✓
			DVI3	VXX: SLSS2=VXX: EDDS1=*****: *: ****		SLSS2=EDDS1=*****: *: ****	✓
			DVI4	VXX: SLSS2=VXX: EDDS2=*****: *: ****		SLSS2=EDDS2=*****: *: ****	✓
		* PARAMETER3	1024x768	VXX: *****=VXX: *****=1024:0768: *: ****		*****=*****=1024:0768: *: ****	✓
			1280x720	VXX: *****=VXX: *****=1280:0720: *: ****		*****=*****=1280:0720: *: ****	✓
			1280x768	VXX: *****=VXX: *****=1280:0768: *: ****		*****=*****=1280:0768: *: ****	✓
			1280x800	VXX: *****=VXX: *****=1280:0800: *: ****		*****=*****=1280:0800: *: ****	✓
			1280x1024	VXX: *****=VXX: *****=1280:1024: *: ****		*****=*****=1280:1024: *: ****	✓
			1366x768	VXX: *****=VXX: *****=1366:0768: *: ****		*****=*****=1366:0768: *: ****	✓
			1400x1050	VXX: *****=VXX: *****=1400:1050: *: ****		*****=*****=1400:1050: *: ****	✓
			1440x900	VXX: *****=VXX: *****=1440:0900: *: ****		*****=*****=1440:0900: *: ****	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ50K SERIES
				COMMANDS	COMMANDS	CALL BACK	
	SLOT : DVI : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETERS	1600x900	VXX: *****=VXX: *****=1600:0900: *: ****		*****=*****=1600:0900: *: ****	✓
			1600x1200	VXX: *****=VXX: *****=1600:1200: *: ****		*****=*****=1600:1200: *: ****	✓
			1680x1050	VXX: *****=VXX: *****=1680:1050: *: ****		*****=*****=1680:1050: *: ****	✓
			1920x1080	VXX: *****=VXX: *****=1920:1080: *: ****		*****=*****=1920:1080: *: ****	✓
			1920x1200	VXX: *****=VXX: *****=1920:1200: *: ****		*****=*****=1920:1200: *: ****	✓
			1920x2160	VXX: *****=VXX: *****=1920:2160: *: ****		*****=*****=1920:2160: *: ****	✓
			2048x1080	VXX: *****=VXX: *****=2048:1080: *: ****		*****=*****=2048:1080: *: ****	✓
			2048x2160	VXX: *****=VXX: *****=2048:2160: *: ****		*****=*****=2048:2160: *: ****	✓
		* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓ ✓
		* PARAMETERS5	60Hz	VXX: *****=VXX: *****=*****: *: 6000		*****=*****=*****: *: 6000	✓
			50Hz	VXX: *****=VXX: *****=*****: *: 5000		*****=*****=*****: *: 5000	✓
			48Hz	VXX: *****=VXX: *****=*****: *: 4800		*****=*****=*****: *: 4800	✓
			30Hz	VXX: *****=VXX: *****=*****: *: 3000		*****=*****=*****: *: 3000	✓
			25Hz	VXX: *****=VXX: *****=*****: *: 2500		*****=*****=*****: *: 2500	✓
			24Hz	VXX: *****=VXX: *****=*****: *: 2400		*****=*****=*****: *: 2400	✓
		* PARAMETER			QVX: *****=QVX: *****	*****=*****=*****: *: ****	✓
		* PARAMETER1, 2	DVI1			SLSS1=ESDS1=*****: *: ****	✓
			DVI2			SLSS1=ESDS2=*****: *: ****	✓
			DVI3			SLSS2=ESDS1=*****: *: ****	✓
			DVI4			SLSS2=ESDS2=*****: *: ****	✓
		* PARAMETER3	1024x768			*****=*****=1024:0768: *: ****	✓
			1280x720			*****=*****=1280:0720: *: ****	✓
			1280x768			*****=*****=1280:0768: *: ****	✓
			1280x800			*****=*****=1280:0800: *: ****	✓
			1280x1024			*****=*****=1280:1024: *: ****	✓
			1366x768			*****=*****=1366:0768: *: ****	✓
			1400x1050			*****=*****=1400:1050: *: ****	✓
			1440x900			*****=*****=1440:0900: *: ****	✓
			1600x900			*****=*****=1600:0900: *: ****	✓
			1600x1200			*****=*****=1600:1200: *: ****	✓
			1680x1050			*****=*****=1680:1050: *: ****	✓
			1920x1080			*****=*****=1920:1080: *: ****	✓
			1920x1200			*****=*****=1920:1200: *: ****	✓
			1920x2160			*****=*****=1920:2160: *: ****	✓
			2048x1080			*****=*****=2048:1080: *: ****	✓
			2048x2160			*****=*****=2048:2160: *: ****	✓
		* PARAMETER4	Progressive Interlace			*****=*****=*****: p: **** *****=*****=*****: i: ****	✓ ✓
		* PARAMETERS5	60Hz			*****=*****=*****: *: 6000	✓
			50Hz			*****=*****=*****: *: 5000	✓
			48Hz			*****=*****=*****: *: 4800	✓
			30Hz			*****=*****=*****: *: 3000	✓
			25Hz			*****=*****=*****: *: 2500	✓
			24Hz			*****=*****=*****: *: 2400	✓
	SLOT : DisplayPort : SIGNAL LEVEL	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: DPLI1=+*****		SLSS1=DPLI1=+*****	✓
			DisplayPort2	VXX: SLSS1=VXX: DPLI2=+*****		SLSS1=DPLI2=+*****	✓
			DisplayPort3	VXX: SLSS2=VXX: DPLI1=+*****		SLSS2=DPLI1=+*****	✓
			DisplayPort4	VXX: SLSS2=VXX: DPLI2=+*****		SLSS2=DPLI2=+*****	✓
		* PARAMETER3	0-1023	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			64-940	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓
			AUTO	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓
	SLOT : DisplayPort : AUTO GAMMA SELECT	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: DAGI1=+*****		SLSS1=DAGI1=+*****	✓
			DisplayPort2	VXX: SLSS1=VXX: DAGI2=+*****		SLSS1=DAGI2=+*****	✓
			DisplayPort3	VXX: SLSS2=VXX: DAGI1=+*****		SLSS2=DAGI1=+*****	✓
			DisplayPort4	VXX: SLSS2=VXX: DAGI2=+*****		SLSS2=DAGI2=+*****	✓
		* PARAMETER3	DISABLE	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			ENABLE	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓
	SLOT : DisplayPort : AUTO COLOR SPACE SELECT	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: DACI1=+*****		SLSS1=DACI1=+*****	✓
			DisplayPort2	VXX: SLSS1=VXX: DACI2=+*****		SLSS1=DACI2=+*****	✓
			DisplayPort3	VXX: SLSS2=VXX: DACI1=+*****		SLSS2=DACI1=+*****	✓
			DisplayPort4	VXX: SLSS2=VXX: DACI2=+*****		SLSS2=DACI2=+*****	✓
		* PARAMETER3	DISABLE	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			ENABLE	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓
	SLOT : DisplayPort : EDID MODE	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDMI8=+*****		SLSS1=EDMI8=+*****	✓
			DisplayPort2	VXX: SLSS1=VXX: EDMI9=+*****		SLSS1=EDMI9=+*****	✓
			DisplayPort3	VXX: SLSS2=VXX: EDMI8=+*****		SLSS2=EDMI8=+*****	✓
			DisplayPort4	VXX: SLSS2=VXX: EDMI9=+*****		SLSS2=EDMI9=+*****	✓
		* PARAMETER3	DEFAULT	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓
			USER	VXX: *****=VXX: *****=+00010		*****=*****=+00010	✓
	SLOT : DisplayPort : EDID RESOLUTION	* PARAMETER		VXX: *****=VXX: *****=*****: *	QVX: *****=QVX: *****	*****=*****=*****: *	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDRS8=*****: *		SLSS1=EDRS8=*****: *	✓
			DisplayPort2	VXX: SLSS1=VXX: EDRS9=*****: *		SLSS1=EDRS9=*****: *	✓
			DisplayPort3	VXX: SLSS2=VXX: EDRS8=*****: *		SLSS2=EDRS8=*****: *	✓
			DisplayPort4	VXX: SLSS2=VXX: EDRS9=*****: *		SLSS2=EDRS9=*****: *	✓
		* PARAMETER3	1024x768	VXX: *****=VXX: *****=1024:0768: *		*****=*****=1024:0768: *	✓
			1280x720	VXX: *****=VXX: *****=1280:0720: *		*****=*****=1280:0720: *	✓
			1280x800	VXX: *****=VXX: *****=1280:0800: *		*****=*****=1280:0800: *	✓
			1400x1050	VXX: *****=VXX: *****=1400:1050: *		*****=*****=1400:1050: *	✓
			1600x900	VXX: *****=VXX: *****=1600:0900: *		*****=*****=1600:0900: *	✓
			1600x1200	VXX: *****=VXX: *****=1600:1200: *		*****=*****=1600:1200: *	✓
			1920x1080	VXX: *****=VXX: *****=1920:1080: *		*****=*****=1920:1080: *	✓
			1920x1200	VXX: *****=VXX: *****=1920:1200: *		*****=*****=1920:1200: *	✓
			2048x1080	VXX: *****=VXX: *****=2048:1080: *		*****=*****=2048:1080: *	✓
			2560x1600	VXX: *****=VXX: *****=2560:1600: *		*****=*****=2560:1600: *	✓
			3840x2400	VXX: *****=VXX: *****=3840:2400: *		*****=*****=3840:2400: *	✓
		* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓ ✓
	SLOT : DisplayPort : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDVI8=+*****		SLSS1=EDVI8=+*****	✓
			DisplayPort2	VXX: SLSS1=VXX: EDVI9=+*****		SLSS1=EDVI9=+*****	✓
			DisplayPort3	VXX: SLSS2=VXX: EDVI8=+*****		SLSS2=EDVI8=+*****	✓
			DisplayPort4	VXX: SLSS2=VXX: EDVI9=+*****		SLSS2=EDVI9=+*****	✓
		* PARAMETER3	60Hz	VXX: *****=VXX: *****=+06000		*****=*****=+06000	✓
			50Hz	VXX: *****=VXX: *****=+05000		*****=*****=+05000	✓
			48Hz	VXX: *****=VXX: *****=+04800		*****=*****=+04800	✓
			30Hz	VXX: *****=VXX: *****=+03000		*****=*****=+03000	✓
			25Hz	VXX: *****=VXX: *****=+02500		*****=*****=+02500	✓
			24Hz	VXX: *****=VXX: *****=+02400		*****=*****=+02400	✓
		* PARAMETER		VXX: *****=VXX: *****=*****: *: ****	QVX: *****=QVX: *****	*****=*****=*****: *: ****	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDPS1=*****: *: ****		SLSS1=EDPS1=*****: *: ****	✓
			DisplayPort2	VXX: SLSS1=VXX: EDPS2=*****: *: ****		SLSS1=EDPS2=*****: *: ****	✓
			DisplayPort3	VXX: SLSS2=VXX: EDPS1=*****: *: ****		SLSS2=EDPS1=*****: *: ****	✓
			DisplayPort4	VXX: SLSS2=VXX: EDPS2=*****: *: ****		SLSS2=EDPS2=*****: *: ****	✓
	SLOT : DisplayPort : EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER3	1024x768	VXX: *****=VXX: *****=1024:0768: *: ****		*****=*****=1024:0768: *: ****	✓
			1280x720	VXX: *****=VXX: *****=1280:0720: *: ****		*****=*****=1280:0720: *: ****	✓
			1280x800	VXX: *****=VXX: *****=1280:0800: *: ****		*****=*****=1280:0800: *: ****	✓
			1400x1050	VXX: *****=VXX: *****=1400:1050: *: ****		*****=*****=1400:1050: *: ****	✓
			1600x900	VXX: *****=VXX: *****=1600:0900: *: ****		*****=*****=1600:0900: *: ****	✓
			1600x1200	VXX: *****=VXX: *****=1600:1200: *: ****		*****=*****=1600:1200: *: ****	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ50K SERIES
				COMMANDS	COMMANDS	CALL BACK	
	SLOT : DisplayPort : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY		1920x1080	VXX:*****=VXX:*****=1920:1080:*.****		*****=*****=1920:1080:*.****	✓
			1920x1200	VXX:*****=VXX:*****=1920:1200:*.****		*****=*****=1920:1200:*.****	✓
			2048x1080	VXX:*****=VXX:*****=2048:1080:*.****		*****=*****=2048:1080:*.****	✓
			2560x1600	VXX:*****=VXX:*****=2560:1600:*.****		*****=*****=2560:1600:*.****	✓
			3840x2400	VXX:*****=VXX:*****=3840:2400:*.****		*****=*****=3840:2400:*.****	✓
		* PARAMETER4	Progressive	VXX:*****=VXX:*****=*****.p		*****=*****=*****.p	✓
			Interlace	VXX:*****=VXX:*****=*****.i		*****=*****=*****.i	✓
		* PARAMETERS5	60Hz	VXX:*****=VXX:*****=*****.*:6000		*****=*****=*****.*:6000	✓
			50Hz	VXX:*****=VXX:*****=*****.*:5000		*****=*****=*****.*:5000	✓
			48Hz	VXX:*****=VXX:*****=*****.*:4800		*****=*****=*****.*:4800	✓
			30Hz	VXX:*****=VXX:*****=*****.*:3000		*****=*****=*****.*:3000	✓
			25Hz	VXX:*****=VXX:*****=*****.*:2500		*****=*****=*****.*:2500	✓
			24Hz	VXX:*****=VXX:*****=*****.*:2400		*****=*****=*****.*:2400	✓
	SLOT : DisplayPort : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX:*****=QVX:*****	*****=*****=*****.*:****	✓
		* PARAMETER1, 2	DisplayPort1			SLSS1=ESPS1=*****.*:****	✓
			DisplayPort2			SLSS1=ESPS2=*****.*:****	✓
			DisplayPort3			SLSS2=ESPS1=*****.*:****	✓
			DisplayPort4			SLSS2=ESPS2=*****.*:****	✓
		* PARAMETER3	1024x768			*****=*****=1024:0768:*.****	✓
			1280x720			*****=*****=1280:0720:*.****	✓
			1280x800			*****=*****=1280:0800:*.****	✓
			1400x1050			*****=*****=1400:1050:*.****	✓
			1600x900			*****=*****=1600:0900:*.****	✓
			1600x1200			*****=*****=1600:1200:*.****	✓
			1920x1080			*****=*****=1920:1080:*.****	✓
			1920x1200			*****=*****=1920:1200:*.****	✓
			2048x1080			*****=*****=2048:1080:*.****	✓
			2560x1600			*****=*****=2560:1600:*.****	✓
			3840x2400			*****=*****=3840:2400:*.****	✓
		* PARAMETER4	Progressive			*****=*****=*****.p:****	✓
			Interlace			*****=*****=*****.i:****	✓
		* PARAMETERS5	60Hz			*****=*****=*****.*:6000	✓
			50Hz			*****=*****=*****.*:5000	✓
			48Hz			*****=*****=*****.*:4800	✓
			30Hz			*****=*****=*****.*:3000	✓
			25Hz			*****=*****=*****.*:2500	✓
			24Hz			*****=*****=*****.*:2400	✓
	MULTI PROJECTOR SYNC - MODE	OFF		VXX:MPSI1=+00000	QYX:MPSI1	MPSI1=+00000	✓
		MASTER		VXX:MPSI1=+00001		MPSI1=+00001	✓
		SLAVE		VXX:MPSI1=+00002		MPSI1=+00002	✓
	FRAME SYNC SETTING(MULTI PROJECTOR SYNC) - CONTRAST	OFF		VXX:CSYI1=+00000	QVX:CSYI1	CSYI1=+00000	✓
		ON		VXX:CSYI1=+00001		CSYI1=+00001	✓
	MULTI PROJECTOR SYNC - SHUTTER SYNC.	OFF		VXX:SSYI1=+00000	QVX:SSYI1	SSYI1=+00000	✓
		ON		VXX:SSYI1=+00001		SSYI1=+00001	✓
	INPUT GUIDE	OFF		OID:0	QDI	0	✓
		ON (SIMPLE)		OID:1		1	✓
	OSD POSITION	UPPER LEFT		ODP:1	QDP	1	✓
		CETRE LEFT		ODP:2		2	✓
		LOWER LEFT		ODP:3		3	✓
		TOP CENTER		ODP:4		4	✓
		CENTER		ODP:5		5	✓
		LOEER CENTER		ODP:6		6	✓
		UPPER RIGHT		ODP:7		7	✓
		CENTER RIGHT		ODP:8		8	✓
		LOWER RIGHT		ODP:9		9	✓
	OSD ROTATION	OFF		VXX:OSRI1=+00000	QVX:OSRI1	OSRI1=+00000	✓
		CLOCKWISE		VXX:OSRI1=+00001		OSRI1=+00001	✓
		COUNTER CLOCKWISE		VXX:OSRI1=+00002		OSRI1=+00002	✓
	OSD MEMORY	OFF		VXX:OMYI0=+00000	QVX:OMYI0	OMYI0=+00000	✓
		ON		VXX:OMYI0=+00001		OMYI0=+00001	✓
	ON SCREEN	OFF		OOS:0	QOS	0	✓
		ON		OOS:1		1	✓
	WARNING MESSAGE	OFF		VXX:WMDI0=+00000	QVX:WMDI0	WMDI0=+00000	✓
		ON		VXX:WMDI0=+00001		WMDI0=+00001	✓
	OSD DESIGN	1(YELLOW)		MOD:0	QOD	0	✓
		2(BLUE)		MOD:1		1	✓
		3(WHITE)		MOD:2		2	✓
		4(GREEN)		MOD:3		3	✓
		5(Peach)		MOD:4		4	✓
		6(BROWN)		MOD:5		5	✓
	MENU MODE	NORMAL		VXX:MMDI1=+00000	QVX:MMDI1	MMDI1=+00000	✓
		SIMPLE		VXX:MMDI1=+00001		MMDI1=+00001	✓
	SCREEN SETTING	16:10		VSF:0	QSF	0	✓
		16:9		VSF:1		1	✓
		4:3		VSF:2		2	✓
		17:9		VSF:3		3	✓
	SCREEN POSITION-VERTICAL	min.		VXX:VSPI0=-.00120	QVX:VSPI0	VSPI0=-.00120	-120
		max.		VXX:VSPI0=+00120		VSPI0=+00120	120
	SCREEN POSITION-HOROZONTAL	min.		VXX:HSPI0=-.00320	QVX:HSPI0	HSPI0=-.00320	-320
		max.		VXX:HSPI0=+00320		HSPI0=+00320	320
	STARTUP LOGO	OFF		MLO:0	QLO	0	✓
		USER LOGO		MLO:1		1	✓
		DEFAULT LOGO		MLO:2		2	✓
	UNIFORMITY-FLEXIBLE CORRECTION *	OFF		VXX:UFMI1=+00000	QVX:UFMI1	UFMI1=+00000	✓
		ON(PRE)		VXX:UFMI1=+00011		UFMI1=+00011	✓
		ON(POST)		VXX:UFMI1=+00021		UFMI1=+00021	✓
	UNIFORMITY-INITILIZE	EXECUTE		VXX:UFMI2=+00001			✓
	UNIFORMITY-MODE	CHROMA ONLY		VXX:UFMI3=+00001	QVX:UFMI3	UFMI3=+00001	✓
		LUMINACE/CHROMA		VXX:UFMI3=+00011		UFMI3=+00011	✓
	UNIFORMITY- WHITE/RED/GREEN/RED	* PARAMETER		E\$W:*,****,****,**	E\$R:*,**	*,****,****	✓
		* PARAMETER 1	WHITE	E\$W:W,****,****,**	E\$R:W,**	*,****,****	✓
			RED	E\$W:R,****,****,**	E\$R:R,**	*,****,****	✓
			GREEN	E\$W:G,****,****,**	E\$R:G,**	*,****,****	✓
			BLUE	E\$W:B,****,****,**	E\$R:B,**	*,****,****	✓
		* PARAMETER 2	VERTICAL(-127)	E\$W:*, -127, ****, **	E\$R:*, **	*, -127, ****	✓
			VERTICAL(+127)	E\$W:*, +127, ****, **	E\$R:*, **	*, +127, ****	✓
		* PARAMETER 3	HORIZONTAL(-127)	E\$W:*, ****, -127, **	E\$R:*, **	*, ****, -127	✓
			HOROZONTAL(+127)	E\$W:*, ****, +127, **	E\$R:*, **	*, ****, +127	✓
		* PARAMETER 4	L1(OFF)	E\$W:*, ****, ****, 0*	E\$R:*, 0*	0*, ****, ****	✓
			L1(ON)	E\$W:*, ****, ****, 1*	E\$R:*, 1*	1*, ****, ****	✓
			L2(OFF)	E\$W:*, ****, ****, *0	E\$R:*, *0	*0, ****, ****	✓
			L2(ON)	E\$W:*, ****, ****, *1	E\$R:*, *1	*1, ****, ****	✓
	SHUTTER SETTING-FADE IN	0.0s(OFF)		VXX:SEFS1=0.0	QVX:SEFS1	SEFS1=0.0	✓
		0.5s		VXX:SEFS1=0.5		SEFS1=0.5	✓
		1.0s		VXX:SEFS1=1.0		SEFS1=1.0	✓
		1.5s		VXX:SEFS1=1.5		SEFS1=1.5	✓
		2.0s		VXX:SEFS1=2.0		SEFS1=2.0	✓
		2.5s		VXX:SEFS1=2.5		SEFS1=2.5	✓
		3.0s		VXX:SEFS1=3.0		SEFS1=3.0	✓
		3.5s		VXX:SEFS1=3.5		SEFS1=3.5	✓
		4.0s		VXX:SEFS1=4.0		SEFS1=4.0	✓
		5.0s		VXX:SEFS1=5.0		SEFS1=5.0	✓
		7.0s		VXX:SEFS1=7.0		SEFS1=7.0	✓
		10.0s		VXX:SEFS1=10.0		SEFS1=10.0	✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
	SHUTTER SETTING-FADE OUT	0.0s(OFF)		VXX:SEFS2=0.0	QVX:SEFS2	SEFS2=0.0	✓
		0.5s		VXX:SEFS2=0.5		SEFS2=0.5	✓
		1.0s		VXX:SEFS2=1.0		SEFS2=1.0	✓
		1.5s		VXX:SEFS2=1.5		SEFS2=1.5	✓
		2.0s		VXX:SEFS2=2.0		SEFS2=2.0	✓
		2.5s		VXX:SEFS2=2.5		SEFS2=2.5	✓
		3.0s		VXX:SEFS2=3.0		SEFS2=3.0	✓
		3.5s		VXX:SEFS2=3.5		SEFS2=3.5	✓
		4.0s		VXX:SEFS2=4.0		SEFS2=4.0	✓
		5.0s		VXX:SEFS2=5.0		SEFS2=5.0	✓
		7.0s		VXX:SEFS2=7.0		SEFS2=7.0	✓
		10.0s		VXX:SEFS2=10.0		SEFS2=10.0	✓
	SHUTTER SETTING -MECHANICAL SHUTTER	DISABLE		VXX:SEFI5=+00000	QVX:SEFI5	SEFS5=+00000	✓
		ENABLE		VXX:SEFI5=+00001		SEFS5=+00001	✓
	SHUTTER SETTING-STARTUP	OPEN		VXX:SEFI3=+00000	QVX:SEFI3	SEFI3=+00000	✓
		CLOSE		VXX:SEFI3=+00001		SEFI3=+00001	✓
	SHUTTER SETTING-SHUT OFF	OPEN		VXX:SEFI4=+00000	QVX:SEFI4	SEFI4=+00000	✓
		CLOSE		VXX:SEFI4=+00001		SEFI4=+00001	✓
		KEEP CURRENT STATE		VXX:SEFI4=+00002		SEFI4=+00002	✓
	BACK COLOR	BLUE		OBC:0	QBC	0	✓
		BLACK		OBC:1		1	✓
		USER LOGO		OBC:2		2	✓
		DEFAULT LOGO		OBC:3		3	✓
	WAVEFORM MONITOR	OFF		OWM:0	QWM	0	✓
		LUMINANCE		OWM:5		5	✓
		RED		OWM:6		6	✓
		GREEN		OWM:7		7	✓
		BLUE		OWM:8		8	✓
	WAVEFORM MONITOR-LINE ADJ.	0		VXX:WMLI0=+00000	QVX:WMLI0	WMLI0=+00000	✓
		+2159		VXX:WMLI0=+02159		WMLI0=+02159	✓
	AC VOLTAGE				QVX:VM0I2	VM0I2=+00000 VM0I2=+99999	✓ ✓
	CUT OFF-RED	OFF		VXX:CUTI1=+00000	QVX:CUTI1	CUTI1=+00000	✓
		ON		VXX:CUTI1=+00001		CUTI1=+00001	✓
	CUT OFF-GREEN	OFF		VXX:CUTI2=+00000	QVX:CUTI2	CUTI2=+00000	✓
		ON		VXX:CUTI2=+00001		CUTI2=+00001	✓
	CUT OFF-BLUE	OFF		VXX:CUTI3=+00000	QVX:CUTI3	CUTI3=+00000	✓
		ON		VXX:CUTI3=+00001		CUTI3=+00001	✓
	PROJECTOR ID	0(ALL)		RIS:00			✓
		64		RIS:64			✓
	ID ALL	OFF		RVS:0	QVY	0	✓
		ON		RVS:1		1	✓
	PROJECTION METHOD INSTALLATION	FRONT/DESK		OIL:0	QSP	0	✓
		REAR/DESK		OIL:1		1	✓
		FRONT/CEILING		OIL:2		2	✓
		REAR/CEILING		OIL:3		3	✓
		FRONT/AUTO		OIL:4		4	✓
		REAR/AUTO		OIL:5		5	✓
	AUTO COOLING CONDITION- STATUS	FLOOR			QVX:ADRI1	ADRI1=+00000	✓
		CEILING				ADRI1=+00001	✓
		VERTICAL UP				ADRI1=+00002	✓
		VERTICAL DOWN				ADRI1=+00003	✓
		PORTRAIT				ADRI1=+00004	✓
	OPERATING MODE	NORMAL		VXX:OPEI1=+00000	QVX:OPEI1	OPEI1=+00000	✓
		ECO		VXX:OPEI1=+00001		OPEI1=+00001	✓
		USER1(USER)		VXX:OPEI1=+00101		OPEI1=+00101	✓
		USER2		VXX:OPEI1=+00102		OPEI1=+00102	✓
		USER3		VXX:OPEI1=+00103		OPEI1=+00103	✓
	LIGHT OUTPUT	min.		VXX:LOPI2=+00050	QVX:LOPI2	LOPI2=+00050	8%
		max.		VXX:LOPI2=+01000		LOPI2=+01000	100%
	MAX LIGHT OUTPUT	min.		VXX:LOPI3=+00050	QVX:LOPI3	LOPI3=+00050	8%
		max.		VXX:LOPI3=+01000		LOPI3=+01000	100%
	BRIGHTNESS CONTROL-SETUP- CONSTANT MODE	OFF		VXX:BCMI0=+00000	QVX:BCMI0	BCMI0=+00000	✓
		AUTO		VXX:BCMI0=+00001		BCMI0=+00001	✓
		PC		VXX:BCMI0=+00002		BCMI0=+00002	✓
	BRIGHTNESS CONTROL-SETUP- LINK	OFF		VXX:BCLI0=+00000	QVX:BCLI0	BCLI0=+00000	✓
		GROUP A		VXX:BCLI0=+00001		BCLI0=+00001	✓
		GROUP B		VXX:BCLI0=+00002		BCLI0=+00002	✓
		GROUP C		VXX:BCLI0=+00003		BCLI0=+00003	✓
		GROUP D		VXX:BCLI0=+00004		BCLI0=+00004	✓
	BRIGHTNESS CONTROL-SETUP APPLY SCHEDULE	APPLY		VXX:BCSI0=+00001			✓
		OFF		VXX:SCHI0=+00000	QVX:SCHI0	SCHI0=+00000	✓
	SCHEDLE-PROGRAM ASSIGN	ON		VXX:SCHI0=+00001		SCHI0=+00001	✓
		OFF		VXX:SPGI*=+00000	QVX:SPGI*	SPGI*=+00000	✓
		PROGRAM1		VXX:SPGI*=+00001		SPGI*=+00001	✓
		PROGRAM2		VXX:SPGI*=+00002		SPGI*=+00002	✓
		PROGRAM3		VXX:SPGI*=+00003		SPGI*=+00003	✓
		PROGRAM4		VXX:SPGI*=+00004		SPGI*=+00004	✓
		PROGRAM5		VXX:SPGI*=+00005		SPGI*=+00005	✓
		PROGRAM6		VXX:SPGI*=+00006		SPGI*=+00006	✓
		PROGRAM7		VXX:SPGI*=+00007		SPGI*=+00007	✓
		* PARAMETER	SUN	VXX:SPGI0=+0000*	QVX:SPGI0	SPGI0=+0000*	✓
			MON	VXX:SPGI1=+0000*	QVX:SPGI1	SPGI1=+0000*	✓
			TUE	VXX:SPGI2=+0000*	QVX:SPGI2	SPGI2=+0000*	✓
			WED	VXX:SPGI3=+0000*	QVX:SPGI3	SPGI3=+0000*	✓
			THU	VXX:SPGI4=+0000*	QVX:SPGI4	SPGI4=+0000*	✓
			FRI	VXX:SPGI5=+0000*	QVX:SPGI5	SPGI5=+0000*	✓
			SAT	VXX:SPGI6=+0000*	QVX:SPGI6	SPGI6=+0000*	✓
	SCHEDULE-COMMAND SETTING	COMMAND Del		VXX:SCCS*=**00****	QVX:SCCS*=**	SCCS*=**00****	✓
		STANDBY		VXX:SCCS*=**10****		SCCS*=**10****	✓
		POWER ON		VXX:SCCS*=**11****		SCCS*=**11****	✓
		SHUTTER OPEN		VXX:SCCS*=**20****		SCCS*=**20****	✓
		SHUTTER CLOSE		VXX:SCCS*=**21****		SCCS*=**21****	✓
		SLOT1-1 INPUT		VXX:SCCS*=**68****		SCCS*=**68****	✓
		SLOT1-2 INPUT		VXX:SCCS*=**69****		SCCS*=**69****	✓
		SLOT2-3 INPUT		VXX:SCCS*=**6A****		SCCS*=**6A****	✓
		SLOT2-4 INPUT		VXX:SCCS*=**6B****		SCCS*=**6B****	✓
		SLOT1-3 INPUT		VXX:SCCS*=**6C****		SCCS*=**6C****	✓
		SLOT1-4 INPUT		VXX:SCCS*=**6D****		SCCS*=**6D****	✓
		SLOT2-1 INPUT		VXX:SCCS*=**6E****		SCCS*=**6E****	✓
		SLOT2-2 INPUT		VXX:SCCS*=**6F****		SCCS*=**6F****	✓
		NORMAL		VXX:SCCS*=**70****		SCCS*=**70****	✓
		ECO		VXX:SCCS*=**71****		SCCS*=**71****	✓
		USER1(USER)		VXX:SCCS*=**75****		SCCS*=**75****	✓
		USER2		VXX:SCCS*=**76****		SCCS*=**76****	✓
		USER3		VXX:SCCS*=**77****		SCCS*=**77****	✓
		DIGITAL LINK		VXX:SCCS*=**B0****		SCCS*=**B0****	✓
		INPUT 1		VXX:SCCS*=**B1****		SCCS*=**B1****	✓
		INPUT 2		VXX:SCCS*=**B2****		SCCS*=**B2****	✓
		INPUT 3		VXX:SCCS*=**B3****		SCCS*=**B3****	✓
		INPUT 4		VXX:SCCS*=**B4****		SCCS*=**B4****	✓
		INPUT 5		VXX:SCCS*=**B5****		SCCS*=**B5****	✓
		INPUT 6		VXX:SCCS*=**B6****		SCCS*=**B6****	✓
		INPUT 7		VXX:SCCS*=**B7****		SCCS*=**B7****	✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
PROJECTOR SETUP		INPUT 8		VXX:SCCS*==**B8****		SCCS*==**B8****	✓
		INPUT 9		VXX:SCCS*==**B9****		SCCS*==**B9****	✓
		INPUT 10		VXX:SCCS*==**BA****		SCCS*==**BA****	✓
		* PARAMETER1	PROGRAM1	VXX:SCCS1=*****	QVX:SCCS1=**	SCCS1=*****	✓
			PROGRAM2	VXX:SCCS2=*****	QVX:SCCS2=**	SCCS2=*****	✓
			PROGRAM3	VXX:SCCS3=*****	QVX:SCCS3=**	SCCS3=*****	✓
			PROGRAM4	VXX:SCCS4=*****	QVX:SCCS4=**	SCCS4=*****	✓
			PROGRAM5	VXX:SCCS5=*****	QVX:SCCS5=**	SCCS5=*****	✓
			PROGRAM6	VXX:SCCS6=*****	QVX:SCCS6=**	SCCS6=*****	✓
			PROGRAM7	VXX:SCCS7=*****	QVX:SCCS7=**	SCCS7=*****	✓
		* PARAMETER2	COMMAND 1	VXX:SCCS*=01*****	QVX:SCCS*=01	SCCS*=01*****	✓
			COMMAND 16	VXX:SCCS*=16*****	QVX:SCCS*=16	SCCS*=16*****	✓
		* PARAMETER3	00:00	VXX:SCCS*==***0000		SCCS*==***0000	✓
			23:59	VXX:SCCS*==***2359		SCCS*==***2359	✓
	STARTUP INPUT SELECT	DIGITAL LINK		VXX:SISS1=DL1	QVX:SISS1	SISS1=DL1	✓
		SLOT1 : SDI1		VXX:SISS1=AU1, SD1		SISS1=AU1, SD1	✓
		SLOT1 : SDI2		VXX:SISS1=AU1, SD2		SISS1=AU1, SD2	✓
		SLOT1 : SDI3		VXX:SISS1=AU1, SD3		SISS1=AU1, SD3	✓
		SLOT1 : SDI4		VXX:SISS1=AU1, SD4		SISS1=AU1, SD4	✓
		SLOT2 : SDI1		VXX:SISS1=AU2, SD1		SISS1=AU2, SD1	✓
		SLOT2 : SDI2		VXX:SISS1=AU2, SD2		SISS1=AU2, SD2	✓
		SLOT2 : SDI3		VXX:SISS1=AU2, SD3		SISS1=AU2, SD3	✓
		SLOT2 : SDI4		VXX:SISS1=AU2, SD4		SISS1=AU2, SD4	✓
		SLOT1 : HDMI1		VXX:SISS1=AU1, HD1		SISS1=AU1, HD1	✓
		SLOT1 : HDMI2		VXX:SISS1=AU1, HD2		SISS1=AU1, HD2	✓
		SLOT2 : HDMI3		VXX:SISS1=AU2, HD3		SISS1=AU2, HD3	✓
		SLOT2 : HDMI4		VXX:SISS1=AU2, HD4		SISS1=AU2, HD4	✓
		SLOT1 : DVI1		VXX:SISS1=AU1, DV1		SISS1=AU1, DV1	✓
		SLOT1 : DVI2		VXX:SISS1=AU1, DV2		SISS1=AU1, DV2	✓
		SLOT2 : DVI3		VXX:SISS1=AU2, DV3		SISS1=AU2, DV3	✓
		SLOT2 : DVI4		VXX:SISS1=AU2, DV4		SISS1=AU2, DV4	✓
		SLOT1 : DisplayPort1		VXX:SISS1=AU1, DP1		SISS1=AU1, DP1	✓
		SLOT1 : DisplayPort2		VXX:SISS1=AU1, DP2		SISS1=AU1, DP2	✓
		SLOT2 : DisplayPort3		VXX:SISS1=AU2, DP3		SISS1=AU2, DP3	✓
		SLOT2 : DisplayPort4		VXX:SISS1=AU2, DP4		SISS1=AU2, DP4	✓
		LAST USED		VXX:SISS1=LSU		SISS1=LSU	✓
	STARTUP INPUT SELECT (DIGITAL LINK)	LAST USED		VXX:SISI2=+00000	QVX:SISI2	SISI2=+00000	✓
		INPUT1		VXX:SISI2=+00001		SISI2=+00001	✓
		INPUT2		VXX:SISI2=+00002		SISI2=+00002	✓
		INPUT3		VXX:SISI2=+00003		SISI2=+00003	✓
		INPUT4		VXX:SISI2=+00004		SISI2=+00004	✓
		INPUT5		VXX:SISI2=+00005		SISI2=+00005	✓
		INPUT6		VXX:SISI2=+00006		SISI2=+00006	✓
		INPUT7		VXX:SISI2=+00007		SISI2=+00007	✓
		INPUT8		VXX:SISI2=+00008		SISI2=+00008	✓
		INPUT9		VXX:SISI2=+00009		SISI2=+00009	✓
		INPIT10		VXX:SISI2=+00010		SISI2=+00010	✓
	NO SIGNAL SHUT-OFF	DISABLE		OAF:00	QAF	00	✓
		10min		OAF:10		10	✓
		20min		OAF:20		20	✓
		30min		OAF:30		30	✓
		40min		OAF:40		40	✓
		50min		OAF:50		50	✓
		60min		OAF:60		60	✓
		70min		OAF:70		70	✓
		80min		OAF:80		80	✓
		90min		ODR:90		90	✓
	NO SIGNAL LIGHTS-OUT	DISABLE		VXX:SLOI1=+00000	QVX:SLOI1	SLOI1=+00000	✓
		10SEC.		VXX:SLOI1=+00010		SLOI1=+00010	✓
		20SEC.		VXX:SLOI1=+00020		SLOI1=+00020	✓
		30SEC.		VXX:SLOI1=+00030		SLOI1=+00030	✓
		1MIN.		VXX:SLOI1=+00060		SLOI1=+00060	✓
		2MIN.		VXX:SLOI1=+00120		SLOI1=+00120	✓
		3MIN.		VXX:SLOI1=+00180		SLOI1=+00180	✓
		5MIN.		VXX:SLOI1=+00300		SLOI1=+00300	✓
	NO SIGNAL SETTING - SECONDARY INPUT	OFF		VXX:SINS1=OFF	QVX:SINS1	SINS1=OFF	✓
		DIGITAL LINK		VXX:SINS1=DL1		SINS1=DL1	✓
		SLOT1 : SDI1		SLOT1 : SDI1		SINS1=AU1, SD1	✓
		SLOT1 : SDI2		SLOT1 : SDI2		SINS1=AU1, SD2	✓
		SLOT1 : SDI3		SLOT1 : SDI3		SINS1=AU1, SD3	✓
		SLOT1 : SDI4		SLOT1 : SDI4		SINS1=AU1, SD4	✓
		SLOT2 : SDI1		SLOT2 : SDI1		SINS1=AU2, SD1	✓
		SLOT2 : SDI2		SLOT2 : SDI2		SINS1=AU2, SD2	✓
		SLOT2 : SDI3		SLOT2 : SDI3		SINS1=AU2, SD3	✓
		SLOT2 : SDI4		SLOT2 : SDI4		SINS1=AU2, SD4	✓
		SLOT1 : HDMI1		SLOT1 : HDMI1		SINS1=AU1, HD1	✓
		SLOT1 : HDMI2		SLOT1 : HDMI2		SINS1=AU1, HD2	✓
		SLOT2 : HDMI3		SLOT2 : HDMI3		SINS1=AU2, HD3	✓
		SLOT2 : HDMI4		SLOT2 : HDMI4		SINS1=AU2, HD4	✓
		SLOT1 : DVI-D1		SLOT1 : DVI-D1		SINS1=AU1, DV1	✓
		SLOT1 : DVI-D2		SLOT1 : DVI-D2		SINS1=AU1, DV2	✓
		SLOT2 : DVI-D3		SLOT2 : DVI-D3		SINS1=AU2, DV3	✓
		SLOT2 : DVI-D4		SLOT2 : DVI-D4		SINS1=AU2, DV4	✓
		SLOT1 : DisplayPort1		SLOT1 : DisplayPort1		SINS1=AU1, DP1	✓
		SLOT1 : DisplayPort2		SLOT1 : DisplayPort2		SINS1=AU1, DP2	✓
		SLOT2 : DisplayPort3		SLOT2 : DisplayPort3		SINS1=AU2, DP3	✓
		SLOT2 : DisplayPort4		SLOT2 : DisplayPort4		SINS1=AU2, DP4	✓
	REMOTE2 - MODE	DEFAULT		VXX:RMPI0=+00000	QVX:RMPI0	RMPI0=+00000	✓
		USER		VXX:RMPI0=+00001		RMPI0=+00001	✓
	REMOTE2 - PIN2	NONE		VXX:RMPS1=P2<NONE	QVX:RMPS1=P2	RMPS1=P2<NONE	✓
		POWER		VXX:RMPS1=P2<POWER		RMPS1=P2<POWER	✓
	REMOTE2 - PIN3 - 7	* PARAMETER		VXX:RMPS1=P*<*****	QVX:RMPS1=P*		✓
		* PARAMETER1	PIN3	VXX:RMPS1=P3<*****		RMPS1=P3<*****	✓
			PIN4	VXX:RMPS1=P4<*****		RMPS1=P4<*****	✓
			PIN5	VXX:RMPS1=P5<*****		RMPS1=P5<*****	✓
			PIN6	VXX:RMPS1=P6<*****		RMPS1=P6<*****	✓
			PIN7	VXX:RMPS1=P7<*****		RMPS1=P7<*****	✓
		* PARAMETER2	NONE	VXX:RMPS1=P*<NONE		RMPS1=P*<NONE	✓
			DIGITAL LINK	VXX:RMPS1=P*<DLINK		RMPS1=P*<DLINK	✓
			SLOT1 : SDI1	VXX:RMPS1=P*<AU1, SD1		RMPS1=P*<AU1, SD1	✓
			SLOT1 : SDI2	VXX:RMPS1=P*<AU1, SD2		RMPS1=P*<AU1, SD2	✓
			SLOT1 : SDI3	VXX:RMPS1=P*<AU1, SD3		RMPS1=P*<AU1, SD3	✓
			SLOT1 : SDI4	VXX:RMPS1=P*<AU1, SD4		RMPS1=P*<AU1, SD4	✓
			SLOT2 : SDI1	VXX:RMPS1=P*<AU2, SD1		RMPS1=P*<AU2, SD1	✓
			SLOT2 : SDI2	VXX:RMPS1=P*<AU2, SD2		RMPS1=P*<AU2, SD2	✓
			SLOT2 : SDI3	VXX:RMPS1=P*<AU2, SD3		RMPS1=P*<AU2, SD3	✓
			SLOT2 : SDI4	VXX:RMPS1=P*<AU2, SD4		RMPS1=P*<AU2, SD4	✓
			SLOT1 : HDMI1	VXX:RMPS1=P*<AU1, HD1		RMPS1=P*<AU1, HD1	✓
			SLOT1 : HDMI2	VXX:RMPS1=P*<AU1, HD2		RMPS1=P*<AU1, HD2	✓
			SLOT2 : HDMI3	VXX:RMPS1=P*<AU2, HD3		RMPS1=P*<AU2, HD3	✓
			SLOT2 : HDMI4	VXX:RMPS1=P*<AU2, HD4		RMPS1=P*<AU2, HD4	✓
			SLOT1 : DVI1	VXX:RMPS1=P*<AU1, DV1		RMPS1=P*<AU1, DV1	✓
			SLOT1 : DVI2	VXX:RMPS1=P*<AU1, DV2		RMPS1=P*<AU1, DV2	✓
			SLOT2 : DVI3	VXX:RMPS1=P*<AU2, DV3		RMPS1=P*<AU2, DV3	✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
			SLOT2 : DV14	VXX:RMPS1=P*<AU2, DV4		RMPS1=P*<AU2, DV4	✓
			SLOT1 : DisplayPort1	VXX:RMPS1=P*<AU1, DP1		RMPS1=P*<AU1, DP1	✓
			SLOT1 : DisplayPort2	VXX:RMPS1=P*<AU1, DP2		RMPS1=P*<AU1, DP2	✓
			SLOT2 : DisplayPort3	VXX:RMPS1=P*<AU2, DP3		RMPS1=P*<AU2, DP3	✓
			SLOT2 : DisplayPort4	VXX:RMPS1=P*<AU2, DP4		RMPS1=P*<AU2, DP4	✓
	REMOTE2 - PIN8	NONE	NONE	VXX:RMPS1=P8<NONE	QVX:RMPS1=P8	RMPS1=P8<NONE	✓
		SHUTTER	SHUTTER	VXX:RMPS1=P8<SHUTTER		RMPS1=P8<SHUTTER	✓
	FUNCTION BUTTON	DISABLE		0FC:0	QFC	0	✓
		SYSTEM SELECTOR		0FC:1		1	✓
		SYSTEM DAYLIGHT VIEW		0FC:2		2	✓
		SUB MEMORY		0FC:3		3	✓
		FREEZE		0FC:4		4	✓
		WAVEFORM MONITOR		0FC:6		6	✓
		LENS MEMORY LOAD		0FC:7		7	✓
		PROJECTION METHOD		0FC:10		10	✓
		GEOMETRY		0FC:13		13	✓
		OSD POSITION		0FC:14		14	✓
	DATE AND TIME-DATE SETTING	Year: yyyy		TSD:201506151	QGD	201506161	✓
		Month: mm		TSD:yyyymmddw		yyyymmddw	✓
		Date: dd					✓
		Day:w(1~7:Mon~Sun)					✓
	DATE AND TIME-TIME SETTING	Hour: hh		TST:154503	QGT	154503	✓
		Minute: mm		TST:hmmss		hmmss	✓
		Second: ss					✓
	DATE AND TIME-NTP SYNCHRONIZATION	OFF		VXX:NTPI0=+00000	QVX:NTPI0	NTPI0=+00000	✓
		ON		VXX:NTPI0=+00001		NTPI0=+00001	✓
	LENS TYPE	ET-D75LE6		VXX:LNEI1=+00001	QVX:LNEI1	LNEI1=+00001	✓
		ET-D75LE10		VXX:LNEI1=+00002		LNEI1=+00002	✓
		ET-D75LE20		VXX:LNEI1=+00003		LNEI1=+00003	✓
		ET-D75LE30		VXX:LNEI1=+00004		LNEI1=+00004	✓
		ET-D75LE40		VXX:LNEI1=+00005		LNEI1=+00005	✓
		ET-D75LE8		VXX:LNEI1=+00006		LNEI1=+00006	✓
		ET-D75LE95		VXX:LNEI1=+00007		LNEI1=+00007	✓
		ET-D75LE90		VXX:LNEI1=+00008		LNEI1=+00008	✓
		ET-D75LE50		VXX:LNEI1=+00009		LNEI1=+00009	✓
	LENS ID	All		VXX:LNEI4=+00000	QVX:LNEI4	LNEI4=+00000	✓
		1		VXX:LNEI4=+00001		LNEI4=+00001	✓
		255		VXX:LNEI4=+00255		LNEI4=+00255	✓
	LENS NAME			VXX:LNES5=LENSNAME	QVX:LNES5	LNES5=LENSNAME	✓
	LENS CALIBRATION	EXECUTE (ALL)		VXX:LNSI0=+00001			✓
		EXECUTE (SHIFT)		VXX:LNSI0=+00011			✓
		EXECUTE (FOCUS)		VXX:LNSI0=+00012			✓
		EXECUTE (ZOOM)		VXX:LNSI0=+00013			✓
		EXECUTE (SHIFT/FOCUS)		VXX:LNSI0=+00021			✓
		EXECUTE (SHIFT/ZOOM)		VXX:LNSI0=+00022			✓
		EXECUTE (FOCUS/ZOOM)		VXX:LNSI0=+00023			✓
	LENS MEMORY1 NAME CHANGE	LENSMEMORY1		VXX:NCGS5=LENSMEMORY1	QVX:NCGS5	NCGS5=LENSMEMORY1	✓
	LENS MEMORY2 NAME CHANGE	LENSMEMORY2		VXX:NCGS6=LENSMEMORY2	QVX:NCGS6	NCGS6=LENSMEMORY2	✓
	LENS MEMORY3 NAME CHANGE	LENSMEMORY3		VXX:NCGS7=LENSMEMORY3	QVX:NCGS7	NCGS7=LENSMEMORY3	✓
	LENS MEMORY4 NAME CHANGE	LENSMEMORY4		VXX:NCGS9=LENSMEMORY4	QVX:NCGS9	NCGS9=LENSMEMORY4	✓
	LENS MEMORY5 NAME CHANGE	LENSMEMORY5		VXX:NCGSA=LENSMEMORY5	QVX:NCGSA	NCGSA=LENSMEMORY5	✓
	LENS MEMORY6 NAME CHANGE	LENSMEMORY6		VXX:NCGSB=LENSMEMORY6	QVX:NCGSB	NCGSB=LENSMEMORY6	✓
	LENS MEMORY7 NAME CHANGE	LENSMEMORY7		VXX:NCGSC=LENSMEMORY7	QVX:NCGSC	NCGSC=LENSMEMORY7	✓
	LENS MEMORY8 NAME CHANGE	LENSMEMORY8		VXX:NCGSD=LENSMEMORY8	QVX:NCGSD	NCGSD=LENSMEMORY8	✓
	LENS MEMORY9 NAME CHANGE	LENSMEMORY9		VXX:NCGSE=LENSMEMORY9	QVX:NCGSE	NCGSE=LENSMEMORY9	✓
	LENS MEMORY10 NAME CHANGE	LENSMEMORY10		VXX:NCGSF=LENSMEMORY10	QVX:NCGSF	NCGSF=LENSMEMORY10	✓
	LENS MEMORY-LOAD	LENS MEMORY1		VXX:LNMI1=+00000			✓
		LENS MEMORY2		VXX:LNMI1=+00001			✓
		LENS MEMORY3		VXX:LNMI1=+00002			✓
		LENS MEMORY4		VXX:LNMI1=+00003			✓
		LENS MEMORY5		VXX:LNMI1=+00004			✓
		LENS MEMORY6		VXX:LNMI1=+00005			✓
		LENS MEMORY7		VXX:LNMI1=+00006			✓
		LENS MEMORY8		VXX:LNMI1=+00007			✓
		LENS MEMORY9		VXX:LNMI1=+00008			✓
		LENS MEMORY10		VXX:LNMI1=+00009			✓
	LENS MEMORY-SAVE	LENS MEMORY1		VXX:LNMI2=+00000			✓
		LENS MEMORY2		VXX:LNMI2=+00001			✓
		LENS MEMORY3		VXX:LNMI2=+00002			✓
		LENS MEMORY4		VXX:LNMI2=+00003			✓
		LENS MEMORY5		VXX:LNMI2=+00004			✓
		LENS MEMORY6		VXX:LNMI2=+00005			✓
		LENS MEMORY7		VXX:LNMI2=+00006			✓
		LENS MEMORY8		VXX:LNMI2=+00007			✓
		LENS MEMORY9		VXX:LNMI2=+00008			✓
		LENS MEMORY10		VXX:LNMI2=+00009			✓
	LENS MEMORY-DELETE	LENS MEMORY1		VXX:LNMI3=+00000			✓
		LENS MEMORY2		VXX:LNMI3=+00001			✓
		LENS MEMORY3		VXX:LNMI3=+00002			✓
		LENS MEMORY4		VXX:LNMI3=+00003			✓
		LENS MEMORY5		VXX:LNMI3=+00004			✓
		LENS MEMORY6		VXX:LNMI3=+00005			✓
		LENS MEMORY7		VXX:LNMI3=+00006			✓
		LENS MEMORY8		VXX:LNMI3=+00007			✓
		LENS MEMORY9		VXX:LNMI3=+00008			✓
		LENS MEMORY10		VXX:LNMI3=+00009			✓
	LENS MEMORY1-DEFAULT NAME	LENSMEMORY1		VXX:NCLI5=+00000			✓
	LENS MEMORY2-DEFAULT NAME	LENSMEMORY2		VXX:NCLI6=+00000			✓
	LENS MEMORY3-DEFAULT NAME	LENSMEMORY3		VXX:NCLI7=+00000			✓
	LENS MEMORY4-DEFAULT NAME	LENSMEMORY4		VXX:NCLI9=+00000			✓
	LENS MEMORY5-DEFAULT NAME	LENSMEMORY5		VXX:NCLIA=+00000			✓
	LENS MEMORY6-DEFAULT NAME	LENSMEMORY6		VXX:NCLIB=+00000			✓
	LENS MEMORY7-DEFAULT NAME	LENSMEMORY7		VXX:NCLIC=+00000			✓
	LENS MEMORY8-DEFAULT NAME	LENSMEMORY8		VXX:NCLID=+00000			✓
	LENS MEMORY9-DEFAULT NAME	LENSMEMORY9		VXX:NCLIE=+00000			✓
	LENS MEMORY10-DEFAULT NAME	LENSMEMORY10		VXX:NCLIF=+00000			✓
	INITIALIZE-ALL USER DATA	USER INITILIZE		VXX:RSTS1=0password			✓
		USER RESTORE		VXX:RSTS1=1password			✓
	INITIAL START UP	STANDBY		OPY:0	QPY	0	✓
		ON		OPY:1		1	✓
		LAST MEMORY		OPY:2		2	✓
	MODEL NAME	MODEL NAME			QID	MODELNAME	✓
	SERIAL NUMBER	SW0101234			QSN	SW0101234	✓
	PROJECTOR RUNTIME	7864320H			QVX:RTMS1	RTMS1=7864320	✓
	LAMP1(LIGHT1) RUNTIME	9999H			Q\$L:1	9999	✓
	LAMP2(LIGHT2) RUNTIME	9999H			Q\$L:2	9999	✓
	LIGHT1 RUNTIME	7864320H			LRTS3=00	LRTS3=00:7864320	✓
	LIGHT2 RUNTIME	7864320H			QVX:LRTS3=01	LRTS3=01:7864320	✓
	LIGHT STATUS	ALL OFF			QLS	0	✓
		1:ON, 2:OFF				1	✓
		1:OFF, 2:ON				2	✓
		ALL ON				3	✓
	CONTINUOUS LIGHTING TIME	7864320H00M			QVX:CLTS1	CLTS1=7864320:00	✓
	CONSOLIDATED RUNTIME	7864320H			QVX:CRTS1	CRTS1=7864320	✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
	LAMP(LIGHT) CONTROL STATUS	LAMP OFF			Q\$S	0	✓
		In turning ON				1	✓
		LAMP ON				2	✓
		LAMP Cooling				3	✓
	POWER STATUS	POWER OFF			QVX:POWI1	POWI1=+00001	✓
		In turning ON				POWI1=+00002	✓
		POWER ON				POWI1=+00003	✓
		Cooling				POWI1=+00004	✓
	MAC ADDRESS	AB0102030405			QMA	AB0102030405	✓
	MAIN FIRMWARE VERSION	V1.00.01			QVX:SVRS0	SVRS0=1.00.01	✓
	NETWORK FIRMWARE VERSION	V1.00			QVX:SVRS1	SVRS1=1.00	✓
	SUB FIRMWARE VERSION	V1.00.01			QVX:SVRS2	SVRS2=1.00.01	✓
	INPUT SIGNAL NAME	CHANNEL1 (MAIN CH)			QVX:NSGS1	NSGS1=****.....	✓
	TEMPERATURE (INTAKE)	0030/0080			QTM:0	0030/0080	✓
	TEMPERATURE (EXHAUST AIR)	0030/0080			QTM:1	0030/0080	✓
	TEMPERATURE (OPTICS MODULE)	0030/0080			QTM:2	0030/0080	✓
	LAN data Cloning Write protect	OFF		LCL:WRP0	QCL:WRP	QCL:WRP0	✓
		ON		LCL:WRP1		QCL:WRP1	✓
	MECH. SHUTTER COUNT				QVX:MSCI0	MSCI0=+*****	✓
	INFO MONITOR SETTING -	OFF		VXX:INFI1=+00000	QVX:INFI1	INFI1=+00000	✓
		USER VIEW		VXX:INFI1=+00001		INFI1=+00001	✓
	INFO MONITOR SETTING - USER	INPUT		VXX:INFS2=01:*****	QVX:INFS2=01	INFS2=01:*****	✓
		SIGNAL		VXX:INFS2=02:*****	QVX:INFS2=02	INFS2=02:*****	✓
		AC VOLTAGE		VXX:INFS2=03:*****	QVX:INFS2=03	INFS2=03:*****	✓
		INTAKE AIR TEMP.		VXX:INFS2=04:*****	QVX:INFS2=04	INFS2=04:*****	✓
		EXHAUST AIR TEMP.		VXX:INFS2=05:*****	QVX:INFS2=05	INFS2=05:*****	✓
		SHUTTER		VXX:INFS2=06:*****	QVX:INFS2=06	INFS2=06:*****	✓
		OSD		VXX:INFS2=07:*****	QVX:INFS2=07	INFS2=07:*****	✓
		IP ADDRESS		VXX:INFS2=08:*****	QVX:INFS2=08	INFS2=08:*****	✓
		OFF		VXX:INFS2=**:00000			✓
		ON		VXX:INFS2=**:00001			✓
	INFO MONITOR SETTING -	AUTO		VXX:INFI3=+00000	QVX:INFI3	INFI3=+00000	✓
		NORMAL		VXX:INFI3=+00001		INFI3=+00001	✓
		FLIPPED		VXX:INFI3=+00002		INFI3=+00002	✓
	INFO MONITOR SETTING -	30%		VXX:INFI4=+00030	QVX:INFI4	INFI4=+00030	✓
		100%		VXX:INFI4=+00100		INFI4=+00100	✓
TEST PATTERN	TEST PATTERN	Off		OTS:00	QTS	00	✓
		White		OTS:01		01	✓
		Black		OTS:02		02	✓
		Window		OTS:05		05	✓
		Reversed Window		OTS:06		06	✓
		Cross Hatch		OTS:07		07	✓
		Color Bar V		OTS:08		08	✓
		Focus (Level 0%)		OTS:32		32	✓
		Focus (Level 50%)		OTS:33		33	✓
		Focus (Level 100%)		OTS:34		34	✓
		Color Bar Side		OTS:51		51	✓
		16:9/4:3		OTS:59		59	✓
		Focus Red		OTS:70		70	✓
		Focus Green		OTS:71		71	✓
		Focus Blue		OTS:72		72	✓
		Focus Cyan		OTS:73		73	✓
		Focus Magenta		OTS:74		74	✓
		Focus Yellow		OTS:75		75	✓
		Focus		OTS:78		78	✓
SIGNAL LIST	SIGNAL LIST-REGISTRATION			OEM			✓
	SIGNAL LIST-DELETE	A1		ODM:A1			✓
		A2		ODM:A2			✓
		A7		ODM:A7			✓
		A8		ODM:A8			✓
		L1		ODM:L1			✓
		L2		ODM:L2			✓
		L7		ODM:L7			✓
		L8		ODM:L8			✓
	SUB MEMORY LIST-CHANGEOVER	01		OCS:01			✓
		96		OCS:96			✓
	SUB MEMORY LIST-CHANGEOVER (EXTENDED)	01		OCS:01-01			✓
		96		OCS:95-96			✓
	SUB MEMORY LIST-REGISTRATION			OES			✓
	SUB MEMORY LIST-DELETE	01		ODS:01-01			✓
		96		ODS:95-96			✓
	SUB MEMORY USAGE STATE	01			QSB	01	✓
		96				96	✓
SECURITY	SECURITY SETTING	OFF			QVX:SPWI1	SPWI1=+00000	✓
		ON				SPWI1=+00001	✓
	CONTROL DEVICE SETUP-CONTROL PANEL	DISABLE		VXX:CDSI1=+00000	QVX:CDSI1	CDSI1=+00000	✓
		ENABLE		VXX:CDSI1=+00001		CDSI1=+00001	✓
		USER		VXX:CDSI1=+00002		CDSI1=+00002	✓
	CONTROL DEVICE SETUP-REMOTE CONTROL	DISABLE		VXX:CDSI2=+00000	QVX:CDSI2	CDSI2=+00000	✓
		ENABLE		VXX:CDSI2=+00001		CDSI2=+00001	✓
		USER		VXX:CDSI2=+00002		CDSI2=+00002	✓
NETWORK	WIRELESS LAN	OFF(DISABLE)		ONS:0	QVX:WLSI1	WLSI1=+00000	✓
		ON(ENABLE)		ONS:14		WLSI1=+00014	✓
	DIGITAL LINK MODE	AUTO		VXX:DKMI1=+00001	QVX:DKMI1	DKMI1=+00001	✓
		DIGITAL LINK		VXX:DKMI1=+00002		DKMI1=+00002	✓
		ETHERNET		VXX:DKMI1=+00003		DKMI1=+00003	✓
		LONG REACH MODE		VXX:DKMI1=+00004		DKMI1=+00004	✓
	DIGITAL LINK STATUS-LINK	NO LINK			QVX:DKSI1	DKSI1=+00000	✓
		DIGITAL LINK				DKSI1=+00001	✓
		LPM				DKSI1=+00002	✓
		ETHERNET				DKSI1=+00003	✓
	DIGITAL LINK STATUS-HDCP STATUS	NO SIGNAL			QVX:DKSI2	DKSI2=+00000	✓
		OFF				DKSI2=+00001	✓
		ON				DKSI2=+00002	✓
	DIGITAL LINK STATUS-SIGNAL QUALITY (MIN)	-255			QVX:DKSI3	DKSI3=-00255	✓
		0				DKSI3=+00000	✓
	DIGITAL LINK STATUS-SIGNAL QUALITY (MAX)	-255			QVX:DKSI4	DKSI4=-00255	✓
		0				DKSI4=+00000	✓
	DIGITAL LINK INPUT CH LIST	HD1:HDMI1,HD2:HDMI2...			QVX:DL1S1	DL1S1=HD1:HDMI1,****;***	✓
	PROJECTOR NAME SETTING	PROJECTOR1		VXX:NCGS8=PROJECTOR1	QVX:NCGS8	NCGS8=PROJECTOR1	✓
	Art-Net SETUP	OFF		VXX:DANI1=+00000	QVX:DANI1	DANI1=+00000	✓
		ON(2.*.*)		VXX:DANI1=+00002		DANI1=+00002	✓
		ON(10.*.*)		VXX:DANI1=+00003		DANI1=+00003	✓
		ON(MANUAL)		VXX:DANI1=+00004		DANI1=+00004	✓
	Art-Net SETUP-START ADDRESS	1		VXX:DANI3=+00001	QVX:DANI3	DANI3=+00001	✓
		501		VXX:DANI3=+00501		DANI3=+00501	✓
	Art-Net SETUP-NET	0		VXX:DANI4=+00000	QVX:DANI4	DANI4=+00000	✓
		127		VXX:DANI4=+00127		DANI4=+00127	✓
	Art-Net SETUP-SUB NET	0		VXX:DANI5=+00000	QVX:DANI5	DANI5=+00000	✓
		15		VXX:DANI5=+00015		DANI5=+00015	✓
	Art-Net SETUP-UNIVERS	0		VXX:DANI6=+00000	QVX:DANI6	DANI6=+00000	✓
		15		VXX:DANI6=+00015		DANI6=+00015	✓
	Art-Net SETUP-CHANNEL SETTING	DEFAULT		VXX:DANI8=+00000	QVX:DANI8	DANI8=+00000	✓
		1		VXX:DANI8=+00001		DANI8=+00001	✓

				CONTROL	QUERY		RQ50K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RQ50K SRQ50KC
		2		VXX:DANI8=+00002		DANI8=+00002	✓
		USER		VXX:DANI8=+00100		DANI8=+00100	✓
	PRESHOW MODE	OFF			QVX:PSMI1	PSMI1=+00000	✓
		ON				PSMI1=+00001	✓

Note: The commands or parameters with "*" shows available commands or parameters for the projector which has been activated by the Upgrade Kit.