
Section 25. Device Configuration

HIGHLIGHTS

This section of the manual contains the following major topics:

25.1	Introduction	25-2
25.2	Device Configuration Registers	25-3
25.3	Configuration Bit Descriptions.....	25-12
25.4	Device Identification Registers.....	25-14
25.5	Register Map.....	25-15
25.6	Related Application Notes.....	25-16
25.7	Revision History	25-17

25.1 INTRODUCTION

The device Configuration registers allow each user to customize certain aspects of the device to fit the needs of the application. Device Configuration registers are nonvolatile locations in program memory that hold settings for the dsPIC[®] DSC device during power-down. The Configuration registers hold global set-up information for the device, such as the oscillator source, Watchdog Timer mode, code protection settings and others.

The device Configuration registers are mapped in program memory locations, starting at address 0xF80000, and are accessible during normal device operation. This region is also referred to as “configuration space”.

The Configuration bits can be programmed (read as ‘0’) or left unprogrammed (read as ‘1’) to select various device configurations.

25.2 DEVICE CONFIGURATION REGISTERS

Each device Configuration register is a 24-bit register. However, only the lower 16 bits of each register hold configuration data. Eight device Configuration registers are available to user software:

- **FBS: Boot Code Segment Configuration Register**
- **FSS: Secure Code Segment Configuration Register**
- **FGS: General Code Segment Configuration Register**
- **FOSCSEL: Oscillator Source Selection Register**
- **FOSC: Oscillator Configuration Register**
- **FWDT: Watchdog Timer Configuration Register**
- **FPOR: POR Configuration Register**
- **FICD: In-Circuit Debugger Configuration Register**

The device Configuration registers can be programmed using Run-Time Self-Programming (RTSP), In-Circuit Serial Programming™ (ICSP™) or a device programmer.

Note: Some Configuration registers and bits may not be present on all dsPIC33F devices. Consult the specific device data sheet for more information.

dsPIC33F Family Reference Manual

Register 25-1: FBS: Boot Code Segment Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23						bit 16	

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15						bit 8	

R/P	R/P	U	U	R/P	R/P	R/P	R/P
RBS<1:0>		—	—	BSS<2:0>			BWRP
bit 7							bit 0

Legend:

R = Readable bit

P = Programmable bit

U = Unimplemented bit, read as '1'

-n = Value at POR

'1' = Bit is set

'0' = Bit is cleared

x = Bit is unknown

bit 23-8 **Unimplemented:** Read as '1'

bit 7-6 **RBS<1:0>:** Boot Segment RAM Code Protection bits

11 = No Boot RAM defined

10 = Boot RAM is 128 bytes

01 = Boot RAM is 256 bytes

00 = Boot RAM is 1024 bytes

bit 5-4 **Unimplemented:** Read as '1'

bit 3-1 **BSS<2:0>:** Boot Segment Program Flash Code Protection Size bits (see the specific device data sheet for more information)

bit 0 **BWRP:** Boot Segment Program Flash Write Protection bit

1 = Boot segment may be written

0 = Boot segment is write-protected

Section 25. Device Configuration

Register 25-2: FSS: Secure Code Segment Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23				bit 16			

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15				bit 8			

R/P	R/P	U	U	R/P	R/P	R/P	R/P
RSS<1:0>		—	—	SSS<2:0>			SWRP
bit 7				bit 0			

Legend:

R = Readable bit

P = Programmable bit

U = Unimplemented bit, read as '1'

-n = Value at POR

'1' = Bit is set

'0' = Bit is cleared

x = Bit is unknown

bit 23-8 **Unimplemented:** Read as '1'

bit 7-6 **RSS<1:0>:** Secure Segment RAM Code Protection bits

11 = No Secure RAM defined

10 = Secure RAM is 256 bytes, less BS RAM

01 = Secure RAM is 2048 bytes, less BS RAM

00 = Secure RAM is 4096 bytes, less BS RAM

bit 5-4 **Unimplemented:** Read as '1'

bit 3-1 **SSS<2:0>:** Secure Segment Program Flash Code Protection Size bits (see the specific device data sheet for more information)

bit 0 **SWRP:** Secure Segment Program Flash Write Protection bit

1 = Secure segment may be written

0 = Secure segment is write-protected

dsPIC33F Family Reference Manual

Register 25-3: FGS: General Code Segment Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23						bit 16	

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15						bit 8	

U	U	U	U	U	R/P	R/P	R/P
—	—	—	—	—	GSS<1:0>		GWRP
bit 7						bit 0	

Legend:

R = Readable bit

P = Programmable bit

U = Unimplemented bit, read as '1'

-n = Value at POR

'1' = Bit is set

'0' = Bit is cleared

x = Bit is unknown

bit 23-3 **Unimplemented:** Read as '1'

bit 2-1 **GSS<1:0>:** General Segment Code-Protect bit
11 = User program memory is not code-protected
10 = Standard security
0x = High security

bit 0 **GWRP:** General Segment Program Flash Write Protection bit
1 = General segment may be written
0 = General segment is write-protected

Section 25. Device Configuration

Register 25-4: FOSCSEL: Oscillator Source Selection Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23				bit 16			

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15				bit 8			

R/P	U	U	U	U	R/P	R/P	R/P
IESO	—	—	—	—	FNOSC<2:0>		
bit 7					bit 0		

Legend:

R = Readable bit

P = Programmable bit

U = Unimplemented bit, read as '1'

-n = Value at POR

'1' = Bit is set

'0' = Bit is cleared

x = Bit is unknown

bit 23-8 **Unimplemented:** Read as '1'

bit 7 **IESO:** Two-speed Oscillator Start-up Enable bit

1 = Start device with FRC, then automatically switch to the user-selected oscillator source when ready

0 = Start device with the user-selected oscillator source

bit 6-3 **Unimplemented:** Read as '1'

bit 2-0 **FNOSC<2:0>:** Initial Oscillator Source Selection bits

111 = Internal Fast RC (FRC) oscillator with postscaler

110 = Internal FRC oscillator with divide-by-16

101 = LPRC oscillator

100 = Secondary (LP) oscillator

011 = Primary (XT, HS, EC) oscillator with PLL

010 = Primary (XT, HS, EC) oscillator

001 = Internal FRC oscillator with PLL

000 = FRC oscillator

dsPIC33F Family Reference Manual

Register 25-5: FOSC: Oscillator Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23						bit 16	

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15						bit 8	

R/P	R/P	R/P	U	U	R/P	R/P	R/P
FCKSM<1:0>		IOL1WAY	—	—	OSCIOFNC	POSCMD<1:0>	
bit 7						bit 0	

Legend:

R = Readable bit

P = Programmable bit

U = Unimplemented bit, read as '1'

-n = Value at POR

'1' = Bit is set

'0' = Bit is cleared

x = Bit is unknown

bit 23-8 **Unimplemented:** Read as '1'

bit 7-6 **FCKSM<1:0>:** Clock Switching Mode bits

1x = Clock switching is disabled; Fail-Safe Clock Monitor is disabled

01 = Clock switching is enabled; Fail-Safe Clock Monitor is disabled

00 = Clock switching is enabled; Fail-Safe Clock Monitor is enabled

bit 5 **IOL1WAY:** Peripheral Pin Select Configuration bit

1 = Allow only one reconfiguration

0 = Allow multiple reconfigurations

bit 4-3 **Unimplemented:** Read as '1'

bit 2 **OSCIOFNC:** OSC2 Pin Function bit (except in XT and HS modes)

1 = OSC2 is clock output

0 = OSC2 is general purpose digital I/O pin

bit 1-0 **POSCMD<1:0>:** Primary Oscillator Mode Select bits

11 = Primary oscillator disabled

10 = HS Crystal Oscillator mode

01 = XT Crystal Oscillator mode

00 = EC (External Clock) mode

Section 25. Device Configuration

Register 25-6: FWDT: Watchdog Timer Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23							bit 16

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15							bit 8

R/P	R/P	R/P	U	U	R/P	R/P	R/P
FWDTEN	WINDIS	—	WDTPRE	WDTPOST<3:0>			
bit 7							bit 0

Legend:

R = Readable bit

P = Programmable bit

U = Unimplemented bit, read as '1'

-n = Value at POR

'1' = Bit is set

'0' = Bit is cleared

x = Bit is unknown

bit 23-8 **Unimplemented:** Read as '1'

bit 7 **FWDTEN:** Watchdog Timer Enable Mode bit

1 = Watchdog Timer always enabled (LPRC oscillator cannot be disabled. Clearing the SWDTEN bit in the RCON register will have no effect)

0 = Watchdog Timer enabled/disabled by user software (LPRC can be disabled by clearing the SWDTEN bit in the RCON register)

bit 6 **WINDIS:** Watchdog Timer Window Enable bit

1 = Watchdog Timer in Non-Window mode

0 = Watchdog Timer in Window mode

bit 5 **Unimplemented:** Read as '1'

bit 4 **WDTPRE:** Watchdog Timer Prescaler bit

1 = 1:128

0 = 1:32

bit 3-0 **WDTPOST<3:0>:** Watchdog Timer Postscaler bits

1111 = 1:32,768

1110 = 1:15,384

.

.

.

0001 = 1:2

0000 = 1:1

dsPIC33F Family Reference Manual

Register 25-7: FPOR: POR Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23				bit 16			

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15				bit 8			

R/P	R/P	R/P	R/P	R/P	R/P	R/P	R/P
PWMPIN	HPOL	LPOL	ALT2C	BOREN	FPWRT<2:0>		
bit 7					bit 0		

Legend:

R = Readable bit

P = Programmable bit

U = Unimplemented bit, read as '1'

-n = Value at POR

'1' = Bit is set

'0' = Bit is cleared

x = Bit is unknown

bit 23-8 **Unimplemented:** Read as '1'

bit 7 **PWMPIN:** Motor Control PWM Module Pin Mode bit

1 = PWM module pins controlled by PORT register at device Reset (tri-stated)

0 = PWM module pins controlled by PWM module at device Reset (configured as output pins)

bit 6 **HPOL:** Motor Control PWM High-Side Polarity bit

1 = PWM module high-side output pins have active-high output polarity

0 = PWM module high-side output pins have active-low output polarity

bit 5 **LPOL:** Motor Control PWM Low-Side Polarity bit

1 = PWM module low-side output pins have active-high output polarity

0 = PWM module low-side output pins have active-low output polarity

bit 4 **ALT2C:** Alternate I²C™ Pins bit

1 = I²C mapped to SDA1/SCL1 pins

0 = I²C mapped to ASDA1/ASCL1 pins

bit 3 **BOREN:** Brown-out Reset Enable bit

1 = BOR is enabled

0 = BOR is disabled

bit 2-0 **FPWRT<2:0>:** Power-on Reset Timer Value Select bits

111 = PWRT = 128 ms

110 = PWRT = 64 ms

101 = PWRT = 32 ms

100 = PWRT = 16 ms

011 = PWRT = 8 ms

010 = PWRT = 4 ms

001 = PWRT = 2 ms

000 = PWRT = Disabled

Section 25. Device Configuration

Register 25-8: FICD: In-Circuit Debugger Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23			bit 16				

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15			bit 8				

R/P	R/P	R/P	U	U	U	R/P	R/P
BKBUG	COE	JTAGEN	—	—	—	ICS<1:0>	
bit 7			bit 0				

Legend:

R = Readable bit

P = Programmable bit

U = Unimplemented bit, read as '1'

-n = Value at POR

'1' = Bit is set

'0' = Bit is cleared

x = Bit is unknown

bit 23-8 **Unimplemented:** Read as '1'

bit 7 **BKBUG:** Background Debug Enable bit

1 = Device will reset in User mode

0 = Device will reset in Debug mode

bit 6 **COE:** Debugger/Emulator Enable bit

1 = Device will reset in Operational mode

0 = Device will reset in Clip-On Emulation mode

bit 5 **JTAGEN:** JTAG Enable bit

1 = JTAG is enabled

0 = JTAG is disabled

bit 4-2 **Unimplemented:** Read as '1'

bit 1-0 **ICS<1:0>:** ICD Communication Channel Select Enable bits

11 = Communicate on PGC1/EMUC1 and PGD1/EMUD1

10 = Communicate on PGC2/EMUC2 and PGD2/EMUD2

01 = Communicate on PGC3/EMUC3 and PGD3/EMUD3

00 = Reserved, do not use

25.3 CONFIGURATION BIT DESCRIPTIONS

This section provides functional information for each of the device Configuration bits.

25.3.1 Code Protection and CodeGuard™ Security

The dsPIC33F product families offer advanced security which protects the intellectual property that users invest in collaborative system designs. CodeGuard Security enables multiple parties to securely share resources (memory, interrupts and peripherals) on a single chip with assurance that their intellectual property rights are not at risk.

The code protection features are controlled by the Configuration registers (FBS, FSS and FGS) and vary from one dsPIC33F device to another. For further information, consult the device data sheet and refer to **Section 23. “CodeGuard™ Security”** (DS70199) in this reference manual.

25.3.2 Oscillator Configuration Bits

The dsPIC33F clock selection, switching and configuration settings are controlled by the Oscillator Source Selection (FOSCSEL) and Oscillator Configuration (FOSC) registers. See **Section 7. “Oscillator”** (DS70186) for more information.

25.3.3 POR Configuration Bits

The POR Configuration bits, found in the FPOR Configuration register, are used to set the Power-up Timer delay time. For more information on these Configuration bits, please refer to **Section 8. “Reset”** (DS70192).

25.3.4 Motor Control PWM Module Configuration Bits

The Motor Control PWM module Configuration bits are located in the FPOR Configuration register and are present only on devices that have the PWM module. The Configuration bits associated with the PWM module have two functions:

- Select the state of the PWM pins at a device Reset (high Z or output).
- Select the active signal polarity for the PWM pins. The polarity for the high-side and low-side PWM pins can be selected independently.

For more information on these Configuration bits, please refer to **Section 14. “Motor Control PWM”** (DS70187).

25.3.5 Watchdog Timer Configuration Bits

The dsPIC33F Watchdog Timer can be enabled and configured using the Watchdog Timer Configuration Register (FWDTR). **Section 9. “Watchdog Timer and Power Savings Modes”** (DS70196) provides more information on these Configuration bits.

25.3.6 JTAG Interface

The dsPIC33F device family implements a JTAG interface, which supports boundary scan device testing, as well as in-circuit programming. Detailed information on this interface is provided in future revisions of the document.

Note: Refer to Section 24. “Programming and Diagnostics” (DS70207) of the dsPIC33F Family Reference Manual for further information on usage, configuration and operation of the JTAG interface.

25.3.7 In-Circuit Serial Programming (ICSP)

The ICSP capability is Microchip's proprietary process for microcontroller programming in the target application. The ICSP interface uses two pins as its core. The programming data pin (PGD) functions as both an input and an output, allowing programming data to be read in and device information to be read out on command. The programming clock pin (PGC) clocks in data and controls the overall process.

Serial programming allows customers to manufacture boards with unprogrammed devices and then to program the digital signal controller just before shipping the product. Serial programming also allows the most recent firmware or a custom firmware to be programmed. Refer to the *"dsPIC33F/PIC24H Flash Programming Specification"* (DS70152) for details about ICSP.

Any of the three pairs of programming clock/data pins can be used:

- PGC1/EMUC1 and PGD1/EMUD1
- PGC2/EMUC2 and PGD2/EMUD2
- PGC3/EMUC3 and PGD3/EMUD3

25.3.8 In-Circuit Debugger

When MPLAB® ICD 2 or MPLAB REAL ICE™ in-circuit emulator is selected as a debugger, the in-circuit debugging functionality is enabled. This function allows simple debugging when used with MPLAB IDE. The debugging functionality is controlled through the EMUCx (emulation/debug clock) and EMUDx (emulation/debug data) pin functions.

Any of the three pairs of debugging clock/data pins can be used:

- PGC1/EMUC1 and PGD1/EMUD1
- PGC2/EMUC2 and PGD2/EMUD2
- PGC3/EMUC3 and PGD3/EMUD3

The debugging clock and data pins must be selected by programming the ICD Communication Channel Select Enable (ICS<1:0>) bits in the In-Circuit Debugger Configuration (FICD<1:0>) register. To use the in-circuit debugger function of the device, the design must implement ICSP connections to MCLR, VDD, VSS, PGCx/EMCx and PGDx/EMUDx pin pairs. In addition, when the feature is enabled, some of the resources are not available for general use. These resources include the first 80 bytes of data RAM and two I/O pins.

25.4 DEVICE IDENTIFICATION REGISTERS

The dsPIC33F devices have two sets of registers located in configuration space that provide identification information.

25.4.1 Device ID (DEVID) Registers

Configuration memory space locations 0xFF0000 and 0xFF0002 are used to store a read-only Device ID number that is set when the device is manufactured. This number identifies the dsPIC33F device type and the silicon revision.

The Device ID registers can be read using table read instructions.

25.4.2 Unit ID Field

The Unit ID field is located at configuration memory space locations 0xF80010 through 0xF80016. This field consists of four Configuration registers (FUID0-FUID3) and can be programmed with unique device information.

25.5 REGISTER MAP

A summary of the registers associated with dsPIC33F device configuration is provided in Table 25-1.

Table 25-1: Device Configuration Register Map

Name	Addr.	Bits 23 - 8 (Not used for device configuration)	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
FBS	0xF80000	—	RBS<1:0>	—	—	—	—	BSS<2:0>	—	BWRP
FSS	0xF80002	—	RSS<1:0>	—	—	—	—	SSS<2:0>	—	SWRP
FGS	0xF80004	—	—	—	—	—	—	GSS<1:0>	—	GWRP
FOSCSEL	0xF80006	—	IESO	—	—	—	—	—	FNOSC<2:0>	—
FOSC	0xF80008	—	FCKSM<1:0>	—	IOL1WAY	—	—	OSCIOFNC	—	—
FWDTPRE	0xF8000A	—	FWDTEN	WINDIS	—	WDTPRE	—	—	WDTPOST<3:0>	—
FPOR	0xF8000C	—	PWMPIIN	HPOL	LPOL	ALT12C	BOREN	—	FPWRT<2:0>	—
FICD	0xF8000E	—	BKBUG	COE	JTAGEN	—	—	—	ICS<1:0>	—
FUID0	0xF80010	—	—	—	—	—	—	—	—	—
FUID1	0xF80012	—	—	—	—	—	—	—	—	—
FUID2	0xF80014	—	—	—	—	—	—	—	—	—
FUID3	0xF80016	—	—	—	—	—	—	—	—	—

Legend: — = unimplemented, read as '1'. Reset values are shown in hexadecimal.

Note: Some Configuration registers and bits may not be present on all dsPIC33F devices. Consult the specific device data sheet for more information.

25.6 RELATED APPLICATION NOTES

This section lists application notes that are related to this section of the manual. These application notes may not be written specifically for the dsPIC33F product family, but the concepts are pertinent and could be used with modification and possible limitations. The current application notes related to Device Configuration include the following:

Title	Application Note #
No related application notes at this time.	

Note: Please visit the Microchip web site (www.microchip.com) for additional Application Notes and code examples for the dsPIC33F family of devices.
--

25.7 REVISION HISTORY

Revision A (February 2007)

This is the initial release of this section.

Revision B (February 2007)

Minor edits throughout document.

Revision C (January 2008)

This revision includes the following corrections and updates:

- Section Changes:
 - Added JTAG Interface Section (see **25.3.6 “JTAG Interface”**)
 - Added In-Circuit Serial Programming Section (see **25.3.7 “In-Circuit Serial Programming (ICSP)”**)
 - Added In-Circuit Debugger Section (see **25.3.8 “In-Circuit Debugger”**)
- Register Changes:
 - Updated FOSCSEL: Oscillator Source Selection Register (see Register 25-4)
 - Updated FPOR: POR Configuration Register (see Register 25-7)
 - Added FICD: In-Circuit Debugger Configuration Register (see Register 25-8)
- Table Changes:
 - Updated Register Map Table (see Table 25-1)

NOTES: