



Powerblu User Manual



Package Contains

- Powerblu headset
- Powerblue powerstation
- USB charging cable
- 5 ear tips for user comfort selection

Features

Headset

- Class II Bluetooth radio
- Advanced Audio Distribution Profile (A2DP) 1.2
- Bluetooth v2.1 + EDR
- Hands-Free Profile (HFP) 1.5
- Headset Profile (HSP) 1.1
- Secure Simple Pairing (SSP)
- Multi-point connectivity (2 devices simultaneously)
- Bluetooth is on (connected to the phone) even when it's being charged

- Background noise cancellation
- Dual microphones for noise cancellation
- Wind screen protected microphone
- Battery meter display on iDevices,
- Voice intelligibility enhancement
- Low audio distortion
- Active speech recognition software with barge-in feature to activate speech recognition while prompts and incoming phone numbers are announced.
- Recorded voice prompts
- Text to speech caller name and number announcement
- Super comfortable ear tip material that wicks away heat and moisture for extended use
- BT headset charges when docked to the PowerStation
- Battery: Typical 105 mAh lithium rechargeable battery
- Talk time: greater than 4 hours
- Standby: 2 ~3 days
- 4 LEDs on outside of headset display battery level indication, on-phone status, BT connect status, power on (standby),

Power Station

- Battery: Typical 900 mAh lithium rechargeable battery
- 5 LEDs on outside of powerstation display battery level indication, BT connect status, and charging status when connected to a mains power supply.
- Headset docks to powerstation for headset recharging
- Total system talk time: over 30 hours
- Total system standby time: over 3 weeks

Check It Out

Power Switch

- Turn headset on or off



Call Button

- Answer a call or end a call
- Click to activate your phone commands (Siri®)
- Reconnect a dropped connection
- Activate pairing mode (Long press after initial setup)



Volume + and - buttons

- Press to eject headset



Eject Button

Micro USB charging port

- Connect the USB cable to your phone charger or computer

Power Status Button

- Press to show battery charge level



Starting for the first time...

1. Slide the Power Blu headset power switch to the ON position.
2. Go to the settings menu on your phone , turn on or enable Bluetooth

Iphone: Setting>General>Bluetooth>On



1. Search, add or discover new Bluetooth Devices on your phone menu.
2. Select the PowerBlu.

Your Power Blu is now connected and ready to be used.

Charging the Headset

Insert the headset into the powerstation as shown.



Charging the Powerstation

Connect the USB cable to your phone charger or computer.

Pairing to Other Bluetooth Devices

1. Turn on or enable Bluetooth in your device menu.
2. Press the PowerBlu Call button for 3 seconds. Or activate speech recognition (press Volume +) and say "Pair".

Answering a Call

- Say "Answer" to answer a call, or press the call button.
- Say "Ignore" to reject a call, or press the call button for 3 seconds.

Note: the Power Blu has a barge-in feature. You can say answer or ignore during the caller ID readout and the phone will respond.

Ear Tip Tips

- To remove an eartip carefully pull it off the headset.
- Trial which eartip size suits you best.
- Clean the eartip regularly by washing with warm water. Do not use chemical cleaners.

Using the Phone Voice Features

Press the call button to activate your phone's voice feature. This uses your phone's voice recognition software such as Siri®, S Voice®, etc.

Note: Most current smartphones support this function: iPhone 3Gs, 4, 4S and 5, most Blackberry smartphones, most Android devices with Android 2.2 and above.

Using the Voice Recognition Commands

Press Volume +.

You can say:

- Pair : to connect to another Bluetooth device
- Check Battery: to know your battery status
- Redial: to dial the last outgoing call
- Call back: to call back to the last incoming call

Multitpoint

The PowerBlu supports two Bluetooth devices connected simultaneously. When two devices have connected to your PowerBlu the primary device is the first device connected.

Note: Only the primary device allows use of the PowerBlu headset phone voice features like Siri, and the Callback plus Redial commands.

To swap the primary phone double-click the Call button.

Warranty Terms

At mophie, we are dedicated to making the best quality products we can. To back this up, our powerblu is warranted for 1 full year from date of purchase. Be sure to register your product at mophie.com to activate it and check for the latest product releases as they develop.

Notices



(Applicable in the European Union) This marking shown on the product or its literature, indicates that it should be disposed with other household wastes at the end of its working life. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate this from other types of wastes and recycle it responsibly to promote

the sustainable reuse of material resources. Household users should contact either the retailer where they purchased this product, or their local government office, for details of where and how they can take this item for environmentally safe recycling. Business users should contact their supplier and check the terms and conditions of the purchase contract. This product should not be mixed with other commercial wastes for disposal.

FCC Notice

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

1) this device may not cause harmful interference, and 2) this device must accept any interference received, including interference that may cause undesired operation.

FCC RF Exposure requirements:

The equipment complies with FCC RF exposure limits set forth for an uncontrolled environment.

This device and its antenna(s) must not be co-located or operating in conjunction with any other antenna or transmitter.

FEDERAL COMMUNICATIONS COMMISSION INTERFERENCE STATEMENT

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/ TV technician for help.

CAUTION:

Any changes or modifications not expressly approved by the grantee of this device could void the user's authority to operate the equipment.