

Recovering MC56F8300 Family Devices from Extreme RFI

by: **John L. Winters**
AI SG, Senior DSC Application Engineer
Tempe Arizona
USA

Contents

1 Introduction

Some DSC's are subjected to extreme Radio Frequency Interference (RFI) during end customer product testing. During this extreme RFI, it is expected that the product will stop functioning. In some very extreme cases the RFI induces a state in the DSC that will not clear itself when the RFI is removed. In this case, the DSC reset pin may be used to restore DSC operation. For the extremely rare case where the reset pin does not clear the condition, the device is cleared with a power cycle. For those customers who do not wish to use a power cycle to restore operation under these extreme conditions, two alternatives to a power cycle are discussed in this application note. Sufficient detail is provided to implement one or the other solution, if needed.

This application note details two alternative methods for resetting a Freescale MC56F8300 family device besides the nominal reset pin function, the nominal JTAG sequences, and the nominal power on reset. The nominal methods are not treated in this document. Information about them is available in:

- Reference manual titled *DSP56800E and DSP56800EX* revision 3, (document number DSP56800ERM)
- The data sheet for your particular device
- User manual titled *56F800 Peripheral User Manual Also Supports 56F8100 Device Family*, revision 10 (document number MC56F8300UM)

Two special methods covered in this application note are:

1	Introduction.....	1
2	Special JTAG sequence to force a logical power on reset.....	2
2.1	HBUG script used to generate the JTAG signal traffic.....	2
2.2	Data capture from logic analyzer.....	3
3	Using the OCR_DIS pin to effect a power on reset.....	11
4	Conclusion.....	11

Special JTAG sequence to force a logical power on reset

- Use of a special JTAG sequence to force a power on reset rather than a pin reset — This approach works on all 56F8300 devices, in all configurations as long as there is access to the JTAG pins and they are configured for use as JTAG pins at the time of the extreme RFI event.
- Use of the OCR_DIS pin in a special manner contraindicated by the data sheet— if available in the package and the design— to force the core voltage level below the reset threshold thereby effecting a true power on reset. This approach works as long as the voltage regulators are used to build up the 2.5 volts needed by the core on the VCAP pins. This is normally the case if capacitors are installed on the VCAP pins rather than a 2.5 volt power source.

2 Special JTAG sequence to force a logical power on reset

It is beyond the scope of this application note to cover all the topics required to use JTAG. However, further information on JTAG and the TAP is available in the documents cited above, as well as the industry standard IEEE1149. This section focuses on the actual JTAG command sequence developed using HBUG, a software tool available from Freescale under NDA. The data on the JTAG interface was captured and recorded using a logic analyzer attached to an MC56F8355 device controlled by HBUG.

The details of the TAP command are proprietary to Freescale, but many of them are documented in the HBUG Perl program and its associated documentation. There is no charge for HBUG, but the execution of an NDA is mandatory to obtain HBUG. HBUG comes with training and documentation materials, but is not supported by Freescale after its delivery.

NOTE

To request HBUG under NDA, please contact your Freescale sales representative or your distributor.

Some Perl scripts for HBUG offer an explanation as a starting point to understand the actual JTAG sequence HBUG produced to effect the power on reset of the 8300 family devices. Then, the actual data capture from the resulting JTAG sequence is shown. Both the rising and falling edges of TCK is used to trigger the state style logic analyzer data capture of the JTAG interface.

2.1 HBUG script used to generate the JTAG signal traffic

The RFI results in a condition where the device does not respond to the reset pin. However, the JTAG tap is working normally. This makes it possible to command the device to effect a power on reset.

The HBUG session log used to generate the power on reset is shown below. The lines that begin with '#' indicate a response from the HBUG program. Lines ending in ';' are a command to HBUG from the HBUG console. HBUG was connected from the PC via the parallel port through a parallel port to the JTAG converter to the JTAG port of the device that was not responding to the reset pin.

The following HBUG commands restore the device to running condition:

```
reset_to_rti();
# Negative transition on RESETB
# Negative transition on TRSTB
# Positive transition on TRSTB
# => 1
check_chip_id(1);
# Found DSP56F8345 (Monza C) chip TAP IDCODE = 11F4401D.
# => 0
shift_instruction(CHIP_LOCKOUT_RECOVERY, X);
# => 01
shift_data("8000",X);
# => 0000
shift_instruction(CHIP_KTR_EN,X);
# => 01
shift_data("0420",X);
# => 0000
```

```
# Negative transition on TRSTB
# Positive transition on TRSTB
# Found DSP56F8345 (Monza C) chip TAP IDCODE = 11F4401D.
# Switching to Hawk V2 TAP controller...
# Found expected Hawk V2 TAP IDCODE value = 02211004.
# Postive transition on RESETB
# D=>Debug: DSP core halted and in Debug Mode
# Negative transition on RESETB
# Negative transition on TRSTB
# Postive transition on RESETB
# Positive transition on TRSTB
```

Subsequent to this, the device operates normally. The JTAG signals were recorded and are included in section 2.2

The key to this script working is the setting of bit 10 of the KTR (kernel test register). This is done with the shift_data HBUG command, shift_data("0420",X).

2.2 Data capture from logic analyzer

The data captured from the logic analyzer is recorded in the table below. The data is available in simple text format as captured on the logic analyzer from Freescale with this application note.

State Counts	TRST_B	RESET_B	TDI	TDO	TMS	TCK
0	0	0	0	0	0	1
1	0	0	0	0	1	0
2	0	0	0	0	1	1
3	0	0	0	0	1	0
4	0	0	0	0	1	1
5	0	0	0	0	1	0
6	0	0	0	0	1	1
7	0	0	0	0	1	0
8	0	0	0	0	1	1
9	0	0	0	0	1	0
10	0	0	0	0	1	1
11	0	0	0	0	1	0
12	1	0	0	0	0	1
13	1	0	0	0	0	0
14	1	0	0	0	0	1
15	1	0	0	0	0	0
16	1	0	0	0	0	1
17	1	0	0	0	0	0
18	1	0	0	0	1	1
19	0	0	0	0	1	0
20	1	0	0	0	1	1
21	1	0	0	0	1	0

Table continues on the next page...

Special JTAG sequence to force a logical power on reset

State Counts	TRST_B	RESET_B	TDI	TDO	TMS	TCK
22	1	0	0	0	0	1
23	1	0	0	0	0	0
24	1	0	0	0	0	1
25	1	0	0	0	0	0
26	1	0	0	0	0	1
27	1	0	0	1	0	0
28	1	0	1	1	0	1
29	1	0	1	0	0	0
30	1	0	0	0	0	1
31	1	0	0	0	0	0
32	1	0	0	0	0	1
33	1	0	0	0	0	0
34	1	0	0	0	0	1
35	1	0	0	0	0	0
36	1	0	0	0	0	1
37	1	0	0	0	0	0
38	1	0	0	0	0	1
39	1	0	0	0	0	0
40	1	0	0	0	1	1
41	1	0	0	0	1	0
42	1	0	0	0	1	1
43	1	0	0	0	1	0
44	1	0	0	0	0	1
45	1	0	0	0	0	0
46	1	0	0	0	1	1
47	1	0	0	0	1	0
48	1	0	0	0	0	1
49	1	0	0	0	0	0
50	1	0	0	0	0	1
51	1	0	0	0	0	0
52	1	0	0	0	0	1
53	1	0	0	1	0	0
54	1	0	0	1	0	1
55	1	0	0	0	0	0
56	1	0	0	0	0	1
57	1	0	0	1	0	0

Table continues on the next page...

State Counts	TRST_B	RESET_B	TDI	TDO	TMS	TCK
58	1	0	0	1	0	1
59	1	0	0	1	0	0
60	1	0	0	1	0	1
61	1	0	0	1	0	0
62	1	0	0	1	0	1
63	1	0	0	0	0	0
64	1	0	0	0	0	1
65	1	0	0	0	0	0
66	1	0	0	0	0	1
67	1	0	0	0	0	0
68	1	0	0	0	0	1
69	1	0	0	0	0	0
70	1	0	0	0	0	1
71	1	0	0	0	0	0
72		0	0	0	0	1
73	1	0	0	0	0	0
74	1	0	0	0	0	1
75	1	0	0	0	0	0
76	1	0	0	0	0	1
77	1	0	0	0	0	0
78	1	0	0	0	0	1
79	1	0	0	0	0	0
80	1	0	0	0	0	1
81	1	0	0	1	0	0
82	1	0	0	1	0	1
83	1	0	0	0	0	0
84	1	0	0	0	0	1
85	1	0	0	0	0	0
86	1	0	0	0	0	1
87	1	0	0	0	0	0
88	1	0	0	0	0	1
89	1	0	0	1	0	0
90	1	0	0	1	0	1
91	1	0	0	0	0	0
92	1	0	0	0	0	1
93	1	0	0	1	0	0

Table continues on the next page...

Special JTAG sequence to force a logical power on reset

State Counts	TRST_B	RESET_B	TDI	TDO	TMS	TCK
94	1	0	0	1	0	1
95	1	0	0	1	0	0
96	1	0	0	1	0	1
97	1	0	0	1	0	0
98	1	0	0	1	0	1
99	1	0	0	1	0	0
100	1	0	0	1	0	1
101	1	0	0	1	0	0
102	1	0	0	1	0	1
103	1	0	0	0	0	0
104	1	0	0	0	0	1
105	1	0	0	0	0	0
106	1	0	0	0	0	1
107	1	0	0	0	0	0
108	1	0	0	0	0	1
109	1	0	0	1	0	0
110	1	0	0	1	0	1
111	1	0	0	0	0	0
112	1	0	0	0	0	1
113	1	0	0	0	0	0
114	1	0	0	0	0	1
115	1	0	0	0	1	0
116	1	0	0	0	1	1
117	1	0	0	0	1	0
118	1	0	0	0	0	1
119	1	0	0	0	0	0
120	1	0	0	0	1	1
121	1	0	0	0	1	0
122	1	0	0	0	1	1
123	1	0	0	0	1	0
124	1	0	0	0	0	1
125	1	0	0	0	0	0
126	1	0	0	0	0	1
127	1	0	0	0	0	0
128	1	0	0	0	0	1
129	1	0	0	1	0	0

Table continues on the next page...

State Counts	TRST_B	RESET_B	TDI	TDO	TMS	TCK
130	1	0	0	1	0	1
131	1	0	0	0	0	0
132	1	0	0	0	0	1
133	1	0	0	0	0	0
134	1	0	1	0	0	1
135	1	0	1	0	0	0
136	1	0	0	0	0	1
137	1	0	0	0	0	0
138	1	0	0	0	0	1
139	1	0	0	0	0	0
140	1	0	0	0	0	1
141	1	0	0	0	0	0
142	1	0	0	0	1	1
143	1	0	0	0	1	0
144	1	0	0	0	1	1
145	1	0	0	0	1	0
146	1	0	0	0	0	1
147	1	0	0	0	0	0
148	1	0	0	0	1	1
149	1	0	0	0	1	0
150	1	0	0	0	0	1
151	1	0	0	0	0	0
152	1	0	0	0	0	1
153	1	0	0	0	0	0
154	1	0	0	0	0	1
155	1	0	0	0	0	0
156	1	0	0	0	0	1
157	1	0	0	0	0	0
158	1	0	0	0	0	1
159	1	0	0	0	0	0
160	1	0	0	0	0	1
161	1	0	0	0	0	0
162	1	0	0	0	0	1
163	1	0	0	0	0	0
164	1	0	0	0	0	1
165	1	0	0	0	0	0

Table continues on the next page...

Special JTAG sequence to force a logical power on reset

State Counts	TRST_B	RESET_B	TDI	TDO	TMS	TCK
166	1	0	0	0	0	1
167	1	0	0	0	0	0
168	1	0	0	0	0	1
169	1	0	0	0	0	0
170	1	0	0	0	0	1
171	1	0	0	0	0	0
172	1	0	0	0	0	1
173	1	0	0	0	0	0
174	1	0	0	0	0	1
175	1	0	0	0	0	0
176	1	0	0	0	0	1
177	1	0	0	0	0	0
178	1	0	0	0	0	1
179	1	0	0	0	0	0
180	1	0	0	0	0	1
181	1	0	0	0	0	0
182	1	0	0	0	0	1
183	1	0	0	0	0	0
184	1	0	1	0	1	1
185	1	0	1	0	1	0
186	1	0	0	0	1	1
187	1	0	0	0	1	0
188	1	0	0	0	0	1
189	1	0	0	0	0	0
190	1	0	0	0	1	1
191	1	0	0	0	1	0
192	1	0	0	0	1	1
193	1	0	0	0	1	0
194	1	0	0	0	0	1
195	1	0	0	0	0	0
196	1	0	0	0	0	1
197	1	0	0	0	0	0
198	1	0	0	0	0	1
199	1	0	0	1	0	0
200	1	0	0	1	0	1
201	1	0	0	0	0	0

Table continues on the next page...

State Counts	TRST_B	RESET_B	TDI	TDO	TMS	TCK
202	1	0	1	0	0	1
203	1	0	1	0	0	0
204	1	0	0	0	0	1
205	1	0	0	0	0	0
206	1	0	0	0	0	1
207	1	0	0	0	0	0
208	1	0	0	0	0	1
209	1	0	0	0	0	0
210	1	0	0	0	0	1
211	1	0	0	0	0	0
212	1	0	0	0	1	1
213	1	0	0	0	1	0
214	1	0	0	0	1	1
215	1	0	0	0	1	0
216	1	0	0	0	0	1
217	1	0	0	0	0	0
218	1	0	0	0	1	1
219	1	0	0	0	1	0
220	1	0	0	0	0	1
221	1	0	0	0	0	0
222	1	0	0	0	0	1
223	1	0	0	0	0	0
224	1	0	0	0	0	1
225	1	0	0	0	0	0
226	1	0	0	0	0	1
227	1	0	0	0	0	0
228	1	0	0	0	0	1
229	1	0	0	0	0	0
230	1	0	0	0	0	1
231	1	0	0	0	0	0
232	1	0	0	0	0	1
233	1	0	0	0	0	0
234	1	0	1	0	0	1
235	1	0	1	0	0	0
236	1	0	0	0	0	1
237	1	0	0	0	0	0

Table continues on the next page...

Special JTAG sequence to force a logical power on reset

State Counts	TRST_B	RESET_B	TDI	TDO	TMS	TCK
238	1	0	0	0	0	1
239	1	0	0	0	0	0
240	1	0	0	0	0	1
241	1	0	0	0	0	0
242	1	0	0	0	0	1
243	1	0	0	0	0	0
244	1	0	1	0	0	1
245	1	0	1	0	0	0
246	1	0	0	0	0	1
247	1	0	0	0	0	0
248	1	0	0	0	0	1
249	1	0	0	0	0	0
250	1	0	0	0	0	1
251	1	0	0	0	0	0
252	1	0	0	0	0	1
253	1	0	0	0	0	0
254	1	0	0	0	1	1
255	1	0	0	0	1	0
256	1	0	0	0	1	1
257	1	0	0	0	1	0
258	1	0	0	0	0	1
259	1	0	0	0	0	0
260	0	0	0	0	0	1
261	0	0	0	0	1	0
262	0	0	0	0	1	1
263	0	0	0	0	1	0
264	0	0	0	0	1	1
265	0	0	0	0	1	0
266	0	0	0	0	1	1
267	0	0	0	0	1	0
268	0	0	0	0	1	1
269	0	0	0	0	1	0
270	0	0	0	0	1	1
271	1	1	0	0	0	0
272	1	1	0	0	0	1
273	1	1	0	0	0	0

Table continues on the next page...

State Counts	TRST_B	RESET_B	TDI	TDO	TMS	TCK
274	1	1	0	0	0	1
275	1	1	0	0	0	0

3 Using the OCR_DIS pin to effect a power on reset

In cases where the OCR_DIS pin is available, and the VCAP pins are attached to capacitors and not to an external voltage source (of 2.5 Volts), the OCR_DIS pin may be used to cause power distribution inside the device to cease. This results in a power on reset.

To use this method, use OCR_DIS to disable the voltage regulator until the voltage on VCAP falls low enough to trigger a power on reset. The time this needs to be held (pulse width on OCR_DIS) depends on the capacitance available and the current draw of the device after being disabled by the extreme RFI.

4 Conclusion

This application note details two alternative methods for resetting a Freescale MC56F8300 family device besides the nominal reset pin function, the nominal JTAG sequences, and the nominal power on reset:

- JTAG pins
- OCR_DIS pin

These methods need to be considered only if the application involves extreme RFI, such as can be achieved with difficulty even in a laboratory environment. Which, if any, of the options to implement would depend on the available resources..

How to Reach Us:

Home Page:

www.freescale.com

Web Support:

<http://www.freescale.com/support>

USA/Europe or Locations Not Listed:

Freescale Semiconductor
Technical Information Center, EL516
2100 East Elliot Road
Tempe, Arizona 85284
+1-800-521-6274 or +1-480-768-2130
www.freescale.com/support

Europe, Middle East, and Africa:

Freescale Halbleiter Deutschland GmbH
Technical Information Center
Schatzbogen 7
81829 Muenchen, Germany
+44 1296 380 456 (English)
+46 8 52200080 (English)
+49 89 92103 559 (German)
+33 1 69 35 48 48 (French)
www.freescale.com/support

Japan:

Freescale Semiconductor Japan Ltd.
Headquarters
ARCO Tower 15F
1-8-1, Shimo-Meguro, Meguro-ku,
Tokyo 153-0064
Japan
0120 191014 or +81 3 5437 9125
support.japan@freescale.com

Asia/Pacific:

Freescale Semiconductor China Ltd.
Exchange Building 23F
No. 118 Jianguo Road
Chaoyang District
Beijing 100022
China
+86 10 5879 8000
support.asia@freescale.com

For Literature Requests Only:

Freescale Semiconductor Literature Distribution Center
1-800-441-2447 or +1-303-675-2140
Fax: +1-303-675-2150
LDCForFreescaleSemiconductor@hibbertgroup.com

Information in this document is provided solely to enable system and software implementers to use Freescale Semiconductors products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Freescale Semiconductor reserves the right to make changes without further notice to any products herein. Freescale Semiconductor makes no warranty, representation, or guarantee regarding the suitability of its products for any particular purpose, nor does Freescale Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any liability, including without limitation consequential or incidental damages. "Typical" parameters that may be provided in Freescale Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals", must be validated for each customer application by customer's technical experts. Freescale Semiconductor does not convey any license under its patent rights nor the rights of others. Freescale Semiconductor products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which failure of the Freescale Semiconductor product could create a situation where personal injury or death may occur. Should Buyer purchase or use Freescale Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify Freescale Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claims alleges that Freescale Semiconductor was negligent regarding the design or manufacture of the part.

RoHS-compliant and/or Pb-free versions of Freescale products have the functionality and electrical characteristics as their non-RoHS-complaint and/or non-Pb-free counterparts. For further information, see <http://www.freescale.com> or contact your Freescale sales representative.

For information on Freescale's Environmental Products program, go to <http://www.freescale.com/epp>.

Freescale™ and the Freescale logo are trademarks of Freescale Semiconductor, Inc. All other product or service names are the property of their respective owners.

© 2012 Freescale Semiconductor, Inc.