

**LYX PRO**  
**BLUETOOTH® AUDIO TRANSMITTER**  
**User Guide**  
 LYXBWR7



Thank you for purchasing the LyxPro Bluetooth® audio transmitter. This User Guide is intended to provide you with guidelines to ensure that operation of this product is safe and does not pose risk to the user. Any use that does not conform to the guidelines described in this User Guide may void the limited warranty.


For the safe and correct use of this product, please read this guide before using the product and keep these instructions for reference.

**Overview**

Instantly add Bluetooth functionality to non-Bluetooth devices. The LyxPro Bluetooth transmitter is compatible with most devices having a 3.5mm aux. output. It broadcasts high-quality stereo sound from your computer, laptop, music player, TV, mic, and other devices to your Bluetooth-enabled headphones, speaker, or audio system. Listen to music, TV, movies, or games via Bluetooth headphones without disturbing others and without wires restricting your movements.

**Package Contents:**

- LyxPro Bluetooth transmitter
- USB charging cable
- User guide



**Safety Precautions**

Please read this user guide carefully and follow all instructions. Retain this guide for future reference.

- Be careful not to drop the device. Damage may occur.
- Keep device away from humidity, water and any other liquid. If the device is exposed to water or other liquids or high moisture, do not operate it to avoid any electrical shock, explosion, damage to the device, or injury to yourself.
- Do not place or keep this device in direct sunlight or near any heat sources such as radiators, stoves or other equipment that produces heat. This may cause an explosion, degrade product performance and/or reduce battery life.
- Do not modify, repair or disassemble device. Doing this will void the warranty.
- Do not place heavy objects on the device.
- Please contact the retailer for replacement or support for this product.
- Unplug this device when unused for long periods of time or during lightning storms.
- The battery used in this device may present a risk of fire or chemical burn if mistreated.

**Battery Information**

This device is equipped with an integrated lithium-polymer battery. The battery cannot be replaced. Do not attempt to remove the battery from the device. Damage could occur. The battery can be charged and discharged several hundred times, but it loses its capacity over time.

**Important:**

If the transmitter is not used for a long period of time, make sure that the battery is fully charged before using the device again. To avoid a complete discharge of the battery, charge it at least every 6 months.

**Charging the Battery**

Charge the battery completely before first using the product.

1. Connect the charging cable to the USB port on the transmitter.
2. Connect the other end of the cable to a USB power supply such as a computer or charging adapter.
3. The red indicator light will turn on while the charger is connected. Charging the battery fully may take up to 2 hours.
4. The red indicator light will turn blue when the battery is fully charged. Disconnect the charger from the device and the power supply.

**NOTE:**

- The fully charged battery provides power for up to 6 hours of play time. Play times may vary according to different Bluetooth devices, usage settings, usage styles, and environments.
- When the battery power is low, the red indicator light will flash.

**Pairing**

Pairing is required only for the first connection to a new earphone or speaker or other audio device.

To pair a device to this receiver requires that the device supports the A2DP Bluetooth profile. Attaching this transmitter to a phone, music player, computer or other audio source requires that the device has a 3.5mm jack.

1. Turn on the pairing mode on your Bluetooth-enabled listening device. Make sure that the Bluetooth transmitter is located within 3 feet of the device.
2. Press and hold the transmitter's multifunction button for 5 seconds to enter the search mode. The LED indicator will flash red and blue.

3. The pairing process may take around 20 – 30 seconds. The indicator will flash blue when pairing is successfully completed.
4. The transmitter is now ready to use. Connect the audio cable to the audio jack of the source device.

NOTE: If pairing is not completed within 5 minutes, the LED indicator will turn off. If this happens, repeat the pairing process.

**Operation**

**TURNING ON AND OFF**

Press and hold multifunction button for 3 seconds.

**CONNECTING TO HEADPHONES OR SPEAKER**

If the transmitter has previously been paired to headphones, a speaker, or other listening device, when you next turn it on it will automatically reconnect to the last device used.

**TURNING OFF**

Press and hold multifunction button for 5 seconds. The indicator light will flash red 3 times and the unit will power off.

**Specifications:**

Bluetooth version: V3.0  
 Operating frequency: 2.402 – 2.48GHz  
 Operating range: up to 30 ft. (10m)  
 Supported profile: A2DP  
 Power input: DC 5V/USB  
 Audio input port: 3.5mm 1/8" jack  
 Dimensions: approx. 1.3/4" x 1" x 1/2" (40 x 25 x 11mm)

**Customer Service:**

info@lyxpro.com | 866-849-3049

Distributed by  
 C&A Marketing, Inc.  
 154 Tweed Lane East  
 Edison, NJ 08837 USA  
 www.lyxpro.com

C&A Marketing UK LTD  
 167 Hermitage Road  
 Crusader Industrial Estate  
 London N4 1LZ  
 United Kingdom

info@lyxpro.com  
 MADE IN CHINA  
 LyxPro is a trademark of  
 C&A IP Holdings, LLC  
 ©2016 All Rights Reserved

**FCC Statement**

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help