

RE152 GE-Compatible Code Keypad

Features

- Secure, 4-digit Code to disarm
- 1-button arming
- Red/Green LED arming feedback
- Small, yet comfortable keypad
- Mounts on wall via VHB® tape, or screws
- · Secure for carrying in purse or mounting on car visor
- Strong, reliable RF signal.
- 4-6 year battery life on CR2032 battery.

Key Instructions

Code programming

Default access code is "1234".

To change access code:

- 1. Enter current 4-digit access code.
- Within 4 seconds, press and hold the "1" and "3" keys simultaneously. After 3 seconds, Red LED will be lit.
- 3. Enter new 4-digit access code. After successfully changing the code, the Green LED will be lit
- 4. Note new access code . BAD GUY CANNOT RESET CODE. So it must be noted and remembered!
- Enrolling:
 - 1. Refer to the GE control unit installation manual.
 - 2. Put the control panel in RF Learning mode.
 - Press both the Stay & Away buttons simultaneously for 3 seconds.
 - 3. ...Or if using a Downloader in ID entry mode
 - Enter the Download ID the device (located on a label on the unit's back or in unit).

Operation

Stay button → Arms panel to STAY, keypad flashes double red.

Away button → Arms panel to AWAY, keypad flashes double red twice.

Stay & Away buttons simultaneously for 3 seconds → Panic Alarm.

Keypad flashes red 8 times.

Entering 4-digit code → Disarms panel, keypad flashes double green.

Specifications

More securely replaces: GE TX-3030-01-1 4-button Wall Touchpad

Crystal Compatibility


Not supervised.

Replacement Battery: CR2032 Lithium / Manganese Dioxide

Temperature Range: 0F to 120F

Housing dimensions: 2x2.25x0.33 inches

Specifications subject to change without notice.



Battery Replacement



Insert Screwdriver here to open



Notices

"GE", "Honeywell", and "DSC" are trademarks owned by General Electric Company. Honeywell International Inc., and Tyco Safety Products Canada LTD, respectively.

Resolution Products, Inc. products will function with one of either GE, DSC or Honeywell systems. However, no Resolution product is produced by, endorsed by, nor is officially associated with GE, Honeywell or DSC. Resolution recommends verifying operation at installation.

Warranty Resolution Products, Inc. will replace products that are defective in their first year.

FCC Notice
This device complies with Part 15 of the FCC rules. Operation is subject to the

This device may not cause harmful interference.

This device must accept any interference that may be received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the Resolution Products, Inc. could void the user's authority to operate this equipment.

FCC ID: U5X-RE152

IC Notice

This product meets the applicable Industry Canada technical specifications/Le présent materiel est conforme aux specifications techniques applicables d'Industrie Canada.

IC: 8310A-RE152