

DIE LAYOUT

200gsm SBS Coated 2-sides

**Front**  
135.7 [5+11/32]  
316.01 [12+7/16]

**Back**  
135.7 [5+11/32]  
316.01 [12+7/16]

**Front View Content:**

- What's in the box:** Cradle and faceplate (for optional wall-mounting), Controller, CR2032 battery (Install + side up).
- What you'll need:** To control Wemo Stage, you'll need an iPhone or iPad and a HomePod, Apple TV or iPad set up as a home hub. Make sure your devices have the latest software and operating system updates. Works with Apple HomeKit.
- Quick setup:** Use the Apple Home app to: 1. Add Wemo Stage as an accessory. 2. Create scenes that control your smart devices. 3. Assign scenes to buttons on Wemo Stage.
- 1 Adding to Apple Home:** 1. Install battery into the controller with the positive side facing up. 2. Wait for the controller to enter setup mode (light blinks yellow and green). 3. Launch the Apple Home app. 4. Hold your phone near the controller and follow the prompts when they appear. For iPhone X or below, you'll need to add (+) Wemo Stage as an accessory in the Home app.
- 2 Creating scenes:** Scenes allow you to automatically control single or multiple smart devices with the touch of a button. **Creating scenes in the Home app:** 1. Add a scene (+) from the Home app. 2. Choose a scene name or create a custom name. 3. Add accessories (smart devices) to the scene. 4. Assign actions to these accessories (example: turn on/off a light).
- 3 Assigning scenes:** Your Wemo Stage can trigger up to 6 scenes. Each button can be assigned a scene for a short press or long press. **Assigning scenes to buttons in the Home app:** 1. Tap your Wemo Stage from the list of accessories. 2. Decide which button you want to assign the scene to, then choose short press or long press. 3. Assign your scenes.

**Back View Content:**

- Example scenes:**
  - Bedtime:** Place Wemo Stage on your bedside table. Before sleeping, press to turn off all your home lights and turn on your security system.
  - Entertainment:** Place Wemo Stage on your coffee table. When ready to party, press to dim the lights and turn on the music or TV.
  - Guest room on/off:** Give guests control of smart lights, fans, blinds, and other devices in their room.
- Status light:**
  - Off:** Working normally; press any button to show status.
  - Green:** A scene has been triggered or setup has just completed.
  - Yellow:** Low-battery level.
  - Blinking Yellow:** An error has occurred.
  - Yellow and Green (Alternating):** Ready for setup.
- Installing or changing battery:** Remove the cover on the back of the controller. Install CR2032 battery in the compartment positive (+) side up. Replace back cover.
- Troubleshooting:**
  - Restart:** Having setup or control issues? Remove and re-insert the battery to restart.
  - Factory restore:** If a restart doesn't help, factory restore your controller. 1. Press and hold Restore button for 5 seconds. 2. Wait for the light to blink yellow, then green and release. 3. Re-add your Wemo Stage to Apple Home and reassign scenes to buttons.
- Wall-mounting:** Thoroughly clean wall surface. Remove the paper from the adhesive strips on the back of the cradle. Attach the cradle to the wall. Snap the faceplate onto the mounted cradle. A magnet in the controller holds it to the wall mount.
- Have questions?:** HomeKit Setup Code. Keep this HomeKit Code handy in case you need it for setup later. Wemo Stage Support. Visit [wemo.com/Stage](http://wemo.com/Stage) for support with your Wemo Stage or call us at 1-844-765-WEMO. For warranty information, go to [wemo.com/warranty](http://wemo.com/warranty).

Business Unit: **Belkin**  
Program Manager:  
Packaging Engineer: **Caleb Nelson**  
Retail Outside Dimension (Including Hang Tab)  
L x W x D (in):  
L x W x D (mm):

DIE/MATERIAL SPECS:  
Material: Please refer to drawing  
Blank Size (in): 316.01 x 308.70  
Blank Size (mm): 316.01 x 308.70

This dieline works for following skus (if any):  
  
WSC010

Unit: IN/MM  
Side Shown: PRINT SIDE  
Flute/Grain: horizontal  
Tolerance: +/- 1/32" - 0.8mm  
Drawing Scale 1:1

RELEASE DATE: 12/15/2020  
DIELINE:  
**Caleb Nelson**

THIS DOCUMENT & THE INFORMATION IN IT ARE THE CONFIDENTIAL PROPERTY OF BELKIN INTERNATIONAL AND MUST NOT BE COPIED, REPRODUCED OR USED IN ANY MANNER WITHOUT THE WRITTEN CONSENT OF BELKIN CORPORATION. IT MUST BE RETURNED UPON REQUEST

PRINT SPECS:  
Color Plates:

Finish: **OVERALL PP COAT**

Notes: ALL TEXT AND GRAPHIC ELEMENTS COLOR: CMYK, PMS 7488C

**DO NOT PRINT DIE LINES, PRINTERS NOTES**