

Motorola, Inc. Consumer Advacacy Office 1307 East Algorous Float Schaumburg, IL 60196

WWW ZWROTOTO COTT 1-8777-MOTOREU 1-886-310-6486 (TTV/TDD United States for Pearing impaired?


Guide Number: 6800516A34-O

Elastooth (D: yourse)

BEFORE YOU BEGIN

Shallow yang tris product, must the traintent Salaty and Jugat Hillemanns participate and foliose by missachure.

Take a moment before you get started to familiarize yourself with your new HTZ-1Bluetooth Handsfree Headset. Along with your headset, both a charger case and charger stand are provided for both charging and storage.





when charging. If you turned headset on, see "Turning Headset On and Off" on reverse side for details on turning headset off.

- 1 Remove plastic seal off of earbud on speaker.
- 2 Plug the Motorola charger into the port on the d'arger case or charger stand.
- 3a If using charger case, place headset into case ensuring that charging contacts on the headset and charging case connect.



Note: Heart is not functional white charging

The indicator light turns red when the bettery is charging. It may take up to 1 minute for the indicator light to turn on. When the headset's bettery is fully charged labout 2.5. hours), the indicator light turns off.

3b If using charger stand, place headset onto stand ensuring that charging contacts on the headsist and charging stand connect.



The indicator light turns red when the bettery is charging. It may take up to 1 minute for the indicator light to turn on. When the Needset's bettery is fully charged labout 2.5 hours), the indicator light turns off.

4 Disconnect the charger.

START BLUETOOTH FEATURE

Your Phone

Your phone's Bluetooth feeture is off by default. To use your headset, you must turn on the Bluetooth feature in your phone.

For most Motorola phones (at the main menul)

- 1 Press (Y) Many . Lettings . Connection . Bineteeth link . Setup.
- 2 Scroll to Power.
- Select Change
- 4 Scroll to On.
- 5 Press Select to turn on the Bluetooth feature. The Bluetooth feature remains on until you turn the feature off.

Note: These steps are for most Motorcia phones. For other phones, see your phone's user's guide.

(3)

PAIR

Your Headset

Before you can use your headset, you must pair flink! it with your phone.

Step A - ENSURE HEADSET IS IN PAIRING MODE

Flemove headset from charging base or stand and power on by sliding Flower switch to the Cin position (towards Flower symbol on headset). The indicator light first flashes during power up, then initiates easy pairing. After a lew moments, the indicator light will be steadily lit in blue to indicate headset is in paining mode



If the headset does not error pairing mode. one TROUBLESHOOTING for help.

Step B - SET YOUR PHONE TO LOOK FOR YOUR HEADSET

For most Motorola phones:

1 On your Motorpia phone, press III Messi » Settings - Connection - Blocketh Link -Bandsfree - Lauk for Bevices.

The phone lists Elsetooth devices it finds.

- 2 Seince Motorola H12
- 3 Select OK or Ves to pair your headset with
- 4 Enter the passing 0000
- 5 Select OK

When your needset successfully pers and connects with your phone, the indicator light changes from sheadily lit to flashing blue and

Note: These steps are for most Motorola phones.

TEST AND USE

Your phone and headset are now paired and ready to make and receive calls.

To make a call.

- 1 Place the headset overyour ear. See Wearing the Headant' on the reverse side of this guide.
- On the priorie, dial the number you want to call and press SEND lies on your priorie

If your phone and headest are successfully paired, you will hear ringing on the headset.

After you have successfully parced your phone and headset, you don't need to repeat these steps. For daily use, ensure that your headset is turned ON and that your phone's Bluetooth feature is ON.

USING YOUR H12-1

Features and **Functions** Guide on the reverse side for information on using your H12-1



TROUBLESHOOTING

My headset will not charge. Make sure your headset is surred off when charging. Your headset will not charge in the chains care while powered on

My headset will not enter pairing mode.

Make sum that any devices previously pared with the headest are turned off. If the indicator light is not steadily in its blue, turn off both the other device and feedball, well 10 seconds, ther turn headset back on Walf for the indicator light to become steadily it in blue, indicating the headset is now in paring mode.

My phone doesn't find my headset.

Make sure the indicator light on your headest is on lift in thus and standy when your phone is searching for devices (see step 3).

My headset worked before but now it's not

working.
Make sure your phone is on and the Bustooth feature is buried in in your phone lake 1969-21.
If the Bustooth feature was farmed off or was turned on only temporarily, you may need to restart the Bluetooth feature (see step 2) and pay your phone and headest again (see step 2).




Features and **Functions Guide**

IMPORTANT: Be sure to first follow the Quick Start Guide

on the reverse side of this guide to complete initial setup of your H12-1

European Union Directives Conformance Statement



- All other relevant EU Describes.




The above gives an exemple of a typical Product Approved Institute

We can new your products Destaution of Continuing (DoC) to Describe 1999; EC to PAFTE Described at some fectorals contribe. To Med your DoC, white the product Approval Manthew from your products below in the "Seaso" for my the west office.

TURNING HEADSET ON AND OFF

To turn your headset on, slide the Power switch on Itowards Power symbol on headset). The indicator light flashes blue and purple for several seconds then flashes blue if pared and connected with another device), or is steadily blue (if ready to be

To turn your headset off, slide the Power switch off. The indicator light will turn off.



Your headset's performance is greatly dependent upon achieving a good fit on your ear. Therefore, we recommend trying all the supplied serbuds with your headset.

EARBUDS AND YOUR HEADSET

Your H12-theadset is supplied with multiple earbuds. The earbud is fitted onto the end of your headset's earpiece speaker, and placed onto your ear when using your headset.



WEARING THE HEADSET

To wear your headset, flex the earhook and loop it over your ear as shown.



Be sure to position the ear bud into your ear canal for optimal audio performance and

CHANGING FOR USE ON OTHER EAR

You can wear your H12-Theadset on your left or right ear. The headset comes ready for the right ear. To change the headset for the left ear.

- 1 Gently lift and pull the top of the earhook up and off speaker stem as
- 2. Flip the headset over.
- 3 Attach the earhook to the speaker stem as: shown.

CHECKING BATTERY LEVEL

While turned on and not on a call, you can check your headset's battery charge level by pressing and holding both Volume

The indicator light displays charge status until you release the buttons. See "Indicator Light" for details on indicator light and charge status.

STORING YOUR HEADSET

Both the charger case and charger stand are used to charge and store your headset. When not using your headset, you should place it in the charger base or stand. Be sure to turn the headset off before placing it into the charger case or charger stand.

For the charger case, a cover can be placed on top of the case, or underheath it to provide support for desktop placement as shown.





MAKING CALLS

Function	Action
Receive a cell	Tap the Call button
Mute or unmute a call	Tap both Volume buttons
Reject a call	Press and hold a Volume button until you hear two descending tones
End a call	Tap the Call button
Reduil last cell	Press and hold the Call button until you have two ascending tones
Make a voice dal call	Tup the Call button and speak the name after the tone

Profiles. Accessing our functions depends upon which pottle your phone supports. See your phone is user's guide An experience information.

MAKING CALLS CONTINUED

MB .	Function	Action	
ne Call button	Answer a second incoming call	Tap the Call button	
oth Volume na	End an active call and	Tap the Call button	
and hold a ne button until lear two ending tones	resume a call on hold		
	Reject a second accoming cell	Press and hold eith Volume button unti you hear an audio	
he Call button		tone.	
and hold the aution until you two secending	Disable the indicator light	Side Power switch off, then press and hold both Volume buttons AMD side Power switch	
he Call button peak the after the tone		on to turn headset ore	
S MANDEL - FILLE, SPECIME	Atomic Street, Street, and address.	when you down a day	

Note: Some Betures are phone/hetivioris dependent

INDICATOR LIGHT

With the Charger Plugged In

Headset Indicator	Headset Status
Red	Charging (battery level less than 80%; charge)
Yellow	Charging (tettery level more than 80% charge)
Green	Charging complete
When Ch	necking Battery Level
Headest Indicator	Avadable Talk Time
Red	Up to 6 hours
Yellow	30 minutes to 5 hours
Direct	Less than 30 minutes

INDICATOR LIGHT

With No Charger Plugged In		
Headset Indicator	Hendset Status	
Off	Power off	
Three blue flashes	Powering pryoff	
Steady blue	Paining mode	
Rapid blumpurple flashes.	Connection successful	
Quick blue flash	Incoming/outgoing call	
Slow blue pulse	Connected ion a call	
Slow blue flesh	Standby (not on a call)	
Slow red flash	idle inot connected to phone)	
Slow purple pulse	Connected call mused	
Quick red flash	Low battery	
Note: After 20 minutes on a self-	or of mactivity. The light stock	

flashing to commerce power but the headed remains on.

AUDIOTONES

Audio Tone	Headset Status
Ring tone	Incoming call
Single high tone	Phone network not evaluable
High to low tone	End call
Single high tone when pressing volume button during a call	Volume at minimum or maximum
Two ascending tones	Mute enabled
Two descending tones	Mute disabled
Low to high tone	Connection confirmation/voice activation
No audio indications; deteriorating quality	Out of range

Low battery

Two tones

repeated every 30 sec.

. Do not store headset williest swright

. Storing headset fully charged in high educe the life of the internal battery.

ADDITIONAL SAFETY INFORMATION

Along with instructions in the Safety and Legal Information pamphiet, please note the following additional safety instructions

- . Do not store or use headast in temperatures lower than 10°C / 4°F or higher than 50°C / 122°F.
- Do not micharge headset in temperatures lower than DYC / 32°F or higher than 40°C / 104°F.
- Conditions inside a parked on sale exceed this temperature range. Do not store headset in a period cer-

- Battery life may temporarily shorten in low-temperature conditions.

FCC statement in User's Manual (for class B)

"Federal Communications Commission (FCC) Statement

This Equipment has been tested and found to comply with the limits for a class B digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC Caution:

- 1.The device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions:
 - (1) This device may not cause harmful interference, and
 - (2) this device must accept any interference received, including interference that may cause undesired operation.
- 2. This device and its antenna(s) must not be co-located or operating in conjunction with any other antenna or transmitter.
- Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user authority to operate the equipment.

IC Statement

In addition to the requirements of Section 7.1.5 in RSS-Gen, the device's shall also contain the following or equivalent statement: "Privacy of communications may not be ensured when using this telephone".

If privacy is provided as a standard feature, the privacy notice may be omitted provided that full justification accompanies the equipment certification application for evaluation by Industry Canada.