



Cobra

CDR855BT

QUICK START GUIDE



drive HD™



Record your ride

HDMI, the HDMI logo, and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing, LLC in the United States and/or other countries.

The Bluetooth® word mark is a registered trademark owned by Bluetooth SIG, Inc. and any use of such marks by Cobra Electronics Corporation is under license. Other trademarks and trade names are those of their respective owners.

©2015 Cobra Electronics Corp., Part No.: 480-1039-P, Printed in China, Version B



CONTROLS & CONNECTIONS



The functions of Buttons 1-4 are indicated by the icon directly above each button and change depending on the state of the unit.

KEY DASH CAM FEATURES



CONTINUOUS LOOP RECORDING

When the MicroSD Card is full it will overwrite the oldest clips to make room for new footage.



G-SENSOR

A built-in accelerometer senses sudden accelerations or collisions and automatically protects footage surrounding the incident so that it will not be overwritten by Loop Recording.



PARKING MODE

Parking Mode provides security while your vehicle is parked. If the dash cam doesn't sense any motion for a set time the screen will turn off and recording will stop.

If motion is detected or the G-Sensor is triggered, the camera will automatically wake up and start recording again.

Note: Parking Mode is **OFF** by default. You can turn it **ON** in the Video Settings Menu.

INSTALLATION

①

MOUNT

Screw the included suction cup into the mount. Slide the mount into the camera and press the lever to secure the unit to your vehicle's windshield.

②



POWER

Plug the unit into your vehicle's cigarette lighter plug.

③


DRIVE!

When power is applied the unit will automatically turn on and start recording.

Press  to stop recording and  to start again.

Pressing  at any time will capture a still photo.

Press  to create an **Emergency Recording**. Emergency Recordings will not be overwritten by Continuous Loop Recording.

Press  to turn the screen **OFF**. The dash cam will continue recording. Press any button to turn the screen back **ON**.



iRadar® APP CONNECTION

The CDR 855 BT uses a Bluetooth® Smart connection to the **Cobra iRadar®** smartphone app. Smartphone integration allows for:

- 1 Embedding GPS, Speed, Heading, and G-Sensor Information into video footage recorded on the dash cam.
- 2 Displaying iRadar driver awareness alerts including:



Download the app from the App Store or Google Play.


iRadar
compatible



For iPhone® 4s and later with Bluetooth® Smart:

- a. Power on your dash cam.
- b. Make sure your iPhone's Bluetooth is ON. The dash cam will **NOT APPEAR** in the iPhone's Bluetooth Settings Menu.
- c. Start the Cobra iRadar App. Press the **Menu** button in the upper left of the app and select **Devices**. Follow the onscreen instructions to complete the pairing and connection.
- d. When complete, a "connected" chime will sound and  will turn white on the dash cam display.

For Android™ Devices with Bluetooth® Smart:

- a. Power on your dash cam.
- b. Enter your Android device's Bluetooth Settings Menu.
- c. Scan for Devices and select **Drive HD** to pair.
- d. Enter the Cobra iRadar App. A "connected" chime will sound, and  will turn white on the dash cam display.

COMPUTER CONNECTION

To view videos on a computer connect the dash cam using the included cable.

Select **Connect to Computer** on the dash cam. It will mount as a drive on the computer called **DriveHD**. Movie clips and photos can be found in the DCIM folder.

Video clips are saved as .MOV files and can be played by most video players on both PC and Mac.

In order to see embedded GPS, Speed, Heading, and G-Sensor information you must view videos using Cobra's **Drive HD™ Player**, which is available for PC only.

Drive HD Player can be downloaded for free at:
www.cobra.com/dashcamsoftware



STORAGE



An 8GB MicroSD card comes installed in this dash cam, but it supports cards up to 32GB as long as they are Class IV or higher.

For full product manuals, firmware updates and additional language support, visit www.cobra.com

For a list of **Bluetooth Smart Ready** devices visit:
www.bluetooth.com



IC STATEMENT

This device complies with Industry Canada's licence-exempt RSSs. Operation is subject to the following two conditions: (1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device.

Cet appareil est conforme aux CNR exemptes de licence d'Industrie Canada . Son fonctionnement est soumis aux deux conditions suivantes :

- (1) Ce dispositif ne peut causer d'interférences ; et
- (2) Ce dispositif doit accepter toute interférence , y compris les interférences qui peuvent causer un mauvais fonctionnement de l'appareil.

FCC Caution.

§ 15.19 Labelling requirements.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

§ 15.21 Changes or modification warning

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

§ 15.105 Information to the user.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

* RF warning for Portable device:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.