Langie

SPEAKING TRANSLATOR



S2

USER GUIDE

MIC

Built-in high quality

that to receive you

voice, another on

receive other voice.

the rear that to

FOUCH SCREEN

Swipe left/right,

FRONT LED

Speak Key.

** Press and Hold it to speak your

** Simply press it to get back to

last screen or home screen from

FRONT SPEAK KEY

lanauaae.

anywhere.

REAR LED

Speak Kev.

Lights on once

you press the Rear

REAR SPEAK KEY-

** Press and Hold it

to let other to speal

their language; the

translation language.

** Simply press it to

get back to last

screen or home

screen from

anvwhere.

Lights on once

up/down or Tap to

use an application.

you press the Front

-- LCD

dual Microphone,

one on the front

INDEX
Features 1
The Translator Layout 4
Languages 5
Charge the Battery 7
Specification 8
Getting Started9
Turning On and Home Screen 9
Status Screen
Setting the device 10
System Language10
Wi-Fi On/Off10
Translator Language 12
Learn Language 13
Sleep Mode14
Backup to MSD/
Transfer from MSD14
About Langie14
Voice Translator15
Voice Search Image18
Offline Translator19
Offline Leaning Flashcards20
Multimedia21

batterv

HEADPHONE

-(3.5mm)

** Insert the USB Power

supply power to your

Adaptor into this port to

Translator or charge the

The stereo combo jack

connects the Lanaie

to headphones or

amplified speakers.

disables the built-in

Using this iack

automatically

speaker.

** The MSD card slot is inside the

** Insert a Micro SD Card into this

** Before using the Langie for the

first time or when the battery is low,

Fully charge the battery up to about

** Use the USB Power Adaptor that

comes with your device, connect

vour device to a power outlet.

you must charge the battery.

4 hours for first time use.

slot for other external memory

extension up to 32GB.

CHARGE THE BATTERY

MSD CARD

plastic cabinet.

Group Interpreter...... 22

Sound Amplifier.....21

Langie

Speaking Translator **User Guide**

A direct voice delivery translator that instantly translates your words as if you are direct communicating with other person.



VOICE TRANSLATOR Recognize your voice and Translate to large amount of lanauaaes The online voice translator will more accurately

identify what you

Wi-Fi connection

say and hear.

needed.

SEARCH **IMAGES**

ecognize your voice and Search large amount of images for your reference. A suitable picture can he**l**p you to easily communicate with people. Wi-Fi connection needed.



GROUP INTERPRETER

only available on some models) Connect group conversation with people in various languages.

Specially designed for meetings, seminars or tourist guide business.

* Connect two Langie Translators to get a private conversation in two languages. Connect multi Lanaie Translators to talk with various language users as if each person has an own interpreter. * Wi-Fi connection needed.

FAVORITE

* Prepare and Save vour translation during online mode, help you to use and review those translation even you are on the status without internet translation.

* You may backup the Favorite translation to a MSD card for using those contents in your computers; or transfe your translation to the Langie through the MSD.

OFFLINE TRANSLATOR

Recognize vour voice of short phrases or simple words. built in algorithm to aenerate an understandable translation. NO internet needed.



OFFLINE LEARNING **FLASHCARDS** A learning drill for language basic. Built in flashcards with image and voice, tap to hear from ABC to basic vocabulary. NO internet needed.

MULTIMEDIA (only available on some models) Contains Gallery, Voice Recorder

Video and Music Player. SOUND **AMPLIFIER** Record and amplify your speaking words. It can help you

to easier communicate with a medium hearing loss people.

** Swipe to Settings screen to

set up vour device. Scroll up

and down to select the item.

Setting the device

Translato

1]. SYSTEM LANGUAGE

language of this device,

e.g. English.

English

Deutsch

21. WI-FI On/Off

performance

to turn off the

tap the block

showing ON.

Wi-Fi, just simply

of the unit.

If you want

** Bv default, vour Lanaie

activates the Wi-Fi feature.

We suggest you to activate

the Wi-Fi feature at any time

which you can feel much better

10

ON

TP-LINK A1F35

** Scroll down to Menu bar and

tap the System, select and tap

your language to be the System

THE TRANSLATOR LAYOUT



-DUAL SPEAKER SYSTEM The Langie is equipped with built-in high quality dual Speakers, one on the rear that the other people can hear clearly what you said. One on the front that you can hear clearly what the other said.

52 Speakin

Afrikaans

Arabic

Bengali

Bulgarian

Cambodian

Cantonese

Chinese

Croatian

Czech

Danish

Dutch

English

Filipino

Finnish

French

German

Greek

Hebrew

Hindi

Hungarian

Indonesian

Italian

Japanese

Javanese

Korean

Lao

Latvian

Lithuanian

Malay

Malayalam

Nepali

Norwegian

Persian

Polish

Portuguese

Romanian

Russian

Serbian

Sinhala

Slovakian

Slovenian

Spanish

Sundanese

Ukrainian

Urdu

LVOLUME

** Press the Volume key (+) to louder, (-) to lower. ** It displays a volume dialog box to indicate the volume level

POWER BUTTON ON/OFF

** Turn ON --

Press and hold the power button for about 5 seconds until you see the display turning

- ** Turn OFF -- Press and hold the power button for about 2 seconds to display the shutdown dialog box, tap POWER OFF to shut down.
- ** Press the power button for sleep mode (off the LCD) when not in use.

4

** Scroll to Wi-Fi bar and tap it. It searches and displays the available Wi-Fi.

Tap the name and connect to a Wi-Fi AP, the LCD displays a keyboard and you may type the password, tap [OK] to confirm and [Connect] to access the internet.





- ** Please note, if the Wi-Fi AP just
- tap 'forget'

(It is not connected if there is none of AP address name below the

11

Swahili Swedish Tamil Telugu Thai Turkish /ietnamese



- show 'Saved', it is not connected and you have to connect again. ** If the password is wrong, you can hold the Wi-Fi name, then
- ** Once the Wi-Fi is successfully connected, swipe to the Status Screen and vou can see the Wi-Fi indicator is On with the AP name, e.g.



Wi-Fi icon)

noted: The languages and data are being continued to add and improve. The updated are pushed over the air (OTA) directly to your Langie device, therefore, other than the above listed specification, you may find more languages or audio in future in your device.

Langle has large amount of languages, the language quantity and

Text

0 --

0 --

0

0

0 0

0 0

0

0

0

0 0

0 0

0 0

0

0 0

0 0

0

0

0

0 0

0 0

0 0

0

0 0

0

0 0

0

0

0

0

0 0

0

0 --

Ω

0

0 0

0

0

0 Ο

0

0 0

0 ---

0

0

0

0

0 0

0 0

0

0

0

--

0

0

0

0

0

--

0

Ω

0

0

0

0

0

0

0 --

Roman

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

Translator Display Audio Phonetic FlashCards Language

Learn

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

Ο

0

0

--

0

Ω

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

--

0

0

0

0

0

0

Ω

0

0

--

0

--

0

0

0

combination depends on different models. Language List -->

Offline

0

0

0

0

0

0

0

0

0

0

0

--

--

Search Image.

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

0

Languages | Group Interpreter

FCC Statement

This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions: 1) this device may not cause harmful interference, and 2) this device must accept any interference received, including interference that may

cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in particular installation. If this equipment does caus-interference will not occur in particular installation. If this equipment does caus-harmful interference to radio or television reception, which can be determined I turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- --Reorient or relocate the receiving antenna.
- --Increase the separation between the equipment and receive --Connect the equipment into an outlet on a circuit different from that to which the
- receiver is connected.

 --Consult the dealer or an experienced radio/TV technician for help.

 Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

RF Exposure Statement

SAR tests are conducted using standard operating positions According FCC standard with the device transmitting at its highest certified power level in all tested frequency bands, although the SAR is determined at the highest certified power level, the actual SAR level of the device while operating can be well below the maximum value. This model product has been tested and meets the FCC RF exposure guidelines with the test

distance from for body worn. The use of belt clips, holsters and similar accessories should not contain metallic components in its assembly. The use of accessories that do not satisfy these requirements may not comply with FCC exposure requirements, and should be avoided

The power plug of the adapter varies

Input Voltage: 100V -- 240VAC Output Voltage: 5.0V.

with your country of origin.

** If the battery is completely discharged, you cannot turn on the device, even while it is charging.

Allow the battery to charge for a few minutes before you try to turn on the device.

- ** When the battery is low, the device will show a low battery message. Recharge the battery to continue using your translator.
- ** When you are not using your device, switch to Sleep Mode by pressing the Power key. This can help you to save battery power and can use the device longer between charges.

SPECIFICATION

CPU-ARM CORTEX-A7 QUAD-CORE @1.3GHz 27.5mm (1.08inch) Circular TFT LCD Battery: 3.7V/2000mAH Lithium-ion Battery BlueTooth: V4.0 WiFi: 802.11b/g/n MSD Card: up to 32GB Earphone jack: 3,5mm Micro USB Charger Input:100V -- 240VAC Output: 5V DC

Unit Dimension: 48x148x17mm

Weight: 125 grams

GETTING STARTED

Turning ON and HOME Screen

11. Press and hold the power button for about 5 seconds until you see the display turning On to Home Page.



2]. The Home Page is the Voice Translator and shows two languages.

The language on top is the speaking language, the language on bottom is the translation language. (This feature requires to connect Wi-Fi)

Status Screen ** The battery indicator is

showing the percentage of battery power status

connected, the Wi-Fi indicator lights on blue and show the AP address name, otherwise it is on White. If there is none of AP address name below the Wi-Fi indicator, ao to Settinas mode to search and connect the Wi-Fi again. ** Tap Settings icon to enter to

** When Wi-Fi is Setting mode.

Bengal

Cantonese

Chinese (S)

Chinese (T)

Croatian

Chinese (S)

3]. TRANSLATOR LANGUAGE ** Scroll up to the top line of Settings screen. tap the icon of Translator to 罢 Translato select vour Speakina Wi-Fi Lanauaae (From and Translation Learn

** The LCD displays a dialog box of (From) Afrikaans language, scroll Arabic up/down to tap your language e.g. English

Language (To).

** It displays a new dialog box of (To) language, scroll to tap your translation language,



** a microphone icon (🖳 == Speaking Language. ** a speaker cross icon (== Translation Language without

12

4]. Translation is displayed on

(noted: We suggest you to

activate Wi-Fi to use Online

Translatorwhich you can get

much better performance.

When you use Offline Translator,

please speak slow, clear, simple

recognizeyour words and give a

b什么沟通如此重

and correct arammar phrase

that can help the translator to

Offline Learning Flashcards

A learning drill for language

on Settinas mode.

11. Tap one of

the category

icon to enter

e.g. ABC

** Select your learning language

** Swipe to the screen of Learn

again

translation.)

5]. Scroll Up

and Down to

display of

or Roman

phonetic

basic.

see the whole

bigger words

LCD, you may tap LCD to hear

41. LEARN LANGUAGE

** You can learn the Flash Card from the Translator.

** In Settings mode, tap LEARN to select the language you like to





5]. HISTORY Turn ON the history, the Lanaie can record what you have translated that you can review. Tap ENTER to see your translation history.

6]. BRIGHTNESS ** Briahten the Langie LCD by taping(+) or (--)



** Tap Sleep Mode to set your unit to turn off LCD from 1 to 5 minutes when you are not using the unit.

Sleep Mod

8]. BACKUP TO MSD/ TRANSFER FROM MSD (only available on some models)

** You may backup the Favorite and History translation to a MSD card for using those contents in your computers. Tap to enter BACKUP screen, press 'YES' to confirm the backup to your MSD card. ** You may make necessary translation amendment in your computer, transfer it to the Langie Favorite mode. Tap to enter TRANSFER screen, press 'YES' to confirm the transfer

If there is file more than one in your MSD, only the latest file can be transferred to the Lanaie.



to Langie.

Transfer from MSD No Yes

9]. ABOUT LANGIE

* Tap to enter to see it's versions. 14

7]. SLEEP MODE Voice Translator (Wi-Fi needed) Recognize your voice and

languages.

of Languages)

language

English to

Chinese

Translate to large amount of

connection, it will more accurately

identify what you say and hear.

(See the Language List on page

speaking language, the language

On the Langie Home Page,

the language on top is the

on bottom is the translation

Front Speak Key -- Speak

11 PRESS and HOLD the front

of the Speak key will light on

e.g. (Why communication

** While finishing with voice

messaging, release the speak

key to have translation instantly.

15

** The Langie will translate your

Speak key, the blue LED on top

•

your language

Once you see

the Speaking icon

((((Q)))) shown on

LCD and hear a

beep sound, you

may speak with

your language,

is so Important?)

This feature requires Wi-Fi

** Input vour name on user column and select your speaking lanauaae

** The Langie activates the internet feature to search other user using the Langie model, it shows you the name of others and you may tap one of your friend to connect, e.g. Andy



** Press and Hold the Front Speak Key to speak and chat, e.g. (where are you from)

words and send voice translation (only available on some models) to the other connecting device. Your friend can hear and see with his language (你是哪国人?) Nǐ shì nă guó rén?) on his device what you said, you can hear and see with your language on your

device what he said.

Tom can Andy can hear and see hear and see n 2017/09/15 16:2 m 2017/09/15 16:2



UPDATE THE LANGIE

The Langie is continuous to provide uparade version on server for any data or feature improvements. You may update your Langie once the LCD shows APP update,

tap 'update' to download and restart your unit. If you want to check a update version, turn off your Langie then turn it ON and connect Wifi again, the APP update icon will appear

on your LCD in 1 minute to ask for

23

update or not.

21. Lanaie delivers

translation at the

same time, if the

other cannot hear

you can tap the LCD translation

and Langie will repeat to speak.

51. Press the front Speak key to

speak new words or phrases.

为什么沟通如此

Save?

the voice clearly.

3]. Scroll up and

down to see the

whole display with

bigger words or

roman phonetic.

4]. Swipe left or

translation on

your Favorite

record.

right to save this

Rear Speak key --

1]. PRESS and HOLD

the back Speak key,

the blue LED on top

of the Rear key will

light on

other language

the voice and

displays the

1. How to increase accuracy of voice recognition and translation?

16

- a) Connect your device to the internet via wifi or share hotspot
- microphone
- c) Try to speak louder and clearer.
- d) Try to use fluent and structured sentence when speak.

Offline translation accuracy of Langie?

- c) Too long or too short phrases
- ** Online Translator can work in noisy environment if the Wi-Fi connection is stable.
- 3. How to connect to wifi after typing password without an
- 4. Why I cannot connect to internet even the wifi name shown as "SAVED"?

it is not a new network but it does not mean LANGIE has already connected to the network Press the network name and connect again.

17

Press and hold the network name, network name again and enter

6. Does Langie still work even without internet connection?

- a) Limited language translation
- 40-50% while Online translation
- c) Learning functions and Multimedia run as usual.

Langie processes translation via cloud server, sometimes it may not be able to access the bia data from the cloud server outside this country if the country controls its own nternet controlling system.

8. What are the techniques in

- a) Do not release your finger when vou are speakina
- the speak button
- c) Do not release your finger immediately after you speak

Voice Search Images (Wi-Fi needed)

Recognize your voice and Search large amount of images for your reference.

** Swipe to the screen of Search **I**maaes



11. PRESS and HOLD the Front Speak key, speak the word of your

lanauaae. Your language is to follow the settings of translator language (From). e.g. London Big Ben

2]. Langie displays your words, starts search from internet and shows you first few images. Scroll up and down to view the pictures.

3]. PRESS and HOLD the Rear Speak key, speak the word of other language to search pictures. The other language is to follow the settings of translator language (To).

Multimedia (only available on some models)

Contains Gallery, Voice Recorder, Video and Music Player. Insert expandable MSD card and tag the feature icon to enter into it's function.



Tap to enter to see the translation record vou have saved.

record.

** Swipe Left

or Right to see

previous or next

Favorite



** Tap · · · to delete the record.

Offline Translator

Recognize your voice of short phrases or simple words built in algorithm to generate an understandable translation. No internet needed

** Swipe to the screen of Offline Translator



1]. Tap (\square) to pull down the language list to select languages. Top language is the Speaking language: Bottom language is the Translation lanauaae.

2]. PRESS and HOLD the Front Speak key to speak your words or phrases.

3]. PRESS and HOLD the Rear Speak key to speak the other language.

19

13. I am a language learner

suggest you to turn ON history or save the phrases in your Favorite record, review them and hear

For a non-Roman language, you may scroll up/down to see the whole display which shows both original characters and Roman pronunciation. It will be easier to you to listen the

size of your card.

if not, please format the card to FAT32 and try it again.

but I am hard to follow the voice, what's your suggestion? For a Roman language, we

several time.

voice following the Roman display.

14. Why the Langie cannot recognize my MicroSD card?

* MicroSD cannot be bigger than 32GB, please check the memory

27

2]. Tap the picture to hear the

3]. Scroll up and down to see the next picture in same category.

13

Sound Amplifier



to easie communicate with a medium hearing loss people.

rear speak key to speak your words.

words and speak it loudly, LCD

** Press and Hold the front or

e.a.(we go out for dinner tonight). ** The Langie records your

shows an amplifier icon. ** If you want the other to hear the same words again, tap the amplifier icon to repeat it.

Group Interpreter (Wi-Fi needed)

** We suggest you to put on an ear phone to have private conversation with your group

** Swipe right from Home page to the screen of

Group Interpreter

e.g. Tom, English, tap OK to confirm.



TROUBLESHOOTING

- from cell phone
- b) Try to speak closer to the
- 2. What else may affect the
- a) Noisy environment b) Different accent

"ENTER" key on the keyboard? Tap "OK" key on keyboard after typing and press "CONNECT".

Saved network only represents

5. How to do when I fail to connect to "SAVED" network?

choose "FORGET", Press the password.

2]. Once hear a

beep sound, the

other can speak

her/his language

(沟通驱使着我们

的生活改善自己)

3]. Langie translates with your

you at the same time.

LCD translation screen.

language, speaks and displays to

if you like to hear it again, tap the

沟通驱使着我们 的生活改善自己

to you with

she speaks

Chinese

e.a.

Yes. Offline functions as below:

- (Refer to Manual). b) Offline translation accuracy at
- accuracy at 90-100%.

7. Why even my Langie has connected to internet, there is still a pop up message showing that the internet is not available?

You may try it again.

using the speak button?

- b) Start to speak only after you hear the sound signal when you press
- hold the speak button for awhile.

does not come in audio but text only? a) Langie may experience a delay

18

after language switch as it takes some time to reload database. b) The audio translation may not

9. Why the translated content

be available of that particular language.

10.What is the meaning of the "MUTE" icon shown next to a language? If there is a "MUTE" icon next

to a language, it means the audio translation of that language is not available. Translated content will only be displayed in text instead of audio.

11. How to repeat playing the audio of translated content? Tap the screen to repeat playing audio of translated content.

is hanged? Press on/off key and don't release it until you can see the

12. What to do when the Langie

* MicroSD format is the FAT32

25 26