

MOGIC

BLUETOOTH SPEAKER





MG-BTS01

QUICK SETUP GUIDE

Package contents
 Bluetooth speaker
 USB charging cable
 Carrying pouch
 Quick Setup Guide

Features

- Bluetooth V4.1, compatible with most Bluetooth devices.
- Pairs and plays in seconds using a Bluetooth wireless connection. Up to 33' range offers flexible use.
- Built-in rechargeable lithium-ion battery, providing up to 8 hours of battery life.
- Built-in Omni-directional microphone
- Lightweight design offering easy portability.

No	Icon	Function Definition
1		Power and Multi-function
		<ul style="list-style-type: none"> ● Short press to power on the speaker-LED ON(Blue LED) flashes slowly ● Short press to turn the speaker off-LED OFF.
2		<ul style="list-style-type: none"> ● In power on state, press and hold the button more than two seconds to enter into pairing mode. The blue LED flashes fast. ● When the phone rings, quickly press the button to answer the phone call. ● To end a call, short press the button again. ● When power is on, the unit automatically connects to the last paired Bluetooth device within six seconds. If the last paired Bluetooth device is not in range, the unit automatically searches for another device to pair to. ● Press and hold the Power/Multi-function button and Volume+ button more than two seconds to clear the paired information. <p>NOTE: For Android users: make sure that the "Phone Audio" function is active in the Bluetooth settings.</p>
3		 Short press to increase the volume 1 step. Long press to play next song.
4		 Short press to decrease the volume 1step Long press to play previous song
5	 Connect the USB charging cable to charge the battery	


6	Status indicator or LED	LED Status Information Power <ul style="list-style-type: none"> ● LED is Blue when speaker is turned on. LED is off when speaker is turned off. Charging <ul style="list-style-type: none"> ● When speaker is off, LED is red while charging. After charging is complete, red LED turns off. ● When speaker is on, LED is purple while charging. After charging is complete, blue LED is on. Other <ul style="list-style-type: none"> ● No Bluetooth connection, blue LED flashes slowly. ● Bluetooth is in pairing mode, blue LED flashes fast. ● Successful Bluetooth connection, solid blue LED. ● In power on states, LED is red when battery is low. Speaker remains on for approximately 10 more minutes.
---	-------------------------	---

Charging the speaker


When the battery is low, the red LED is on.

- To charge, connect the charging cable to your Bluetooth speaker and an available USB port on your computer.

The red LED turns off when finished.




Turning on and off

- Short press the Power/Multi-function button  to turn your speaker on or off.

Bluetooth pairing

Note: The Bluetooth range is 33 feet(10 meters)

- 1 Press and hold the Power/Multi-function button  until the LED blinking quickly.
- 2 Navigate to your device's Bluetooth settings, turn on Bluetooth, then search for available devices.
- 3 Select **MG-BTS01** from the list of available devices on your Bluetooth device. The LED lights solid blue when your device is paired.
Note: For more information on entering pairing mode, see the instructions that came with your Bluetooth device.
- 4 To unpair, turn off Bluetooth on your Bluetooth device.

Controlling volume and playback

- Use your audio device to play, pause and select tracks.
- Press + or - to increase/decrease the volume.

Note: Make sure the volume level on your Bluetooth device is at least 50%.

Using the speakerphone

When paired to your mobile phone:

- To answer a call, press the Power/Multi-function button once to answer the phone.
- Press + or - to increase/decrease the speakerphone volume.
- Press the Power/Multi-function button again to end the phone call.

Specifications

Dimensions (L x W x H)	3.4 x 3.4 x 1.6 in. (87 x 87 x 39.6mm)
Frequency	150Hz-20KHz 3W power with 1% THD
Playtime on battery power	8 hours
Battery charging time	2 hours
Weight	132g
Bluetooth range	33 feet (10 m)
Supported Bluetooth profiles	A2DP, HFP

FCC Statement

This device complies with Part 15 of the FCC Rules and Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measure:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

IC Statement

This equipment complies with IC radiation exposure limits set forth for an uncontrolled environment.

One-year limited warranty

Contact MOGIC:

For customer support, call 1-216-598-3823 (U.S. area)
 3170 Warren Rd., Cleveland, Ohio 44111, U.S.A.

All rights reserved. MOGIC is a trademark of Compupal (Group) Corporation. Registered in some countries. All other products and brand names are trademarks of their respective owners.