## Certification and

safety approvals

TAG HEUER is the world first digital wireless headset that delivers high quality 2.0-channel stereo audio with extra sound clarity and soft, deep bass effects. It provides a voice back channel that allows you to talk in conjunction with any kinds of PC voice applications. Examples of such applications include Skype,on-line gaming, and more. With the high performance audio and the unique feature set, TAG HEUER brings you a great value. To start, we like to introduce to you the important certification and safety approvals on this headset.



- Unique 2.0-Channel design Each ear cup contains specially designed speaker driver to deliver extra audio clarity.
- USB Plug-and-Play wireless headset that supports PC music/game sounds and back-channel voice simultaneously, no need to switch back and forth.
- USB Dongle(Transmitter) direct plug-in to the PC for instant use of VoIP, on-line game, DVD, and all kinds of entertainment running Windows 2000/XP.Vista.
- Ease of use, no software installation needed.
- Long standing use, up to 6 hours of continuous listening time per charge.
- Easy charging through dongle DC out. Microphone switch on/off control.
- 30 to 45 feet distance for effective use.





PC USB Wireless Headset \* 1pc







Warranty Card \* 1pc

### Specification

Wireless TAG HEUFR

USB Plug & Play 2-Way Interactive CD-Quality Audio

PC USB Headset


Model	TAG HEUER
Wireless Technology	WiStereo <sup>™</sup> for advanced 2-way digital transmission in the 2.4 GHz frequency band
Listen Time (per charge)	Up to 6 hours
Standby Time	Approximately 3 months
Charge Time (full charge)	Approximately 2.5 hours
Distance of Use	30 ~ 45 feet
Headset Weight	4.7 ounces
USB Dongle Weight	1.8 ounces
Charging Method	Through Dongle DC Out
Battery Type	Lithium Polymer
Headset Speaker	40mm Neodymium
Frequency Response	20Hz~20,000Hz
	(perfect for all music, game,
	and voice)
Audio Quality	Uncompressed audio for
	music (CD-quality) and voice
	(extra clarity)
Distortion (T.H.D.)	≤0.08% (professional grade
	audio performance)

Maximum Range:

Results may vary according to environment

5 Parts Introduction





- 1 VOL+/VOL-
- (2) LEDIndicator
- (3) Pair / Pick Up / Hang Up
- 4 Power On/Off
- (5) DC-IN Port
- 6 Microphone
- (7) Microphone On/Off

2

### VOL+ / VOL-

Pressto increasethe headset volume. Pressto decreasethe headset volume.

### **LED Indicator**

A red indicator represents power functions. A green indicator represents signal connections.

### Pair / Pick Up / Hang Up

Press pair button to connect the wireless headset and the USB Dongle.

Answer---Press pair button to answer the call Hang up---Press pair button to end the call

### Power On/Off

Press this button to control power on/off.

### **DC-IN Port**

Connect the cable Connect the DGIN cable from dongle for recharging.

### Microphone

Receives voice input when the microphone is switched on.

Microphone On/Off

Switch the button to control microphone on/off.



User Guide Symbols

### Steady red light



· The headset is chaging

### Steady blue light




· Devices are paired

### Flashing blue light



- Devices are waiting for pairing
- · Devices are not paired

 First time use: Charge 4 hours before using the headset



 Regular use: Charge the headset approximately 2 hours if the battery was completely used up.

### 12

## Unplug the USB charging cable if any of the following conditions exist

- The USB cable or plug has become frayed or damaged.
- The USB cable has been exposed to rain, liquids, or excessive moisture.
- You suspect the headset needs service or repair.
- You want to clean the headset.

### Avoiding hearing damage


Permanent hearing loss may occur if a headset is used at high volume. Set the volume to a safe level. You can adapt over time to a higher volume of sound that may sound normal but can be damaging to your hearing. If you experience ringing in your ears or muffled speech, stop listening and have your hearing checked. The louder the volume, the less time is required before your hearing could be affected.





The headset is charging

- Steady red light is turned off when the headset is fully charged.
- To ensure this headseto work properly, pleaseavoid recharging while using.



Connect the USB Dongle with PC for signal transmission.

### 13

Hearing experts suggest that to protect your hearing:

- Limit the amount of time you use the headset at high volume.
- Avoid turning up the volume to block out noisy surroundings.
- Turn down the volume if you can't hear people speaking near you.

### **Maintaining battery life**

Due to the physical nature of battery, the charging time may become longer and the actual capacity of battery may decrease. If you have any questions regarding the replacement of the built-in battery, please contact our service center.

### Turn on/off the headset



- Steady red light is turned off when the headset is fully charged.
- To ensure this headset to work properly, please avoid recharging while using.

### Pairing the headset to the USB Dongle



Press **PAIR** button to connect the signal transmission.



Devices are waiting Devices a for pairing



Devices are paired



### **Troubleshooting**

### No signal connection to the headset

Make sure the headset is charged and the USB Dongle is properly connected to the PC. Within the range of signal coverage, power on the headset again.

The headset is automatically switched off

The battery is too low. The indicator light on the headset is off.

**Unexpected behavior** 

Reset the headset. (see p.5)

#### No audio at the headset

- Check the headset and the computer volume control. Make sure they are not in the lowest volume level or muted.
- Check the pair status of the USB Dongle and the headset. Make sure two devices are paired properly.
- Check if the PC Media Player is properly installed, and audio file is playable.
- The listening party can not hear you over the internet. Check if the microphone switch is on.

# Important User Information

### Handling the headset

11

Do not bend, drop, crush, puncture, incinerate, or open the headset.

### Repairing the headset

Never attempt to repair the headset yourself. The headset does not contain any user serviceable parts. For service information, choose the headset help from the warranty card. The rechargeable battery in the headset should be replaced only by authorized service providers.

15

### IC Statement

Canada Warnin

Industry Canada regulatory information Operation is subject to the following two conditions: (1)this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device." The user is cautioned that this device should be used only as specified within this manual to meet RF exposure requirements. Use of this device in a manner inconsistent with this manual could lead to excessive RF exposure conditions.

#### FCC Statemen

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.\*

FEDERAL COMMUNICATIONS COMMISSION INTERFERENCE STATEMENT This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions may cause harmful interference to radio communications. However there is no quarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:--Reorient or relocate the receiving antenna,--Increase the separation between the equipment and receiver.--Connect the equipment into an outlet on a circuit different from that to which the receiver is connected .-- Consult the dealer or an experienced radio/TV technician for help.

#### RF exposure warning

The equipment complies with FCC RF exposure limits set forth for an uncontrolled

The equipment must not be co-located or operating in conjunction with any other antenna or transmitter.

Any changes or modifications not expressly approved by the grantee of this device could void the user's authority to operate the equipment.

#### • C

This Product is CE marked according to the provisions of R& TTE Directive. (99/5/EC)