

BSH09B USER MANUAL

Product overview

- Designed for an active lifestyle, BSH09B Bluetooth Stereo Headset combines the stylish design and reliable wireless technology in the ideal mini size units. It's completely accord with the requirement of fashion life.
- With the Bluetooth wireless technology, BSH09B gives you the convenience wireless way to enjoy the steaming stereo music transmitted from the Bluetooth A2DP
- Switching between music and phone calling. BSH09B allows you answer or make calls with the Bluetooth enabled mobile phone while you are listening to music. After you ended the call, the music will follow to be streamed in few seconds.
- Besides the wireless stereo and mobile hands-free applications, you also can apply the BSH09B to the Bluetooth enabled PC with the internet messenger such as Skype, MSN Messenger or Yahoo! Messenger.

-1-

BSH09B Bluetooth Stereo Headset Structure



- Vol +
- Vol -
- Speaker
- Multifunction button
- charge & earphone socket
- indicator LED
- Microphone

Primarily Operation

1. Switch on: In the off state, press and hold multifunction key for 3 seconds until the blue LED light 3 seconds.
2. Switch off: In the on state, press and hold multifunction key for 7 seconds until red LED light 3 seconds

-2-

3. Pairing mode: In the off state, press and hold the multifunction key 7 seconds until red and blue LED flash alternatively.
4. Answer a call: Press the multifunction key one time while the call coming to answer from the headset.
5. End a call: Press the multifunction key one time while the talking state to end a call from the headset
6. Reject a call: Press and hold multifunction key about 3S until there is a prompt sound from the headset to reject the incoming call.
7. Voice dialing: Under the headset and mobile connecting state, press and hold multifunction key 3S until you hear a beep prompt to operate the voice dialing. To use this function, your mobile must support this option.
8. Redial number: Under the headset and mobile connecting state, press multifunction key two times until hear beep prompt to redial the last dialed number.
9. Play / Pause music: In the standby state, press multifunction key one time to play or pause music
- 10: Vol +: Under talking or music state, press "Vol+" one time, the volume up a degree. Press the button and hear beep prompt that's the max volume.

-3-

11. Play previous song: Press and hold the "Vol +" for 3S to play the previous song.
12. Vol -: Under talking or music state, press Vol- one time, the volume down a degree. Press the button and hear beep prompt that's the min volume.
13. Play next song: Press and hold the Vol- for 3s to play the next song.
14. On/off mute: Press "Vol +" & "Vol-" for 3s until hear beep prompt to turn on/off MIC.

Important operation notice

Bluetooth pairing

Bluetooth pairing is professional word for Bluetooth products use: it makes the Bluetooth devices to wireless connect via simple operation. For example, you have to use the Bluetooth function built-in mobilephone to search Bluetooth device if you want to use the mobile and Bluetooth headset, then take the option , pair and connect by password.

BSH09B Bluetooth Stereo Headset Pairing:

4

1. Make sure the headset under off state(see Switch on/off)
 2. Press and hold multifunction key for 7s until red and blue LED flash alternatively.
 3. Follow the operating instruction of your Bluetooth mobile phone to start the pairing process. Typically, this is done by going to a "Connect" or "Setup" menu and then selecting the option to search the Bluetooth devices.
 4. The mobile will find BSH09B and ask whether you are willing to connect your mobile with the headset. Press "Yes" or "Confirm" to confirm this action.
 5. Enter password or PIN 0000, and press " Yes" or " Confirm" .
(Notice: If the connection is successful, the blue LED of the headset will flash 3 times. Then blue LED will flash one time every 7 seconds. If the pairing is unsuccessful, THE red and blue LED still flash alternatively. You please turn off the headset and pairing again.
- Voice dialing(dialing a number by saying a name)
The voice dialing is available, if the voice recognition turn on, and headset connected have been set up.

-5-

1. Press multifunction key of the headset one time, you will hear a beep prompt.
 2. Say the name of the person you wish to call loudly
(Notice: That's key to make sure your mobile phone support voice dialing function)
- Play music
Press the multifunction key one time to play or pause music when mobile is not in talking state.
(Notice: Some stereo mobile phone with not good compatibility. You have to follow this operation if want to make the stereo working normally:
First, your mobile phone must support stereo. Second, make sure the connection is from your mobile to stereo headset. That's mean when you turn on again headset after the switch off, the headset will connect with mobile automatically, then cut connect by mobile, re-connect by mobile to headset, you could use the stereo function normally).

-6-

Contents

Product overview	1
BSH09B Bluetooth Stereo Headset Structure	2
Primarily Operation	2
Important operation notice.....	4
Bluetooth pairing.....	4
Battery charging and low voltage alert	7
Battery information	8

Battery charging and low voltage alert.

Correct connecting charging cable, the red LED light during charging, and light off after charging full. It costs 2-3 hours. The power use out soon, when the red LED flash one time every 7 seconds, and hear alert prompt every 30 seconds, you have to charge it right now. If not, the headset will be turn off automatically after 5-10 minutes.

Notice:

If disconnection occurs, please check the following factors:

1. Ensure that the headset has enough power, is turned on and has been successfully paired to the mobile.
2. The Bluetooth function of the mobile is enabled.
3. Check whether the range between the headset and mobile is over 10 meters, or there is wall or other disturbance or other electrical devices between headset and mobile.

-7-

will reduce the capacity and lifetime of the battery. Always try to keep the battery between 15 and 25. A device with a hot or cold battery may not work temporarily, even when the battery is fully charged. Battery performance is particularly limited in temperatures well below freezing. Do not dispose of batteries in a fire as they may explode. Battery may also explode if damaged.

-9-

4. Bluetooth music devices or the music devices with Bluetooth connector /Bluetooth stereo dongle must support A2DP.
5. Some mobile can't support the switching between music and calling for Bluetooth connection, it caused the function lost that switch between music and phone call by headset.

Battery information:

Your device is powered by a rechargeable battery. The full performance of a new battery is achieved only after two or three complete charge and discharge cycles. The battery can be charged and discharged hundreds of times, but it will eventually wear out. Please cut the connection between charger and headset when not charging. Do not leave a fully charged battery connected to a charger, since overcharging may shorten battery lifetime. If left unused, a fully charged battery will lose power with time past. Leaving the device in hot or cold places, such as in closed car in summer or winter conditions,

-8-

FCC Information

This device complies with Part 15 of the FCC rules.

Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received; including interference that may cause undesired operation.

Federal Communications Commission (FCC) Statement

This Equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user authority to operate the equipment.

Tested to comply with FCC standard. FOR HOME OR OFFICE USE.

Warning :

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. & This device and its antenna(s) must not be co-located or conjunction with any other antenna or transmitter.