TITAN

CONTENTS

ENGLISH

1. Gently pull crown out to its outermost position **B**.

2. Rotate the crown to the correct time.

3. Press the crown to return it to its normal position **A**.

NOTE: If you are storing the watch, make sure to pull the crown out to its outermost position **B**.

Before you set up the watch, you must charge the watch fully and then turn it on.

1. Charge the watch for at least two hours **1**, **2**, **3**.

WARNING: Do not attempt to change the battery yourself. Opening the watch case will void your warranty. Using an incorrect battery may cause the watch to overheat or catch fire.

NOTE: The first time you charge the watch, the display might be blank. After you set up the watch, the charging icon ⚡ is displayed while the watch charges.

2. To turn on the watch, press and hold the top watch button until the setup screen displays.

1. Install the Titan Smartwatch app. On your phone, go to watches.hp.com or search for Titan smartwatch in your app store.
   NOTE: Your phone must have either iOS 8 or higher or Android 4.4 operating system or higher.

2. Make sure that your phone's Bluetooth® is turned on. See your phone documentation for instructions.

3. Open the Titan Smartwatch app on your phone, and then follow the on-screen instructions to set up your account.

4. The phone app automatically searches for nearby watches. Press the top watch button ❶ so that the setup screen is displayed and the app can find your watch.

5. In the phone app, select your watch. If prompted, press the top watch button ❶ and enter the PIN displayed on your watch.

6. In the phone app, enable notification permissions. You can choose to push any notifications from a third-party app, such as Facebook or Twitter, to the watch. See your phone documentation for instructions for enabling notifications.

7. To configure the watch, in the phone app, select **Activity Tracker**, **World Clock**, **Notifications**, or **Preferences**. **Notifications** also controls vibration notification settings. See Vibration Notifications on page 12 for more information.

DISPLAYING THE WATCH STATUS

To display the watch status, press and hold button ❷ for three seconds. The status dismisses automatically after five seconds.

✳ Bluetooth status icon: Appears when Bluetooth is disconnected.

⚡ Charging status icon: Appears when the watch is connected to power.

🔋 Battery status icon: Displays remaining battery charge.

RESTARTING THE WATCH

To restart the watch, press and hold both buttons for three seconds. Press button ❷ to confirm.

TURNING BLUETOOTH ON OR OFF

To turn Bluetooth on or off, press and hold button ❷ for three seconds.

NAVIGATING BETWEEN APPS

To navigate between apps (such as World Clock and Activity Tracker), press button ❶. To scroll the screen to read a text message or view the next page of an app (such as yesterday's steps in the Activity Tracker app), press button ❷.

DISMISSING NOTIFICATIONS

To dismiss notifications or to decline a call, press button ❶. Press and hold button ❶ to dismiss all notifications.

TURNING AIRPLANE MODE ON OR OFF

To turn airplane mode on or off, press both buttons.

RESETTING TO FACTORY SETTINGS

To reset to factory settings, press and hold button ❷ while pressing button ❶ three times. Press button ❷ to confirm.

INCOMING CALL

When you have an incoming call, the caller's name is displayed. If the caller is not in your contacts, their phone number is displayed instead. Press button ❶ to decline the call.

TEXT MESSAGE

When you receive a text message, the sender's name and message are displayed. Press button ❷ to scroll and press button ❶ to dismiss the text.

ACTIVITY TRACKER

The activity tracker keeps track of your daily steps and your progress to your daily goal. You can check today and yesterday's steps on the watch. A notification is displayed when you reach your daily goal. Use the app to check your progress over the week or the month.

WORLD CLOCK

The world clock syncs automatically with your phone. In the app, you can select other time zones to be displayed. Press button ❷ to scroll through your selected cities.

CALENDAR REMINDERS

The watch syncs with the calendar on your phone to notify you of upcoming appointments. Press button ❷ to scroll for more information, such as meeting time and location. Press button ❶ to dismiss the notification.

BATTERY STATUS

When the watch battery has less than a 20% charge, there is a notification. There is also a notification when the watch battery has less than a 10% charge.

VIBRATION NOTIFICATIONS

In addition to on-screen messages, your watch vibrates to notify you of events. The following table describes the default vibration patterns for notifications.

NOTIFICATION	VIBRATION PATTERN	DEFAULT
Incoming call		On
Text message		On
Activity goal reached		On
Calendar reminder		On
Email		Off

KEY ● = Short pulse   ▬ = Long pulse

Vibration notifications are either high or low urgency. High-urgency notifications use a stronger vibration than low-urgency notifications.

To enable, disable, or change the urgency level of vibration notifications:

1. In the app, select **Notifications**.

2. Click the slider next to the notification to enable or disable that notification. Click **Edit** to change the vibration urgency level to high or low.

NOTE: You can enable a vibrations notification for any third-party app. All vibration notifications not enabled by default are set automatically to low urgency.

RECONNECTING THE WATCH WITH YOUR PHONE

If the phone and watch are disconnected, the watch displays the Bluetooth icon ✳.

To reconnect:

1. Make sure that your phone's Bluetooth is turned on. See your phone documentation for instructions.

2. Press the top watch button until the Setup screen displays.

3. Open the Titan Smartwatch app on your phone, and then follow the on-screen instructions to reconnect the watch to your phone.

WARRANTY AND SUPPORT

For warranty and support information, go to watches.hp.com. This site contains detailed online documentation as well as accessories and spare parts information.

For regulatory and safety notices, refer to the *Product Notices* included with your product.

FR FRENCH

1. Gently pull crown out to its outermost position **B**.

2. Rotate the crown to the correct time.

3. Press the crown to return it to its normal position **A**.

NOTE: If you are storing the watch, make sure to pull the crown out to its outermost position **B**.

Before you set up the watch, you must charge the watch fully and then turn it on.

1. Charge the watch for at least two hours **1**, **2**, **3**.

WARNING: Do not attempt to change the battery yourself. Opening the watch case will void your warranty. Using an incorrect battery may cause the watch to overheat or catch fire.

NOTE: The first time you charge the watch, the display might be blank. After you set up the watch, the charging icon ⚡ is displayed while the watch charges.

2. To turn on the watch, press and hold the top watch button until the setup screen displays.

1. Install the Titan Smartwatch app. On your phone, go to watches.hp.com or search for Titan smartwatch in your app store.
   NOTE: Your phone must have either iOS 8 or higher or Android 4.4 operating system or higher.

2. Make sure that your phone's Bluetooth® is turned on. See your phone documentation for instructions.

3. Open the Titan Smartwatch app on your phone, and then follow the on-screen instructions to set up your account.

4. The phone app automatically searches for nearby watches. Press the top watch button ❶ so that the setup screen is displayed and the app can find your watch.

5. In the phone app, select your watch. If prompted, press the top watch button ❶ and enter the PIN displayed on your watch.

6. In the phone app, enable notification permissions. You can choose to push any notifications from a third-party app, such as Facebook or Twitter, to the watch. See your phone documentation for instructions for enabling notifications.

7. To configure the watch, in the phone app, select **Activity Tracker**, **World Clock**, **Notifications**, or **Preferences**. **Notifications** also controls vibration notification settings. See Vibration Notifications on page 12 for more information.

DISPLAYING THE WATCH STATUS

To display the watch status, press and hold button ❷ for three seconds. The status dismisses automatically after five seconds.

✳ Bluetooth status icon: Appears when Bluetooth is disconnected.

⚡ Charging status icon: Appears when the watch is connected to power.

🔋 Battery status icon: Displays remaining battery charge.

RESTARTING THE WATCH

To restart the watch, press and hold both buttons for three seconds. Press button ❷ to confirm.

TURNING BLUETOOTH ON OR OFF

To turn Bluetooth on or off, press and hold button ❷ for three seconds.

NAVIGATING BETWEEN APPS

To navigate between apps (such as World Clock and Activity Tracker), press button ❶. To scroll the screen to read a text message or view the next page of an app (such as yesterday's steps in the Activity Tracker app), press button ❷.

DISMISSING NOTIFICATIONS

To dismiss notifications or to decline a call, press button ❶. Press and hold button ❶ to dismiss all notifications.

TURNING AIRPLANE MODE ON OR OFF

To turn airplane mode on or off, press both buttons.

RESETTING TO FACTORY SETTINGS

To reset to factory settings, press and hold button ❷ while pressing button ❶ three times. Press button ❷ to confirm.

INCOMING CALL

When you have an incoming call, the caller's name is displayed. If the caller is not in your contacts, their phone number is displayed instead. Press button **1** to decline the call.

TEXT MESSAGE

When you receive a text message, the sender's name and message are displayed. Press button **2** to scroll and press button **1** to dismiss the text.

ACTIVITY TRACKER

The activity tracker keeps track of your daily steps and your progress to your daily goal. You can check today and yesterday's steps on the watch. A notification is displayed when you reach your daily goal. Use the app to check your progress over the week or the month.

WORLD CLOCK

The world clock syncs automatically with your phone. In the app, you can select other time zones to be displayed. Press button **2** to scroll through your selected cities.

CALENDAR REMINDERS

The watch syncs with the calendar on your phone to notify you of upcoming appointments. Press button **2** to scroll for more information, such as meeting time and location. Press button **1** to dismiss the notification.

BATTERY STATUS

When the watch battery has less than a 20% charge, there is a notification. There is also a notification when the watch battery has less than a 10% charge.

In addition to on-screen messages, your watch vibrates to notify you of events. The following table describes the default vibration patterns for notifications.

NOTIFICATION	VIBRATION PATTERN	DEFAULT
Incoming call		On
Text message		On
Activity goal reached		On
Calendar reminder		On
Email		Off

KEY ● = Short pulse   ━ = Long pulse

Vibration notifications are either high or low urgency. High-urgency notifications use a stronger vibration than low-urgency notifications.

To enable, disable, or change the urgency level of vibration notifications:

1. In the app, select **Notifications**.

2. Click the slider next to the notification to enable or disable that notification. Click **Edit** to change the vibration urgency level to high or low.

NOTE: You can enable a vibrations notification for any third-party app. All vibration notifications not enabled by default are set automatically to low urgency.

RECONNECTING THE WATCH WITH YOUR PHONE

If the phone and watch are disconnected, the watch displays the Bluetooth icon *.

To reconnect:

1. Make sure that your phone's Bluetooth is turned on. See your phone documentation for instructions.

2. Press the top watch button until the Setup screen displays.

3. Open the Titan Smartwatch app on your phone, and then follow the on-screen instructions to reconnect the watch to your phone.

WARRANTY AND SUPPORT

For warranty and support information, go to watches.hp.com. This site contains detailed online documentation as well as accessories and spare parts information.

For regulatory and safety notices, refer to the *Product Notices* included with your product.

FEDERAL COMMUNICATIONS COMMISSION NOTICE

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
• Reorient or relocate the receiving antenna.
• Increase the separation between the equipment and receiver.
• Connect the equipment to an outlet on a circuit different from that to which the receiver is connected.
• Consult the dealer or an experienced radio or television technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

If you have questions about the product that are not related to this declaration, write to: HP Inc., 1501 Page Mill Road, Palo Alto, CA 94304 or call HP at 650-857-1501.

For questions regarding this FCC declaration, write to: HP Inc., 1501 Page Mill Road, Palo Alto, CA 94304 or call HP at 650-857-1501.

To identify your product, refer to the part, series, or model number located on the product.

MODIFICATIONS
The FCC requires the user to be notified that any changes or modifications made to this device that are not expressly approved by HP may void the user's authority to operate the equipment.

CABLES
To maintain compliance with FCC Rules and Regulations, connections to this device must be made with shielded cables having metallic RFI/EMI connector hoods.

CANADA NOTICES

This Class B digital apparatus meets all requirements of the Canadian Interference-Causing Equipment Regulations CAN ICES-3(B)/NMB-3(B). If this device has WLAN or Bluetooth capability, the device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

AVIS CANADIEN
Ce dispositif numérique de Classe B répond aux exigences de la réglementation du Canada relative aux équipements causant des interférences CAN ICES-3(B)/NMB-3(B). Si ce dispositif est doté de fonctionnalités de réseau sans fil ou Bluetooth, il est conforme aux normes d'exemption de licence RSS d'Industrie Canada. Son fonctionnement est assujetti aux deux conditions suivantes : 1) Ce dispositif ne doit causer aucune interférence dangereuse, et 2) ce dispositif doit accepter toute interférence reçue, y compris les interférences pouvant provoquer un fonctionnement indésirable.

CHEMICAL SUBSTANCES
HP is committed to providing our customers with information about the chemical substances in our products as needed to comply with legal requirements such as REACH (Regulation

EC No1907/2006 of the European Parliament and the Council). A chemical information report for this product can be found at www.hp.com/go/reach.

SUSTANCIAS QUÍMICAS
HP se compromete con la tarea de brindar a nuestros clientes información acerca de los productos químicos incluidos en nuestros productos necesaria para cumplir con requisitos legales como REACH (Regulación EC N.º 1907/2006 del Parlamento Europeo y del Consejo). Podrá encontrar un informe con los datos químicos relacionados con este producto en www.hp.com/go/reach.

SUBSTANCES CHIMIQUES
HP s'engage à fournir à ses clients des informations concernant les substances chimiques contenues dans ses produits, conformément aux dispositions légales telles que REACH (Règlement CE n° 1907/2006 du Parlement Européen et du Conseil de l'Union Européenne). Un rapport d'informations sur les substances chimiques de ce produit est disponible à l'adresse www.hp.com/go/reach.

EUROPEAN UNION REGULATORY NOTICES

DECLARATION OF CONFORMITY
Hereby, HP declares that this equipment: Titan is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. The full Declaration of Conformity can be found at the following web site: URL. For regulatory matters the manufacturer, HP Inc., can be contacted at: 650-857-1501.

For regulatory matters the importer, HP Inc., can be contacted at: HP, HQ-TRE, 71025 Boeblingen, Germany.

BATTERY NOTICES
The battery(ies) in this product cannot be easily replaced by users themselves. Removing or replacing the battery could affect your warranty coverage. If a battery is no longer holding a charge, contact support.

When a battery has reached the end of its useful life, do not dispose of the battery in general household waste. Follow the local laws and regulations in your area for battery disposal.

ELECTRONIC HARDWARE AND BATTERY RECYCLING
HP encourage customers to recycle used electronic hardware and rechargeable batteries. For more information about recycling programs, see the HP Web site at www.hp.com/recycle.

DISPOSAL OF WASTE EQUIPMENT BY USERS
This symbol means do not dispose of your product with your other household waste. Instead, you should protect human health and the environment by handing over your waste equipment to a designated collection point for the recycling of waste electrical and electronic equipment. For more information, please contact your household waste disposal service or go to www.hp.com/recycle.

The device meets the exemption from the routine evaluation limits in section 2.5 of RSS 102 and compliance with RSS-102 RF exposure, users can obtain Canadian information on RF exposure and compliance.

Le dispositif rencontre l'exemption des limites courantes d'évaluation dans la section 2.5 de RSS 102 et la conformité à l'exposition de RSS-102 rf, utilisateurs peut obtenir l'information canadienne et la conformité de rf.

This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter. This equipment should be installed and operated with a minimum distance of less than 5 millimeters between the radiator and your body.

Cet émetteur ne doit pas être Co-placé ou ne fonctionnant en même temps qu'aucune autre antenne ou émetteur. Cet équipement devrait être installé et actionné avec une distance minimum moins de 5 millimètres entre le radiateur et votre corps.

FCC ID: O4GTITAN
IC: 7666A-TITAN
Model: HSTNW-D02W