

6160CR-2

COMMERCIAL FIRE ALPHA KEYPAD
UL864 REV 9 LISTED



The 6160CR-2 is an addressable remote keypad intended for use in commercial fire applications with Honeywell's commercial fire control panels. The keys are continuously backlit for convenience and easy visibility. The LCD display

is backlit only when a key is depressed*, or when the system is in alarm or trouble condition.

*Note: The LCD may be programmed to remain on at all times (see panel instructions for details).

FEATURES

- Four programmable function keys
- Built-in sounder
- Seven Status LEDs
 - Armed (Red)
 - Ready (Green)
 - Power (Green)
 - Fire Alarm (Red)
 - Silenced (Yellow)
 - Supervisory (Yellow)
 - Trouble (Yellow)
- Large easy-to-read display
- Red removable door
- Physical
5.250" W x 7.437" H x 1.312" D

SPECIFICATIONS

Sounder

- High-quality speaker

Electrical

- 45mA standby 160mA in alarm (sounder, back light and LED on)

Compatibility

- Supports Control Panels
 - VISTA-32FB Rev 5 and higher
 - VISTA-128FBP Rev 4 and higher
 - VISTA-250FBP Rev 4 and higher

UL/CUL and residential Listed for commercial fire and burglary installations. To be employed with manufacturer's listed control units as indicated in the installation instructions.

Product specifications subject to change.

ORDERING

6160CR-2 Commercial Fire Alpha Keypad

For more information: www.honeywell.com/security/hsc

Automation and Control Solutions

Honeywell Security & Communications
2 Corporate Center Dr. Suite 100
Melville, NY 11747
1.800.467.5875
www.honeywell.com

L/6160CR2D/D
September 2009
© 2009 Honeywell International Inc.

Honeywell