










# 7841 Cisco IP Phone











## Quick Reference Guide

### 7841 Phone Layout and Key Descriptions



## 7841 Phone Descriptions

1	Handset Light Strip	Indicates an incoming call (flashing red) or new voice message (steady red).
2	Programmable Feature Buttons 	Depending on how your system administrator sets up the phone, programmable feature buttons provide access to: <ul style="list-style-type: none"> <li>• Phone lines and intercom lines</li> <li>• Speed-dial numbers (speed-dial buttons, including the Line Status</li> <li>• speed-dial features)</li> <li>• Web-based services (for example, a Personal Address Book button)</li> <li>• Call features (for example, a Privacy button)</li> </ul> Buttons illuminate to indicate status: <ul style="list-style-type: none"> <li> Green, steady: Active call or two-way intercom call</li> <li> Green, flashing: Held call</li> <li> Amber, steady: Privacy in use, one-way intercom call, DND active, or logged into Hunt Group</li> <li> Amber, flashing: Incoming call or reverting call</li> <li> Red, steady: Remote line in use (shared line or Line Status)</li> <li> Red, flashing: Remote line on hold</li> </ul>
3	Phone Screen	Shows information about your phone such as directory number, call and line status, softkey options, speed dials, placed calls, and phone menu listings.
4	Softkey Buttons 	Depending on how your system administrator sets up the phone, enabled softkey options display on your phone screen.
5	Navigation Ring and Select Button 	The navigation ring and select button allows you to scroll through, highlight, and select items.

6	<b>Hold / Resume Button</b> 	Places an active call on hold or resumes the held call.
7	<b>Conference Button</b> 	Creates a conference call.
8	<b>Transfer Button</b> 	Transfers a call.
9	<b>Speakerphone Button</b> 	Toggles the speakerphone on or off. When the speakerphone is on, the button is lit.
10	<b>Headset Button</b> 	Toggles the headset on or off. When the headset is on, the button is lit.
11	<b>Mute Button</b> 	Toggles the microphone on or off. When the microphone is muted, the button is lit.
12	<b>Keypad</b>	Allows you to dial phone numbers, enter letters, and select menu items (by entering the item number).
13	<b>Volume Button</b> 	Controls the handset, headset, and speakerphone volume (off hook) and the ringer volume (on hook).
14	<b>Contacts Button</b> 	Opens or closes the Directories menu. Use the Contacts button to access personal and corporate directories.
15	<b>Applications Button</b> 	Opens or closes the Applications menu. Use the Applications button to access call history, user preferences, phone settings, and phone model information.
16	<b>Messages</b> 	Autodials your voice messaging system (varies by system).
17	<b>Handset</b>	The handset contains the primary mic and speaker.

---

## 7841 Phone Quick Task Guide

---

### DIALING AND ANSWERING

To make a call:

- Lift the handset and dial a number.
- Press **Speakerphone** or **Headset** and dial a number if using speakerphone/headset.
- **For Internal calls** - enter the 4 digit extension number.
- **For external calls** - dial 9 + the number (add 1 + area code for long distance calls).

To answer a call on your primary line:

- Lift the handset.
- If you are using the speakerphone, press **Speakerphone** button.
- If you are using the headset, press **Headset** button.

To end a call:

- Hang up handset.
- If you are using the speakerphone, press **Speakerphone** button or **End-Call** softkey.
- If you are using the headset, press the **Headset** button or **End-Call** softkey.

### DECLINE

To immediately decline a call:

- Highlight the call and press **Decline** softkey.

To send call to voicemail:

- Press **Volume** down once to silence the incoming call, then wait for the call go to voicemail.

### HOLD AND RESUME

To place a call on hold:

- Press the **Hold / Resume** button.

To resume a call:

- Press the **Resume** softkey or the **Hold / Resume** button.

## FORWARD

To forward calls:

1. At idle phone, press **Fwd All** softkey.
2. Dial the destination number.

To cancel forwarding:

- Press **Fwd Off** softkey.

## TRANSFER

To transfer a call to another extension:

- Press **Transfer** button.
- At dial tone, dial desired number.
- Press **Transfer** button again.

To retrieve the call if no one answers:

- Press **Cancel** softkey.

## CORPORATE DIRECTORY

Look up subscribers by first name, last name or extension number:

1. Press the **Contacts** Button.
2. Scroll to and select **Corporate Directory**.
3. Fill in search criteria and press **Submit** softkey.
4. Highlight desired contact and press **Dial (or Call)** softkey.

## CONFERENCE (AD-HOC)

To conference in participants (up to six participants):

1. During a connected call, press **Conference** button.
2. Select a held call and press **Yes**.
3. **OR** dial the desired number and press **Conference** button again.

To end a conference call:

- Hang up handset.
- Press **Cancel** softkey.

To view conference participants:

- Press **Details** softkey.

## VOLUME

To adjust the handset, headset, or speakerphone volume:

- During the call, press **Volume** button up or down.

To adjust the ringer volume:

- At an idle phone, press **Volume** button up or down.

## MEET-ME CONFERENCE CALL

To establish a Meet-Me conference:

1. Lift the handset
2. Press **Meet Me** softkey and dial the Meet-Me conference number (Contact the helpdesk to receive a conference number).

To participate in a Meet-Me conference:

- Dial the Meet-Me conference number (provided by the conference initiator).

To end a Meet-Me conference:

- Hang up or press **Cancel** softkey.

## USER PREFERENCES

To adjust user preferences:

1. Press **Applications** button.
2. Scroll to and select **Preferences** option.

To change the ring tone:

1. Select **Ringtone** from **Preferences**.
2. Scroll through ring type options.
3. Press **Play** softkey to sample ring.
4. Press **Set** softkey to make choice.
5. Press **Apply** softkey to finalize choice.

To change contrast:

1. Select **Contrast** from **Preferences**.
2. Use **Navigation** ring to adjust contrast.
3. Press **Save** softkey to save contrast settings.

## CALL HISTORY

To view call history:

1. Press Applications button.
2. Scroll to and select Call History option.
3. Select All Lines or the line that you want to view.
4. Select a call record and press Details softkey.

To dial a number in the call history:

1. Scroll to a listing in the call log, and press Dial.

To edit a number in a call log:

1. Highlight the desired number.
2. Press EditDial softkey.