



Service Manual

Washer dryer

Frontloader

AWZ 410

Model	AWZ 410	
Version	8575 410 01000	Page
	Technical data	2
	Spare part list	3 - 4
	Exploded view	5 - 7
	Wiring diagram	8
	Circuit diagram	9
	Program diagram	10 - 13

Technical data

Dimension

Height	85	cm
Width	59.5	cm
Depth	53	cm

Weight

Gross	82	kg
Net	79	kg

Main connection

Voltage	230 +6% -10% V
Frequency	50 Hz
Power Consumption	2200 W
Fuse rating	10 A

Drum data

Volume	42.5	l
Cotton/synthetics (washing-rinsing)	50 - 60	rpm
Pre-spinning	100	rpm
Low spinning	500	rpm
High spinning	1000	rpm

Capacity of dry laundry

Loading - washing max.	5.0	kg
Loading - drying max.	2.5	kg

Heating

Rated power draft:		
- washing	1950	W
- drying(2)	1150	W

Drain-pump

Power consumption	34	W
Capacity	20 - 25	l/min.
Rotation speed	~ 2800	rpm
Height of drain hose :		
max.	0.90	m
min.	0.60	m

Motor

Type	Universal
------	-----------

Timer washing

Type	1837-01
Basic cycles	3
	- normal washing
	- delicate washing

Thermostat

A- washing fixed thermostat	90	°C
B- drying fixed thermostat	107	°C
C- safety thermostat	142	°C
D- safety thermostat	170	°C
E- adjustable thermostat	10 - 90	°C

Pressostat (without laundry)

Low level	7	l
High level	12.5	l
Very high level (wool)	15	l
Overflow level	35	l

Push button switch unit

Version with 5 buttons
- On/off
- Low/High speed
- Rinse hold
- Intensiv rinse
- Half load

Timer drying

Type	Eaton 8403-01
Voltage	220/240 V
Frequency	50 Hz
drying time	2 to 120 min
cooling time	20 min

Drying motor

Type	Plaset 63318
Voltage	220/240 V
Frequency	50 Hz

Spare part list

Model
Service No.
Version

AWZ 410
857541001000
857541001000

Pos. No.	12NC Code	Description
001 0	4812 440 10616	Cabinet
003 0	4819 404 43391	Bearer hook crosspiece
011 0	4819 462 47014	Foot adjustable
024 0	4819 903 03649	Panel, rear
030 0	4812 440 10614	Table top
041 0	4819 417 19534	Hinge
054 0	4812 462 28312	Cover filter
061 0	4819 466 88802	Counter weight
061 1	4819 466 89461	Counter weight bottom
061 2	4819 404 79294	Bracket
065 0	4812 325 18002	Insulation
083 0	4819 466 47003	Friction plate
086 0	4819 492 68576	Spring
086 1	4819 502 18407	Fastener counter weight
086 2	4819 310 39573	Kit fixation
086 3	4819 466 89132	Fastener counter weight
086 5	4812 904 48018	Friction pad unit
110 0	4819 498 78431	Handle
110 1	4819 498 78432	Handle cpl
131 0	4819 903 10159	Lock Plate
133 0	4819 903 10175	Door latch
133 1	4819 903 10174	Pin handle
133 2	4819 903 10176	Door catch lever
140 0	4819 450 58178	Door glass
141 1	4819 466 98878	Protector
143 0	4819 903 02494	Strap
144 0	4819 903 10179	Frame,door glas
144 1	4812 416 18441	Frame,door glas
144 2	4819 532 88054	Collarring
190 0	4819 468 18285	Door bellow
200 0	4812 418 18233	Tub
201 0	4812 310 18587	Bearing unit
201 1	4819 903 02529	Ring tub
201 3	4819 532 38088	Ring kit
210 0	4819 404 49869	Crosspiece,drum
220 0	4819 418 18251	Drum
220 1	4819 418 18303	Drum with cross piece
271 0	4812 358 18182	Belt
272 0	4812 528 88098	Pulley
278 0	4812 535 98097	Rod,pull dispenser
291 0	4819 903 03668	Gasket tub
301 0	4812 464 69009	Control panel
303 1	4812 498 78213	Handle, drawer
331 0	4812 412 58947	Knob,changeover Timer
331 1	4812 413 78646	Knob disc timer
331 2	4812 413 78645	Knob,timer
332 0	4812 410 28854	Button,push
335 0	4812 412 58919	Knob thermostat
338 0	4812 412 58949	Knob,timer drying
351 0	4819 134 48503	Pilot lamp
351 1	4812 381 18276	Lamp screen
401 0	4812 361 78017	Motor
401 1	4812 361 78019	Motor fan
421 0	4812 121 18212	Interf.filter
422 0	4812 214 78504	Tachometer

Pos. No.	12NC Code	Description
430 0	4819 360 18217	Pump,draining
432 0	4812 480 58146	Filter body
443 0	4812 515 48011	Fan wheel
451 0	4819 259 28799	Heating element
451 1	4812 418 38086	Heating chamber
451 3	4812 259 28712	Heating element drying
483 0	4812 321 78151	Cable harness
490 0	4812 321 18122	Cable,mains
491 0	4819 401 18738	Clamp
501 0	4812 282 18663	Timer 1837/1
501 1	4812 282 19288	Timer 8403-01, dryer
521 0	4812 214 58074	Unit electrical
551 0	4819 282 28627	Thermostat MRTL 170 °C
551 1	4812 282 28214	Thermostat 100 °C
551 2	4812 282 28215	Thermostat 47 °C
551 9	4812 271 28445	Thermostat
554 0	4819 903 08226	Potentiometer
572 0	4812 271 28443	Valve,magnet cold
583 0	4812 271 28421	Pressostat
620 0	4819 276 18368	Switch
630 0	4812 280 58028	Door lock
701 0	4819 530 28932	Hose, inlet 1.5 m cold water
708 4	4819 530 28545	Drainhose inner
711 0	4819 418 78886	Dispenser
711 1	4819 462 79036	Cover dispenser housing
711 2	4812 462 28316	Cover dispenser complete
712 0	4819 418 78067	Drawer
713 0	4819 418 78989	Accessory deterg. fluid
714 0	4819 418 78988	Container liquid detergent
714 1	4819 418 78166	Tray bleach
718 0	4819 360 69849	Nozzle
718 1	4819 310 38651	Accessories liquid detergent
742 0	4812 360 78054	Cover
743 0	4819 466 69941	Hose
743 1	4812 310 38436	Air guide
743 2	4812 526 48046	Air guide
743 3	4812 526 48045	Air guide upper
754 0	4819 530 28862	Drainhose
760 0	4819 480 58082	Filter
760 1	4819 462 78861	Grip filter
781 0	4812 530 29045	Hose,draining
781 1	4819 903 02515	Hose
781 2	4812 903 08205	Container Non-Overflow
781 3	4812 903 08206	Tube Non-Overflow-Filter cas.
783 0	4819 530 28861	Hose pressostat
783 1	4819 526 48213	Air guide
783 2	4812 530 28926	Hose
783 3	4812 530 28927	Hose
783 4	4812 530 28928	Hose
783 5	4819 903 10156	Hose
792 0	4812 466 68593	Seal for blower
794 0	4819 903 04978	Gasket
794 1	4819 310 38057	Gasket
794 2	4819 532 68309	Cover filter
900 0	4819 401 13348	Hook


Spare part list

Model
Service No.
Version

AWZ 410
857541001000
857541001000


Pos. No.	12NC Code	Description
900 1	4819 466 98528	Clamping piece
900 4	4819 401 13349	Hook
900 5	4819 466 89459	Holder
900 7	4819 535 38151	Hook
901 0	4822 401 10258	Clamp,hose 10-18 mm
901 1	4812 401 18458	Strap
901 2	4812 401 18576	Clamp,hose
901 3	4819 401 18351	Clamp,hose
901 4	4819 401 18174	Clamp,hose 25-45 mm
901 5	4819 492 68475	Strap
901 6	4819 401 18817	Clamp,hose
902 0	4819 903 02468	Lever
902 1	4812 418 79639	Holder unit electrical
902 2	4812 404 48664	Holder
902 3	4812 418 78991	Holder Modul
903 0	4819 492 68392	Clamp
903 1	4819 903 02535	Silent bloc
903 2	4819 401 18348	Holder,hose
903 3	4819 903 02466	Lever
903 4	4819 903 10167	Door glass insert
903 5	4819 903 02469	Rocker
903 6	4819 492 68488	Clip
903 7	4819 401 18429	Clamp
903 8	4819 401 18883	Staple
910 1	4819 502 18347	Screw
910 2	4819 502 18406	Screw
910 3	4819 502 33254	Screw
910 6	4812 502 18415	Screw
910 7	4812 502 18417	Screw
912 0	4819 502 18414	Screw
912 2	4819 440 19616	Cover Screw
914 0	4819 505 13084	Nut
921 0	4819 532 13433	Washer pulley
921 1	4819 532 38083	Washer
923 0	4819 532 68726	Washer
931 0	4819 903 10178	Spring
931 2	4819 903 02471	Spring
931 3	4819 492 68872	Spring,tension
931 5	4819 903 10172	Spring,ret.
932 0	4812 492 68142	Spring Thermostat
932 1	4812 526 48047	Spring
933 0	4819 903 03659	Spring,tension
941 1	4812 530 68027	Shaft seal
951 1	4819 530 57019	Gasket
952 0	4819 466 69816	Gasket
952 1	4819 903 02447	Gasket thermostat
993 0	4819 401 18345	Bow

Exploded view




8575 410 01000

Exploded view




Wiring diagram



TM	Timer Motor
EM	Thermostop
IF	Interference Filter
RSS	Spin delay button
SDE	No spin button
LWS	Half load button
e	Eco button
CWS	Cold wash button
PRL	Low level pressostat
PRH	High level pressostat
WVC	Water valve (cold fill)
WWW	Water valve (hot fill)
PREH	Pressostat
DSS	Micro delay switch
DPM	Drain motor pump
VAT	Variable temperature
VSS	Variable spin speed
TR	Thermal resistivity
TK	Tachometer
WV	Water valve
CC	Spin capacitor
CL	Wash capacitor
HE	Heating element
RE	Relay
RF	Heating Protector
AS	ON-OFF button
ER	Extra rinse button
TH(10°-90°C)	Adjustable thermostat
TH	Fixed thermostat 90°C
TH	Fixed thermostat 107°C
TH	Fixed thermostat 142°C
TH	Fixed thermostat 170°C
M	Main motor
SM	Spin dry motor
WM	Wash motor
CU	Control unit
Z	Drying timer
VA	Dryer motor
EVA	Dryer water valve
MC	Low/high speed
GPL1	Pilot lamp
GPL2	Door pilot lamp
ZM	Drying timer motor
DE	Drying element
PS	Drain pump
R	Heating element
P	Pressure switch

B	Brown
G	Blue
⏏	Yellow-Green

460608702



KEY		STEP TIME		Type	Code Number	Timer Description	
AAL	Very High Level	1"	From step 1 to step 26	TIMER 1837-01	516009801	220-240V 50Hz	
AL	High Level		From step 32 to step 57	TIMER 1837-03	516015701	220V 60Hz	
B/A	Low Level / High Level		2"	From step 27 to step 31	TIMER 1837-05	516016901	110V 60Hz
BL	Low Level			From step 58 to step 60	TIMER 0767-01	516018801	220-240V 50Hz
D	Fine Washing						
DD	Very delicate Washing						
N	Normal Washing						
P	Time to Reach Water Level						
T	Time to Reach Temperature						
TA	Drying Time						
LSS	Low Speed Spin						
HSS	High Speed Spin						

460601400

Program diagram

DRYING TIMER EATON 8314-01 for WASHER-DRYER 120'

		DRYING WARM AIR												COOL DOWN STOP	
16	HEATING+DRYING WATER VALVE	4	Z3												
17	HEATING	1	Z10												
18	LINE + DRYER MOTOR	2	Z1												
	TIMER POSITION			1	2	3	4	5	6	7	8	9	10	11	12
	STEP DURATION			1	2	3	4	5	6	7	8	9	10	11	12

DRYING TIMER EATON 8314-03 FOR WASHER-DRYER 150'

		DRYING WARM AIR												COOL DOWN STOP	
16	HEATING+DRYING WATER VALVE	4	Z3												
17	HEATING	1	Z10												
18	LINE+DRYER MOTOR	2	Z1												
	TIMER POSITION			1	2	3	4	5	6	7	8	9	10	11	12
	STEP DURATION			1	2	3	4	5	6	7	8	9	10	11	12

460601400

SEQUENCE CHART I

1		STOP		CONTACTS POSITIONS		CONTACTS POSITIONS		CAM POSITIONS	
2		2		INF TO		2		ADVANCING	
3		3		2		2		8314-08	
4		4		2		2		8314-09	
5		5		2		2		8314-10-11	
6		6		2		2		IMPULSE	
7		7		2		2			
8		8		2		2			
9		9		2		2			
10		10		2		2			
11		11		2		2			
12		12		2		2			
13		13		2		2			
14		14		2		2			
15		15		2		2			
16		16		2		2			
17		17		2		2			
18		18		2		2			
19		19		2		2			
20		20		2		2			
21		21		2		2			
22		22		2		2			
23		23		2		2			
24		24		2		2			
25		25		2		2			
26		26		2		2			
27		27		2		2			
28		28		2		2			
29		29		2		2			
30		30		2		2			
31		31		2		2			
32		32		2		2			
33		33		2		2			
34		34		2		2			
35		35		2		2			
36		36		2		2			
37		37		2		2			
38		38		2		2			
39		39		2		2			
40		40		2		2			
41		41		2		2			
42		42		2		2			
43		43		2		2			
44		44		2		2			
45		45		2		2			
46		46		2		2			
47		47		2		2			
48		48		2		2			
49		49		2		2			
50		50		2		2			
51		51		2		2			
52		52		2		2			
53		53		2		2			
54		54		2		2			
55		55		2		2			
56		56		2		2			
57		57		2		2			
58		58		2		2			
59		59		2		2			
60		60		2		2			
1		1		INF TO		1		CAM POSITIONS	
2		2		2		2		LINE	
3		3		10		10		2	
4		4		3		3		10	
5		5		3		3		3	
6		6		5		5		3	
7		7		8		8		3	
8		8		8		8		8	
9		9							
10		10							
11		11							
12		12							
13		13							
14		14							
15		15							
16		16							
17		17							
18		18							
19		19							
20		20							
21		21							
22		22							
23		23							
24		24							
25		25							
26		26							
27		27							
28		28							
29		29							
30		30							
31		31							
32		32							
33		33							
34		34							
35		35							
36		36							
37		37							
38		38							
39		39							
40		40							
41		41							
42		42							
43		43							
44		44							
45		45							
46		46							
47		47							
48		48							
49		49							
50		50							
51		51							
52		52							
53		53							
54		54							
55		55							
56		56							
57		57							
58		58							
59		59							
60		60							
1		1		INF TO		1		CAM POSITIONS	
2		2		2		2		LINE	
3		3		10		10		2	
4		4		3		3		10	
5		5		3		3		3	
6		6		5		5		3	
7		7		8		8		3	
8		8		8		8		8	
9		9							
10		10							
11		11							
12		12							
13		13							
14		14							
15		15							
16		16							
17		17							
18		18							
19		19							
20		20							
21		21							
22		22							
23		23							
24		24							
25		25							
26		26							
27		27							
28		28							
29		29							
30		30							
31		31							
32		32							
33		33							
34		34							
35		35							
36		36							
37		37							
38		38							
39		39							
40		40							
41		41							
42		42							
43		43							
44		44							
45		45							
46		46							
47		47							
48		48							
49		49							
50		50							
51		51							
52		52							
53		53							
54		54							
55		55							
56		56							
57		57							
58		58							
59		59							
60		60							
1		1		INF TO		1		CAM POSITIONS	
2		2		2		2		LINE	
3		3		10		10		2	
4		4		3		3		10	
5		5		3		3		3	
6		6		5		5		3	
7		7		8		8		3	
8		8		8		8		8	
9		9							
10		10							
11		11							
12		12							
13		13							
14		14							
15		15							
16		16							
17		17							
18		18							
19		19							
20		20							
21		21							
22		22							
23		23							
24		24							
25		25							
26		26							
27		27							
28		28							
29		29							
30		30							
31		31							
32		32							
33		33							
34		34							
35		35							
36		36							
37		37							
38		38							
39		39							
40		40							
41		41							
42		42							
43		43							
44		44							
45		45							
46		46							
47		47							
48		48							
49		49							
50		50							
51		51							
52		52							
53		53							
54		54							
55		55							
56		56							
57		57							
58		58							
59		59							
60		60							
1		1		INF TO		1		CAM POSITIONS	
2		2		2		2		LINE	
3		3		10		10		2	
4		4		3		3		10	
5		5		3		3		3	
6		6		5		5		3	
7		7		8		8		3	
8		8		8		8		8	
9		9							
10		10							
11		11							
12		12							
13		13							
14		14							
15		15							
16		16							
17		17							
18		18							
19		19							
20		20							
21		21							
22		22							
23		23							
24		24							
25		25							
26		26							

Type	Code Number	Timer Description
TEMP 8314-08	536002300	220-240V 50Hz
TEMP 8314-09	536002400	220-240V 50Hz
TEMP 8314-10	536002500	220V 60Hz
TEMP 8314-11	536002600	110V 60Hz

TECHNICAL FEATURE	8314-10-11
VOLTAGE See below FAST CAM: a 50 Hz 1 turn in 25° Nr. tooth = 60, nr. mark = 10 SLOW CAM: a 50 Hz 1 turn in 2180° Nr. tooth = 60 Contact current carrying capacity = 15A	
CONTACT 1-2: Close 147°(177°) - Open: CONTACT 1-10: Close 102°(145°) - Open:	
ZBN	8314-10
Voltage	220V 60Hz
Voltage	110V 60Hz
Motor	M904
	M908

TECHNICAL FEATURE	8314-09
VOLTAGE: 220/240 V - 50 Hz FAST CAM : a 50 Hz 1 turn in 28°, Nr. tooth= 52, Nr. mark = 11 SLOW CAM : a 50 Hz 1 turn in 142°, Nr. tooth = 60 Contact current carrying capacity = 15A CONTACT 1-2: Close 140° - Open 2° CONTACT 1-10: Close 114° - Open 28°	

TECHNICAL FEATURE	8314.08
VOLTAGE: 220 - 240V 50Hz FAST CAM: a 50 Hz 1 turn in 24', Nr. tooth= 48; nr. mark= 12 SLOW CAM: a 50 Hz 1 turn in 2 hours, Nr. tooth = 60 Contact current carrying capacity = 15A CONTACT 1-2: Close: 118° - Open: 2° CONTACT 1-10: Close: 106° - Open: 14°	

460601400

