

Data Sheet

FUJITSU IoT Solution UBIQUITOUSWARE Locator / Focusing Locator


The locator is the core part of Fujitsu high accuracy indoor positioning solution. By combining it with BLE devices including the Ubiquitousware Vital band or Location badge / tag you can track and monitor in real time.

The locator is designed to fit well into any indoor environment, it is a compact and lightweight device.

The locator comes with an easy to use mounting bracket and is powered using standard Power over Ethernet (PoE) to make deployment fast and efficient.


Benefits

- The indoor positioning solution can be used to monitor people and things in real time ensuring risk alerts and efficiencies can be delivered.
- By integrating with location badges/tags, they can be tracked indoors in real time to an accuracy of approximately > 1 ft. (30cm).
- The locators can act as a gateway for the majority of vital data, vital alerts (event) and motion alerts (event) collected by Fujitsu Ubiquitousware sensors.









A focusing locator is required to identify and focus the locators during initial system configuration.

Software License (*1)

Depending on the application of use, there are 2 options of licenses available, these support performance level options for latency and location update regularity as displayed in the table below. The solution is supported by a full telemetry system, allowing for remote configuration, automatic diagnostics, and fault recovery.

| Positioning Engine Options | License A | License B |
|----------------------------|-----------|-----------|
| Latency | 0.2 sec | 1.0 sec |
| Location Update | 10 Hz | 5 Hz |

^{*1} To discuss the license options available and specific user case definition please contact your local Fujitsu sales representative

Page 1/3 www.fujitsu.com/us

Locator / Focusing Locator

| Technical data | | | | |
|--|---|--|--|--|
| Notes | The product is not for medical use and requires additional software to provide functionality | | | |
| Description | RF transceiver using the 2.4 GHz frequencies | | | |
| Radio transmission | Bi-directional Bi-directional | | | |
| Number of channels | 81 channels (1 MHz) but only one at the same time | | | |
| Operating frequency range | 24012481MHz | | | |
| Modulation | GFSK | | | |
| Transmission Power | 2.5mW | | | |
| Antenna | Integrated printed patch antenna with -6 dBi gain | | | |
| Antenna connector | N/A | | | |
| Operating voltage when using PoE | 48V | | | |
| Typical power consumption | 2 W | | | |
| Special features | | | | |
| Indicator | Colored LED x 1 *Refer to the Instruction Manual for the details. | | | |
| Compliance | | | | |
| Europe | CE CB | | | |
| USA/Canada | FCC/IC Class B UL/cUL | | | |
| Dimensions / Weight / Environmental | | | | |
| Dimension details | Approx. 7.95 in x 1.6 in.(202 mm x 40 mm) Dimensions Locator mounting bracket: Approx: 4.72 in x 0.20in (120 mm x 5 mm) | | | |
| Weight | approx. 1.10 lbs. (500 g) | | | |
| Operating temperature range | 32°F to140°F (0°C to +60°C) | | | |
| Storage temperature range | 14 °F to158° (-10° to +70°C) | | | |
| | • | | | |

| _ | | | | • | | |
|---|-----|-----|----|-----|-----|-------|
| |)rc | ŀРГ | ın | וחל | rma | ation |

| order mornador | | | | |
|----------------|-------------|------------------|--|--|
| FPCSK395AB | CP719290-01 | Locator | | |
| FPCSK396AP | CP719292-01 | Focusing locator | | |

Warranh

Please contact your Fujitsu sales representative for regional specific warranty terms

Page 2/3 www.fujitsu.com/us

About Fujitsu Americas

Fujitsu America, Inc. is the parent and/or management company of a group of Fujitsu-owned companies operating in North, Central and South America and Caribbean, dedicated to delivering the full range of Fujitsu products, solutions and services in ICT to our customers in the Western Hemisphere. These companies are collectively referred to as Fujitsu Americas. Fujitsu enables clients to meet their business objectives through integrated offerings and solutions, including consulting, systems integration, managed services, outsourcing and cloud services for infrastructure, platforms and applications; data center and field services; and server, storage, software and mobile/tablet technologies. For more information, please visit: www.fujitsu.com/us and http://twitter.com/fujitsuamerica.

Fujitsu OPTIMIZATION Services

Products

www.fujitsu.com/global/products/
In addition to the FUJITSU IoT Solution
UBIQUITOUSWARE Locator / Focusing Locator,
Fujitsu provides a range of platform
solutions. They combine reliable Fujitsu
products with the best in services, know-how
and worldwide partnerships.

Fujitsu Portfolio

Build on industry standards, Fujitsu offers a full portfolio of IT hardware and software products, services, solutions and cloud offering, ranging from clients to atacenter solutions and includes the broad stack of Business Solutions, as well as the full stack of Cloud offering. This allows customers to leverage from alternative sourcing and delivery models to increase their business agility and to improve their IT operation's reliability.

Computing Products

www.fujitsu.com/global/products/computing/

Software

www.fujitsu.com/software/

More information

Learn more about FUJITSU IoT Solution UBIQUITOUSWARE Locator / Focusing Locator, please contact your Fujitsu sales representative or Fujitsu Business partner, or visit our website. www.fujitsu.com/us

Fujitsu green policy innovation

www.fujitsu.com/global/about/environment/ Fujitsu Green Policy Innovation is our worldwide project for reducing burdens on the environment. Using our global know-how, we aim to resolve issues of environmental energy efficiency through IT. Please find further information at: http://www.fujitsu.com/global/about/environment



Copyright

Fujitsu and the Fujitsu logo are trademarks or registered trademarks of Fujitsu Limited in the United States and other countries. Bluetooth and the Bluetooth logo are registered trademarks of Bluetooth SIG, Inc. in the United States and other countries. All other trademarks referenced herein are the property of their respective owners.

Disclaimer

The statements provided herein are for informational purposes only and may be amended or altered by Fujitsu America, Inc. without notice or liability. Product description data represents Fujitsu design objectives and is provided for comparative purposes; actual results may vary based on a variety of factors. Specifications are subject to change without notice.

Copyright[©] 2017 Fujitsu America, Inc. All rights reserved. FPC65-7797-01 08/17. 17.0807.0137bh

Contact

FUJITSU AMERICA, INC.

Address: 1250 East Arques Avenue Sunnyvale, CA

94085-3470, U.S.A.

Telephone: 800 831 3183 or 408 746 6000

Website: www.fujitsu.com/us

Contact Form: us.fujitsu.com/ContactFujitsu

Have a question? Email us at: AskFujitsu@us.fujitsu.com