



## Low battery warning

The headset needs re-charging when the red indicator is blinking once every about 3 sec.. You can also hear a special tone of “DO-LU-DO-LU-DO” from the headset every about 40 sec.. When you talk by the headset under battery low situation, the headset red indicator is blinking 4 times every about 3 sec.. Once the low battery warning indicator starts, you have around 10 minutes of talk time left and you will then need to charge the battery in the headset.



## Audio and visual indicators

### Indicator light chart:

#### Headset state

Power Off  
 Standby mode  
  
 Charging in process  
 Charging complete  
 Low power  
  
 Pairing mode  
  
 Pairing successful  
  
 Active / on call

#### LED indication state

Indicators off  
 Blue indicator flash once every about 3 sec.  
 Blue indicator lit steady on  
 Indicators off  
 Standby: red indicator flash once every about 3 sec.  
 Talk: red indicator flash 4 times every about 3 sec.  
 Blue indicator and red indicator cross flash  
 Blue indicator flash once every about 3 sec.  
 Blue indicator flash 4 times every about 3 sec.



## Audio indicator chart:

### Headset state

Volume button

Incoming call

Low battery

Initiate voice dial

### Audio indication

Repeated single tone when the button either lower or upper is pressed.

Ring tone

DO-LU-DO-LU-DO tone every about 40 sec.

The headset rings as the cell phone default sound.



## GG301 Bluetooth headset specification

Bluetooth compliance

Bluetooth power

Maximum cordless distance

Weight of headset

Typical standby time

Typical talk time

Typical re-charge time

Battery type

Bluetooth 1.1 with headset profile

2.5mW (0.0025 watts)

30 Feet (10 meters)

Premium type: 18.8g

Eco type: 14.5g

Premium type: 266 hours

Eco type: 200 hours

Premium type: 5.7 hours

Eco type: 4.2 hours

About 2.5-3 hours

Premium type: Li-ion type rechargeable type

Eco type: Li polymer type rechargeable type

NOTE: Talk time and standby time are varied according to different mobile phones.



## Storage of headset

1. Always store the GG301 with power off and safety protected.
2. Avoid storage at high temperatures (above 60°C/134°F) – such as in a hot vehicle or in direct sunlight. (Storage at high temperature can degrade performance and reduce battery life.)
3. Do not expose the headset or any of its supplied parts to rain or other liquids.



## Certification and safety approvals/general information

This product is CE, FCC, BQB marked.

Please note that this product uses radio frequency bands not harmonized within EU. Within the EU, this product is intended to be used in Austria, Belgium, Denmark, Finland, France, Germany, Greece, Ireland, Italy, Luxembourg, The Netherlands, Portugal, Spain, Sweden, United Kingdom and within EFTA in Iceland, Norway and Switzerland.

Users are not permitted to make changes or modify the device in any way. Changes or modifications not expressly approved by G.G. Telecom will void the users' authority to operate the equipment.

Bluetooth is a trade mark owned by Bluetooth SIG, Inc.



## Warranty and parts replacement



Battery: GG301 is equipped with a lithium polymer or a lithium ion rechargeable battery. Replacement or service must be done at a qualified service centre or returned to the manufacturer. Use only the battery supplied.

Use only the supplied and approved AC charger.

G.G. Telecom warrants this product against all defects in material and workmanship for a period of one year from the date of original purchase. The conditions of this warranty and our responsibilities under this warranty are as follows:

- \* The warranty is limited to the original purchaser.
- \* A copy of your receipt or other proof of purchase is required. Without proof of purchase, your warranty is defined as beginning on the date of manufacture as labeled on the products.

- \* The warranty is void if the serial number, date code label or product label is removed, or if the product has been subject to physical abuse, improper installation, modification, or repair by unauthorized third parties.
- \* The responsibility of G.G. Telecom products shall be limited to the repair or replacement of the product at its sole discretion.
- \* Any implied warranty on G.G. Telecom products is limited to one year from the date of purchase on all parts, including any cords and connectors.
- \* Specifically exempt from any warranty are limited-life consumable components subject to normal wear and tear, such as microphone, decorative finishes, batteries, and other accessories.



- \* G.G. Telecom is not liable for any incidental or consequential damages arising from the use or misuse of any G.G. Telecom product.
- \* This warranty gives you specific rights and you may have other rights which vary from area to area.
- \* Unless otherwise instructed in the user guide, the user may not, under any circumstances, attempt to perform service, adjustments or repairs on this unit, whether in or out of warranty. It must be returned to the purchase point, factory or authorized service agency for all such work.
- \* G.G. Telecom will not assume any responsibility for any loss or damage incurred in shipping. Any repair work on G.G. Telecom products by unauthorized third parties voids any warranty.



#### FCC Notices

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

\*FCC RF Exposure requirements:

This device and its antenna(s) must not be co-located or operation in conjunction with any other antenna or transmitter.\*

**NOTE: THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.**