Bluetooth Stereo Receiver Ouick Guide

Congratulation! You have got a Mobile HIFI system.

Please read this manual thoroughly, and set up your Bluetooth wireless music World.

1. Check the package contents

The package include:




Bluetooth Stereo Receiver




Stand for receiver



Power Adapter







USB charging Cable



Stereo RCA interconnect cable



Earphone



Quick Guide

6. Using with your PC

Before using, please check if your PC has Bluetooth A2DP profile, if you are not sure of that, please consult with your PC provider. If your PChas no A2DP profile, you can upgrade it by a Bluetooth Audio Dongle, afterfinishing upgrading Bluetoothyour PC, you can pair the receiver.

5. Using with your mobile phone

Before using, please check if your mobile phone has Bluetooth A2DP profile, if you are not sure of that, please consult with your mobile provider. If your mobile phone doesn't support A2DP, you have to buy a Bluetooth transmitter to pair with the receiver.

To pair with your phone

- 1. Enable Bluetoothon your phone.
- 2. Turnon vour mobile phone.
- 3. Turnon the receiver by pressing "reset" key.
- 4. In the phone's Bluetooth menu, search for devices.
- 5. Select "Bluexon"
- 6. Enter the PINcode "0000". Select and play the Musicon your mobile phone, select "Use Bluetooth". Your mobile phone will be connected with the receiver and send the music. To terminate the music transportation, select "Use mobile"

For further details, pleaserefer to your user manual of mobile phone.

2. Charge the battery

The device canwork continuously forsix hours. If it is almost no power, the power LED will flash red, please using the power adapter or the USB cable to charge.

Plug the USB cable

Plug one end of the USB iack into the receiver, and insert the other end to a USB port of your PC. (Make sure your PC is on) or

Plug the power adapter

Plug one end of the USB jack into the receiver, and the other end into the power adapter. (Make sure the power adapter connected to the power) When it is being charged, the power LED keeps lighting red. If it is fully charged, the powerLED will turn green.






Note: Before the first use, charge the battery fully for about 10 hours. Thereafter, recharging takes about 90 Minutes.

3. To turn on the power

To turn on the power. Press and hold the connect button (about 2 seconds) until the Connect indicator light blue.

To turn off the power, Press and hold the connect button (about 2 seconds) until the Connectindicator light off.



Blue LED: power is on

Blue flashing LED: finish connected successfully.


Red LED: Battery is charging, turnsgreen when chargedfully.

Red flashing LED: Battery is low

4. How to connect

Ensure your mobile or PC was built in BLUETOOTH A2DP profile before using, Remark: A2DP means Advanced Audio Distribution Profile.

- 1. Connect the Bluetooth receiver to your stereo system by the enclosed Stereo RCA interconnect cable. Or connect the earphone to the RCA iack of the receiver.
- 2. Connect the mobile phone or PC to your Bluetooth stereo receiver. The Blue LED on the receiver will flash when connected. (Please refer the chapter 5 and 6)
- 3. Open your favorite play list and press "Play" from your mobile or PC.
- 4. Sit back, relax and enjoy your music!



7. Troubleshooting

If the Bluetooth Stereo System does not work, try the following:

- Ensure your mobile or PC was built in BLUETOOTH A2DP profile.
- Check whether the system is out off power.
- Check the operation distance.
- Power off the receiver and reconnect again and ensure the right paring password "0000".
- Check whether other Bluetooth device is connected.
- Check whether the system is connected correctly.
- Check whether Bluetooth function of device is turned on.

8. Specifications

- Operating frequency band: 2.4 to 2.48GHzunlicensed ISM band
- Bluetooth specification: V1.2
- Output power class: class 2
- Transmission power: +3dbm to-20dbm
- · Maximum data rate
- Asynchronous: 723.2/57.6kbps
- Synchronous: 433.9/433.9Kbps
- Operation temperature: -40 to +85 degrees
- Receiving signal range: -83dbm to -20dbm
- Receiving sensitivity: -83 dBm 0.1% BER
- Storage temperature: -40 to +105 degrees
- Transmit powerconsumption: 46mA
- Pairing code: "0000"
- Power supply: Standard Li-lon battery, 350mAh Rating: 3.7V 5vdc 50 – 100mA
- Only use the USB cable and net adaptor supplied.
- Physical Specification: Dimension: 62 mm x 42 mm x 12 mm

9. Caution:

This device complise with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: THE MANUFACTURERIS NOT RESPONSIBLEFOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATETHE EQUIPMENT.

10. Copyright

Bluedio is a trademark owned by G. Tech Technology Ltd. Other product names used in this quick guide are the properties of their respective owners and are acknowledged.