

# HIT 731-UHF User's Manual



# Hana Micron

## Table of Contents

User's Warning .....	4
Product Component.....	5
Boot-up Screen .....	6
Start Screen .....	6
Main Menu.....	7
Registration.....	8
Cow Registration.....	8
Farm Registration.....	9
Identification .....	12
Cow Identification .....	12
Farm Identification .....	13
Procedures.....	14
Trade.....	14
Vaccination .....	15
Count Cows.....	16
Update .....	17
Setting.....	18
GPRS.....	18
Key, ICON component of HIT 731-UHF.....	21
SIM, Smart Card aux slot .....	22
Troubleshooting.....	24

## HIT 731-UHF Manual

### FCC Compliance Information

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

### Caution

Modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of FCC Rules. Operation is subject to the following two conditions:

- (1) the device may not cause interference, and
- (2) the device must accept any interference, including interference that may cause undesired operation of this device.

### FCC RF Radiation Exposure Statement:

When RFID function is used, this equipment should be operated with a minimum distance of 20 centimeters between the radiator and your body. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

## User's Warning

### User's Warning



To clean this product, turn the power off and use only a damp cloth for cleaning exterior of terminal using either water or light detergent. Do not use flammable substances such as benzene thinner



Before the use of this product, read all instructions in your user's manual and keep it for future references



Do not unplug terminal while it's in use. If you wish to unplug the terminal, please make sure the machine is turned off, then unplug it.




Do not attempt to service this terminal yourself, as opening or removing the cover may expose you to dangerous voltage. (refer all servicing to authorized personnel)



If there is smoke coming out of the terminal, turn the terminal off and unplug it from the outlet.

**Product Component**







### Boot-up Screen

#	Terminal Screen	Descriptions for Key Operation and Summary
1	<div style="border: 1px solid black; padding: 5px; background-color: #e0f2f1;"> <p style="text-align: center;"><b>GPS</b></p> <p>Time 00:00:00                      Latitude :                      [0.000000]                      Longitude :                      [0.000000]                      Press Enter for Continue</p> </div>	<p>Terminal starts to read its GPS location when it boots up</p> <p>Press <b>Enter</b> to continue to the Start Screen</p>


### Start Screen

#	Terminal Screen	Descriptions for Key Operation and Summary
1	<div style="border: 1px solid black; padding: 5px; background-color: #e0f2f1;">  <p>Hana Micron America                      Enter for Main Menu</p> </div>	<p>Press <b>Enter</b> for Main Menu</p>



## Main Menu

#	Terminal Screen	Descriptions for Key Operation and Summary
1	 <p style="text-align: center;"><b>Main Menu</b></p> <ol style="list-style-type: none"> <li>1. Registration</li> <li>2. Identification</li> <li>3. Procedures</li> <li>4. Update</li> <li>5. Setting</li> </ol>	<p>* key for moving up                      # key for moving down                      1 ~ 5 key for direct moving                      Enter key for selected menu</p>

## Registration

#	Terminal Screen	Descriptions for Key Operation and Summary
1	 <p>Registration 1. Cow 2. Farm</p>	<p>* key for moving up # key for moving down 1 ~ 2 key for direct moving Enter key for selected menu</p>

## Cow Registration

#	Terminal Screen	Descriptions for Key Operation and Summary
1	 <p>Cow Registration  Scanning for Cow's Tag ...</p>	<p>Point the terminal to cow's tag to get Cows' ID numbers</p>
2	 <p>Cow Registration  Cow ID # 105500217811534</p>	<p>Get Cow ID numbers  Press <b>Enter</b> to continue</p>



## HIT 731-UHF Manual

3	<p style="text-align: center;"><b>Cow Registration</b>  <b>Birthday : _ / /</b></p>	<p>Input cow's birthday (dd/mm/yyyy)</p> <p>Press <b>Enter</b> to continue</p>
4	<p style="text-align: center;"><b>Cow Registration</b>  <b>Birthday : 01/01/2000</b>  <b>Sex : _</b></p>	<p>Input cow's sex (Male : M, Female : F)</p> <p>Press <b>Enter</b> to continue</p>
5	<p style="text-align: center;"><b>Cow Registration</b>  <b>Birthday : 01/01/2000</b>  <b>Sex : M</b>  <b>Weight(kg) : __</b></p>	<p>Input cow's weight</p> <p>Press <b>Enter</b> to continue</p>
6	<p style="text-align: center;"><b>Cow Registration</b>  <b>SISBOV : 105500217811534</b>  <b>Birthday : 01/01/2000</b>  <b>Sex : M</b>  <b>Weight(kg) : 500</b></p> <p style="text-align: center;"><b>Press Enter to confirm</b></p>	<p>Confirm information</p> <p>Press <b>Enter</b> to finish</p>

### Farm Registration

#	Terminal Screen	Descriptions for Key Operation and Summary
---	-----------------	--------------------------------------------


## HIT 731-UHF Manual

1	<p style="text-align: center;"><b>Farm Registration</b></p> <p>Point #1  Latitude :  [0.000000]  Longitude :  [0.000000]</p> <p style="text-align: center;">Press Enter to confirm</p>	Go to the first corner of the premise and press <b>Enter</b>
2	<p style="text-align: center;"><b>Farm Registration</b></p> <p>Point #2  Latitude :  [0.000000]  Longitude :  [0.000000]</p> <p style="text-align: center;">Press Enter to confirm</p>	Go to the second corner of the premise and press <b>Enter</b>
3	<p style="text-align: center;"><b>Farm Registration</b></p> <p>Point #3  Latitude :  [0.000000]  Longitude :  [0.000000]</p> <p style="text-align: center;">Press Enter to confirm</p>	Go to the third corner of the premise and press <b>Enter</b>
4	<p style="text-align: center;"><b>Farm Registration</b></p> <p>Point #4  Latitude :  [0.000000]  Longitude :  [0.000000]</p> <p style="text-align: center;">Press Enter to confirm</p>	Go to the fourth corner of the premise and press <b>Enter</b>
3	<p style="text-align: center;"><b>Farm Registration</b></p> <p>Owner : _</p>	Input farm owner's name  Press <b>Enter</b> to continue



## HIT 731-UHF Manual

4	<p>Farm Registration Owner : Hana Micron Address :</p> <hr/> <hr/>	<p>Input farm address</p> <p>Press <b>Enter</b> to continue</p>
5	<p>Farm Registration Owner : Hana Micron Address : 1551 McCarthy Blvd STE 201, Milpitas, CA 95035</p> <p>Press Enter to confirm</p>	<p>Confirm information</p> <p>Press <b>Enter</b> to finish</p>

## Identification

#	Terminal Screen	Descriptions for Key Operation and Summary
1	 <p style="text-align: center;"><b>Identification</b> 1. Cow 2. Farm</p>	<p>* key for moving up # key for moving down 1 ~ 2 key for direct moving Enter key for selected menu</p>

## Cow Identification

#	Terminal Screen	Descriptions for Key Operation and Summary
1	 <p style="text-align: center;"><b>Cow Registration</b>  Scanning for Cow's Tag ...</p>	<p>Point the terminal to cow's tag for identification</p>
2	 <p style="text-align: center;"><b>Cow Identification</b> ID# : 105500217811534 Birthday : 01/01/2000 Sex : M Weight(kg) : 500</p>	<p>(If cow is registered) Show cow's information Enter key for finish</p>


## HIT 731-UHF Manual

<b>3</b>	<div style="border: 1px solid black; padding: 10px; background-color: #e0f2f7;"> <p><b>Cow Identification</b></p> <p><b>No Information</b></p> </div>	<p>(If cow is not registered)            Show No Information message            Enter key for finish</p>
----------	-------------------------------------------------------------------------------------------------------------------------------------------------------	------------------------------------------------------------------------------------------------------------------



### Farm Identification

#	Terminal Screen	Descriptions for Key Operation and Summary
<b>1</b>	<div style="border: 1px solid black; padding: 10px; background-color: #e0f2f7;"> <p><b>Farm Identification</b>            Owner : Hana Micron            Address :            1551 McCarthy Blvd STE            201, Milpitas, CA 95035</p> </div>	<p>(If in farm area)            Show farm information            Enter key for finish</p>
<b>2</b>	<div style="border: 1px solid black; padding: 10px; background-color: #e0f2f7;"> <p><b>Farm Identification</b></p> <p><b>No Information</b></p> </div>	<p>(If not in farm area)            Show No Information message            Enter key for finish</p>

## Procedures

#	Terminal Screen	Descriptions for Key Operation and Summary
1	 <p style="text-align: center;"><b>Procedures</b> 1. Trade 2. Vaccination 3. Count Cows</p>	* key for moving up # key for moving down 1 ~ 3 key for direct moving Enter key for selected menu

## Trade

#	Terminal Screen	Descriptions for Key Operation and Summary
1	 <p style="text-align: center;"><b>Trade</b> Seller ID : _</p>	Input seller ID Enter key for next step
2	 <p style="text-align: center;"><b>Trade</b> Buyer ID : _</p>	Input buyer ID Enter key for next step

## HIT 731-UHF Manual

3	<p>Trade</p> <p>Counting cows...</p> <p>Counted : 123</p>	<p>Count cows and get cow's ID numbers while cows are passing through the gate</p> <p>Press <b>Enter</b> when finished</p>
4	<p>Trade</p> <p>Seller ID : 123456</p> <p>Buyer ID : 456789</p> <p>Amount : 123</p> <p>Date : 04/06/2010</p> <p>Press Enter to confirm</p>	<p>Confirm trade information</p> <p>Press <b>Enter</b> to confirm</p>

### Vaccination

#	Terminal Screen	Descriptions for Key Operation and Summary
1	<p>Cow Registration</p> <p>Scanning for Cow's Tag ...</p>	<p>Point the terminal to cow's tag to get ID numbers</p>
2	<p>Vaccination</p> <p>Cow ID # : 105500217811534</p>	<p>Press <b>Enter</b> to continue</p>

## HIT 731-UHF Manual




3	<p><b>Vaccination</b> Vaccine ID : _</p>	<p>Input the vaccine ID</p> <p>Press <b>Enter</b> to continue</p>
4	<p><b>Vaccination</b> SISBOV : 105500217811534 Vaccine : 123456 Date : 04/06/2010</p> <p>Press Enter to confirm</p>	<p>Confirm the vaccination information</p> <p>Press <b>Enter</b> to confirm</p>

### Count Cows


#	Terminal Screen	Descriptions for Key Operation and Summary
1	<p><b>Count Cows</b></p> <p>Counting...</p> <p>123</p> <p>Reset : Clear</p>	<p>Count number of cow tags in range</p> <p>Press <b>Clear</b> to reset</p> <p>Press <b>Enter</b> to finish</p>





## Update

#	Terminal Screen	Descriptions for Key Operation and Summary
1	 <p>The terminal screen displays the word "Update" at the top and "Updating..." in the center, indicating the start of the update process.</p>	<p>Send any updated information (Registration, Trade, Vaccination) to the server, if there is any</p>
2	 <p>The terminal screen displays the word "Update" at the top and "Success" in the center, indicating that the update was completed successfully.</p>	<p>(If success)            Show success message            Enter key for finish</p>
3	 <p>The terminal screen displays the word "Update" at the top and "Failed" in the center, indicating that the update process did not complete successfully.</p>	<p>(If fail)            Show failed message            Enter key for finish</p>

## Setting

#	Terminal Screen	Descriptions for Key Operation and Summary
1	 <p>The terminal screen displays the word "Setting" at the top right. Below it, the option "1. GPRS" is highlighted in a light blue background.</p>	GPRS setting only Enter key for selected menu

## GPRS

#	Terminal Screen	Descriptions for Key Operation and Summary
1	 <p>The terminal screen displays "GPRS Band" at the top right. Below it, a list of seven options is shown, each on a new line: "1. 850", "2. 900", "3. 1800", "4. 1900", "5. 850/1900", "6. 900/1800", and "7. 900/1900".</p>	Select band of the network carrier and press <b>Enter</b>
2	 <p>The terminal screen displays "GPRS Network Info" at the top right. Below it, the text "APN :" is followed by a horizontal line indicating an input field.</p>	Input APN and press <b>Enter</b>

## HIT 731-UHF Manual


3	<p><b>GPRS Network Info</b> APN : epc.tmobile.com PPP ID : _____</p>	Input PPP ID and press <b>Enter</b>
4	<p><b>GPRS Network Info</b> APN : epc.tmobile.com PPP ID : guest PPP P/W : _____</p>	Input PPP Password and press <b>Enter</b>
5	<p><b>Host Info</b> Server IP : _</p>	Input server IP and press <b>Enter</b>
6	<p><b>Host Info</b> Server Port : _</p>	Input server port and press <b>Enter</b>



## Key, ICON component of HIT 731-UHF



ICON Component



**SIM, Smart Card aux slot**



## Troubleshooting

Problem	Cause	Follow-up measures
When Power On, LCD screen do not operation	Power supply error LCD contrast error Terminal error	Confirm a wall socket. Confirm connection Between a wall socket and power plug. Confirm power plug. Adjust LCD contrast. Request A/S.
LCD show too Dark or too Bright	LCD adjustment error LCD device error Terminal error	Adjust LCD contrast. Request A/S.
Paper is not clear	Printer head error Printer device error Bad paper Terminal error	Open the printer cover and Confirm printer device. Request A/S. * Paper keep in dry place.
When Printer paper hanging on Printer device	Bad paper use Paper Insert error Terminal error	Use Up key. And eliminate the paper. Clean paper Insert. Request A/S.
Character is not normal at LCD screen	LCD error LCD device error Terminal error	Request A/S.
When card don't Read	Card Insert error Bad card use Terminal error	Confirm insert direction. Confirm card. Confirm magnetic line. Request A/S.
When pinpad do not operate	Pinpad error	Confirm connection between terminal and pinpad. Request A/S.
When time is not correct	TimeSetting is wrong Timer error	Time Setting. (Date & Time) Request A/S.