

LG- 4600 User Guide

Ver. 0.1
2003.08.01

Unlocking Your Phone	4
View of Phone	4
Installing and Removing the Battery.....	5
Turning Your Phone On and Off.....	5
Main Menu.....	6
Power Save Mode.....	6
Menu Navigation	6
Entering Characters Using the Keypad(T9)	7
Display Icons.....	8
Antenna	8
Signal Strength	9
Battery Capacity	9
Using the AC Adapter	9
Using Your Phone.....	10
Placing a Call	10
Roaming With Your Telus Mobility Phone™	10
Calling Experience.....	10
Correcting Dialing Mistakes	11
In Call Options	11
Incoming Call Notification.....	12
Answering Calls	12
Displaying Your Phone Number(phone book – not functioning).....	13
Setting the Ring Volume to Vibrate	13
Getting the Most From Telus Mobility Service	13
New Message Alerts	13
Retrieving Page/Text Messages	13
Page/Text Message Storage	15
Roaming on to Other Service Providers	15
(Call History- not functioning)	15
Page/Text Messages	15
Erasing Page/Text Messages.....	15
Sounds	16
Adjusting the Volume.....	16
Selecting Ring Types for Voice Calls	16

Tone Length	18
Display Menu.....	19
Security	19
Locking Your Phone.....	19
Unlocking Your Phone	20
Changing the Lock Code.....	20
Answering Your Phone with the Hands-Free Car Kit	20

Unlocking Your Phone

If you received your Telus Mobility LG-4600 in the mail, you may need to unlock it before making calls.

1. Press the END/PWR Switch for 2 ~3 secs.
2. press Unlock menu
3. Enter your four-digit lock code. For security purposes, the code will not be visible as you type.

Note: If you can't recall your lock code, try using the last four digits of your Social Security number, the last four digits of your Telus Mobility Phone Number or 0000.

View of Phone

1. **END/PWR Switch:** Lets you power the phone on or off.
2. **Antenna:** Fixed antenna provides optimum reception for 1900 MHz frequencies.
3. **Headset Jack:** Provides connection for an optional headset.
4. **Volume Control Keys:** Adjust the Ring Volume in the Main Menu or the Voice Volume during a call. The keys also scroll through months in the Calendar or pages in the MiniBrowser.
5. **Mouse Key:** Allows quick and easy scrolling through the menus.
6. **TALK:** Lets you place a call, receive a call or end a call.
7. **CLR:** Lets you clear an entry or back-up in the menu.
8. **Folder :** Lets you answer or end calls.



Installing and Removing the Battery

To install the battery, insert the bottom of the battery into the opening on the back of the phone. Then, push the battery down until the latch clicks.

To remove the battery, press down on the latch and remove the battery from the phone.

Turning Your Phone On and Off

To turn your phone on, press and hold PWR button 2-3 seconds. Your phone performs a short self-test before letting you know it is operational.

If your phone does not turn on, make sure the battery is installed correctly and is adequately charged or has external power (via the AC Adapter, Cigarette Lighter Adapter or Hands-Free Car Kit).

To turn your phone off, press and hold the PWR key 2-3 seconds.


Main Menu


Incoming Log

When your phone acquires Telus Mobility Service, the Greeting (a banner of text), the current time and date and the Main Menu are displayed. If you are in a Telus Mobility or authorized analog cellular provider's service area, you are ready to send and receive calls.



Menu Navigation

The Mouse Key lets you scroll circularly through menus quickly and easily.



As you navigate through a menu, the options are highlighted. Select an option by highlighting it and pressing . The scroll bar at the right of the menu keeps track of your position in the menu at all times.

For example, if you want to view your last incoming call:

1. From the Main Menu, highlight **Call History** and press  (It may already be highlighted.)
2. Press the Mouse Key down to highlight **3.Incoming Calls** and press .

If you have received any calls, they are displayed on the screen.

Entering Characters Using the Keypad(Multi-tab)

To enter a letter, punctuation or number when creating Phone Book or Scheduler entries, press the corresponding key until the desired character appears. By default, the first letter of a word is capitalized and following letters are lowercase. Characters in the following order:

















After a character is entered, the cursor automatically advances to the next space after two seconds. You can also advance the cursor by pressing or entering a character not on the same key.

If you make a mistake, press to move the cursor left or **CLR** to erase a character. To clear the entire entry, press and hold **CLR** for two seconds.

Display Icons

Display icons are the symbols your phone uses to communicate important information. They are as follows:

ICON	DESCRIPTION
	SSL
	TTY
	Signal Strength (full strength)
	In call stateUse
	Digital
	Roaming (occurs in a non-Telus Mobility area)
	Analog Service Available
	New Downloads
	No Service May result from one of the following : <ul style="list-style-type: none"> Searching for service no service maintenance required
	Manner Mode
	New text messages
	New voicemails
	New text & voicemails
	Battery Charge Status (fully charged)

Antenna

The antenna on your Telus Mobility LG-4600 provides maximum reception without the inconvenience of extending or retracting it.

!!! WARNING – CHOKING HAZARD – ANTENNA MAY BECOME DISLODGED

Attempting to remove or repeated twisting of the antenna will loosen the materials securing it into the antenna. Once the antenna is loosened or removed, only an authorized Telus Mobility Representative can restore the antenna's original integrity. Do not attempt to remove or twist the antenna.

Signal Strength

The quality of each call you make or receive depends on the signal strength in your area. The number of bars in the Signal Strength icon informs you of the current strength. The more bars, the stronger the signal.

Battery Capacity

Your Telus Mobility LG-4600 is equipped with a Lithium Ion (LiIon) battery. It allows you to recharge your battery before it is fully drained. The battery provides approximately 110 hours of continuous digital talk time or approximately 200 hours of continuous digital standby time.

Note: Long backlight settings affect the battery's talk and standby times.

When the battery reaches 5% of its capacity, the battery icon blinks. When there is about one minute of talk time left, the phone sounds an audible alert every 30 seconds and then powers down.

If the battery's charge is completely run down, it takes 2 to 3 hours to fully recharge. It is not necessary to let the battery completely run down before recharging.

To charge your batteries, use only Telus Mobility-approved charging accessories.

Using the AC Adapter

To charge the battery, plug the AC Adapter into a standard wall outlet and connect it to the phone via the I/O Connector on the bottom of the phone. Alternatively, you can place the phone in the charging cradle provided with your phone and connect the AC Adapter to the back of the cradle.

The battery Charge Status icon flashes during charging. When the battery is fully charged, the battery icon stops flashing.

Using Your Phone

Placing a Call

When the phone is turned on, check the Signal Strength icon to see if you are in a Telus Mobility Service Area or authorized PCS CDMA or AMPS provider's service area.

1. Open the Flip.
2. Enter the phone number and press **TALK** button.
3. When you are finished with your call, press **END** button.

Roaming With Your Telus Mobility Phone™

Your Telus Mobility Phone™ is you can use it to make and receive calls in many places.

☞ In any city where Telus Mobility provides service.

☞ On other PCS CDMA or AMPS networks there Telus Mobility has implemented roaming agreements.

When you use your phone outside Telus Mobility Network, it's called roaming. If you're roaming in areas where agreements are in place with PCS CDMA or AMPS providers, you will pay the roaming rate plus long-distance charges, where they apply. (See "Display Icons" for network indication icons.) Always dial using 10 digits (area code + number) when calling from outside your Telus Mobility Home Service Area.

Setting Your Phone's Mode

Your Telus Mobility Phone™ allows you to control your ability to roam. (See "Set Mode")

Calling Experience

When you use your phone on other than Telus Mobility networks, your calling experience and call quality will be quite similar to what you experience when making calls within the Telus Mobility Network. Although certain calling features may not be available, your phone calls are still private and secure.

If you need customer service for any reason while using your phone outside the Telus Mobility Nationwide Network, just dial 611 from your Telus Mobility Phone. However, because you're outside the Telus Mobility Network, you may reach the local service provider's customer service instead of Telus Mobility Customer Care.

Correcting Dialing Mistakes

To delete one digit at a time, press **CLR** button. To delete all digits, press and hold **CLR** button.

Redialing Last Outgoing Number

Press and hold **TALK** button for 2 seconds.

Dialing Options

When you enter numbers in the Main Menu, dialing options are displayed.

To select an option, highlight it and press **[OK]**.

☞ Search – Displays phone numbers in your Phone Book that contain the entered numbers. (See “Finding a Phone Number”)

☞ Hard Pause – Inserts a Hard Pause. (See “Dialing and Saving Phone Numbers With Pauses”)

☞ 2-sec pause – Inserts a two-second pause. (See “Dialing and Saving Phone Numbers With Pauses”)

Tip! To speed dial a Phone Book entry from the Main Menu, press and hold the entry's number. If the entry number is two digits, enter the first digit, then press and hold the second digit. (This feature will not work when the Roam Confirm option is enabled.)

In Call Options

During a call, your phone displays menu options.

To select an option, press **Options** menu.

- ☞ 3 Way call – Lets you dial another phone number.
- ☞ Search – Let's you search an entry from Phonebook.
- ☞ Record – Start recording the conversation.
- ☞ Write memo – Start the Notepad for you to write memo on it.
- ☞ Menu – Let's you access Main Menu.

Incoming Call Notification

Depending on your settings, your phone notifies you of incoming calls in the following ways:

- ☞ The phone rings or vibrates
- ☞ The backlight illuminates
- ☞ The screen displays an incoming call message
- ☞ The phone number of the caller is displayed if the phone number is available
- ☞ The caller's name is displayed if the phone number is in your Phone Book

The following options are also displayed.

- ☞ Quite – Mutes the ringer
- ☞ Ignore – Abandon incoming call.

Note: You can also mute the ringer by pressing the up or down Volume Control key or [CLR].

Answering Calls

To answer incoming calls, open the Flip (in Active Flip Mode) or press [TALK].

Note: If you open the Flip (in Active Flip Mode) and then press [TALK], you will hang up on the caller.

Displaying Your Telus Mobility Phone Number

To display your phone number:

1. From the Main Menu, highlight **Phone Info** and press [OK].

Setting the Ring Volume to Vibrate

To set the phone to Vibrate Mode, press the down Volume Control key until **Vibrate** is displayed. **Vibrate On-** is displayed on idle screen.

To set the phone to Vibrate Mode using the Main Menu, see “Adjusting the Volume” .

Getting the Most From Telus Mobility Service

New Message Alerts

If it is a voicemail message, the following options are displayed. To select an option, highlight it and press [OK].

- ☞ Listen – make a call to listen to the message.
- ☞ Ignore - ignore the message.

If it is a text message, the following options are displayed. To select an option, highlight it and press [OK].

- ☞ View – Displays the message.
- ☞ Ignore – Returns to the Main Menu. (You can also press [CLR].)

Note: If you are out of Telus Mobility Service Area coverage, you are not notified of new messages. You will be notified when you reenter a Telus Mobility Service Area.

Retrieving Text Messages

To retrieve text messages:

1. From the Main Menu, highlight **Messaging** and press [OK].

Tip! You can also access Messaging from the Main Menu by pressing the Mouse Key Right.

2. Highlight **Text Messaging** and press [OK].
3. Highlight the message you want to display and press [OK]. Press the Mouse Key down to display additional text.

Tip! You can view the next or previous message by pressing the Mouse Key left (previous) or right (next)

4. Press [OK] to display message options.

To select an option, highlight it and press [OK].

Page Message options:

~~⌘~~ Erase Message – Deletes the message.

~~⌘~~ Read – Displays the message again.

~~⌘~~ Exit – Returns to the Main Menu.

Text Message options:

~~⌘~~ Extract #s – Extracts phone numbers (if there are numbers contained in the text message).(See the following chapter.)

~~⌘~~ Erase Message – Deletes the message.

~~⌘~~ Read – Displays the message again.

~~⌘~~ Exit – Returns to the Main Menu.

Extracting Phone Numbers From Text Messages

To extract a phone number from a text message:

1. While displaying a text message, press **Options** menu to view the Text Message options.
2. Highlight **Extract Number** and press [OK]. All the phone numbers contained in the message are displayed.


Note: If there are no phone numbers to extract from the message, nothing is displayed.

3. Select and highlight one of the numbers that you want to save and press [OK]

Text Message Storage

Your Telus Mobility LG-4600 can store up to 50 text messages. When the message memory is 75% full, a warning message prompts you to erase messages to obtain more memory space.

Roaming on to Other Service Providers

Roaming occurs when you are in an area serviced by another authorized service provider. When this situation occurs, the **R** icon and Digital Roam or Analog Roam are displayed. If there is no service available, the  icon is displayed.

(Call History - not functioning)

Text Messaging

For information on text messaging, see “Retrieving Text Messages” .

Erasing Text Messages

To erase all text messages:

1. From the Main Menu, highlight **Messaging** and press [OK].
2. Highlight **Text Messaging** and press [OK]
3. Highlight **Erase** and press [OK]
4. Highlight **All** and press [OK].
5. Highlight **yes** and press [OK].

Sounds

Adjusting the Volume

1. From the Main Menu, highlight **Settings** and press [OK].
2. Highlight **Sounds** and press [OK].
3. Highlight **Volume** and press [OK].
4. Highlight **Ringer**, **Ear Piece**, **Key Beep**, **Power On/Off** or **Game** and press [OK].
5. Highlight **High**, **High Med**, **Med**, **Med Low**, **Low** or **Vibrate** (for Ringer only) and press [OK].

Tip! You can use the Volume Control keys to adjust the Ring Volume in the Main Menu or the Voice Volume during a call.

Note: When the phone is in Vibrate Mode and attached to an accessory (Desktop Charger, Hands-Free Car Kit, etc.), it uses the Standard Ring Type to alert you of incoming calls, alarms or messages.

Selecting Ring Types for Voice Calls

To Select a Ring Type for Voice Calls:

1. From the Main Menu, highlight **Settings** and press [OK].
2. Highlight **Sounds** and press [OK].
3. Highlight **Ringers** and press [OK].
4. Highlight **Voice Calls** and press [OK].
5. Highlight **Caller ID**, **No Caller ID** or **Roaming** and press [OK].

Note: If you select Roaming, the Ring Type is used for all incoming roaming calls.

6. Scroll the list and highlight a ringer type. You will hear a preview of the ringer type when you highlight it.

Tip! You can also assign different Ring Types to individual Phone Book entries. (See “Selecting an ID Finger”)

Selecting Ring Types for Messages

To select a Ring Type for Messages:

1. From the Main Menu, highlight **Settings** and press [OK].
2. Highlight **Sounds** and press [OK].
3. Highlight **Ringers** and press [OK].
4. Highlight **Messages** and press [OK].
5. Highlight **Voicemail** or **Page/Text** and press [OK].
6. Scroll the list and highlight a ringer type. You will hear a preview of the ringer type when you highlight it.

Tone Length

Longer tone lengths may be better for tone recognition when dialing voicemail or other automated systems.

To select a tone length:

1. From the Main Menu, highlight **Settings** and press [OK].
2. Highlight **Sounds** and press [OK].
3. Highlight **Key Tones** and press [OK].
4. Highlight **Short Tones** or **Long Tones** and press [OK].

Alert Notification

To enable or disable alert sounds:

1. From the Main Menu, highlight **Settings** and press [OK].
2. Highlight **Sounds** and press [OK].
3. Highlight **Alerts** and press [OK].
4. Select one of the alert type from the selection list by highlighting it and pressing [OK].

~~☞~~ Service Change – An alert sounds when you exit or enter AMPS, PCS CDMA or cellular coverage.

~~☞~~ Minute Beep – Your phone beeps once a minute when you are on a call. (The beep is not audible to the other party.)

~~☞~~ Call Connect – An alert sounds when a call is established.

5. Highlight **ON** or **Off** and press [OK].

Display

For information on changing Backlight, Greeting or Contrast settings, see **Handy Tips**.

Security

Accessing the Security Menu

You must enter your lock code to view the Security menu. If you forget your lock code, try using the last four digits of your Telus Mobility Phone Number or 0000.

Security Menu

To access the Security menu:

1. From the Main Menu, highlight **Settings** and press [OK].
2. Highlight **Security** and press [OK]
3. Enter your lock code.

Locking Your Phone

When your phone is locked, you can only make calls to 911, Customer Care and Special Numbers or receive incoming calls.

To lock your phone:

1. From the Settings menu, highlight **Security** and press [OK].
2. Enter your lock code.
3. From the Security menu, highlight **Lock Phone** and press [OK].

4. Highlight **Lock** and press [OK].

Unlocking Your Phone

1. Highlight **Unlock** and press [OK].
2. Enter your lock code.

Changing the Lock Code

To change your lock code:

1. From the Main Menu, highlight **Settings** and press [OK].
2. Highlight **Security** menu and press [OK].
3. Highlight **Change Lock** and press [OK].
4. Enter your new lock code.
5. Reenter your new lock code.

Answering Your Phone with the Hands-Free Car Kit

You can select different answering options like below when your phone is connected to the Telus Mobility Hands-Free Car Kit.

~~☞~~ Any Key Answer - You can answer calls by pressing any key (not including the [CLR] key, Mouse Key or Volume Control keys)

~~☞~~ Auto Answer - Your phone answers incoming calls automatically after five seconds.

To answer calls by pressing any key:

1. From the Main Menu, highlight **Settings** and press [OK].

2. Highlight **Setup** and press [OK].
3. Highlight **Call Answer** and press [OK]
4. Select **Open/Any Key** from the selection list and press [OK]

To answer calls automatically

1. From the Main Menu, highlight **Settings** and press [OK]
2. Highlight **Setup** and press [OK].
3. Highlight **Auto-Answer** and press [OK]
4. Select **Car-Kit** from the selection list and press [OK]

FCC RF EXPOSURE INFORMATION

WARNING! *Read this information before using your phone*



In August 1996 the Federal Communications Commission (FCC) of the United States with its action in Report and Order FCC 96-326 adopted an updated safety standard for human exposure to radio frequency electromagnetic energy emitted by FCC regulated transmitters. Those guidelines are consistent with the safety standard previously set by both U.S. and international standards bodies. The design of this phone complies with the FCC guidelines and these international standards.



Use only the supplied or an approved antenna. Unauthorized antennas, modifications, or attachments could impair call quality, damage the phone, or result in violation of FCC regulations.

Do not use the phone with a damaged antenna. If a damaged antenna comes into contact with the skin, a minor burn may result. Please contact your local dealer for replacement antenna.

Body-worn Operation

This device was tested for typical body-worn operations using the optional belt-clip/holster, which places the phone 0.78 inches (2.0 cm) from the body. To comply with FCC RF exposure requirements, a minimum separation distance of 0.78 inches (2.0 cm) must be maintained between the user's body and the phone, including the antenna whether extended or retracted. The use of non-tested accessories may not comply with FCC RF Exposure requirements and should be avoided.