

Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4											
	0	1	2	3	4	5	6	7	8		9	0	1	2	3	4	5	6	7		8	9	0	1	2	3	4	5	6	7	8	9
234	携	敬	景	桂	溪	畦	稽	系	經	繼	264	哉	塞	妻	宰	彩	才	採	裁	歲	濟	294	夙	宿	淑	祝	縮	肅	塾	熟	出	術
235	繫	野	荃	荊	蚩	計	詣	警	輕	頸	265	災	采	犀	碎	砦	祭	齋	細	菜	裁	295	述	俊	峻	春	瞬	竣	舜	駿	准	循
236	鷄	芸	迎	鯨	劇	戟	擊	激	隙	桁	266	載	際	劑	在	材	罪	財	牙	坂	阪	296	旬	楯	殉	淳	準	潤	盾	純	巡	遵
237	傑	欠	決	潔	穴	結	血	訣	月	件	267	塚	棟	肴	咲	崎	埼	碕	鷺	作	削	297	醇	順	処	初	所	暑	曙	渚	庶	緒
238	儉	倦	健	兼	券	劍	喧	圈	堅	嫌	268	咋	搾	昨	朔	柵	窄	策	索	錯	桜	298	署	書	薯	諸	諸	助	叙	女	序	徐
239	建	憲	懸	拳	捲						269	鮭	笹	匙	冊	刷						299	恕		鋤	除	傷	償				
240		檢	榷	牽	犬	獻	研	硯	絹	梟	270		察	撈	撮	擦	札	殺	薩	雜	阜	300		勝	匠	升	召	哨	商	唱	嘗	獎
241	肩	見	謙	賢	軒	遣	鍵	險	顯	驗	271	鯖	捌	鏑	絞	血	晒	三	傘	參	山	301	妾	娼	宵	將	小	尚	庄	床	廠	
242	齟	元	原	嚴	幻	弦	減	源	玄	現	272	慘	撒	散	棧	燦	珊	產	算	纂	蚕	302	彰	承	抄	招	掌	捷	昇	昌	昭	晶
243	絃	舷	原	諺	限	乎	個	古	呼	固	273	讚	贊	酸	餐	斬	暫	殘	仕	仔	伺	303	松	梢	樟	樵	沼	消	昇	湘	燒	焦
244	姑	孤	己	庫	弧	戶	故	枯	湖	狐	274	使	刺	司	史	嗣	四	士	始	姉	姿	304	照	症	省	硝	礁	祥	称	章	笑	粧
245	糊	袴	股	胡	菰	虎	誇	跨	鈷	雇	275	子	屍	市	師	志	思	指	支	孜	斯	305	紹	肖	菖	蔣	蕉	衝	裳	訟	証	詔
246	顧	鼓	五	互	伍	午	吳	吾	娛	後	276	施	旨	枝	止	死	氏	獅	祉	私	糸	306	詳	象	賞	醬	鈺	鍾	鐘	障	鞘	上
247	御	悟	梧	檣	瑚	暮	語	誤	護	公	277	紙	紫	肢	脂	至	視	詞	詩	試	誌	307	文	丞	乘	冗	剩	城	場	壤	孃	常
248	乞	鯉	交	佼	侯	候	倖	光	公	功	278	諮	資	賜	雌	飼	視	齒	事	似	侍	308	情	擾	条	杖	淨	狀	置	穰	蒸	讓
249	効	勾	厚	口	向						279	字	寺	慈	持	時						309	釀	錠	嘱	墟	飾	燭				
250		后	喉	坑	垢	好	孔	孝	宏	工	280		次	滋	治	爾	璽	痔	磁	示	而	310		拭	植	殖	燭	織	職	色	觸	食
251	巧	巷	幸	広	庚	康	弘	恒	慌	抗	281	耳	自	蒔	辞	夕	鹿	式	識	鳴	竺	311	蝕	辱	尻	伸	信	侵	唇	娠	寢	審
252	拘	控	攻	昂	晃	更	杭	校	梗	構	282	軸	穴	霏	七	叱	執	失	嫉	室	悉	312	心	慎	振	新	晋	森	榛	浸	深	申
253	江	洪	浩	港	溝	甲	皇	硬	稿	糠	283	湿	漆	疾	質	実	蔀	篠	悃	柴	芝	313	疹	真	神	秦	紳	臣	芯	薪	親	診
254	紅	紘	絞	綱	耕	考	肯	肱	腔	膏	284	屢	蕊	縞	舍	写	射	捨	赦	斜	煮	314	身	辛	進	針	震	人	仁	刃	塵	壬
255	航	荒	行	衡	講	貢	購	郊	醉	鉞	285	社	紗	者	謝	車	遮	蛇	邪	借	勺	315	尋	甚	尽	腎	訊	迅	陣	鞞	筍	誡
256	砧	鋼	閤	降	項	香	高	鴻	剛	劫	286	尺	杓	灼	爵	守	积	錫	若	寂	弱	316	須	酢	凶	厨	逗	吹	垂	帥	推	水
257	号	合	壕	拷	濠	豪	轟	趨	克	刻	287	惹	主	取	守	手	朱	殊	狩	珠	種	317	炊	睡	粹	翠	衰	遂	醉	錘	錘	隨
258	告	国	穀	酷	鵠	黑	獄	漉	腰	甌	288	腫	趣	酒	首	儒	受	呪	寿	授	樹	318	瑞	髓	崇	嵩	数	枢	趨	錘	錘	杉
259	忽	惚	骨	拍	込						289	綬	需	囚	収	周						319	相	菅	頗	雀	裾					
260		此	頃	今	困	坤	墾	婚	恨	懇	290		宗	就	州	修	愁	拾	洲	秀	秋	320		澄	摺	寸	世	瀨	畝	是	淒	制
261	昏	昆	根	梱	混	痕	紺	良	魂	些	291	終	繡	習	臭	舟	蒐	衆	襲	讐	蹴	321	勢	姓	征	性	成	政	整	星	晴	棲
262	佐	又	唆	嵯	左	差	查	沙	磋	砂	292	輯	週	酋	酬	集	醜	什	住	充	十	322	栖	正	清	性	生	盛	精	聖	声	製
263	詐	鎖	娑	坐	座	挫	債	催	再	最	293	從	戎	柔	汁	洪	獸	縱	重	銃	叔	323	西	誠	誓	請	逝	醒	青	静	齊	稅

# Appendix

Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4								
	0	1	2	3	4	5	6	7	8		9	0	1	2	3	4	5	6	7		8	9	0	1	2	3	4	5	6		7	8	9	0	1	2	3	4	5
324	脆	隻	席	惜	戚	斥	昔	析	石	積	354	暖	檀	段	男	談	值	知	地	弛	恥	384	独	讀	析	橡	凸	突	椴	届	鳶	苦							
325	籍	績	脊	責	赤	跡	蹟	碩	切	拙	355	智	池	痴	稚	置	致	蜘	遲	馳	築	385	寅	酉	瀟	噸	屯	惇	敦	沌	豚	遁							
326	接	撰	折	設	窃	節	說	雪	絕	舌	356	畜	竹	筑	蓄	逐	秩	窒	茶	嫡	着	386	頓	吞	曇	鈍	奈	那	内	乍	瓜	薤							
327	蟬	仙	先	千	占	宣	專	尖	川	戰	357	中	仲	宙	忠	抽	昼	柱	注	虫	衷	387	謎	灘	捺	鍋	槽	馴	繩	罨	南	楠							
328	扇	撰	先	千	占	宣	專	尖	川	戰	358	註	耐	鏄	駐	樗	豬	芋	著	貯	388	軟	難	汝	二	尼	式	迹	句	賑	肉								
329	煽	旋	穿	箭	線						359	丁	兆	凋	喋	寵					389	虹	廿	日	乳	入													
330		織	羨	腺	舛	船	薦	詮	賤	踐	360		帖	帳	斤	弔	張	彫	徵	懲	挑	390		如	尿	菲	任	妊	忍	認	濡	襦							
331	選	遷	錢	銑	閃	鮮	前	善	漸	然	361	暢	朝	潮	牒	町	眺	聽	脹	腸	蝶	391	衤	寧	葱	猫	熱	年	念	捻	撚	能							
332	全	禪	繕	膳	糗	噌	塑	岨	措	曾	362	調	謀	超	跳	鈔	長	頂	鳥	勅	抄	392	粘	乃	迺	之	楚	囊	惱	濃	納	能							
333	曾	楚	狙	疏	疎	礎	祖	租	粗	素	363	直	朕	沈	珍	賃	鎮	陳	津	墜	椎	393	腦	膿	農	視	蚤	巴	把	播	霸	杷							
334	組	蘇	訴	阻	遯	鼠	僧	創	双	叢	364	槌	追	鎚	痛	通	塚	姆	摑	槻	佃	394	波	派	琶	破	婆	罵	芭	馬	俳	廢							
335	倉	喪	壯	奏	爽	宋	層	匠	惣	想	365	漬	柘	辻	蔦	綴	鏢	椿	潰	坪	壺	395	拜	排	敗	杯	盃	牌	背	肺	輩	配							
336	搜	掃	插	搔	操	早	曹	巢	槍	槽	366	孀	紬	爪	吊	釣	鶴	亭	低	停	偵	396	倍	培	媒	梅	煤	煤	狼	買	壳	賠							
337	漕	燥	争	瘦	相	窓	糴	總	綜	聰	367	荆	貞	呈	堤	定	帝	底	庭	廷	弟	397	陪	這	蠅	秤	矧	荻	伯	剥	博	拍							
338	草	莊	葬	蒼	藻	裝	走	送	遭	鎗	368	悌	抵	挺	提	梯	汀	碇	禎	程	締	398	柏	泊	白	箔	粕	舩	薄	迫	曝	漠							
339	霜	騷	像	增	憎						369	艇	訂	諦	蹄	逦						399	爆	縛	莫	駁	麥												
340		臟	藏	贈	造	促	側	則	即	息	370		邸	鄭	釘	鼎	泥	摘	擢	敵	滴	400		函	箱	砧	箸	肇	筭	櫨	幡	肌							
341	捉	束	測	足	俗	屬	賊	族	統	遜	371	的	笛	適	鎬	溺	哲	徹	撤	輒	迭	401	焜	畠	八	鉢	澆	豨	髮	伐	判								
342	卒	袖	其	揃	存	孫	尊	損	村	遜	372	鉄	典	填	天	展	店	添	纏	甜	貼	402	拔	筏	閩	鳩	嘶	塙	蛤	隼	伴	判							
343	他	多	太	汰	訖	唾	墮	妥	情	打	373	轉	顛	点	伝	殿	澱	田	電	兔	吐	403	半	反	叛	帆	搬	斑	板	汎	版	煩							
344	柁	舵	太	陀	馱	驂	體	堆	对	耐	374	堵	塗	妬	屠	徒	斗	杜	渡	登	菟	404	犯	班	畔	繁	般	藩	販	範	采	煩							
345	岱	帶	待	怠	態	戴	替	泰	滯	胎	375	賭	途	都	鍍	砥	斫	努	度	土	奴	405	頒	飯	挽	晚	番	盤	盤	蕃	蚤	匪							
346	腿	苔	袋	貸	退	逮	隊	黛	鯛	代	376	怒	倒	党	冬	凍	刀	唐	塔	塘	套	406	卑	否	妃	庇	彼	悲	扉	批	披	斐							
347	台	大	第	醜	題	鷹	淹	瀧	卓	啄	377	宕	島	嶋	悼	投	搭	東	桃	禱	棟	407	比	泌	疲	皮	碑	秘	緹	罷	肥	被							
348	宅	托	扞	拓	沢	濯	琢	託	鐸	濁	378	盜	淘	湯	涛	灯	燈	當	痘	禱	等	408	誹	費	避	非	飛	秘	緹	罷	肥	被							
349	諾	茸	夙	蛸	只						379	答	筒	糖	統	到						409	枇	毘	琵琶	眉	美												
350		叩	但	達	辰	奪	脱	翼	豎	辿	380		董	蕩	藤	討	騰	豆	踏	逃	透	410		鼻	柁	稗	匹	疋	髻	彦	膝	菱							
351	棚	谷	狸	鱈	樽	誰	丹	单	嘆	坦	381	鐙	陶	頭	騰	鬪	働	動	同	堂	導	411	肘	弼	必	畢	標	逼	桧	姬	媛	紐							
352	担	探	旦	歎	淡	湛	炭	短	端	筆	382	懂	撞	洞	瞳	童	胴	苟	道	銅	峠	412	百	謬	依	彪	標	水	漂	瓢	票	表							
353	綻	耽	胆	蛋	誕	鍛	団	壇	彈	斷	383	鴉	匿	得	德	澆	特	督	禿	篤	毒	413	評	豹	廟	描	病	秒	苗	錨	鈇	蒜							

Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4													
	0	1	2	3	4	5	6	7	8		9	0	1	2	3	4	5	6	7		8	9	0	1	2	3	4	5	6	7	8	9		
414	蛭	鱒	品	彬	斌	浜	瀕	貧	寶	頻	444	免	棉	綿	緬	面	麵	摸	模	茂	妄	474	杵	驚	互	亘	鰐	詫	藁	蕨	椀	湾		
415	敏	瓶	不	付	埠	夫	婦	富	富	布	445	孟	毛	猛	盲	網	耗	蒙	儲	木	默	475	碗	腕										
416	府	怖	扶	敷	斧	普	浮	父	符	腐	446	目	李	勿	餅	尤	戾	糶	賞	問	悶	476												
417	膚	芙	譜	負	賦	赴	阜	附	侮	撫	447	紋	門	勿	也	冶	夜	爺	耶	野	弥	477												
418	武	舞	葡	蕪	部	封	楓	風	葺	葺	448	矢	厄	役	約	葉	訊	躍	靖	柳	藪	478												
419	伏		副	復	幅	服					449	鍵	愉	愈	油	癒						479												
420		福	腹	複	覆	淵	弗	弘	沸	仏	450		諭	輸	唯	佑	優	勇	友	宥	幽	480												
421	物	鮒	分	吻	噴	墳	憤	扮	焚	奮	451	悠	憂	揖	有	柚	湧	涌	猶	猷	由	481	乖	乘	亂	丕	个	卅	、	井	丿	乂		
422	粉	糞	紛	雰	文	聞	丙	併	兵	塀	452	祐	裕	誘	遊	邑	郵	雄	融	夕	予	482	乖	一	亢	京	豫	事	舒	式	于	亞		
423	幣	平	弊	柄	並	蔽	閉	陛	米	頁	453	余	与	譽	輿	預	傭	幼	妖	容	庸	483	佻	仗	仞	仞	仞	仞	仞	仞	仞	仞		
424	僻	壁	癖	碧	別	警	蔑	篋	偏	變	454	揚	搖	擁	曜	楊	樣	洋	溶	熔	用	484	佻	佻	佻	佻	佻	佻	佻	佻	佻	佻	佻	
425	片	篇	編	辺	返	遍	便	勉	婉	弁	455	窯	羊	耀	葉	蓉	要	謠	踊	遙	陽	485	侑	侑	侑	侑	侑	侑	侑	侑	侑	侑	侑	
426	鞭	保	舖	鋪	圃	捕	步	甫	補	輔	456	養	慾	抑	欲	沃	浴	翌	翼	淀	羅	486	俑	俚	俐	俐	俐	俐	俐	俐	俐	俐	俐	
427	穗	募	墓	慕	戊	暮	母	簿	菩	做	457	螺	裸	來	萊	賴	雷	洛	絡	落	酪	487	倅	倅	倅	倅	倅	倅	倅	倅	倅	倅	倅	
428	捧	包	呆	報	奉	寶	峰	峯	崩	庖	458	乱	卵	嵐	欄	濫	藍	蘭	覽	利	吏	488	偃	假	會	借	修	偈	做	偈	偈	偈	偈	
429	抱		放	方	朋						459	履	李	梨	理	璃						489	傀	倣	倣	倣	倣	倣	倣	倣	倣	倣	倣	
430		法	泡	烹	砲	縫	胞	芳	萌	蓬	460		痢	裏	裡	離	陸	律	率	立	490		僉	僉	僉	僉	僉	僉	僉	僉	僉	僉	僉	
431	蜂	褒	訪	豐	邦	鋒	飽	鳳	鵬	乏	461	葎	掠	略	劉	溜	琉	留	疏	粒	491	僮	價	儂	儂	儂	儂	儂	儂	儂	儂	儂	儂	
432	亡	傍	剖	坊	妨	帽	忘	忙	房	暴	462	隆	竜	龍	侶	慮	旅	虜	了	亮	僚	492	僞	僞	僞	僞	僞	僞	僞	僞	僞	僞	僞	僞
433	望	某	棒	冒	紡	肪	膨	謀	貌	貿	463	兩	凌	寮	料	涼	獵	療	瞭	稜	493	僞	兢	兢	兢	兢	兢	兢	兢	兢	兢	兢	兢	兢
434	鉞	防	吠	類	北	僕	卜	墨	撲	朴	464	糧	良	諒	遼	量	陵	領	力	綠	倫	494	罔	胄	菁	晁	冂	冂	冂	冂	冂	冂	冂	
435	牧	睦	穆	卸	勃	沒	殆	堀	幌	奔	465	厘	林	淋	熈	琳	臨	輪	隣	鱗	麟	495	丿	决	沅	冲	冰	况	冽	涸	凉	凜	凜	凜
436	本	翻	凡	盆	摩	磨	魔	麻	埋	妹	466	瑠	壘	淚	累	類	令	伶	例	冷	勵	496	几	几	几	几	几	几	几	几	几	几	几	几
437	味	枚	每	哩	禎	幕	膜	枕	鮪	枉	467	嶺	伶	玲	礼	苓	鈴	隸	零	靈	麗	497	勿	勿	勿	勿	勿	勿	勿	勿	勿	勿	勿	勿
438	鱒	枿	亦	侯	又	抹	末	沫	迄	仄	468	齡	曆	歷	列	劣	裂	廉	恋	憐	憐	498	劊	劊	劊	劊	劊	劊	劊	劊	劊	劊	劊	劊
439	繭	廐	万	慢	滿						469	漣	煉	簾	練	聯						499	劊	劊	劊	劊	劊	劊	劊	劊	劊	劊	劊	劊
440		漫	蔓	味	未	魅	巳	箕	岬	密	470		蓮	連	鍊	呂	魯	櫓	炉	賂	路	500		辦	劬	劬	劬	劬	劬	劬	劬	劬	劬	劬
441	蜜	湊	蓑	稔	脈	妙	耗	民	眠	務	471	露	勞	婁	廊	弄	朗	樓	榔	浪	漏	501	勸	勸	勸	勸	勸	勸	勸	勸	勸	勸	勸	勸
442	夢	無	牟	矛	霧	鷓	棕	婿	娘	冥	472	牢	狼	箠	老	聾	蠟	郎	六	麓	祿	502	匍	匍	匍	匍	匍	匍	匍	匍	匍	匍	匍	匍
443	名	命	明	盟	迷	銘	鳴	姪	牝	滅	473	肋	錄	論	倭	和	話	歪	賄	脇	惑	503	匍	匍	匍	匍	匍	匍	匍	匍	匍	匍	匍	匍



# Appendix

Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4												
	0	1	2	3	4	5	6	7	8		9	0	1	2	3	4	5	6	7		8	9	0	1	2	3	4	5	6	7	8	9	
504	后	卯	卻	卷	厂	厖	厠	厦	厥	厮	534	嬌	嬋	嬖	嬗	嫩	嬾	嬭	嬯	嬰	嬱	564	愴	博	湧	慄	慳	慷	慘	慙	慚	慜	慝
505	廠	厶	參	纂	雙	叟	曼	變	叮	叨	535	孀	子	孕	孚	孛	孛	孩	孰	孳	瞬	565	惴	傷	慄	慄	慄	慄	慄	慄	慄	慄	慄
506	叭	叭	吁	吡	呀	听	吭	吼	吮	呐	536	學	孛	孛	孛	孛	孛	孛	孛	孛	孛	566	愬	愬	愬	愬	愬	愬	愬	愬	愬	愬	愬
507	吩	吝	呖	咏	呵	咎	咭	呱	呷	咭	537	寔	寐	寤	寤	寤	寤	寤	寤	寤	寤	567	應	懷	懈	懃	懃	懃	懃	懃	懃	懃	懃
508	咒	呻	咀	呶	咄	附	咆	哇	呶	呶	538	寶	剋	將	專	對	爾	尠	尠	尠	尠	568	慙	懶	懈	懃	懃	懃	懃	懃	懃	懃	懃
509	啞	咬	哄	哈	咨						539	尹	屁	屆	屎	屎	屎	屎	屎	屎	屎	569	戍	戍	戍	戍	戍	戍	戍	戍	戍	戍	戍
510		咫	晒	咤	咤	高	听	哥	哦	唏	540		屐	屐	屐	屐	屐	屐	屐	屐	屐	570		戛	戛	戛	戛	戛	戛	戛	戛	戛	戛
511	唔	哽	哮	哭	哺	哢	啞	啞	啞	啞	541	岑	岔	岌	岌	岌	岌	岌	岌	岌	岌	571	扞	扣	扛	扛	扛	扛	扛	扛	扛	扛	扛
512	售	啜	啜	啜	啜	啜	啜	啜	啜	啜	542	岑	峙	岌	岌	岌	岌	岌	岌	岌	岌	572	扞	抖	抖	抖	抖	抖	抖	抖	抖	抖	抖
513	咯	喊	啜	啜	啜	啜	啜	啜	啜	啜	543	岑	峙	岌	岌	岌	岌	岌	岌	岌	岌	573	拆	擔	拈	拈	拈	拈	拈	拈	拈	拈	拈
514	喻	喇	曉	嗚	嗚	嗚	嗚	嗚	嗚	嗚	544	嵌	岳	嶼	嶼	嶼	嶼	嶼	嶼	嶼	嶼	574	格	拈	拈	拈	拈	拈	拈	拈	拈	拈	拈
515	嘔	嗽	噴	喉	嗽	嗽	嗽	嗽	嗽	嗽	545	嶢	嶢	嶢	嶢	嶢	嶢	嶢	嶢	嶢	嶢	575	捍	搜	捏	掖	掖	掖	掖	掖	掖	掖	掖
516	嘴	嘶	嘲	嚙	噫	噫	噫	噫	噫	噫	546	巔	巔	巔	巔	巔	巔	巔	巔	巔	巔	576	掉	掙	掙	掙	掙	掙	掙	掙	掙	掙	掙
517	啞	鼻	嚙	嚙	嚙	嚙	嚙	嚙	嚙	嚙	547	帑	帑	帑	帑	帑	帑	帑	帑	帑	帑	577	揉	插	擲	揄	搖	搵	搵	搵	搵	搵	搵
518	嚼	囁	囁	囁	囁	囁	囁	囁	囁	囁	548	幟	幢	幣	幫	幟	幟	幟	幟	幟	幟	578	撮	搗	搗	搗	搗	搗	搗	搗	搗	搗	搗
519	囿	囿	囿	囿	囿	囿	囿	囿	囿	囿	549	廁	廂	廂	廂	廂	廂	廂	廂	廂	廂	579	撓	撥	撩	撈	撓	撓	撓	撓	撓	撓	撓
520		圈	國	圍	圓	團	圖	嗇	圓	圪	550		廖	廣	廡	廡	廡	廡	廡	廡	廡	580		據	擒	擅	擇	撻	擲	擲	擲	擲	擲
521	坏	址	坎	圪	圪	坏	圪	圪	圪	圪	551	廬	廬	廬	廬	廬	廬	廬	廬	廬	廬	581	舉	擠	擡	擡	擡	擡	擡	擡	擡	擡	擡
522	坳	坳	坳	坳	坳	坳	坳	坳	坳	坳	552	彝	弋	弋	弋	弋	弋	弋	弋	弋	弋	582	舉	攀	攀	攀	攀	攀	攀	攀	攀	攀	攀
523	埔	埕	埕	埕	埕	埕	埕	埕	埕	埕	553	彎	弯	弯	弯	弯	弯	弯	弯	弯	弯	583	攸	攸	攸	攸	攸	攸	攸	攸	攸	攸	攸
524	堡	塢	塢	塢	塢	塢	塢	塢	塢	塢	554	徕	徕	徕	徕	徕	徕	徕	徕	徕	徕	584	做	做	做	做	做	做	做	做	做	做	做
525	墟	墟	墟	墟	墟	墟	墟	墟	墟	墟	555	徕	徕	徕	徕	徕	徕	徕	徕	徕	徕	585	斷	旃	旃	旃	旃	旃	旃	旃	旃	旃	旃
526	墟	墟	墟	墟	墟	墟	墟	墟	墟	墟	556	惠	惠	惠	惠	惠	惠	惠	惠	惠	惠	586	断	旃	旃	旃	旃	旃	旃	旃	旃	旃	旃
527	壻	壻	壻	壻	壻	壻	壻	壻	壻	壻	557	怕	怕	怕	怕	怕	怕	怕	怕	怕	怕	587	易	晏	晁	晁	晁	晁	晁	晁	晁	晁	晁
528	夭	夭	夭	夭	夭	夭	夭	夭	夭	夭	558	協	恆	恆	恆	恆	恆	恆	恆	恆	恆	588	晁	晁	晁	晁	晁	晁	晁	晁	晁	晁	晁
529	奢	奢	奢	奢	奢	奢	奢	奢	奢	奢	559	悃	悃	悃	悃	悃	悃	悃	悃	悃	悃	589	暨	暹	暹	暹	暹	暹	暹	暹	暹	暹	暹
530		奸	妁	妝	佞	佞	妲	妲	媪	媪	560		悄	悛	悛	悛	悛	悛	悛	悛	悛	590		曄	瞭	瞭	瞭	瞭	瞭	瞭	瞭	瞭	瞭
531	姜	妍	姘	姚	娥	娟	娉	娜	娉	媪	561	惠	惓	惓	惓	惓	惓	惓	惓	惓	惓	591	曳	曷	肱	肱	肱	肱	肱	肱	肱	肱	肱
532	婀	姘	婉	姘	姘	姘	姘	姘	姘	姘	562	愆	愆	愆	愆	愆	愆	愆	愆	愆	愆	592	朶	朶	朶	朶	朶	朶	朶	朶	朶	朶	朶
533	嫻	嫻	嫻	嫻	嫻	嫻	嫻	嫻	嫻	嫻	563	愆	愆	愆	愆	愆	愆	愆	愆	愆	愆	593	枉	杰	杰	杰	杰	杰	杰	杰	杰	杰	杰

Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4										
	0	1	2	3	4	5	6	7	8		9	0	1	2	3	4	5	6	7		8	9	0	1	2	3	4	5	6	7	8
594	枷	柯	枒	東	枳	柅	枸	祖	柞	柝	624	浙	淺	淙	淤	塗	淪	淮	渭	湮	湫	654	疊	疊	疊	疔	疚	疝	疥	疣	疖
595	柢	柎	枹	東	枳	柅	枸	祖	柞	柝	625	渙	淺	淙	淤	塗	淪	淮	渭	湮	湫	655	痃	疝	疽	疽	疚	痂	疥	瘡	疖
596	桀	柎	枹	東	枳	柅	枸	祖	柞	柝	626	湃	淺	淙	淤	塗	淪	淮	渭	湮	湫	656	痃	疝	疽	疽	疚	痂	疥	瘡	疖
597	梟	柎	枹	東	枳	柅	枸	祖	柞	柝	627	滉	淺	淙	淤	塗	淪	淮	渭	湮	湫	657	瘋	瘍	癩	癩	瘡	瘡	癩	癩	癩
598	梵	柎	枹	東	枳	柅	枸	祖	柞	柝	628	溥	淺	淙	淤	塗	淪	淮	渭	湮	湫	658	癩	癩	癩	癩	癩	癩	癩	癩	癩
599	梟	柎	枹	東	枳	柅	枸	祖	柞	柝	629	滲	淺	淙	淤	塗	淪	淮	渭	湮	湫	659	癩	癩	癩	癩	癩	癩	癩	癩	癩
600		柎	枹	東	枳	柅	枸	祖	柞	柝	630		淺	淙	淤	塗	淪	淮	渭	湮	湫	660		癩	癩	癩	癩	癩	癩	癩	癩
601	棹	棠	楡	楸	楸	楸	楸	楸	楸	楸	631	潛	潛	潭	激	澆	潘	潛	潛	潛	潛	661	皖	皓	皙	皙	皙	皙	皙	皙	皙
602	楷	棠	楡	楸	楸	楸	楸	楸	楸	楸	632	澳	潛	潭	激	澆	潘	潛	潛	潛	潛	662	盍	盍	盍	盍	盍	盍	盍	盍	盍
603	楸	棠	楡	楸	楸	楸	楸	楸	楸	楸	633	灑	潛	潭	激	澆	潘	潛	潛	潛	潛	663	眈	眈	眈	眈	眈	眈	眈	眈	眈
604	攄	棠	楡	楸	楸	楸	楸	楸	楸	楸	634	瀏	潛	潭	激	澆	潘	潛	潛	潛	潛	664	眸	眸	眸	眸	眸	眸	眸	眸	眸
605	榷	棠	楡	楸	楸	楸	楸	楸	楸	楸	635	激	潛	潭	激	澆	潘	潛	潛	潛	潛	665	瞎	瞎	瞎	瞎	瞎	瞎	瞎	瞎	瞎
606	樛	棠	楡	楸	楸	楸	楸	楸	楸	楸	636	炮	煙	焦	炆	炆	炆	炆	炆	炆	炆	666	瞽	瞽	瞽	瞽	瞽	瞽	瞽	瞽	瞽
607	櫟	棠	楡	楸	楸	楸	楸	楸	楸	楸	637	熙	熙	熙	熙	熙	熙	熙	熙	熙	熙	667	砌	砌	砌	砌	砌	砌	砌	砌	砌
608	楫	棠	楡	楸	楸	楸	楸	楸	楸	楸	638	煩	熨	熬	熨	熨	熨	熨	熨	熨	熨	668	砗	砗	砗	砗	砗	砗	砗	砗	砗
609	楫	棠	楡	楸	楸	楸	楸	楸	楸	楸	639	燠	燠	燠	燠	燠	燠	燠	燠	燠	燠	669	碾	碾	碾	碾	碾	碾	碾	碾	碾
610		棠	楡	楸	楸	楸	楸	楸	楸	楸	640		燠	燠	燠	燠	燠	燠	燠	燠	燠	670		磧	磧	磧	磧	磧	磧	磧	磧
611	櫟	棠	楡	楸	楸	楸	楸	楸	楸	楸	641	爲	犁	犁	犁	犁	犁	犁	犁	犁	犁	671	礫	礫	礫	礫	礫	礫	礫	礫	礫
612	欖	鬱	欖	欖	欖	欖	欖	欖	欖	欖	642	犁	犁	犁	犁	犁	犁	犁	犁	犁	犁	672	禊	禊	禊	禊	禊	禊	禊	禊	禊
613	歉	歐	歐	歐	歐	歐	歐	歐	歐	歐	643	狃	狃	狃	狃	狃	狃	狃	狃	狃	狃	673	靴	靴	靴	靴	靴	靴	靴	靴	靴
614	妖	殄	殄	殄	殄	殄	殄	殄	殄	殄	644	狃	狃	狃	狃	狃	狃	狃	狃	狃	狃	674	稟	稟	稟	稟	稟	稟	稟	稟	稟
615	殄	殄	殄	殄	殄	殄	殄	殄	殄	殄	645	獎	獾	默	獾	獾	獾	獾	獾	獾	獾	675	穢	穢	穢	穢	穢	穢	穢	穢	穢
616	毬	毫	毳	毳	毳	毳	毳	毳	毳	毳	646	獺	珈	玳	玳	玳	玳	玳	玳	玳	玳	676	穢	窩	窩	窩	窩	窩	窩	窩	窩
617	氣	汞	汕	汕	汕	汕	汕	汕	汕	汕	647	琅	瑯	瑯	瑯	瑯	瑯	瑯	瑯	瑯	瑯	677	竊	竊	竊	竊	竊	竊	竊	竊	竊
618	汾	汨	汨	汨	汨	汨	汨	汨	汨	汨	648	瑁	瑜	瑩	瑩	瑩	瑩	瑩	瑩	瑩	瑩	678	竊	竊	竊	竊	竊	竊	竊	竊	竊
619	泗	汨	汨	汨	汨	汨	汨	汨	汨	汨	649	璧	瓊	瓊	瓊	瓊	瓊	瓊	瓊	瓊	瓊	679	筌	筌	筌	筌	筌	筌	筌	筌	筌
620		汨	汨	汨	汨	汨	汨	汨	汨	汨	650		瓊	瓊	瓊	瓊	瓊	瓊	瓊	瓊	瓊	680		筌	筌	筌	筌	筌	筌	筌	筌
621	洽	泐	泐	泐	泐	泐	泐	泐	泐	泐	651	盜	甄	甄	甄	甄	甄	甄	甄	甄	甄	681	筌	筌	筌	筌	筌	筌	筌	筌	筌
622	浚	泐	泐	泐	泐	泐	泐	泐	泐	泐	652	甦	甦	甦	甦	甦	甦	甦	甦	甦	甦	682	筌	筌	筌	筌	筌	筌	筌	筌	筌
623	涵	淇	淇	淇	淇	淇	淇	淇	淇	淇	653	眈	眈	眈	眈	眈	眈	眈	眈	眈	眈	683	箴	箴	箴	箴	箴	箴	箴	箴	箴





Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4									Kuten digit 1 to 3	Kuten digit 4												
	0	1	2	3	4	5	6	7	8		9	0	1	2	3	4	5	6	7		8	9	0	1	2	3	4	5	6	7	8	9	
774	軾	輗	輅	輈	載	輊	輋	輌	輍	輎	804	霹	霽	霏	霏	霏	靈	靈	靈	靜	靠	834	麩	慶	麒	麩	麩	麩	麥	麩	麩	麩	麩
775	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	805	砲	靦	靦	靦	靦	靦	靦	靦	靦	靦	835	麩	糜	覺	黎	黏	麩	黔	黝	黝	黝	黝
776	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	806	靦	靦	靦	靦	靦	靦	靦	靦	靦	靦	836	黝	黝	黝	黝	黝	黝	黝	黝	黝	黝	黝
777	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	807	靦	靦	靦	靦	靦	靦	靦	靦	靦	靦	837	黝	黝	黝	黝	黝	黝	黝	黝	黝	黝	黝
778	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	808	靦	靦	靦	靦	靦	靦	靦	靦	靦	靦	838	黝	黝	黝	黝	黝	黝	黝	黝	黝	黝	黝
779	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	809	靦	靦	靦	靦	靦	靦	靦	靦	靦	靦	839	黝	黝	黝	黝	黝	黝	黝	黝	黝	黝	黝
780	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	810	靦	靦	靦	靦	靦	靦	靦	靦	靦	靦	840	黝	黝	黝	黝	黝	黝	黝	黝	黝	黝	黝
781	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	811	靦	靦	靦	靦	靦	靦	靦	靦	靦	靦												
782	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	812	靦	靦	靦	靦	靦	靦	靦	靦	靦	靦												
783	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	813	靦	靦	靦	靦	靦	靦	靦	靦	靦	靦												
784	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	814	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
785	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	815	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
786	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	816	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
787	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	817	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
788	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	818	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
789	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	819	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
790	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	820	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
791	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	821	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
792	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	822	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
793	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	823	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
794	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	824	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
795	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	825	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
796	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	826	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
797	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	827	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
798	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	828	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
799	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	829	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
800	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	830	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
801	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	831	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
802	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	832	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												
803	輗	輗	輗	輗	輗	輗	輗	輗	輗	輗	833	馮	馮	馮	馮	馮	馮	馮	馮	馮	馮												

Appendix

## List of city in World time

Country name	City name	Country name	City name	Country name	City name
Afghanistan	Kabul	Iran	Tehran	Taiwan	Taipei
Argentina	Buenos Aires	Ireland	Dublin	Thailand	Bangkok
Australia	Canberra	Italy	Rome	UAE	Abu Dhabi
	Sydney	Japan	Tokyo	UK	London
Austria	Vienna	Kuwait	Kuwait	USA	Anchorage
Bangladesh	Dhaka	Lebanon	Beirut		Boston
Belgium	Azores	Mexico	Mexico City		Chicago
	Brussels	Netherlands	Amsterdam		Dallas
Brazil	Rio de Janeiro	New Zealand	Auckland		Denver
Canada	Montreal	People's Republic of China	Beijing		Detroit
Czech	Prague		Hong Kong		Guam
Denmark	Copenhagen	Philippines	Manila		Honolulu
Egypt	Cairo	Portugal	Lisbon		Los Angeles
Finland	Helsinki	Russia	Moscow		New York
France	Paris	Republic of Korea	Seoul	Seattle	
Germany	Berlin	Saudi Arabia	Jedda	Washington D.C.	
Greece	Athens	Singapore	Singapore	Venezuela	Caracas
Hungary	Budapest	Spain	Madrid	Viet Nam	Hanoi
India	New Delhi	Sri Lanka	Colombo		
Indonesia	Jakarta	Sweden	Stockholm		



## Multiaccess Combination Patterns

You can simultaneously use a voice call and packet transmission (i-mode, i-mode mail, etc.) as well as SMS with the multiaccessing function on the FOMA phone. The available combinations of operations for the multiaccessing function are shown below:

Transmission Added Current Transmission	Voice call		Video-phone		i-appli	i-mode	i-mode mail		SMS		Packet transmission
	Outgoing	Incoming	Outgoing	Incoming			Sending	Receiving	Send	Receive	Sending
During a call	○※1	○※1※2	×	×	○	○	○	○	○	○	○
During a Video-phone call	×	×	×	×	×	×	×	×	×	×	×
While using i-appli	○	○	○	○	—	×	×	×	—	×	○
During i-mode	○	○	×	×	○	—	○	○	—	○	×
During a packet transmission with PC connection	○	○	×	×	○	×	×	×	○	○	—

○ : Available    × : Not available    — : The combination is functionally not possible.

※1: If you have signed up for Call Waiting Service, you can make another voice call with the current voice call put on hold.

※2: If you have signed up for “Voice Mail” or “Call Forwarding Service”, and you have not yet activated either service, you can answer another incoming call after ending the current transmission.

※3: You can check the missed call after ending a call.

※4: You cannot use this menu during communicating i-appli.

※5: The message will be stored in i-mode center with a mark on upper of screen.

(The mark is not displayed on the top of the screen during a packet transmission connecting with a personal computer.)

※6: You cannot receive message while downloading.

※7: You can receive SMS after ending current transmission.

※8: You cannot activate i-appli which needs data communication while transmitting by packet.

※9: If i-appli runs without connecting the network, the packet transmission cannot be activated.

※10: You can activate i-appli only if you call from site of i-mode.


※11: You can send i-mode mail or i-appli if you compose the mail from the submenus of i-mode browser. You can insert the displayed site or URL into the body of mail.

## Multitask Combination Patterns













You can run multiple functions simultaneously and use them switching displays with the Multitask function.





### Using Multitask

#### 1. While running each function,




You can confirm the functions running.  
You can switch functions by selecting the icon.

Icon	Description	Icon	Description
	Voice call function running		Calculator function running
	Mail function running		
	i-mode function running		Own number is displayed
	i-appli function running		Setting the network/ Displaying the history of recent calls
	Phonebook function <sup>*1</sup> running		
 (  )	Data box function running (The player is playing back)		Tool function running <sup>*4</sup>
			Setting the sound function

Icon	Description	Icon	Description
	Multimedia function running		Setting the display menu
			Setting the setting menu
	Scheduler function running		

※1: "Own number" function is not included.

※2: If you switch i-mode/ i-appli, the play is ended, and then  is displayed.

※3: "Schedule" function is not included.

※4: "Custom menu", "Infrared".

#### 2. Select ► ► Select from the following new functions ►

##### **Call**

The Phone Number entry screen appears. → P48

##### **Mail**

The Mail menu appears. → P137

##### **i-mode**

The i-mode menu appears. → P119

##### **i-appli**

The Software List screen appears. → P159

##### **Search phonebook**

The Phonebook Search screen appears. → P66

##### **Melody**

The Melody Folder List screen appears. → P176

** Camera-mode**

The Still Image Finder screen appears. → P110

---

** Scheduler**

The Monthly Schedule screen appears. → P191

---

** Calculator**

The Calculator screen appears. → P184

---


** Own number**

Own number is displayed. → P72



---


- A few functions are not selected depending on activating the task.  
→ P282

**Information**

- To bring up the Task Menu display from Stand-by screen, press and hold  for 1 or more seconds.
- When you activate multitask function, the submenus can be used.
- It may be a few cases that you cannot use “Search phonebook” depending on the memory status of FOMA handset.

**Ending the task/ Going back to previous task**

1.  / 

- You can terminate the running function.
- When an application is running or i-mode is being connected, terminate it by pressing .

## Combination of Functions

You may not be able to select some items on the Task Menu display depending on the added function. The combinations of active functions and added functions performable from the Task Menu are as follows:

Task menu item / Active function	Voice call	Mail	i-mode	i-appi	Phonebook search
During a Voice call	×	○	○	○	○※1
A function in the Mail menu running	○	×	×	×	○※1
A function in the i-mode menu running	○	×	×	×	○※1
A function in the i-appli menu running	○	×	×	×	○
A function in a menu other than the Mail/i-mode/i-appli menu running	○	○	○	○	○※2
Own number displayed	○	○	○	○	○


○ : Available

× : Not available

※1: You cannot use this menu when activating the menu from phonebook. You cannot use new phonebook function.

※2: You cannot use this menu when using phonebook function.

※3: You cannot use this menu when activating function from Received calls / Dialed calls / Phonebook.

- While using or running the following functions, pressing  does not work:
  - On displaying the warning message or info message / During a voice call / video-phone call / while making / receiving a call
  - During a video-phone call
  - During data transmission with a personal computer connected
  - While recording moving image
  - While copying data / moving data / deleting all data / downloading data
  - While exchanging a data via infrared



Task menu item / Active function	Melody	Camera	Schedule	Calculator	Own number
During a Voice call	×	×	○ <sup>**3</sup>	○ <sup>**3</sup>	○
A function in the Mail menu running	×	×	○ <sup>**3</sup>	○ <sup>**3</sup>	○
A function in the i-mode menu running	×	×	○ <sup>**3</sup>	○ <sup>**3</sup>	○
A function in the i-appli menu running	×	×	○	○	○
A function in a menu other than the Mail/i-mode/i-appli menu running	×	×	×	×	○
Own number displayed	○	○	○	○	×

## Service Available with FOMA Phones

Available services	Phone number
Collect call (Calls charged to the receiver)	(No prefix) 106
Directory assistance for ordinary phones and DoCoMo mobile phones (Charges apply) (Unlisted phone numbers cannot be given.)	(No prefix) 104
Telegrams (Charges apply) 8 a.m. to 10 p.m.	(No prefix) 115
Time information (Charges apply)	(No prefix) 117
Weather forecast (Charges apply)	Area code + 177
Emergency calls to police	(No prefix) 110
Emergency calls to fire station and ambulance	(No prefix) 119
Emergency calls for accidents at sea	(No prefix) 118
Disaster messaging service (Charges apply)	(No prefix) 171

### Information

- When making a collect call (106), the recipient is charged call fee and a handling fee of ¥90 (¥94.5 including tax) for each a call. (As of October, 2006)
- When using the Directory Assistance Service (104), you are charged a guidance fee of ¥100 (¥105 including tax) plus a call fee. For whom having weak eyesight or handicapped arms, the guidance is available charge free. For more details, dial 116 (NTT inquiry counter) from ordinary phones. (As of October, 2006)

- When you dial 110/119/118 from the FOMA phone, you cannot be located. Tell the staff at the police/fire station that you are calling from a mobile phone and then notify your phone number and a correct description of your current location so that they can call you back to confirm. Furthermore, remain still while talking to prevent your call from being disconnected. Do not turn off the power immediately after the call, but instead make sure that your phone can receive calls for at least 10 minutes.
- You may not be connected to regional police/fire station depending on the area from where you call. If this happens, use payphones or ordinary phones.
- If you use “Call Forwarding Service” for the ordinary phone and specify a mobile phone or automobile phone (mobile phone) as the forwarding destination, callers may hear ringing tone even when the mobile phone is busy, out of the service area, or the power is turned off depending on the settings of the ordinary phone/mobile phone.
- Note that the FOMA phone is not available to 116 (NTT inquiry counter), Dial Q2, Message Dial, and credit call services. (You can use auto credit call to the FOMA phone from ordinary phones or payphones.)

## Introduction of Data Link

“FOMA L602i Data Link” is the program for data such as phonebook, bookmark, contents exchange or transmission using FOMA phone to a personal computer via connecting the FOMA USB cable (option). You can edit and save the data using personal computer.

- LG Electronics Japan [jp.wowlg.com](http://jp.wowlg.com)

For details of installation, environments, operation, and limit, refer to web page or Installation guide and Help file of Data Link program.

### ■ OS

Windows2000, WindowsXP (Japanese version)

- PC/AT transmission operator supported these OS

### ■ Warranty Limitation

LG Electronics Japan, Inc. shall undertake the flaw warranty of this software, and no other responsibility of a qualification. Moreover, any problems concerning Data Link software and related data shall be solved by responsibility and expense of an user.

“FOMA Data Link”

#### <Customer Service of LG Electronics Japan Inc.>

■ Phone number ☎ 0120-813-023

※Can be called from mobile phone or PHS 03-5675-7323

- Please confirm the phone number before you dial.

■ Business hours 10:00 a.m. ~ 6:00 p.m.

(Except for Saturday, Sunday and Holiday)

### Information

- While synchronizing Data link, you cannot use other functions.
- You can synchronize Data link only from Stand-by screen.

## Troubleshooting

Problem	Check point	Reference
The FOMA phone cannot be turned on. (Cannot be used)	Make sure the battery pack is attached to the FOMA phone correctly.	P39
	Make sure the battery is fully charged.	P42
Cannot operate by pressing buttons.	Turn off the power once and back on, or reinstall the battery pack.	P39, 44
Cannot be charged.	Make sure the battery pack is attached to the phone correctly.	P39
	Make sure that the charging is performed in a correct way.	P40
☎外 appears and a busy tone sounds when making a call.	You may be out of the service area or receiving weak radio waves.	P31
Camera images are dark showing nothing when using the camera/video camera, or making a video-phone call.	Check the rotation direction of the camera.	P29, 109
"All lock" is displayed on the Stand-by display.	This may be because All Lock is activated.	P99
Different ring tones sound for incoming calls/incoming mails.	This may be because the call/mail from a party whose ring tone/mail ring tone is set by Utilities per mail address.	P65
	This may be because the call/mail from a party stored in a group and set with a ring tone/mail ring tone in Group Setting.	P71
Images or melodies selected return to default.	Make sure the same UIM that was attached when you downloaded images or melodies is inserted.	P38



■ When using at overseas

Problem	Check point	Reference
☎外 stays displayed, and the International Roaming Service cannot be used.	Make sure the phone is in the international roaming service area and is not receiving weak radio waves.	P224
	Check the “Network Services User's Guide” (Chapter of International Service) or WORLD WING's web page to see whether the service area or the carrier can be used with your phone.	—
	Change the “Network mode” to “Auto” or to the network supporting the service.	P97
Cannot use Video-phone call/SMS/i-mode/Packet transmission.	Check the “Network Services User's Guide” (Chapter of International Service) or WORLD WING's web page to see whether the service area or the carrier can be used with your phone.	—
	Change the “3G”/“GSM/GPRS” to “Auto” or to the network supporting the service.	P97
Cannot receive Voice call or Video-phone call.	Make sure “Barring All Incoming when roam” is not set to restrict incoming calls.	P207
Remains ☎外 after returned from overseas.	Make sure “Network mode” is not set to “GSM” only.	P97

## Error Messages


Message	Description	Reference
Invalid UIM requested software can't start	Cannot auto start i-appli software because of the UIM restrictions. Insert the UIM which was inserted when the file was obtained and try again.	–
Invalid UIM requested service not available.	Cannot send mail because of the UIM restrictions. Insert the UIM which was inserted when the mail was created and try again.	–
Invalid UIM cannot send	Cannot operate because of the UIM restrictions. Insert the UIM which was inserted when the file was obtained and try again.	–
Invalid UIM, incorrect display	Cannot display because of the UIM restrictions. Insert the UIM which was inserted when the mail was created and try again.	–
Insert FOMA card(UIM) / Insert UIM	No UIM is inserted. Insert it and try again.	–
Invalid UIM requested software can't start	Cannot start i-appli software because of the UIM restrictions. Insert the UIM which was inserted when the file was obtained and try again.	–
Could not check new message	Was not able to check new message successfully.	–
i-mode mail service is busy. Please try again later (555)	The line facility has trouble or line is very busy. Try again later.	–

Message	Description	Reference
Invalid PUK1 Remaining: X	The entered PIN1 unblock code is wrong. Enter the correct one.	P105
Invalid PIN1 Remaining: X	The entered PIN1 code is wrong. Enter the correct one.	P105
Invalid PIN1 (PIN2) Remaining: X	If you enter wrong PIN1/ PIN2 code 3 times in a row, PIN is locked. To unlock it, enter PIN unlock code.	P105
Invalid PIN1 (PIN2) Remaining: X	If you enter wrong PIN1/ PIN2 code 3 times in a row, PIN is locked. To unlock it, enter PIN unlock code.	P105
Please check SMS Center settings	The setting of the SMS center is wrong. Make the settings correctly and try again.	P102
SSL session cannot be established.	Connection was not established to the site which is supporting SSL communication. Try again.	–
Root certificate is not valid.	The SSL certificate for that server is set to "Invalid" in the "Certificate" setting. Change the setting to "Valid" and try again.	P128
Please set "To type" receiver	The mail address (To-type) is not entered. Perform a transfer after entering it.	P149
There is data that can't register to UIM	When you copy the entry of phonebook from handset to UIM, the character may be entered over the limit or entered the item that cannot be registered.	P64
URL is too long to register	The URL for the site is too long, so it cannot be registered.	–
URL is too long to display	The URL for the site is too long, so it cannot be displayed.	–


## Appendix

Message	Description	Reference
Invalid URL	The URL is not entered correctly. Enter it correctly and try again.	–
No URL history	URL history is not recorded.	–
9K size cannot be used	"Multi shot" or "Frame shot" cannot be set because "File size restriction" is set to "9KB". When you want to set "Multi shot" or "Frame shot", set "File size restriction" to "No restriction".	P113
There is no empty memory.	Since the entered memory number was already in use, the phonebook entry cannot be saved. Enter a different memory number.	–
Address is not valid (451)	SMS was not able to be sent since the address is wrong. Perform the operation after entering a correct address.	–
Please input address	No address is entered. Perform a transmission after entering an address.	P149
Upgrade was terminated.	An error occurred, and upgrade was terminated.	–
No empty memory	An error occurred so you cannot create the animation.	–
Cannot start application	An error occurred so the i-mode function could not be started.	–
Incorrect password	The Terminal Security Code is wrong. Enter the correct Terminal Security Code.	P104
Can't copy some data Continue?	The data which cannot be copied is included. If you want to copy in this situation, select "Yes".	–
Not moved	An error occurred so the file could not be moved.	–
error	An error occurred, so the operation of i-appli has been terminated.	–
Cannot rename Error in renaming	An error occurred so you cannot change the name.	–



Message	Description	Reference
No response (408)	No response from the site or the Internet web page, so could not connect. Try again.	–
Same URL already stored. Overwrite?	The same URL is already registered. Select "Yes" to overwrite.	–
Same address is entered. Send?	The same address is entered. Select "Yes" to delete and send.	–
Exist same file	The same file name exists. Change the file name to save.	–
Exist same file	The same folder name exists. Change the folder name.	–
Cannot add same desktop icon	You cannot copy the file in the same folder. Select the other folder, and then  [Add].	–
All lock	All lock is set. After releasing the lock, try it again.	P99
MessageF (free) service unavailable while abroad. Please make sure the Center Inquiry functions on your mobile phone, does not check for MessageF, when making inquires to the i-mode center(556)	You cannot request MessageF overseas. Exclude "MessageF" from "Request i-mode" items to be used overseas.	P129, 155
Not available if size is restricted	You cannot set "Setting saved quality" if you set "File size restriction" to other than "No restriction". Before you set it, set "File size restriction" to "No restriction".	P112
Error in image. Does not work correctly	The memory space is not enough or an error occurred, so it does not run correctly.	–
Cannot save image	An error occurred, so the image cannot be saved.	–

## Appendix

Message	Description	Reference
Screen memos is full.	The screen memos are saved up to the maximum. By pressing "Yes", you can delete unnecessary screen memos.	–
Screen memos is full. Select item to delete	The screen memos are saved up to the maximum so that it cannot save any more. Select "Yes" and delete unnecessary screen memos.	P122
Failed to load screen memo	Failed to read the screen memo so that it cannot be displayed.	–
No screen memos	No screen memos are saved.	–
Cannot add screen memo	An error occurred, so the screen memo could not be saved.	–
Unable to view file. Access to URL is limited (491)	The maximum number of accessible times exceeded, so could not be displayed.	–
Failed to launch.	Failed to start software because of an error.	–
Out of service area	You are either out of the service area or where radio waves are not received. Move to a place where  is displayed.	–
Terminal and UIM ID will be sent	This is displayed when IP (Information Service Provider) needs to identify a customer with "Serial number of your mobile phone/UIM". "Serial number of your mobile phone/UIM" is sent to IP over the Internet, so it could be perceived by third parties. However, your phone number, address, age and gender are not notified to the IP (Information Service Provider) or others by this operation. Select "Yes" to connect.	–
Already downloaded by different UIM. Overwrite?	Already the same i-appli downloaded with a different UIM exists. Select "Yes" to overwrite.	–

Message	Description	Reference
This card cannot be recognized	The UIM cannot be recognized, or an invalid UIM is inserted. Either reinsert the UIM or insert a valid UIM and try the operation again.	P37
Cannot zoom in this image size	Since the "Size" is set to "1280x1024", zoom does not work. Set the "Size" to "640x480" or smaller to use the zoom.	P111
Certificate is rejected (tampered)	Could not connect since an altered SSL certificate was received.	–
This site is not certified. Do you connect?	The SSL certificate which is not supported has been received. Select "Yes" to connect.	–
This certificate has expired. Do you connect?	You have connected to a site supporting SSL communication without your clock being set. Please perform "set time".	–
	An expired or premature SSL certificate is received. Select "Yes" to connect.	–
Root certificate has expired. Do you connect?	The SSL certificate in the FOMA phone has expired. Select "Yes" to connect.	–
	You have connected to a site supporting SSL communication without your clock being set. Please perform "Set time".	P95
	A request to send a client certificate occurred while connecting to a site supporting SSL communication. Select "Yes" to connect.	–
This certificate is not valid for this URL Do you connect?	When the CN of SSL certificate does not match, this error message will be displayed. Select "Yes" to connect.	–

Message	Description	Reference
Terminal and UIM ID will be sent.	This is displayed at download for an IP (Information Service Provider) to identify a customer and judge whether it can be used with the mobile phone. "Serial number of your mobile phone/UIM" is sent to IP over the Internet, so it could be perceived by third parties. However, your phone number, address, age and gender are not notified to the IP (Information Service Provider) or others by this operation. Select "Yes" to connect.	–
This software will use saved data.	The registered data (such as phonebook, bookmark or schedule) saved in your mobile phone is used at download.	–
Some media is used only with-in your phone.	Since the file protected with copyright protection technology is included, it cannot be transmitted.	–
This data cannot be moved	The file cannot be moved since it is protected with copyright protection technology.	–
This data cannot be copied	The file cannot be copied since it is protected with copyright protection technology.	–
The data may not be replayed	Since downloaded data is not valid, it may not be able to be played.	–
This data cannot be set	Cannot be set since it is protected with copyright protection technology.	–
This data cannot be sent	Cannot be sent since it is protected with copyright protection technology.	–
This data cannot be edited	Cannot be edited since it is protected with copyright protection technology.	–
The data cannot be saved.	The data from a site cannot be saved since the data is invalid.	–

Message	Description	Reference
The data cannot be saved. Download?	You cannot save the data even though you obtain it because the data cannot be saved. Select "Yes" to obtain it.	–
Please set the clock to obtain data	Cannot acquire this data because the clock is not set. Perform this operation after setting the clock.	P95
This file cannot be set as a wallpaper	This file cannot be set as a wallpaper.	–
Failed copy.	Failed to copy the phone number and the mail address since an error occurred in the data of the phone number and the mail address while copying the phonebook.	–
Cannot add folder	The maximum number of folders that can be created has been reached, so cannot create any more. Delete unnecessary folders and try again.	–
Too many items are protected	The maximum number of files that can be protected has been reached so cannot protect any more. Release protection for other files and try again.	–
Unable to connect to server.	Connection to the server failed for some reason. Try again	–
Service is not provided	The i-mode service is not subscribed to, so the service cannot be used. Please subscribe to the service.	–
Connection failed	Cannot send since you are in an area where SMS service is not provided.	–
Not supported image size	You cannot insert "Frame" since the sizes are "1280X1024", "640X480" and "Phonebook".	–
This motion is not complete	Cannot save the data since the data was not completely acquired.	–
This data can no longer be replayed Delete?	An i-motion movie with playable frequency reached is selected. Select "Yes" to delete it.	–

## Appendix

Message	Description	Reference
Replay period has expired Delete?	An i-motion movie with expired replay period is selected. Select "Yes" to delete it.	–
Replay period has not yet started	You are selecting an i-motion movie whose playable date has not yet come. Check the playable date.	–
Cannot obtain in error to play back	There is an error in the playback control in i-motion, so cannot be acquired.	–
Unable to obtain data due to replay restriction data error	There is an error in the playback restriction data for i-motion, so cannot be acquired.	–
Can't play	An error occurred, so cannot be played back.	–
Could not play	An error occurred, so could not be played back.	–
Size of this page is not supported	The maximum size of data exceeded, so could not be downloaded successfully.	–
Size of this page is not supported		
Unable to download. Data exceeds maximum size. (452)	The size of data receiving exceeded the maximum size, so could not be received.	–
URL address changed. (301)	The site or Internet web page is automatically transferring the URL or the URL has been changed. If this is registered in the bookmark or Home, reregister it.	–
Connection failed (XXX)	Could not connect to the site for some reasons. Try again. A 3-digit number is displayed in (XXX).	–
File with copyright is deleted	A file prohibited to be output from the FOMA phone is attached to the i-mode mail you are sending.	–
Could not delete	Failed to delete because an error occurred.	–
Page is not found. (404)	The site was not found. The site may not exist.	–



Message	Description	Reference
No content is available. (204)	There is no data to display at the connected site.	–
No requested software	There was no i-appli to start from the site or mail.	–
No requested software. End?	There was no i-appli to start from the site or mail.	–
Run selected software?	The URL to activate i-appli is activated. If you activate it, select “Yes”.	–
Requested software unavailable	Could not start an i-appli from the site or mail.	–
Unable to retrieve the requested URL (504)	Could not connect to the specified site for some reason. Try again.	–
No Requested File (492)	The selected file does not exist in the FOMA phone.	–
cannot register anymore	All software programs that can be auto started have already been set up, so you cannot set up any more.	–
Please wait	The line facility has trouble or the line is very busy. Try again later.	–
Low battery	The battery level is too low to activate the function. After charging it, try again.	P40
Cannot receive message	Failed to obtain mail.	–
No messages	The received mail has not been saved.	–
No Certificates	SSL certificate has not been saved.	–
Inbox message is full	Received mail is saved up to the maximum number or the memory space for received mails is already full, and no more can be saved. Delete unnecessary received mails.	P141

Message	Description	Reference
Schedule is full	The schedule is set up to maximum, and no more can be set. Delete unnecessary schedule.	P192, 193
Streaming play not supported	You cannot play the file because i-motion of streaming type is not supported.	–
Invalid data. Connection cannot be established (400)	Could not access i-mode for some reasons. A 3-digit number is displayed in (XXX).	–
Connection interrupted	The line is busy or a transmission error occurred, so connection was interrupted. Try again later.	–
Connection failed	An error occurred during a download. Select “Retry” to reconnect.	–
	Radio waves are weak, so cannot connect. Move to a place where radio waves are strong enough and try again.	
Connection failed	Could not connect because of network trouble. Wait a while and try again.	–
Connection failed (562)		
SSL session failed.	Cannot connect because of the error in the server's authentication.	
Time out	Could not connect within the time set at “Connection Timeout”. Change the setting or try the operation again.	P129
Network unavailable	You are either out of the service area or where radio waves are not received; so you cannot set the network service because the network is not connected. Move to a place where radio waves can be reached.	–
Sent message is full	Sent mails was saved up to the maximum number, and no more mail can be saved. Delete unnecessary saved mail.	P146

Message	Description	Reference
Sending error	A sending error occurred.	–
Address is not valid (451)	Could not send the message correctly. Check the address and send again.	–
Transmission failed	The mail could not be sent correctly.	–
Transmission failed (XXX)	A 3-digit number is displayed in (XXX).	–
Server is full (551)	The recipient's mail is full.	–
No messages	Sent mail has not been saved.	–
Software updated	The S/W is not updated so you cannot activate the function.	–
Application(s) exist. Folder can't be deleted.	Software is saved in the folder so the folder cannot be deleted. Delete the software and try again.	P162
The software contains an error.	There is an error in the software, so the folder download and version upgrade cannot be performed.	–
This software contains an error. Unable to download.	There is an error in the software, so download and version upgrade cannot be performed.	–
Memory full. Overwrite existing software?	Memory for storing software is not enough, so no more can be saved. Delete unnecessary software.	P162
This software is not supported by this phone.	The software to download or to update the version is not compatible with this FOMA phone.	–
Installation cancelled	An error occurred, so downloading was interrupted.	–
Already downloaded.	The same version of the software has already been downloaded.	–
i-mode mail service is busy. Please try again later(553)	The line is very busy. Try again later.	–

## Appendix

Message	Description	Reference
Invalid speed dial	No phonebook entry with a memory number corresponding to the number entered on the Phonebook Entry display has been registered.	P64
Security code is wrong	The Terminal Security Code is wrong. Enter the correct Terminal Security Code.	P104
Not allowed	Could not make a phone call since the connection to the network failed. Try making the call again.	–
Call rejected	Rejected a call when incoming call from the other party not registered in phonebook. To receive a call, set “Memory reject call” to “Permit”.	P90
	Rejected a call from the other party registered “Reject on list”.	P90
	Rejected a call when “Reject all calls” sets to “Disconnect call”.	P90
Interrupted	The i-mode inquiry was suspended for some reason. Try the operation again.	–
Connection interrupted. Retry?	An error occurred during Infrared communication, so transmission has been suspended. Select “Yes” to retry the connection.	–
Interrupted	An error occurred during Infrared communication, so Infrared reception has been suspended.	–
This data cannot be sent	The file cannot be sent from the FOMA phone, so you cannot send a mail attaching the file.	–
Begin data exchange?	The message to activate infrared function is displayed. Select “Yes” to activate this function.	P182
Battery low	The battery level is low. Perform the operation after charging the battery.	P40



Message	Description	Reference
Data full	Data is stored to the maximum, so cannot save any more. Delete unnecessary data.	P141, 162, 168, 169, 175
Invalid data	An invalid data has been downloaded.	–
Receiving canceled	Could not obtain because of invalid data.	–
Low battery Exit camera-mode	Because the battery level is low, the camera is terminated. Try again after charging the battery.	P40
Low battery Cannot start camera-mode	The remaining battery level is getting low. Perform the operation after charging the battery.	P40
Attached file size is over.	The file size of the message you attempt to send exceeds the maximum size.	P151
Cannot attach more than file	No attachable files have been saved.	–
Delete attached file	The file was deleted because there was an attachment with UIM restrictions.	–
Delete end the phone number is too long	The number of digits of the phone number entered in the address of SMS message by looking up the phonebook exceeds the maximum number of characters that can be entered.	–
Failed to copy the phone number	The phone number failed to be copied because there was an error in the data of the phone number while it was copied to the phonebook.	–
Registration num is over Can't copy	The phone book memory in the UIM is full, so the phone book cannot be copied. Try again after deleting unnecessary phonebook.	P68
Memory is full	Since the memory of the selected storage place is full, the phone book cannot be stored. Perform the operation after deleting unnecessary phonebook entries.	P68

Message	Description	Reference
Registration is in progress (554)	Cannot operate because the user is being registered. Wait a while and try again.	–
Not registered	An error occurred so the data cannot be registered.	–
Cancel and discard work in progress?	You are about to terminate the edited content without saving. Select "Yes" to terminate the content without saving.	–
Enter name.	The name of the phonebook is not entered. Save after entering a name.	P64
Too much data was entered	Too many characters have been entered in the text box or URL, so it cannot be sent. Reduce the number of characters to send.	–
Input error (205)	The data (such as text) entered and transmitted from a site are wrong. Check the entered contents and try again.	–
Authentication type is not supported(401)	Cannot connect because the authentication type is not supported.	–
Invalid	An error occurred so you cannot register it.	–
Auth. password wrong. Retry?	The authentication password entered is incorrect. Select "Yes" to continue.	P184
Authentication canceled (XXX)	This will be displayed when "Cancel" is selected from the authentication screen. A 3-digit number is displayed in (XXX).	–
Enter correct Network Security Code	The Network Security Code is wrong. Enter the correct Network Security Code.	P104
No network found	You cannot set the network service because the network is not connected. Please wait a while and try again.	–
No response from network. Activate manually?	Cannot search for the network automatically.To search manually, select "Yes".	P96



Message	Description	Reference
Password is not correct.	The entered password is wrong. Enter the correct password.	–
Password is not correct. (401)		
Select ON for caller ID notification	Cannot notify the phone number. After setting on in caller ID notification, try again.	P202
File error	Because the file has an error, it cannot be saved.	–
Invalid File	Cannot operate since the file is corrupted.	–
Invalid File (493)		
The file is not supported.	A file that cannot be set is selected.	–
Invalid data	Because the file is invalid, cannot be displayed/played/saved.	–
File size is too big	The file is too big to attach to mail.	–
Image with digital right is included	Since the file protected with copyright protection technology is included in the folder, animation cannot be created. Select a file with no restrictions.	–
File is deleted	This is displayed when incoming mail with a file attached is forwarded. Perform attaching operation in order to attach the file.	P150
Enter file name	File name has not been entered. After entering file name, try again.	P169, 170, 174
Can't attach file	The file cannot be attached since it will exceed the size of mail that can be sent.	–
Cannot read file Unknown file format	This file format is not supported in this FOMA phone.	–
Can't create folder. Folder already exists.	The folder cannot be created since there is already a folder with the same name. Change the name.	–

## Appendix

Message	Description	Reference
Can't rename folder. Folder already exists.	The folder cannot be created since there is already a folder with the same name. Change the name.	–
Cannot delete folder	Mail is saved in the folder, so the folder cannot be deleted. Delete the folder after deleting all the mail in the folder.	P141
Incorrect folder name	A character invalid for a folder name is included.	–
Cannot create folder	The maximum number of folders are created, so cannot create any more. Delete unnecessary folders and try again.	P141,161,168
Can't create folder any more	An error occurred so the folder was not created.	–
Bookmark is full. Select item to delete	The maximum number of data items are bookmarked, so cannot bookmark any more. Delete unnecessary bookmarks by selecting “Yes”.	P121
Cannot add bookmark	An error occurred, so could not bookmark.	–
No bookmarks	Bookmark not registered. Register bookmark beforehand.	P130
Unknown browser error	An unknown error occurred.	–
Invalid content	Invalid page, so cannot be displayed.	–
Total size is too big	Total page size exceeded the maximum size, so it cannot be received successfully.	–
Your data will be lost. Quit?	You are about to terminate without saving the edited contents such as phonebook entries by pressing  or  . Select “Yes” to terminate without saving the contents.	–
Cancel editing?	You are about to terminate without saving the edited contents. If you do not want to save it, select “Yes”. To continue editing, select “No”.	–
Home page not set.	Home is not set. Perform the operation after setting Home.	P128

Message	Description	Reference
Home page disable	The URL registered in Home is not entered correctly. Perform the operation after entering it correctly.	P128
Save failed.	An error occurred, so could not save.	–
No messages	No unsent mail messages saved.	–
No save area	Cannot save because there is no room available in the storage area. Delete unnecessary files.	–
Message too long Cannot enter	Cannot enter because the text size exceeded 70 full-pitch characters or 160 half-pitch characters when an SMS message was transmitted.	–
Message too long	The mail size exceeds 5,000 full-pitch characters if a signature is pasted, so it cannot be pasted. Make the text of the message shorter or delete attached data to reduce the size down to less than 5,000 full-pitch characters.	P156
No space to attach signature	The mail size exceeds 5,000 full-pitch characters if a signature is pasted, so it cannot be pasted. Make the text of the message shorter or delete attached data to reduce the size down to less than 5,000 full-pitch characters.	P156
Message too long End of message will be deleted	When received mail is replied to with quote or forwarded, the message will exceed 5,000 full-pitch characters, so the last part of the message will be truncated.	–
Cannot edit message	The text cannot be entered because data equivalent to the size of 5,000 full-pitch characters is attached to the mail.	–
Manner mode Play with sound?	The FOMA phone is set to manner mode. When you play the streaming file with sound, select "Yes".	–
Play with sound?	The FOMA phone is set to manner mode. Select "Yes" to play sound of moving images or a melody.	–
Outbox or Unsent message is full	Cannot save the mail because the unsent message is full. Delete the unnecessary unsent mail.	P148

## Appendix

Message	Description	Reference
There's empty input. Input required	There are items not entered. Perform the operation after entering these items.	–
Empty message cannot be saved	Cannot be saved because nothing is entered to address/subject/text field and no file is attached to the message.	P149
Invalid data. Data size is not supported.	There is an error in the received data, so it cannot be displayed. The received data will be destroyed. A 3-digit number is displayed in (XXX).	–
Invalid data. Data size is not supported. (XXX)		
Nuisance call barring service denied	The Nuisance call barring service is not subscribed to so it cannot be set. In order to use this feature, please subscribe to the Nuisance call barring service.	P202
Failed to copy mail address	Failed to copy the mail address because an error occurred in the data of the mail address during the copy operation to the phonebook.	–
Please make sure "Receive option" in "Mail Settings" is turned ON	The Receive Option setting is set to "OFF". Change the setting to "ON" and try again.	P154
Message data is broken	An error occurred so the mail cannot be displayed or created.	–
10 files limit for message	The maximum number of files attachable to mail is exceeded. The maximum number of files that can be attached to mail is 10.	P150
Folder is full	Inbox is full, so no new message can be received. Delete unnecessary received mails.	P141
Message data is broken	The message data is corrupted and cannot be displayed.	–
No messages F	There is no MessageF saved.	–
No messages R	There is no MessageR saved.	–

Message	Description	Reference
Memory full	Because the memory of the FOMA phone is full, the data received by Infrared communication or moving images cannot be saved. Perform the operation after deleting unnecessary data.	P68,121, 168, 169, 175
	Because the memory is full, the shot still images cannot be saved.	–
	Because the memory is full, the edited still images cannot be saved.	–
Not enough memory Can't save	Because there is not enough memory, each function cannot be started.	–
	Because there is not enough memory, no still images can be taken.	
Not enough memory	Because the number of characters transmittable is exceeded, the end of text will be truncated. Select "Yes" to send.	–
Exceeds limit. Unable to paste all letters. Paste?	Because the maximum number of characters is exceeded, part of the text could not be pasted. Select "Yes" to paste the portion that can be pasted.	–
Exceeds limit. Unable to paste.	Because the maximum number of characters is exceeded, the text cannot be pasted. Perform the operation after deleting unnecessary text by pressing <input type="button" value="CLR/⏏"/> .	–
Not enough memory Please delete some files	The memory is full. After deleting the unnecessary files, try again.	P168, 169, 175