## ThinkCentre Tiny-in-One (TIO) 22 Gen3

Model	Non-touch model: Touch model:	10R1PAR1++/10R1P 10R0PAR1++/10R0P	,	I		
Form factor	Tiny-in-One, offers a full All-In-One experience when optional Tiny slots into the back of TIO, clean cabling and effortless setup					
Compatible Tiny:		-	15 / M93/p* / M83 / M73* / M53 /			
	Chromebox Tiny * Non-TIO models can't be turned on by pressing power button of TIO					
Panel	TFT-LCD, In-Plane Switching technology**, White LED backlight					
Viewable image size	Notes: In-Plane Switching may refer to VA, PLS, and IPS panels 21.5" (546.1mm) diagonal					
Max view area (W x H)	18.74" x 10.54" / 476.1mm x 267.8mm					
Bezel Width	Top / Side: 2mm, Bottom: 22.1mm					
Native resolution Multi-touch	1920x1080 Ontional 10-point multi-touch, supports Wake on Touch					
Aspect ratio	Optional 10-point multi-touch, supports Wake on Touch 16:9					
Pixel pitch (mm)	0.24795mm					
Dot/Pixel per Inch Brightness	102.4 dpi 250 pits or od/m² (typical)					
Contrast ratio	250 nits or cd/m² (typical) 1000:1 (typical)					
Pixel response time	14ms (default), over drive to 4ms, 6ms					
Color gamut	72%					
Anti-reflective Anti-glare Viewing angle at 10:1 CR178° (+/- 89°) horizontal, 178° (+/- 89°) vertical						
Preset resolutions	640x350 @ 70Hz	, , ,				
	640x480 @ 60Hz,	66Hz, 72Hz, 75Hz				
	720x400 @ 70Hz					
	800x600 @ 60Hz, 72Hz, 75Hz 1024x768 @ 60Hz, 70Hz, 75Hz 1152x864 @ 75Hz 1280x800 @ 60Hz 1280x1024 @ 60Hz, 72Hz, 75Hz 1366x768 @ 60Hz					
	1440x900 @ 60Hz, 75Hz					
	1600x1200 @ 60Hz, 70Hz, 75Hz					
	1680x1050 @ 60H 1920x1080 @ 60H					
Presets / user settings	Presets: 25; user s					
On screen display		with digital user contro	ls (8 languages)	l		
Control features	rol features Ftont: Exit button, Left / Mode-switching button (TIO / monitor mode), Right / Brightness button, Enter / Menu button, Power button					
		ightness button, Enter o button, Volume down				
Tiny-in-One Power On			Power button positioned on TIO			
	can turn on both TIO and Tiny (only some Tiny support, see compatible list)					
Side ports (TIO)	One USB 3.1 Gen1 / USB 2.0 (when M73 or M53 installed or USB 2.0 connected via USB upstream port)					
			en a Tiny is istalled or a PC is			
	connected	via USB upstream por	t			
Side ports (Tiny)	Side ports offered by installed Tiny (optional)					
Rear ports 3-in-1 Cable	One DisplayPort in port, one USB upstream port, one power connector Undetachable 3-in-1 cable (Power connecter, USB [supports USB 3.1 Gen1]					
o III i oubic			ing to Tiny installed (optional)			
Camera	720p camera with dual microphone for VOIP, LED indicator					
Internal Speaker	2 watt x2					
Security	Security keyhole for attachment of optional cable lock (Kensington® lock compatible), locks optional Tiny with TIO together, more security features offered by Tiny installed (optional)					
Mechanical	Dimensions	TIO without stand	TIO with stand			
	W x D x H (inch)	19.26 x 2.85 x 13.35	19.26 x 10.76 x 14.59 - 18.93			
	W x D x H (mm)	489.3 x 72.5 x 339	489.3 x 273.3 x 370.7 - 480.7			
	Weight (Approx.)	7.01 lb / 3.19 kg	11.77 lb / 5.34 kg			
				1		

Mounting features	Wall or desk mounting using the extend arm or third-party accessories meeting the VESA FPMPMI® (100mm mount)		
Adjustable stand	Tilt: 30° back, -5° forward;  lift: 4.3" (110mm);  swivel: +/-45°;  Pivot: clockwise 0° to 90°		
Power supply Power consumption	90 watts AC/DC adapter, 88% PSU, universal 19 watts typical, 32 watts maximum, <0.5 watts standby / suspend		
Limited warranty	3-years, Customer Carry-In or Mail-In via Rapid Replacement Service		
VESA-compliant Ergonomics Emission standards Environmental Windows certifications	VESA DDC2B/CI, VESA DPMS-compliant ISO 9241-307, TUV Eye Comfort certified FCC Class B TCO 7.0, TCO Edge 2.0, WEEE, RoHS, ENERGY STAR® 7.0, EPEAT™ Gold rating, ULE Gold, TUV, VOC Windows 7 and Windows 10 certified		
Ship group	TIO (Monitor), detachable stand, AC/DC power adapter, power cord, user's guide and driver CD, quick start and safety poster		
Accessories	For compatible accessories, please go to http://www.lenovoquickpick.com		
	· · · · · · · · · · · · · · · · · · ·		

ThinkCentre Tiny-in-One 22 Gen3 Compatible list						
Model	M910 / M710 / M900 / M700 /	M93/p Tiny,	Chromebox			
	M600 / M715 / M83 / M53 Tiny	M73 Tiny				
Turn on TIO and						
Tiny together via	All models	All models	Not support			
Alt + P on USB KB						
Turn on TIO and						
Tiny together via	All models	TIO models	All models			
TIO Power Button						