Meets Federal Specification FF-P-110-G

8077

Exposed Shackle **Padlock**

8077 8077A - Green Dial 8077AB

8077AC -Black Dial

WARRANTY

workmanship for a period of one free of defects in materials and This lock is guaranteed to be

S&G for a Return Goods option, any lock which proves to 634-4843. 885-9411, or FAX S&G at (800) technical assistance at (606) Authorization (RGA) or returned to our factory. Contact warranty period, providing it is be defective within the one year We will repair or replace, at our




SARGENT & GREENLEAF INC One Security Drive Nicholasville, KY 40356

> on the lock before it is put into new combination should be set combination number of 25. A from the factory set on a single service. All new 8077 locks are shipped

should be thoroughly familiar and familiarize yourself with padlock, study the illustrations with the opening procedures. to change the combination, you of the lock. Before attempting the names of the various parts Before attempting to operate this

combination and the index. align the numbers of the changing the combination, care should be taken to very precisely difficulties in opening the lock. Failure to do this could cause When opening the lock, or



OPENING PROCEDURE

use the following procedure: factory shipping combination, 1. If the lock is set to the

the following procedure:

three number combination, use

If the lock is set to a true,

combination has been set to just being put into service, its the single number "25." A. If the lock is new and is

clockwise align the number 25 on the On the B. Turn the dial counterdial with the opening index. fourth revolution, four revolutions.

opening index. Turn the dial clockwise align zero with the

sharply to open the lock. the shackle

compensate for possible open: Dial 1/2 number + or - (i.e. 24 1/2 or 25 1/2) to variation of the factory NOTE: If the lock fails to


- aligns with the opening index number of the combination terclockwise) until the first A. Turn the dial left (coun-
- the fourth time.
- wise) aligns with the opening index number of the combination B. Turn the dial right (clockthe third time. until the second
- C. Turn the dial left until ing index the second time. bination aligns with the openthe third number of the com-
- opening index the first time. until zero is aligned with the D. Turn the dial clockwise
- sharply to open the lock. on the shackle

IMPORTANT:

mechanism is fully locked. either direction to insure the five complete revolutions in After re-locking the padlock the dial must be turned at least

PROCEDURE

- With the present combination, open the lock as described in the OPENING PROCEDURE.
- 2. Use the screwdriver end of the change key (Fig. B) to turn the cover locking screw (Fig. C) clockwise until it comes to a complete stop.
- Remove rear cover plate by sliding it upward.
- Turn the cover lock screw counterclockwise, backing it out of the lock body as far as possible. It does not have a positive stop.
- Close the shackle.
- 6. Cover the opening index mark with a small piece of tape or your thumb to prevent the possibility of dialing the numbers to the opening index.
- 7. Dial the present combination to the *changing index*. All numbers of the combination, including the last turn to zero, are used in the combination changing procedure.
- A. In the event the lock is new and just being put into service, the single number of 25 is the combination. Turn the dial left (counterclockwise) until 25 aligns with the changing index the fourth time. Turn the dial right (clockwise) one-half revolution, stopping when zero is aligned with the changing index the first time. Do not pull on the shackle.



- 8. In the event that any other combination is set on the lock, use the same procedure outlined for opening the lock, but dial the combination numbers to the changing index.
- 9. Use the elbow of the changing key (Fig. B) to turn the key hole screw on the back of the lock (Fig. C) clockwise to the open position. If the screw will not turn, repeat the procedures in step 7 or 8, whichever applies.
- 10. Insert the change key (tip first) into the key hole in the back of the lock. The change key is properly seated when the tab on the key is fully inside the lock. Turn the key clockwise one-quarter turn.
- 12. Set the new combination as follows:
- A. Turn the dial left until the first number of the new combination aligns with the changing index the fourth time.




Fig. C

COVER REMOVED

- B. Turn the dial right until the second number of the new combination aligns with the changing index the third time.
- C. Turn the dial left until the third number of the new combination aligns with the changing index the second time.
- D. Turn the dial clockwise until zero aligns with the changing index the first time.
- 13. Once the new combination is set, and zero is aligned with the changing index, turn the change key counterclockwise one-fourth turn and remove. Do not turn the key hole screw.

- NOTE: To insure you have correctly set the combination, you should once again completely redial the new combination as directed in Step 12. Re-insert the change key fully into the lock, but do not turn. If the key will fully insert, you have set the combination correctly.
- 14. Remove the change key and again dial the new combination (including the final turn right to zero) to the changing index. Using the change key elbow, turn the key hole screw to the closed position, and close the shackle.
- 15. If the key hole screw will not return to the closed position, the combination has been incorrectly dialed. Redial the combination to the *changing index* and try again.
- 16. Remove the tape or your thumb from the opening index. Dial the new combination to the opening index following the steps in the "OPENING PROCEDURE," and pull on the shackle sharply to open the lock.
- 17. Turn the cover locking screw clockwise until it comes to a complete stop.
- Slide the rear cover into place.
- Turn the cover locking screw counterclockwise as far as possible. Close the shackle.
- 20. After any combination number change, it is advisable to operate the lock at least three times before putting it into use.

ISSUE DATE: June 1, 1992

8077 PADLOCK COMBINATION RECOVERY

A lost combination for an 8077 padlock can be recovered if the following conditions exist:

- 1. The cover is removed from the padlock.
- The shutter control screw is rotated so the change key hole is open and not blocked by the change key hole shutter (see Figure 1).

If either of these two conditions is not met, the lock should be discarded and replaced with a new 8077. Combination recovery techniques which involve drilling holes or removing the inside cover are not acceptable. The 8077 is designed to show evidence of forced entry, so any procedure which leaves marks or holes — even though they may be repaired — is not allowed. Repair parts are not available from S&G for any version of the 8077 padlock.






Figure 1

A standard 8077 change key and a special reset key (Figure 2) are required to perform the combination recovery procedure.



PROCEDURE

- Step 1 Insert end A of the reset key through the change key hole, and keep the tip of the key in contact with the #3 wheel as you slowly rotate the padlock dial counterclockwise.
- Step 2 When the change key opening in the wheel passes underneath the tip of the reset key, the key will move into the lock until the first depth mark is just barely outside the lock body (Figure 3).



Step 3 – Turn the reset key clockwise ninety degrees.
 You should feel a slight release of tension in the wheel mechanism. Again rotate the padlock dial counterclockwise.

Note: If the dial will not move more than a number or two, the tip of the reset key is not in the change key opening of the wheel. If this happens, pull the key out of the lock just until you can move the dial counterclockwise, then apply light inward pressure on the key as you continue to rotate the dial counterclockwise. Pick up the procedure at Step 2.

- Step 4 When the change key opening in the #2
 wheel passes underneath the tip of the change key, the key
 will move into the lock until the second depth mark is just
 barely outside the lock body.
- Step 5 Turn the reset key clockwise ninety degrees.
 You should feel a slight release of tension in the wheel mechanism. Again rotate the padlock dial counterclockwise.

Note: If the dial will not move more than a number or two, the tip of the reset key is not in the change key opening of the 2 wheel. If this happens, pull the key out of the lock just far enough to allow you to rotate the dial counterclockwise. Pick up the procedure at Step 4.


(continued on the reverse side)

Sargent & Greenleaf


- Step 6 When the change key opening in the #1
 wheel passes underneath the tip of the change key, the key
 will move into the lock until the change key rib is just
 barely outside the lock body.
- Step 7 Turn the reset key clockwise ninety degrees. You should feel a slight release of tension in the wheel mechanism. Again rotate the padlock dial counterclockwise.

Note: If the dial will not move more than a number or two, the tip of the reset key is not in the change key opening of the 1 wheel. If this happens, pull the key out of the lock just far enough to allow you to rotate the dial counterclockwise. Pick up the procedure at Step 6.


- Step 8 Carefully remove the reset key from the padlock. It may be necessary to wiggle the key slightly to withdraw it. Avoid moving the dial during this step.
- Step 9 Insert end **B** of the reset key (Figure 4) through the padlock's change key hole until the rib of the key is just outside the padlock (Figure 5). It may be necessary to wiggle the key slightly to insert it fully into the lock.



- Step 10 With the reset key in the padlock, turn the dial left (counterclockwise) until "25" aligns with the changing index (Figure 7) the fourth time.
- Step 11 Turn the change key ninety degrees counterclockwise, and pull it straight out of the padlock. Do not turn the key as it is being withdrawn, and make sure the dial does not move off "25." As soon as the reset key is withdrawn, insert the standard change key (tip first) into the padlock's change key hole. The standard change key is properly seated when the tab on the key is fully inside the lock (Figure 6). Turn the key clockwise one-quarter turn.



- Step 12 Set the new combination as follows:
- A. Turn the dial left until the first number of the new combination aligns with the **changing index** the fourth time.
- B. Turn the dial right until the second number of the new combination aligns with the **changing in**dex the third time.
- C. Turn the dial left until the third number of the new combination aligns with the **changing index** the second time
- D. Turn the dial clockwise until zero aligns with the **changing index** the first time.



NOTE: To insure you have correctly set the combination, you should once again completely redial the new combination as directed in Step 12. Re-insert

the change key fully into the lock, but do not turn. If the key will fully insert, it simply means you have set the combination correctly.

- Step 14 Remove the change key and again dial the new combination (including the final turn right to zero) to the changing index. Using the change key elbow, turn the shutter control screw to the closed position.
- Step 15 If the shutter control screw will not return to the closed position, the combination has been incorrectly dialed. Redial the combination to the changing index and try again.
- Step 16 Dial the new combination to the opening index following the steps under OPENING PROCEDURE in the standard 8077 PADLOCK OPERATING INSTRUCTIONS (document 630-159), and pull on the shackle sharply to open the lock.
- Step 17 Turn the cover locking screw clockwise until it comes to a complete stop.
 - Step 18 Slide the rear cover into place.
- Step 19 Turn the cover locking screw counterclockwise as far as possible. Close the shackle.
- Step 20 After any combination number change, it is advisable to operate the lock at least three times before putting it into use.