

Logitech® Fold-Up Keyboard

Setup and turn on

1. Insert iPad 2

[Illustration showing iPad inserting into Keyboard](#)

Slide your iPad 2 into the tray from right to left, and then push it in place. The “Click” lets you know that the keyboard is in place.

2. Open the keyboard

[Illustration showing Keyboard opening and the movement of the product](#)

Press the release button and lift the tray upwards. Lifting the tray expands and turns on the keyboard. The blue LED lights for six seconds to confirm the keyboard is on.

Pairing the Fold-Up Keyboard

The Bluetooth Fold-Up Keyboard should only need to pair to your iPad 2 once.

[Illustration showing close up of product button](#)

1. On the open keyboard, press the CONNECT button.

The Bluetooth status light blinks. The keyboard is “discoverable” for three minutes, or until it is paired with the iPad 2.

2. On the iPad 2, select: Settings > General > Bluetooth > On.

3. Select “Logitech Fold-Up Keyboard (IPD)” from the iPad 2 list of available devices. The iPad 2 displays a code.

4. Type the code on the keyboard and press Enter. The Fold-Up Keyboard is paired to the iPad 2.

Close and turn off

1. Close the keyboard

[Illustration showing Keyboard separating to closed position](#)

Hold and gently push both front corners of the keyboard towards the back of the unit until completely closed. Closing the unit turns off the keyboard.

Caution

- Hold the keyboard until fully closed to prevent the iPad 2 from falling.
- Avoid putting your fingers between the tray and the bottom case to prevent pinching.

2. Remove the iPad

[Illustration showing iPad released from Keyboard](#)

Press the release mechanism on the right—the iPad 2 pops up and can be removed from the tray.

Tip: During flights, keep keyboard closed.

Function keys

[Illustration showing function keys](#)

The Fold-Up Keyboard is designed with special function keys (F-key) for more control of your iPad 2. To use the enhanced functions, press and hold the FN key followed by an F-key.

1. **Home** Returns you to the iPad 2 home screen
2. **Search** Brings up the iPad 2 search screen
3. **Slideshow** Starts playing slideshow of saved pictures
4. **Virtual keyboard** Allows you to hide or show iPad 2 onscreen keyboard
5. **Previous track** Skips to previous track on current playlist
6. **Play/Pause** Starts or stops current playlist
7. **Next track** Skips to next track on current playlist
8. **Mute** Mutes audio on iPad 2
9. **Volume down** Decreases volume on iPad 2
10. **Volume up** Increases volume on iPad 2
11. **Lock** Makes the iPad 2 screen go dark and come back when pressed again

LED Indicators

Bluetooth LED

- Pairing Blinks while discoverable, or until paired.
- Power ON Solid glow for the first six seconds after power on.

Charging LED

- Solid green glow while charging; turns off when fully charged.
- Blinks red when battery status drops below 5%, or less than one hour. LED continues to blink until battery is completely dead and the unit turns off.

Battery Management

The Fold-Up Keyboard features a rechargeable battery.

Charging information

[Illustration showing Keyboard charging when both open and shut](#)

- To recharge the keyboard, use the provided USB cable. Plug the micro USB end into the unit and the other end into an iPad 2 adapter or a computer USB port. The keyboard will charge when open or closed:
- The battery LED is green while charging. It turns off when the keyboard is fully charged.
- It takes about 3 hours to completely recharge the keyboard.
- The battery life is approximately 500 hours of typing.

Product end of life: keyboard battery disposal

Removing the battery requires disassembly and will destroy the unit.

1. Using an appropriate tool, break the battery cover.
2. Locate the battery.
3. Grasp and tug firmly to separate the battery from the circuit board...
4. Dispose of the battery according to local regulations. Recycle remaining keyboard parts.

Help with setup

Mechanical problems

- Cannot open or close the keyboard
- It's hard to remove the iPad from the tray

Radio problems

- Connection drops

Charging problems

- Cable lost (any standard USB to micro USB cable will do...)