# microlab



Outlander300

**User Manual** 

FCC ID:OR8-OUTLANDER300 Bluetooth



Previous: Short press previous button "<", music

Next: Short press next button ">", music will play next

Answer Call: Short press multifunction button "▶II" to answer the incoming call.

End call: Press Volume up button "+"for 2 seconds call ended.

seconds again, call switched to headphone.

Call Mute function: Press Volume down button "-" Battery Capacity status: When headphone is connected to iOS devices, iOS devices show the headphone battery power status on the upper right

**Charging**: New headphone has enough power for pairing and dialing out several times. When in low battery, please charge via USB cable for 2 hours. Red LED keeps lighting during charging. Once blue

## Important Safety Instructions

IMPORTANT SAFETY INSTRUCTIONS Read these instructions – All the safety and operating instructions should be read

before this product is operated. Keep these instructions – The safety and operating instructions should be retained for future reference.

- Heed all warnings All warnings on the appliance and in the operating instructions should be adhered to.
  Follow all instructions – All operating and
- ise instructions should be followed Do not use this apparatus near water – The appliance should not be used near water or moisture – for example, in a wet basement
- or near a swimming pool, and the like.

  Clean only with dry cloth.
  Do not block any ventilation openings.
  Install in accordance with the
  manufacture's instructions.

  Do not install near any heat sources such as
- radiators, heat registers, stoves, or other apparatus (including amplifiers) that
- produce heat.

  9. Only use attachments/accessor specified by the manufacturer.

  10. Use only with the cart, stand, tripod, bracket, or table specified by the manufacturer, o sold with the apparatus. When a cart or rack is used, use caution when moving the
- Unplug the apparatus during lightning storms or when unused for long periods of
- 12. Refer all servicing to qualified personne Servicing is required when the apparatu has been damaged in any way, such as power supply cord or plug is damaged, fallen into the apparatus has been expo
- 13. WARNING: To reduce the risk of fire or apparatus to rain or moisture. The apparatus shall not be exposed to dripping or splashing and that objects filled with liquids, such as vases, shall not be placed
- CAUTION: Danger of explosion if battery is incorrectly replaced. Replace only with the same or equivalent type.

15. WARNING: The battery (battery or batteries or battery pack) shall not be exposed to excessive heat such as sunshine, fire or



16.This lightning flash with arrowhead symbol within an equilateral triangle is intended to alert the user to the presence of non-insulated 'dangerous voltage'within the product's enclosure that may be of sufficient magnitude to constitute a risk of

Warning: To reduce the risk of electric shock, do not remove cover (or back) as The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance instructions in the literature accom panying the appliance.

Correct Disposal of this product.
This marking indicates that this product should not be disposed with other household wastes throughout the EU. To prevent

possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsibly to promote the sustainable reuse of material resources. To return your used device, please use the retailer where the product was purchased They can take this product for onmental safe recycling.

- 19. Replacement parts When replacement
- replacement parts when replacement parts are required, ensure the service technician has used replacement parts specified by the manufacturer or have the same characteristics as the original part. Unauthorized substitutions may result in fire, electric shock or other hazards. Try to install the product near a wall socked or extension cord and shall be easily

#### FCC and Canada EMC Compliance linformation

(2) l'utilisateur de l'appareil doit accepter tou

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide easonable protection against harmful nterference in a residential installation. This nterierence in a residential installation. This equipment generates uses and can radiate radi requency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one a report of the following nterference by one or more of the following

- Reorient or relocate the receiving antenna. · Increase the separation between the
- equipment and receiver. Connect the equipment into an outlet on a circuit different from that to which the receiver
- · Consult the dealer or an experience radio/TV technician for help.

  Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
  The device has been evaluated to meet general
- used in portable exposure condition withou This device complies with Industry Canada licence-exempt RSS standard(s).

  Operation is subject to the following two conditions: (1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device. Le présent appareil est conforme aux CNR l'Industrie Canada applicables aux apparei

(1) l'appareil ne doit pas produire de brouillage


# **Getting started**

Congratulations!Thank you for choosing the Outlander 300 BT stereo headphone. Before using the Outlander 300, users should read this manual to familiarize themselves with the BT functions of your mobile phone or other devices.

#### **Features**

- 1.3.5mm music line-in function
- 2. Supports connecting 2 phone devices
- 3. The headphone battery power status showed on iOS
- 4.qptx® audio technology

# Connection Diagram



### Illustrations

# How to use

### 1. General functions

Operation	LED Status
Power on	Blue LED flashes 2 times
Power off	Red LED flashes 2 times
Pairing	Red LED & Blue LED flashes alternately
Standby	Blue LED flashes 3 times in 5 seconds
Incoming call	Blue LED slow flash
Low battery	Red LED flashes 2 times every 2 seconds
Charging	Red LED keeps lighting during charging
	Blue LED keeps lighting charging finished

# 2. Basic Button Operations

Power on: Press multifunction button "▶" " for 2 seconds, Blue LED flashes 2 times. Headphone turned on. Power off: Press multifunction button " ▶ " "for 3 seconde, Red LED turn off after flashes 2 times, headphone turned

**Volume adjust**: Press volume up "+" or volume down button "-", for each level of desired increase. When volume reaches to Max or Minimum you will hear a voice reminder. Play/Pause: Short press multifunction button #" " music pauses. Press it again, music continues.

reverts to previous song.

Reject call: During the phone conversation, press volume up button "+" for 2 seconds, call switched to mobile phone .Press the volume up button "+" for 2

Last number redial: In standby status, continuously press headphone multifunction button "▶II" twice to redial the last number.

for 2 seconds, call mute. Press volume down button "-' for 2 seconds again, call mute function cancelled.

LED shows, charging is finished.

Reset Mode: Connect the headphone to computer via Micro USB cable. When red LED light flashes. headphone reset finished.


3.5mm music line-in function: Connect audio line in cable to 3.5 audio jack for wired music. (phone call function cannot be used in this mode.)

Auto power off: Headphone will auto power off without connecting in 30 minutes

The headphone is off status.

A) Connect the 3.5 audio wire to the headphone and

B) You can adjust volume bottom of the audio player or music player to reach right volume to listen music.




Pairing(One headphone supports connecting 2 phone devices)

Pairing with one phone or other devices Make sure the headphones is powered off.

Press and hold the multifunctional button for 5 seconds to enter into the pairing mode.

After red LED & blue LED flash alternately, there be smart voice reminding entering into pairing mode. Activate BT function on your phone or device. and search for headphone. From the list to found devices on your mobile phone, select the headphone "Outlander 300" to mobile phone, select the instruction to enter "0000" as "PIN if the mobile phone reminder appears. Headphone or device can be used to play your

# Active noise cancellation function(ANC)



When there is too much noise in your surroundings, short press the ANC key. The ANC function can effectively remove 90% of low frequency noise, providing excellent and beautiful

# Pairing with two phones or other devices at the same time

This headphone can support multi-connection to 2 devices. It can pair with two mobile phones simultaneously, taking the call from any of them. After completing pairing with the first phone, turn off the headphone,t hen re-do the paring procedure with the other phone. Once finished pairing, restart the headphone. It will automatically connect. Press both the volume "+" and volume "-" buttons simultaneously to enable the multipoint Connection function. From the list of found devices on another mobile phone, select the headphone "F6PA" to connect.

# 4. Sound quality with Aptx code

Featuring the apt-X code, the headsets can connect wirelessly to any apt-X enabled devices, vastly improving the quality to BT streaming and delivering CD quality sound

## **Kit Contents**

- 1.1x Stereo BT headphone Outlander 300
- 2.1x Charging micro USB cable
- 3.1x User manual
- 4.1x 3.5mm audio wire

# Warning

- 1. You must choose a qualified charger from a regular manufacturer to charge the headphone.
- 2. You must charge the headphone if it has not been used for more than 12 months.

## **Specifications**

Talk time: 22h 90 Oh Stand-by time: Music play time: 20h Wireless range: 10m

Wireless profiles: A2DP/ AVRCP / HSP / HFP

Impedance: 32 Ω  $115 \pm 3dB$ Sound pressure level: Frequency Response: 20Hz----20KHz

Weight: 270g Dimension: 190 x 164 x 75mm

> 尺寸: A4 材质:157G双铜 单色印刷