

Radio Frequency (RF) Signals

THIS MODEL PHONE MEETS THE U.S. GOVERNMENT'S REQUIREMENTS FOR EXPOSURE TO RADIO WAVES.

Your wireless phone contains a radio transmitter and receiver. Your phone is designed and manufactured not to exceed the emission limits for exposure to radio frequency (RF) energy set by the Federal Communications Commission of the U.S. Government. These limits are part of comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies.

The exposure standard for wireless mobile phones employs a unit of measurement known as the Specific Absorption Rate (SAR). The SAR limit set by the FCC is 1.6 W/kg.* Tests for SAR are conducted using standard operating positions accepted by the FCC with the phone transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR level of the phone while operating can be well below the maximum value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the output.

Before a phone model is available for sale to the public, it must be tested and certified to the FCC that it does not exceed the limit established by the U.S. government-adopted requirement for safe exposure. The tests are performed on position and locations (for example, at the ear and worn on the body) as required by FCC for each model. The highest SAR value for this model phone as reported to the FCC when tested for use at the ear is 0.999 W/kg, and when worn on the body, is 0.799 W/kg. (Body-worn measurements differ among phone models, depending upon available accessories and FCC requirements). While there may be differences between the SAR levels of various phones and at various positions, they all meet the U.S. government requirement.

The FCC has granted an Equipment Authorization for this model phone with all reported SAR levels evaluated as in compliance with the FCC RF exposure guidelines. SAR information on this model phone is on file with the FCC and can be found under the Display Grant section at <https://gulfoss2.fcc.gov/oetcf/eas/reports/GenericSearch.cfm> after search on FCC ID A98-TBP4266.

For body worn operation, this phone has been tested and meets the FCC RF exposure guidelines when used with an accessory designated for this product or when used with an accessory that contains no metal and that positions the handset a minimum of 1.5 cm from the body. Non-compliance with the above restrictions may result in violation of FCC RF Exposure guidelines.

* In the United States, the SAR limit for wireless mobile phones used by the public is 1.6 watts/kg (W/kg) averaged over one gram of tissue. SAR values may vary depending upon national reporting requirements and the network band.

FCC Regulations

This mobile phone complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This mobile phone has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation; if this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Calling

You can use the Phone application to make a call. You can dial an incoming, outgoing, or missed call number recorded in the call log.

Making a call

You can use the FOMA terminal to make international calls and emergency calls, as well as standard calls.

Making a call

- 1 Tap [Phone] icon on the Home screen.
- 2 Enter the phone number → tap [Phone] icon.
 - If you enter a wrong number, tap [Back] icon to delete the number.

Making an emergency call

- 1 Tap [Phone] icon on the Home screen.
- 2 Enter any emergency number (110; Police, 119; Fire department or ambulance service, 118; Japan Coast Guard) → tap [Phone] icon.

<Note>

- While the Screen lock is set, you cannot use FOMA terminal without releasing the Screen lock. However, you can only make an emergency call.
- In Japan, making an emergency call (110, 119 and 118) is not possible without a UIM.
- In Japan, making an emergency call (110, 119 and 118) is not possible from the PIN code input screen.

Ending a call

- 1 Tap [End a call] icon during a call.

Making an international call (WORLD CALL)

WORLD CALL is an international phone service that can be used from DOCOMO mobile phones.

Customers who have subscribed to the FOMA service would also have automatically subscribed to "WORLD CALL" at the same time. However, if you declined to use "WORLD CALL" when you subscribed to the FOMA services, you need to make a separate application.

1 Tap [Phone] icon on the Home screen.

2 Touch [0] for over 1 second.

- A plus sign "+" appears. When making an international call from Japan, "+" is replaced by an international call access code.

3 Enter the country code → area code → recipient's phone number, and tap [Phone] icon.

<Note>

- If the area code begins with "0", omit "0". However, "0" may be required for calling some countries or areas, such as Italy.
- For details on WORLD CALL, refer to DOCOMO "International Services website".

Receiving a call

The FOMA terminal plays a ringtone when there is an incoming call. In Silent mode, the ringtone does not sound. If the FOMA terminal has been set to Vibrate, it vibrates when there is an incoming call.

Receiving a call

1 When you receive an incoming call, tap [Answer a call] icon.

<Note>

- If the caller has been saved in Contacts, the Incoming Call screen appears. This screen displays the caller's name and phone number. If the caller is not saved in Contacts, only the phone number is displayed.

Declining a call

1 When you receive an incoming call, tap [Decline].

Operations during a call

During a call, you can adjust the call volume, turn the speaker ON/OFF, mute the microphone, and put the call on hold, depending on the usage conditions.

Adjusting the call volume

During a call, you can adjust the reception volume.

- 1 During a call, press Sidekeys.
 - The call volume changes accordingly.

Turning the speaker ON/OFF

During a call, you can put the caller onto speaker.

- 1 Tap [Speaker] icon during a call.
 - You can hear the caller's voice through the speaker.
- 2 With the speaker ON, tap [Speaker] icon.
 - You can no longer hear the caller's voice through the speaker.

<Note>

- Do not hold the FOMA terminal against your ear with the speaker ON.
- Speak into the FOMA terminal from a distance of no more than 50 cm.
If you find it difficult to hear what is being said, turn off the speaker.

Muting the microphone

During a call, you can temporarily mute the microphone.

- 1 Tap [Mute] icon during a call.
 - The caller cannot hear what you are saying.
- 2 With the microphone OFF, tap [Mute] icon.
 - The caller can hear what you are saying again.

Holding a call

- 1 During a call, tap [Hold] icon.
 - The call is put on hold.
- 2 In the hold state, tap [Unhold] icon.
 - Hold is cancelled, and you can resume the call.