
# **Boombero GREAT** Model: ZP388 Instruction manual

# FN

# PRODUCT OVERVIEW



# CONTENTS

- 1. Boombero GREAT.
- 2. USB cable
- 3. Line-in cable

## SET UP

1. Plug the BOOMBERO GREAT into an outlet using the included wall charger. 2. The Charging LED light will turn white when it is fully charged. It would take around 2.5 hr for full charge.

#### Note:

Please charge the battery at least 3 to 4 hours at the first time.

#### PAIRING BLUETOOTH<sup>®</sup> DEVICE

- 1. Pair your Bluetooth ® device to the speaker when you turn on the speaker for the first time.
- 2. The speaker pairs with devices that use the Bluetooth ® Hands Free Profile (HFP) and/or the Advanced Audio Distribution Profile (A2DP). HFP enables hands-free communication and the A2DP dictates how audio is streamed from one device to another over a Bluetooth® connection.
- 3. When you pair devices to the speaker, the devices operate accounting to their protocols.

## NFC FUNCTION WORK FLOW

- 1. Please upload NFC- BT Easy to your Android operated smart phone with NFC function if your android platform is under 4.1 version
- Please be reminded to turn on your smart phone's Bluetooth connection Tap your smart phone to NFC sensor region at the top of speaker. This refers to 3.
- "NFC" wording in white color 4. Then your smart phone will instantly pair with Bluetooth speaker for music enjoyment
- 5. To disconnect it, please tab your connected smart phone at NFC sensor region again

#### Note:

- Please ensure your smart phone is equipped with NFC function.
- To ensure your smart phone got NFC function, please find updated NFC phone list at below website at http://www.nfcworld.com/nfc-phones-list/

# PAIRING MODEL AND PAIRING


- 1. In Press and hold with the voice "Hi BOOMBERO is on" and press in to enter the pairing mode
- 3
- Select the searching mode on your Bluetooth ® device Your Bluetooth ® device should find "BOOMBERO Great", select it and pair it 4. 5. Verify that you are connected to the speaker. The Bluetooth ® LED & the
- speaker will change to a solid blue when paring is complete

# **KEY FLOWS**

### Status:

c.

- Status: "OFF" stage with rechargeable batteries not fully charged 1. DC Plug in → "RED" charging LED breathe 2 seconds a.
- 2
- Press & Hold the 003 second and power on the unit and then enter into the 3. Standby mode
- Status: "Standby mode" 4.
  - Line in plug in→ Play music immediately a.
  - 1second : "BLUE" LED flash alternatively, Enter to Press & Hold b. Bluetooth pairing mode and connect with your Bluetooth ® devices
    - Press & Hold () in 1 second and then turn-off the unit.
- Status: "Bluetooth connected" 5.
  - "RED" LED Light on ( power-on state ) a.
  - Bluetooth signal disconnected → Searching 10second and then enter b. standby if no further signal connected
  - C. Line in plug in  $\rightarrow$  Music channel change to line in signal immediately and resume Bluetooth channel immediately when line in plug out
  - in 1second  $\rightarrow$  enter Bluetooth pairing mode, Press & Hold the d. "BLUE" LED indicator flash
- 6. Status: Music plaving
  - Press vand then the music volume are going down а
- 7. Status: Music plaving



- Speaker Phone 8. When phone calling a.

  - Answer a call Press the to enter conference call b
  - to cut the incoming Reject a call - Press Hold ( 3 seconds ) the C.
  - to hang-up the call d. Hang-up a call - Press the
- D00 Play / Pause Button 9

When playing music, - Press

- $\triangleright 00$ , music playing Pause
- Press again, music resume playing (Volume are resume to before)
- MaxxBass On / Off Button (Default are ON when power on) 10.
  - When playing music (Bluetooth or Line-in) a.
    - Turn off MaxxBass function Press again – Turn On MaxxBass level 1 Press - Press "again – Turn On MaxxBass level 2

# LINE-IN FUNCTION

- 1. Plug in the line in cable into the rear of the speaker Aux in socket.
- 2. Connect the other end of the line in cable to your devices headphone socket.
- 3. Recommend to play the speaker unit at maximum sound level

## SPECIFICATIONS

Power input:	5V, 2A
Total output:	8W, (4W/Channel)
	Passive Radiator
Playtime (via Bluetooth <sup>®</sup> connect):	Approximately 8~10 hours
Recharging Time:	25 hours
Dimension:	208 X 65 X 91mm
Audio input	3.5mm Line-in jack, Bluetooth 3.0(A2DP)
Wireless	Bluetooth 3.0, NFC
Built Battery	3.7V, 2200mAh Li-Polymer battery

# WARNINGS

Before using this product, please kindly read these safety warnings and cautions carefully to ensure your personal safety and prevent property damage. Please retain this manual for future reference. Please kindly read the instructions for BOOMBERO Great Bluetooth Speaker.

# IMPORTANT SAFETY INSTRUCTIONS

- Observe all warnings, precautions and instructions
- Please keep out of the reach of the children.
- Please read all safety warnings and instructions that require an electrical devices that require an electrical device or radio product to be switched off in designated areas such as gas/refueling stations, hospitals, blasting areas, potentially explosive atmospheres or aircraft.
- Dispose of the BOOMBERO Great and its batteries in accordance with local regulations. Do not dispose of the battery with regular household waste.

# PRECAUTIONS

- Do not expose the speaker to high temperature, high humidity, rain or direct sunlight. Do not use the BOOMBERO Great near a bathtub, sink, sauna, pool, or steam room. Expose of the BOOMBERO Great to moisture could result in electric shock.
- Do not throw or drop the speaker or subject it to strong physical shock.
- Do not disassemble, open, crush, bend, deform, puncture, shred, microwave, incinerate, paint, or insert foreign object into the BOOMBERO Great. Such actions could result in electric shock.
- Do not allow liquid or small particles to get into the speaker
- Use a soft and dry cloth to clean the headset. Do not use solvents or other chemicals. Do not wipe with a chemically treated cleaning cloth.
- Do not keep your BOOMBERO Great near open flames such as cooking burners, candles or fireplaces.
- Do not block any ventilation openings.
- Do not place the BOOMBERO Great on high surfaces such as shelves, the speaker may shift and fall off from shelves when the speaker plays.

#### WHEN CHARGING

- Only charge the battery in accordance with the user instructions supplied with the BOOMBERO Great.
- Do not attempt to replace your BOOMBERO Great battery, it is built-in and is not changeable.
- Use only the manufacturer supplied charger to charge your BOOMBERO Great. Other chargers may look similar, but using them could result in electric shock and could damage the BOOMBERO Great.
- Do not charge the BOOMBERO Great in damp areas or in extremely high or low temperatures because this could result in electric shock.
- Do not clean the BOOMBERO Great when it is being charged. Always unplug the charger first before cleaning the BOOMBERO Great.
- The AC adapter is as disconnect device, the socket-outlet shall be installed near the equipment and shall be easily accessible

#### NOTE:

The technical specifications for this product and the contents of the user manual are subject to change without notice.

# ABOUT OREGON SCIENTIFIC

Visit our website <u>www.oregonscientific.com</u> to learn more about Oregon Scientific products.

For any enquiry, please contact our Customer Services at info@oregonscientific.com

## **EU-DECLARATION OF CONFORMITY**

Hereby, Oregon Scientific, declares that this Boombero GREAT (model: ZP388) is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. A copy of the signed and dated Declaration of Conformity is available on request via our Oregon Scientific Customer Service.



COUNTRIES RTTE APPROVED COMPLIED All EU countries, Switzerland

and Norway 🕚

© 2013 Oregon Scientific. All rights reserved.

Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED CHANGES OR MODIFICATIONS TO THIS EQUIPMENT. SUCH CHANGES OR MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- -- Reorient or relocate the receiving antenna.
- -- Increase the separation between the equipment and receiver.
- -- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- -- Consult the dealer or an experienced radio/TV technician for help.