

NOKIA 6820

USER GUIDE



Your office on the road

Nokia 6820 User Guide

What information is needed?	Numbers	Where is the number?
My number		Wireless service provider
Voice mail number		Wireless service provider
Wireless provider's number		Wireless service provider
Provider's customer care		Wireless service provider
Model number	6820	Title page and phone label (under battery)
Phone type		Phone label
IMEI number		Phone label

LEGAL INFORMATION

CE 168

DECLARATION OF CONFORMITY

We, NOKIA CORPORATION declare under our sole responsibility that the products NHL-9 and RH-26 are in conformity with the provision of the following Council Directive: 1999/5/EC. A copy of the Declaration of Conformity can be found from http://www.nokia.com/phones/declaration_of_conformity/

PART NO. 9231553, ISSUE NO. 1

Copyright © 2004 Nokia. All rights reserved.

Nokia, Nokia Connecting People, Nokia 6820, Pop-Port, Nokia Tune, and the Nokia Original Enhancements logos are trademarks or registered trademarks of Nokia Corporation. Other company and product names mentioned herein may be trademarks or trade names of their respective owners.

Printed in Canada 11/2004.

Bluetooth is a registered trademark of Bluetooth SIG, Inc.

US Patent No 5818437, and other pending patents. T9 text input software
Copyright © 1999-2003. Tegic Communications, Inc. All rights reserved.



Includes RSA BSAFE cryptographic or security protocol software from RSA Security.



Java is a trademark of Sun Microsystems, Inc.

The information contained in this user guide was written for the Nokia 6820 product. Nokia operates a policy of ongoing development. Nokia reserves the right to make changes to any of the products described in this document without prior notice.

UNDER NO CIRCUMSTANCES SHALL NOKIA BE RESPONSIBLE FOR ANY LOSS OF DATA OR INCOME OR ANY SPECIAL, INCIDENTAL, AND CONSEQUENTIAL OR INDIRECT DAMAGES HOWSOEVER CAUSED. THE CONTENTS OF THIS DOCUMENT ARE PROVIDED "AS IS." EXCEPT AS REQUIRED BY APPLICABLE LAW, NO WARRANTIES OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, ARE MADE IN RELATION TO THE ACCURACY AND RELIABILITY OR CONTENTS OF THIS DOCUMENT. NOKIA RESERVES THE RIGHT TO REVISE THIS DOCUMENT OR WITHDRAW IT AT ANY TIME WITHOUT PRIOR NOTICE.

EXPORT CONTROLS

This device may contain commodities, technology or software subject to export laws and regulations from the US and other countries. Diversion contrary to law is prohibited.

FCC/INDUSTRY CANADA NOTICE

Your device may cause TV or radio interference (for example, when using a telephone in close proximity to receiving equipment). The FCC or Industry Canada can require you to stop using your telephone if such interference cannot be eliminated. If you require assistance, contact your local service facility. This device complies with part 15 of the FCC rules. Operation is subject to the condition that this device does not cause harmful interference.

Contents

	For your safety	1
	Quick Guide	4
1	Welcome to Nokia	5
	About your phone	5
	Overview of phone functions	5
	Network services	6
	Shared Memory	6
	Accessibility solutions	6
2	Phone setup	7
	Connectors	7
	Install SIM card and battery	7
	Charge the battery	9
	Switch the phone on and off	9
	How to hold your phone	9
	How to get help	10
3	Phone basics	11
	Open the keyboard	11
	Key functions (keyboard closed)	13
	Key functions (keyboard open)	14
	About the five-way joystick	15
	The standby mode	15
	Customize the Go to menu	16
	Switch the keyboard lights on or off	16
	Keypad lock (keyguard)	18
	Over-the-air settings service	18
4	Call functions	19
	Make a call	19
	Answer or reject an incoming call	20
	Options during a call	20
5	Text entry	22
	Write text with the keyboard open	22
	Write text with the keyboard closed	23
6	The menu	25
	Scroll to a menu function	25
	Menu shortcuts	25

7	Messages	26
	Text messages (SMS)	26
	Archive folder and custom folders	28
	Text and picture templates	28
	Manage distribution lists	29
	Text message counter	29
	Multimedia messages	30
	Delete messages	32
	E-mail messages	32
	Voice messages	34
	Info messages	35
	Message settings	35
	E-mail settings	36
	Font size setting	37
	Service commands	37
8	Call log	38
	Recent call lists	38
	Timers and counters	38
9	Contacts	40
	Contacts settings	40
	Add contacts	40
	Search for a contact	41
	Delete contacts	42
	Edit or delete details in contacts	42
	Copy contacts	42
	Send and receive business cards	42
	Speed dialing	43
	Voice dialing	43
	Save numbers on the SIM card	44
	Caller groups	44
10	Settings	45
	Profiles	45
	Tone settings	45
	Display settings	46
	Time and date settings	46
	Personal shortcuts	47
	Connectivity and related settings	47

EGPRS modem settings	51
Call settings	51
Phone settings	52
Enhancement settings	53
Security settings	53
Restore factory settings	55
11 Gallery	56
12 Camera	58
Camera settings	58
Take a photo	58
Record a video clip	59
13 Organizer	60
Alarm clock	60
Calendar	60
To-do list	62
Notes	62
Wallet	63
Synchronization	65
14 Applications	68
Games	68
Collection	69
Extras	70
15 Services	73
Phone setup	73
Browse the pages of a service	74
Use the phone keys while browsing	74
Options while browsing	74
Bookmarks	76
Downloads	76
Service inbox	76
Cache memory	77
Browser security	77
16 SIM services	79
17 PC connectivity	80
PC Suite	80
Data communications applications	81

18	Enhancements	82
	Safety	82
	Enhancements for your phone	82
19	Reference Information	83
	Battery information	83
	Enhancements, Batteries, and Chargers	83
	Care and maintenance	84
	Additional safety information	84
	Technical information	88
	Nokia One-Year Limited Warranty	89
	Appendix A	91
	Index	95

For your safety

Read these simple guidelines. Not following them may be dangerous or illegal. Read the complete user guide for further information.



SWITCH ON SAFELY

Do not switch the phone on when wireless phone use is prohibited or when it may cause interference or danger.



ROAD SAFETY COMES FIRST

Obey all local laws. Always keep your hands free to operate the vehicle while driving. Your first consideration while driving should be road safety.



INTERFERENCE

All wireless phones may be susceptible to interference, which could affect performance.



SWITCH OFF IN HOSPITALS

Follow any restrictions. Switch the phone off near medical equipment.



SWITCH OFF IN AIRCRAFT

Follow any restrictions. Wireless devices can cause interference in aircraft.



SWITCH OFF WHEN REFUELING

Don't use the phone at a refueling point. Don't use near fuel or chemicals.



SWITCH OFF NEAR BLASTING

Follow any restrictions. Don't use the phone where blasting is in progress.



USE SENSIBLY

Use only in the normal position as explained in the product documentation. Don't touch the antenna unnecessarily.



QUALIFIED SERVICE

Only qualified personnel may install or repair this product.



ENHANCEMENTS AND BATTERIES

Use only approved enhancements and batteries. Do not connect incompatible products.



WATER-RESISTANCE

Your phone is not water-resistant. Keep it dry.



BACK-UP COPIES

Remember to make back-up copies or keep a written record of all important information stored in your phone.



CONNECTING TO OTHER DEVICES


When connecting to any other device, read its user guide for detailed safety instructions. Do not connect incompatible products.



EMERGENCY CALLS

Ensure the phone is switched on and in service. Select **End** as many times as needed to clear the display and return to the main screen. Enter the emergency number; then select the **Talk** key. Give your location. Do not end the call until given permission to do so.

Nokia 6820 phone at a glance



Quick Guide

Make a call	Enter a phone number, and press the Talk key.
Answer a call	Press the Talk key, or select Loudspeaker .
Answer call during call	Press the Talk key.
End a call	Press the End key.
Decline a call	Press the End key (sends the call to voice mail, if available).
Mute a call	Select Mute during a call.
Redial	Press the Talk key twice.
Adjust call volume	Press the joystick to the left or the right.
Use the in-call menu	Select Options during a call.
Save a name and number	Enter a number, select Save , enter a name, and select OK .
Use 1-touch dialing	Press and hold a key (2–8). You must first assign a key to a number in the phone book.
Look up a name	Select Names > Find .
Check voice mail	Press and hold the 1 key. (Contact your service provider for details.)
Write and Send a text message	Select Menu > Messages > Text Messages > Create Message . Write the message, select Send , enter the phone number, and select OK .
Send a picture, video, or audio file	Select Menu > Gallery . Select a folder and locate the item you wish to send. Select Options > Send . Enter the phone number and select OK .
Read a new message	If New Message appears, select Read , highlight the message, and select Read again.
Reply to a message	After viewing a message, select Reply . Write your reply and select Send .
Press	Press a key briefly and release it.
Press and hold	Press a key, hold it for two to three seconds, and release it.



1 Welcome to Nokia

Congratulations on your purchase of the Nokia 6820 mobile phone.

• ABOUT YOUR PHONE

The Nokia 6820 phone comes in two model types—the Nokia 6820a phone, which is approved for use in 900, 1800, and 1900 MHz GSM networks, and the Nokia 6820b phone which is approved for use in 850, 1800, and 1900 MHz GSM networks.

To view your model type, refer to the information label under the battery. For more information about where this label is located, see “Find the information label” on page 10.

When using the features in this device, obey all laws and respect privacy and legitimate rights of others.



Warning: To use any features in this device, other than the alarm clock, the phone must be switched on. Do not switch the device on when wireless phone use may cause interference or danger.

• OVERVIEW OF PHONE FUNCTIONS

Your Nokia 6820 phone provides many useful features:

Messaging keyboard—provides a complete keyboard designed for easy text writing. You can use all of the phone functions with the keyboard either closed or open. When you open the keyboard you have the extra benefit of a full messaging keyboard.

Speakerphone—allows you to have hands-free conversations. You can activate the loudspeaker at any time during a call. To activate the speakerphone, select **Loudsp**. To deactivate the speakerphone during a call, select **Handset**.

EDGE (enhanced data rates for GSM evolution)—allows you to use EDGE packet transmission networks for connections that are faster than GPRS.

XHTML browser—allows you to retrieve and view colourful and rich graphical content from Web servers.

Instant messaging—lets you send short text messages that are delivered to online users.

E-mail—lets you write, send, and retrieve e-mail from your compatible e-mail account.

MMS (multimedia messaging service)—lets you send and receive multimedia messages containing text, pictures, sound or video clips to and from compatible devices. You can save the pictures and ringing tones on your phone.

GPRS (general packet radio service)—allows your phone to send and receive data over a mobile network. Applications such as WAP, MMS and SMS messaging, and Java™ may use GPRS.

Polyphonic sound—consists of several sound components that are played at the same time. The phone has sound components from over 40 instruments and can play up to 16 instruments at the same time. The phone supports scalable polyphonic MIDI (SP-MIDI) format.

J2METM (Java 2 Micro Edition) support—lets you play the included Java applications and games and supports many applications and games that you can download.

OTA (over-the-air) settings service—allows you to receive WAP, MMS, GPRS and other wireless service settings directly as an OTA message. You only need to save the settings on your phone. For more information on the availability of the settings, contact your service provider or the nearest authorized Nokia dealer.

• NETWORK SERVICES

To use the phone you must have service from a wireless service provider. Many of the features in this device depend on features in the wireless network to function. These Network Services may not be available on all networks or you may have to make specific arrangements with your service provider before you can utilize Network Services. Your service provider may need to give you additional instructions for their use and explain what charges will apply. Some networks may have limitations that affect how you can use Network Services. For instance, some networks may not support all language-dependent characters and services.

Your service provider may have requested that certain features be disabled or not activated in your device. If so, they will not appear on your device menu. Contact your service provider for more information.

• SHARED MEMORY

The following features in this device may share memory: contacts, text, IM and multimedia messages, e-mail, voice tags and SMS distribution lists, images, ringing tones, video and sound clips in the gallery, camera, calendar, to-do notes, Java games, applications, and the notes feature. Use of one or more of these features may reduce the memory available for the remaining features sharing memory. For example, saving many images may use all of the available memory. Your phone may display a message that the memory is full when you try to use a shared memory feature. In this case, delete some of the information or entries stored in the shared memory features before continuing. Some of the features, such as calendar notes, may have a certain amount of memory specially allotted to them in addition to the amount of memory shared with other features.


• ACCESSIBILITY SOLUTIONS

Nokia is committed to making mobile phones easy to use for all individuals. Nokia maintains an Internet site that is dedicated to accessibility solutions. For more information about phone features, enhancements, alternate format user guides, and other Nokia products designed with your needs in mind, visit the Web site at www.nokiaaccessibility.com or call 1-888-226-6542.

2 Phone setup

• CONNECTORS

- 1 Connector for battery charger.
- 2 Connector for headsets, data cable and other accessories.
- 3 Connector for microphone.




• INSTALL SIM CARD AND BATTERY

Keep all SIM cards out of the reach of small children. For availability and information on using SIM card services, contact your SIM card vendor. This may be the service provider or another vendor.



The SIM card and its contacts can be easily damaged by scratches or bending, so be careful when handling, inserting, or removing the card.

Before installing the SIM card, always make sure that the phone is switched off and disconnected from the charger or any enhancement; then remove the battery.

- With the back of the phone facing you, push the back cover release button (1) and, at the same time, lift the back cover off the phone (2)
- Slide the battery into the back cover (3) until you hear it click into place.





Important: Insert the battery exactly as shown in the diagram. The contacts on the battery must be aligned with the contacts on the phone for the phone to operate.




- To release the SIM card holder, slide the card holder backwards (4), and open it by lifting it up (5).
- Insert the SIM card into the SIM card holder (6).

Make sure that the SIM card is properly inserted and that the golden contact area on the card is facing downwards.

- Close the SIM card holder (7) and slide it back into place (8).




- Direct the back cover towards the locking catches on the inside of the phone (9), and slide the back cover until it locks into place (10).



• CHARGE THE BATTERY

- 1 Connect the charger to a wall socket.
- 2 Connect the lead from the charger to the socket on the bottom of your phone.

Charging appears briefly if the phone is switched on. If the battery is completely discharged, it may take a few moments before the charging indicator appears on the display or before any calls can be made.



You can use the phone while the charger is connected.

Charging time depends on the charger and the battery used. For example, charging a BL-5C battery with the ACP-12U travel charger takes about 1 and a half hours while the phone is in the standby mode.

• SWITCH THE PHONE ON AND OFF

To switch on the phone, select and hold the **Power** key.

- If the phone prompts you for a PIN code or a security code, key in the code and select **OK**. (For more information, see "Access codes" on page 54.)
- If the phone displays **Insert SIM card**, even though the SIM card is properly inserted, or **SIM card not supported**, contact your provider. Your phone does not support 5-V SIM cards.



• HOW TO HOLD YOUR PHONE

Hold the phone as shown with the antenna area pointing up.



TIPS ON EFFICIENT OPERATION: Your phone has a built-in antenna. As with any other radio transmitting device, do not touch the antenna unnecessarily when the phone is switched on. Contact with the antenna affects call quality and may cause the phone to operate at a higher power level than otherwise needed. Not touching the antenna area during a phone call optimizes the antenna performance and the talk time of your phone.




• HOW TO GET HELP

If you need help, Nokia Customer Care is available for assistance.

Find the information label

We recommend that you obtain the label information so it can be available if you call. This information is on the back of the phone, beneath the battery.

- The international mobile equipment identity (IMEI) number
- The phone model number



Contact Nokia

Please have your phone or enhancement with you when you place the call.


Nokia Customer Care Center, USA	Customer Care, Canada
Nokia Inc. 7725 Woodland Center Boulevard Suite 150 Tampa, Florida 33614 Tel: 1-888-NOKIA-2U (1-888-665-4228) Fax: 1-813-249-9619 TTY: 1-800-24-NOKIA (hearing impaired only) (1-800-246-6542)	Nokia Products Ltd. 601 Westney Road South Ajax, Ontario L1S 4N7 Tel: 1-888-22-NOKIA (1-888-226-6542) 1-905-427-1373 Fax: 1-905-619-4360 Web site: www.nokia.ca

3 Phone basics


Your phone can be used with the keyboard open or closed.

- **OPEN THE KEYBOARD**


- 1 Hold the phone with both hands, and open the keyboard as shown.



- 2 Extend the keyboard until you hear it click into place.




- 3 Turn the phone to a horizontal position and hold it as shown.



• KEY FUNCTIONS (KEYBOARD CLOSED)


- 1 **Power** key (⏻)—switches the phone on and off. When the keypad is locked, it turns the phone display lights on for about 15 seconds.
- 2 **Left selection** key (↙)—becomes **Left selection** key when the keyboard is open. This key has no function when the keyboard is closed.
- 3 **Left selection** key (↙) and **right selection** key (↘)—provides a variety of functions that are indicated in guiding text on the display above the keys.
- 4 Five-way joystick (⬆)—moves in four directions and selects the active menu option when pressed. For details, see "About the five-way joystick" on page 15.
- 5 **Talk** key (☎)—dials a phone number and answers a call. In the standby mode it accesses the list of most recently called numbers.
- 6 **End** key (⏻)—ends an active call or exits from the current function.
- 7 Typing keys—enters numbers and characters.




Note: Some phones may not display the mobile Internet symbol on the (0) key.

• KEY FUNCTIONS (KEYBOARD OPEN)

When the keyboard is opened, the display graphics rotate 90 degrees and the **Left**, **Middle**, and **Right** selection keys change positions. The guiding text near the **Left** and **Right** selection keys does not change.



- 1 **Keyboard light** key ()—switches the keyboard light on or off.
- 2 **Power** key ()—switches the phone on and off.
- 3 Five-way joystick ()—moves in four directions and selects the displayed menu option. (See illustration.)
- 4 **Backspace** key ()—deletes characters.
- 5 **Character** key ()—opens a set of characters and symbols during text writing.
- 6 **Shift** keys (and)—enters upper case letters and symbols. You can either press the **Shift** key first and then the desired key or press both keys at the same time.
- 7 **Space bar** keys (and)—enters a space.
- 8 **Talk** key ()—dials a phone number and answers a call. In the standby mode it accesses the list of most recently called numbers.
- 9 **Left selection** key () and **Right selection** key ()—selects the menu option shown in the guiding text displayed above the key.
- 10 **End** key ()—ends an active call or exits from a function.
- 11 **Enter** key ()—starts a new line when writing text.



• ABOUT THE FIVE-WAY JOYSTICK


The five-way joystick provides a variety of functions:

- Allows you to scroll through lists.
- Moves the cursor up and down, right and left when writing text, using the calendar, and in some game applications.
- Selects the active menu item when pressed briefly (or confirms a selection).
- Adjusts the volume when moved to the left (to decrease volume) or to the right (to increase volume) during a call.
- Activates the camera when moved up in the standby mode.
- Opens the text editing screen to write a text message when moved to the left in the standby mode.
- Opens the calendar when moved to the right in the standby mode.
- Opens the contacts list when moved down in the standby mode.

• THE STANDBY MODE

When the phone is ready for use (the keyboard can be either closed or open), and you have not keyed in any characters, the phone is in the standby mode. The following list describes the sections of the screen while in the standby mode. (For detailed descriptions of the screen icons, see "Icons in the standby mode" on page 16.)

- 1 **Network**—shows the name of the network or the operator logo, to indicate in which cellular network the phone is currently being used.
- 2 **Signal strength**—shows the signal strength of the cellular network at the current location. The higher the bar, the stronger the signal.
- 3 **Battery charge**—shows the battery charge level. The higher the bar, the more power in the battery.
- 4 **Left selection key menu option**—shows the menu option, which is **Go to** in standby mode.
- 5 **Menu**—shows the joystick menu option.
- 6 **Right selection key menu option**—shows the **Right selection** key menu option that can be customized to display your preferred shortcut. The default setting is **Contact**, which accesses the **Contacts** menu. To choose your own menu option for this key, see "Personal shortcuts" on page 47.



• CUSTOMIZE THE GO TO MENU

Use these steps to customize the **Go to** menu.

- 1 Select **Go to** to view the list of shortcuts in your personal shortcut list.
- 2 To add items to the **Go to** menu, or remove items from the menu, choose **Options > Select Options**.
Scroll to the desired function and select **Mark** to add it to the shortcut list. To remove a function from the list, select **Unmark**.
- 3 To rearrange items in the **Go to** menu, choose **Options > Organize**.
Select the desired function and select **Move**; then select the location where you want to move the function.

• SWITCH THE KEYBOARD LIGHTS ON OR OFF

When you open the keyboard, the main display is lit, but the keyboard lights do not automatically illuminate. To turn on the keyboard lights, press the **Keyboard light** key , located on the top left corner of the keyboard. The keyboard lights are switched off after a certain time, but they are turned on again as soon as you press any key. To switch the keyboard lights off, press the **Keyboard light** key or close the keyboard.

Screensaver

With the keyboard closed, the phone automatically activates a screensaver while in the standby mode. This occurs after a certain length of time when none of the phone functions have been used. For more information on the display, see "Display settings" on page 46.

Wallpaper

You can set your phone to display a background picture as wallpaper when the phone is in the standby mode. For information on customizing your wallpaper, see "Display settings" on page 46.

Icons in the standby mode

Icon	Indicates...
------	--------------



You have one or more new text or picture messages.



You have one or more new multimedia messages.



Your phone is connected to the IM service and the availability status is online or offline, respectively.



You have one or more IM messages and you are connected to the IM service.

Icon	Indicates...
	The phone keypad is locked.
	The phone will not ring for an incoming call or a text message because Incoming call alert and Message alert tone are set to Off .
	The alarm clock is set to On .
	The countdown timer is running.
	The stopwatch is running in the background.
	The EGPRS connection mode is set to Always online and EGPRS service is available.
	An EGPRS connection is active.
	The EGPRS connection is suspended (on hold).
	There is an active IR connection.
	Your calls are forwarded to another number. If you have two phone lines, the icon for the first line is  and for the second line is  .
1 or 2	The selected phone line (only appears if you have two phone lines).
	The loudspeaker is activated.
	Calls are limited to a closed user group. See "Security settings" on page 53.
	The timed profile is selected.
	A headset enhancement is connected to the phone.
	A hands-free enhancement is connected to the phone.
	A loopset enhancement is connected to the phone.
	A music stand enhancement is connected to the phone.

• KEYPAD LOCK (KEYGUARD)

The keyguard feature locks the keypad to prevent the keys from being accidentally pressed. You can lock the keypad only when the keyboard is closed.

Security keyguard is an additional feature that allows you to set up a code to unlock your phone before use. For information on security keyguard, see "Phone settings" on page 52.



Note: When keyguard is on, calls may be possible to the emergency number programmed into your phone. Key in the emergency number and press the **Talk** key . The number is displayed only after you have keyed in its last digit.

LOCK THE KEYPAD

- In the standby mode, select **Menu**; then press the * key within 1.5 seconds.
- To lock the keypad during a call, select **Options > Lock Keypad**.
- To answer a call when keyguard is on, press the **Talk** key. During the call, the phone can be operated normally. When you end or reject the call, the keypad automatically locks.

UNLOCK THE KEYPAD

Select **Unlock**; then press the * key within 1.5 seconds, or open the keyboard. The keyguard does not automatically reactivate when you close the keyboard.

• OVER-THE-AIR SETTINGS SERVICE

To use wireless services such as MMS and EGPRS, you need to have proper connection settings on your phone. These settings may have already been set up by your service provider. If not, you may obtain the settings directly as an OTA message, and save them on your phone. For more information, contact your service provider.

You may be able to receive the connection settings for EGPRS, multimedia messages, synchronization, e-mail, and multimode browser.

When you have received the connection settings as an OTA message, **Connection settings received** is displayed.

- To save the settings, select **Options > Save**. If the phone prompts you to enter the PIN code for the settings, key in the PIN code and select **OK**. To obtain the PIN code, contact the service provider that supplies the settings. If no settings have been saved yet, the settings are saved under the first free connection set.
- To view the received settings first, select **Options > View**. To save the settings, select **Save**.
- To discard the received settings, select **Options > Discard**.

To activate the settings, see "Connect to a service" on page 74.

4 Call functions

• MAKE A CALL

You can make a call with the keyboard open or closed. If you open the keyboard, the loudspeaker automatically activates.

Enter the phone number

- 1 Key in the phone number, including the area code.

If you key in an incorrect character, select **Clear** to delete it. To make a call when the keyboard is open, key in the phone number using the number keys.

For international calls, press the * key twice for the international prefix or, if the keyboard is open, press +. (The + character replaces the international access code.) Then key in the country code, the area code (without the leading 0), if necessary, and the phone number.

- 2 Press the **Talk** key to call the number.
- 3 Press the **End** key to end the call or to cancel the call attempt.



Note: To adjust the volume during a call, move the joystick to the right to increase the volume or to the left to decrease the volume.

For more information, see "Options during a call" on page 20.

Use the contact list

- 1 Select **Names > Find** and select a name from the list.
- 2 Choose a phone number for the contact and press the **Talk** key.
- 3 Press the **End** key to end the call or to cancel the call attempt.

To search for a name/phone number that you have saved in **Contacts**, see "Search for a contact" on page 41.

Last number redial

In the standby mode, press the **Talk** key once to access the list of the last 20 numbers you called or attempted to call. Scroll to the number or name that you want, and press the **Send** key to call the number.

Call your voice mailbox

In the standby mode when the keyboard is closed, press and hold the **1** key, or press the **1** key, then the **Talk** key. When the keyboard is open, press and hold the corresponding number key on the keyboard.

If you are prompted to supply a voice mailbox number, key it in and select **OK**. Contact your service provider to obtain your voice mailbox number. For more information, see "Voice messages" on page 34.

Speed dial a phone number

Before you can use 1-touch dialing you need to assign speed dial numbers. For more information, see "Speed dialing" on page 43.

If **1-touch dialing** is set to off, press the speed dialing number and then press the **Talk** key.

If **1-touch dialing** is set to on, press and hold a speed dialing key until the call is started.



Note: To activate 1-touch dialing, select **Menu > Settings > More Settings > Call settings > 1-touch dialing > On**.

• ANSWER OR REJECT AN INCOMING CALL

Press the **Send** key to answer an incoming call, and press the **End** key to end the call.

Press the **End** key to reject an incoming call.

If you select **Silence**, only the ringing tone is muted. Then, either answer or reject the call.

If you are using a headset with a headset key, you can also answer and end a call by pressing the headset key.

If the **Call forwarding** function has been activated to forward calls, rejecting an incoming call will also forward the call. See "Call settings" on page 51.

Caller ID

When there is an incoming call, the phone shows the caller's name, phone number, or the text **Private number** or **Call**.

If more than one name is found in **Contacts** with the same seven last digits of the phone number as the caller's number, only the phone number will be displayed (if it is available).

If the caller's number has not been saved in **Contacts**, but there is another name saved with the same seven last digits in the phone number as in the phone number of the caller, the phone may display an incorrect name.

Call waiting

During a call, press the **Send** key to answer the waiting call. The first call is put on hold. Press the **End** key to end the active call.

To activate call waiting, see "Call settings" on page 51.

• OPTIONS DURING A CALL

Many of the options during a call are dependent on network services. For availability, contact your service provider.

When you select **Options** during a call, you can select one of the following basic options: **Lock keypad**, **Record**, **End call**, **New call**, **End all calls**, **Contacts**, **Menu**, **Mute** or **Unmute**, **Hold** or **Unhold**, **Private**, **Answer** and **Reject**.

The following options are also available:

Conference—allows you to make a conference call that allows up to five people to take part in a conference call. During a call, make a call to a new participant (**New call**). The first call is put on hold. When you have answered the new call, select **Conference** to include the first participant in the call. To have a private conversation with one of the participants, select **Private** and select the participant. To rejoin the conference call after a private conversation, select **Conference**.

Touch tones—sends DTMF (dual tone multifrequency) tone strings, such as passwords or bank account numbers. The DTMF system is used by all touch-tone telephones. Key in the DTMF string, or search for it in contacts. You can key in the wait character (w) and the pause character (p) by repeatedly pressing the * key.

Swap—switches between the active call and the call on hold, **Transfer** to connect a call on hold to an active call and to disconnect yourself from the calls.

Loudspeaker—activates the loudspeaker during a call. Do not hold the phone to your ear during loudspeaker operation. To activate the loudspeaker, open the keyboard or, if the keyboard is closed, select **Options > Loudspeaker** or select **Loudsp.**, if available.

During a call with the keyboard open, you can select **Handset** to deactivate the loudspeaker or close the keyboard. When the keyboard is closed, select **Options > Handset** or select **Handset**, if available to deactivate the loudspeaker.

The loudspeaker is deactivated automatically when you end a call (or a call attempt), when you connect a compatible hands-free unit or a headset to the phone, or when you close the keyboard.

If you have connected a compatible hands-free unit or a headset to the phone, the **Handset** option is replaced with **Handsfree** or **Headset** and the selection key **Handset** is replaced with **Handsfr.** or **Headset** respectively.

5 Text entry

Your phone is specifically designed for easy and comfortable text writing. The easiest way to write is using your thumbs to type on the messaging keyboard. You can start writing a message using the keyboard, close the keyboard and continue writing with either traditional or predictive text input. Predictive text input is not available when the keyboard is open.

• WRITE TEXT WITH THE KEYBOARD OPEN

When the keyboard is open, you can start to write a message in several ways.

- Select **Menu > Messages > Text messages > Create message**.
- Move the joystick to the left in the standby mode.
- Press any of the letter keys in the standby mode (except the pause character *p* or the waiting character *w*) to open **Notes**.

AVAILABLE FUNCTIONS

The following functions are available when writing text with the keyboard open:

- To insert a number, press a number key. (If you pressing a number key in the standby mode, it initiates a normal call procedure.)
- To switch between the lower and upper case, indicated by **Abc**, **abc** or **ABC** on the top left of the display, or to key in symbols, press the **Shift** keys on the keyboard. You can either press a **Shift** key and the desired character consecutively, or press and hold a **Shift** key and the desired letter key at the same time.
- To write in upper case only, press one of the **Shift** keys twice.
- To delete characters from the display, press the **Backspace** key or select **Clear**. Press the **Backspace** key briefly to clear one character at a time. Use a longer keypress to delete characters more quickly.
- To add a space, press one of the **Space** keys at the bottom of the keyboard.
- To create a line break, press the **Enter** key.

TYPING ACCENTED CHARACTERS

The characters available depend on the language selected in the **Phone language** menu. To type accented characters or symbols that are not printed on the keyboard, do one of the following:

- To access a set of punctuation marks, accented characters, and symbols, press the **Character** key. Scroll through the character set by moving the joystick, and select **Insert** to enter the selected character.
- To type an accented character that is not included in the list of special characters under the **Character** key, such as á, press and hold the **Character** key and simultaneously press “a” repeatedly until the desired accented variant of “a” appears on the display.

• WRITE TEXT WITH THE KEYBOARD CLOSED

You can use predictive or traditional text input when the keyboard is closed. During writing, predictive text input is indicated by  and traditional text input by  on the top left of the display. You can change the character case (shown as **Abc**, **abc** or **ABC**) by pressing the **#** key. The number mode is indicated by **123**, and you can change between the letter and number modes by pressing and holding the **#** key.

Set predictive text on or off

Predictive text anticipates the words you are typing to make text entry more efficient. This feature is available when the keyboard is closed.

To use the dictionary, select **Options > Predictive text** when writing or editing text. Then, select a language from the dictionary options list. Predictive text input is only available for the languages on the list.

To revert to traditional text input, select **Prediction off**.

To quickly set the predictive text input on or off when writing text, press the **#** key twice, or press and hold **Options**.

Predictive text

You can key in any letter with a single keypress. Predictive text is based on a built-in dictionary to which you can also add new words. For more instructions for writing text, see "Tips for writing text" on page 24.

- 1 Start writing a word using the **2–9** keys.

Press each key once for one letter. The word may change after each keystroke. For example, to write *Nokia* with the English dictionary selected, press the **6** key once for *N*, the **6** key once for *o*, the **5** key once for *k*, the **4** key once for *i*, and the **2** key once for *a*. To insert a number while in letter mode, press and hold the desired number key.

- 2 When you have finished writing the word and it is correct, confirm it by pressing the **0** key to add a space or by moving the joystick to the right.
- 3 If the word is not the one you are looking for, press the ***** key repeatedly or select **Options > Matches**.
- 4 When the word you want appears, confirm it.

If the **?** character appears after the word, the word that you intended to write is not in the dictionary.

- 5 To add a word to the dictionary, select **Spell**, key in the word (traditional text input is used) and select **Save**.

When the dictionary becomes full, the new word replaces the oldest one that was added.

- 6 Start writing the next word.

COMPOUND WORDS

Key in the first part of the word and confirm it by moving the joystick to the right. Write the last part of the word and confirm it by moving the joystick to the right.

Traditional text input

Press a number key **1–9**, repeatedly until the desired character appears. The characters available depend on the language selected in the **Phone language** menu.

To insert a number while in letter mode, press and hold the desired number key.

- If the next letter you want is located on the same key as the present one, wait until the cursor appears, or move the joystick to the right and key in the letter.
- To access the most common punctuation marks and special characters, use the **1** key.

Tips for writing text

The following functions may also be available for writing text in predictive or traditional input:

- To insert a space, press the **0** key.
- To move the cursor to the right, left, up or down, move the joystick respectively.
- To delete a character from the display, select **Clear**. Press and hold **Clear** to delete the characters more quickly.
To delete all the characters simultaneously when writing a message, select **Options > Clear text**.
- To insert a word that is not in the dictionary when using predictive text input, select **Options > Insert word**. Write the word using traditional text input and select **Save**. The word is also added to the dictionary.
- To insert a special character when using traditional text input, press the ***** key. When using predictive text input, press and hold the ***** key, or select **Options > Insert symbol**.
Move the cursor with the joystick to a character, and select **Use** to select it.
- You can also scroll to a character by pressing the **2, 4, 6, and 8** keys, and select it by pressing the **5** key.

The following options are available when writing text messages:

- To insert a phone number while in letter mode, select **Options > Insert number**. Key in the number or select **Find** to search for it in **Contacts**. When done, select **OK**.
- To insert a name from **Contacts**, select **Options > Insert contact**. To insert a phone number or a text item attached to the contact name, select **Options > View details**.

6 The menu

Your phone offers you an extensive range of functions that are grouped into menus. Most of the menu functions include Help text. To view the Help text, scroll to the menu function you want and wait 15 seconds. To exit the help text, select **Back**.

You can view the main menu as a grid of icons or in list view. To change the menu view, see "Display settings" on page 46.

- **SCROLL TO A MENU FUNCTION**

- 1 To access the menu, select **Menu**.
- 2 Scroll through the menu by moving the joystick up or down (or right and left if the grid menu is selected), and press the joystick to select a highlighted menu item.
- 3 If the menu contains submenus, select the one you want.
- 4 If the selected submenu contains further submenus, repeat step 3.
- 5 Select the setting of your choice.
- 6 Select **Back** to return to the previous menu level, and **Exit** to exit the menu.

- **MENU SHORTCUTS**

Each menu, submenu, and settings option is numbered for quick access. The shortcut numbers appear the upper corner of the display. If you frequently use a specific menu, you can key in the shortcut numbers to go directly to that location without scrolling.

To use shortcuts, select **Menu** and, within 2 seconds, press the sequence of number keys associated with the menu function you want to view or activate. To access menu functions in menu 1, press **Menu > 1** and then key in the rest of the desired shortcut number. Select **Back** to return to the previous menu level and **Exit** to exit the menu.

7 Messages



You can read, write, send, and save text, multimedia, and e-mail messages. All messages are organized in folders.

Before you can send text, picture or text (SMS) e-mail messages, you need to save your message center number. See "Message settings" on page 35. The default setting of the multimedia message service is generally on.



Note: When sending messages using the SMS network service, your phone may display "**Message sent**". This is an indication that the message has been sent by your phone to the message center number programmed into your phone. This is not an indication that the message has been received at the intended destination. For more details about SMS services, check with your service provider.

The appearance of a multimedia message may vary depending on the receiving device.

• TEXT MESSAGES (SMS)

You can use SMS (short message service) to send and receive multipart messages that consist of several ordinary text messages. This feature requires network services. See your service provider for more information about service availability and pricing.

Your phone allows you to send text messages beyond the normal 160-character limit. If your message exceeds 160 characters, it is sent as a series of two or more messages. In the navigation bar, you can see the message length indicator counting backwards from 160. For example, 10 (2) means that you can still add 10 characters for the text to be sent as two messages.

Using special (Unicode) characters, such as ã, â, á, ì, takes up more space. If there are special characters in your message, the indicator may not show the message length correctly. Before the message is sent, the device tells you if the message exceeds the maximum length allowed for one message. You can cancel sending by pressing **Cancel** or you can save the message in the inbox.

You can also send and receive text messages that contain pictures. This feature must be supported by your network services or service provider. Only phones that offer picture message features can receive and display picture messages. The text messages function uses shared memory.

Write and send a message

In the standby mode, you can move the joystick to the left to start writing a message quickly. The *number of available characters/the current part number* of a multipart message are shown on the top right of the display (such as 120/2).

- 1 Select **Menu > Messages > Text messages > Create message**.
- 2 Key in your message.
- 3 To send the message, press the **Send** key.
- 4 Enter the recipient's phone number or search for it in **Contacts**, and select **OK**.

Options when sending a message

After you have written a message, select **Options > Sending options** to choose from the following options:

Send to many—to send a message to several recipients. When you have sent the message to all the intended recipients, select **Done**.

Send to list—to send a message using a distribution list.

Write and send SMS e-mail

Before you can send an e-mail using SMS, you need to save the settings for sending e-mail. For availability and subscription to the e-mail service, contact your service provider.

- 1 Select **Menu > Messages > Text messages > Create SMS e-mail**.
- 2 Key in the recipient's e-mail address or search for it in **Contacts**, and select **OK**.
- 3 If you wish, you can key in a subject for the e-mail and select **OK**.
- 4 Key in the e-mail message.

The total number of characters that you can key in is shown on the top right of the display. The e-mail address and subject are included in the total number of characters.

Also see "Text and picture templates" on page 28. Pictures cannot be inserted.

- 5 To send the e-mail, press the **Send** key.

If you have not saved the settings for sending e-mail, the phone prompts you to enter the number of the e-mail server. Key in the information and select **OK** to send the e-mail.



Note: When sending e-mail using the SMS network service, your phone may display the words **Message sent**. This is an indication that the e-mail has been sent by your phone to the e-mail server. This is not an indication that the e-mail has been received at the intended destination. For more details about e-mail services, check with your service provider.

Read and reply to SMS messages or SMS e-mail

When you receive a message or an e-mail, the new message icon  and the number of new messages followed by **message(s) received** is shown.

The blinking icon  indicates that the message memory is full. Before you can receive new messages, delete some of your old messages from the **Inbox** folder.

- 1 Select **Show** to view the new message. You can also select **Exit** to view it later. Later, you can view the message by selecting **Menu > Messages > Text messages > Inbox**.
- 2 If more than one message has been received, select the one that you want to read.

An unread text message is indicated by  in front of it.

- 3 While reading or viewing the message, you can select from a series of basic options, such as **Delete**, **Forward**, **Edit** (as a text message or an e-mail), **Rename**, or **Move**. You can also select one of the following options:
 - Copy to calendar**—to copy text from the beginning of the message to your calendar as a memo for the current day.
 - Message details**—to view, if available, the sender's name and phone number, the message center used, and the date and time of receipt.
 - Use detail**—to extract numbers, e-mail and Web site addresses from the current message.
 - Save picture**—(when viewing a picture message), to save the picture in the **Templates** folder.
- 4 Select **Reply** to reply to a message.
- 5 Select **Original text** to include the original message in the reply, or select a standard answer to be included in the reply, or select **Empty screen**.
When replying to an e-mail message, confirm or edit the e-mail address and subject first. Then write your reply message.
- 6 Press the **Send** key to send the message to the displayed number.

Inbox and sent items folders

The phone saves incoming text messages in the **Inbox** folder and sent messages in the **Sent items** folder of the **Text messages** submenu.

Text messages that you wish to send later can be saved in the **Archive**, **My folders**, or **Templates** folder.

• ARCHIVE FOLDER AND CUSTOM FOLDERS

To organize your messages, move them to the **Archive** folder or add new folders for your messages.

While reading a message, select **Options > Move** and select the folder to which you want to move the message.

To add or delete a folder, select **Menu > Messages > Text messages > My folders**.

- To add a folder, select **Options > Add folder**. If you have not saved any folders, select **Add** to create one.
- To delete a folder, locate the folder that you want to delete and select **Options > Delete folder**.

• TEXT AND PICTURE TEMPLATES

Your phone includes text templates, indicated by , and picture templates, indicated by .

To access the template list, select **Menu > Messages > Text messages > Templates**.

- To insert a text template into a message or an e-mail, select **Options > Use template** and select the template you want to insert.

- To insert a picture into a text message, select **Options > Insert picture** and select a picture to view it. Select **Insert** to insert the picture into your message. The  icon in the header of the message indicates that a picture has been attached. The number of characters allowed in the message depends on the size of the picture.
- To view the text and the picture together before sending the message, select **Options > Preview**.

• MANAGE DISTRIBUTION LISTS

If you send messages frequently to a fixed group of people, you can define and save distribution lists. The phone sends the message separately to each recipient on the list, so sending a message using a distribution list may cost more than sending a message to one recipient.

Make sure that each contact you want to add to the distribution list is already set up in your phone. Use these steps to set up and name distribution lists.

- 1 In the standby mode, select **Menu > Messages > Text messages > Distribution lists**. If you have created distribution lists, the current list appears. If you have not yet created a list, **Add** appears.
- 2 To create a distribution list, select **Add** if it is the first list, or select **Options > Add** for a new list.
- 3 Key in a name for the list and select **OK**.
- 4 To add names to the list, select the list; then select **View > Add** to open Contacts list. Select the desired contact.

Use these steps to manage and edit lists.

- 1 To work with a list, select the list name and select **Options**; then choose from the following options:
 - **Add List**—to create a new list.
 - **Rename List**—to change the name of a list.
 - **Clear List**—to empty the list of names.
 - **Delete List**—to delete the list entirely.
- 2 To access the names on a list, locate the desired list and select **View**. Then choose from the following options:
 - To view the contact information for a recipient, locate the desired name, select **Options > View details**.
 - To delete a recipient from the list, locate the desired name, select **Options > Delete contact**.

• TEXT MESSAGE COUNTER

The text message counter shows the number of sent and received text and picture messages. Picture messages may consist of more than one message. You can view the recipient or sender of the message, or view the details of the message.

• MULTIMEDIA MESSAGES

A multimedia message can contain text and one image, sound clip, video clip or a slide. This function can be used only if it is supported by your service provider. Only phones that offer compatible multimedia message features can receive and display multimedia messages.

The phone supports multimedia messages that are up to 100 kB in size. If the message contains an image, the phone scales it down to fit the display area. If the maximum size is exceeded, the phone may not be able to receive the message. Some service providers send a text message with a link or Internet address where you can view the multimedia message.



Note: If **Allow multimedia reception** is set to **Yes** or **In home network**, your operator or service provider may charge you for each message you receive.

Multimedia messaging works with the following formats:

- Picture: JPEG, GIF, WBMP, BMP, PNG, and OTA-BMP
- Sound: scalable polyphonic MIDI (SP-MIDI), AMR audio and monophonic ringing tones
- Video clips in H.263 format with SubQCIF image size and AMR audio

The phone does not necessarily support all variations of the listed file formats. If a received message contains any unsupported elements, they may be replaced with the file name and the text **Object format not supported**.

You cannot receive any multimedia messages if you have a call in progress, a game or another Java application running, or if you have an active browsing session over GSM data. Because delivery of multimedia messages can fail for a variety of reasons, do not rely solely upon them for essential communications.

Your phone allows you to send and receive multimedia messages that contain several pages, or slides. To insert a slide into a message, select **Options > Insert > Slide**. Each slide can contain text, one image and one sound clip. To move the text part to the top or bottom of the message, select **Options > Text on top** or **Options > Text on bottom**.

Copyright protections may prevent some images, ringing tones, or other content from being copied, modified, transferred or forwarded.

Write and send a multimedia message

To define the settings for multimedia messaging, see "Settings for multimedia messages" on page 35. For information about subscribing to multimedia messaging services, contact your service provider.

- 1 Select **Menu > Messages > Multimedia msgs. > Create message**.
- 2 Key in a message.
 - To add a file to the message, select **Options > Insert**.
 - Select **Image, Sound clip, New sound clip, Calendar note, Business card, Video clip, or Slide**.

- Open the folder that contains the item you want to add to the message, locate the desired file, and select **Options > Insert**.

An attached file is indicated by the file name in the message.

- 3 To insert a name from **Contacts**, select **Options > More options > Insert contact**, and select the desired name.
- 4 To insert a number, select **Options > More options > Insert number**. Key in the number or search for it in **Contacts**, and select **OK**.
- 5 To view the message before sending it, select **Options > Preview**.
- 6 Press the **Talk** key to send the message, or select **Options > Send to e-mail** or **Send to many**.
- 7 Enter the recipient's phone number (or e-mail address) or search for it in **Contacts**.
- 8 Select **OK**.

It takes more time to send a multimedia message than a text message. While the multimedia message is being sent, the animated icon  is displayed and you can use other functions on the phone. If there is an interruption while the message is being sent, the phone makes a few more attempts to send it. If this fails, the message remains in the **Outbox** folder and you can try to send it later.

Sent messages are saved in the **Sent items** folder if the setting **Save sent messages** is set to **Yes**. (See "Settings for multimedia messages" on page 35.) This is not, however, a confirmation that the message has been received at the intended destination.

Read and reply to a multimedia message

When your phone is receiving a multimedia message, the animated icon  is displayed. When the message has been received, the icon  and the text **Multimedia message received** are shown.

The blinking icon  indicates that the memory for multimedia messages is full, see "Multimedia messages memory full" on page 32.

- 1 Select **Show** to view the message, or select **Exit** to view it later.
(To read the message later, select **Menu > Messages > Multimedia msgs. > Inbox**.)
The function of the middle selection key changes according to the displayed object.
- 2 Choose from the following:
 - To reply to the message, select **Reply**.
 - To delete an object contained in the message, select **Delete**. Otherwise, select **Options > Delete message**.
 - To listen to a sound clip or view a video clip contained in the message, select **Play**.
 - To zoom in on an attached image, select **Zoom**.

If you select **Options**, some of the following options are available:

Delete message—deletes a saved message.

Reply or **Reply to all**—lets you reply to the message.

Use detail—extracts phone numbers, e-mail addresses, or Web addresses from the message.

Forward to no., **Forward to e-mail** or **Send to many**—forwards the message.

Edit—edits a message that you have written.

Message details—displays the subject, size and class of the message.

Details—displays the details of the attached image or sound.

Play presentation—displays the presentation attached in the message.

Save image, **Save sound clip** or **Save video clip**—saves the file in the **Gallery**.

Inbox, Outbox, Saved and Sent items folders

The phone saves multimedia messages that have been received in the **Inbox** folder of the **Multimedia msgs.** submenu.

Multimedia messages that are waiting to be sent are stored in the **Outbox** folder of the **Multimedia msgs.** submenu.

Multimedia messages that you wish to save and send later can be saved in the **Saved items** folder of the **Multimedia msgs.** submenu.

Multimedia messages that have been sent are saved in the **Sent items** folder of the **Multimedia msgs.** submenu, if the setting **Save sent messages** is set to **Yes**. (For more information see "Settings for multimedia messages" on page 35.)

MULTIMEDIA MESSAGES MEMORY FULL

When you have a new multimedia message waiting and the memory for the messages is full, the icon  blinks and **Multimedia memory full, view waiting msg.** is shown. To view the waiting message, select **Show**. To save the message, select **Save** and delete old messages by first selecting the folder and then the message to be deleted.

To discard the waiting message, select **Exit** > **Yes**. If you select **No**, you can view the message.

• DELETE MESSAGES

To delete text messages, select **Menu** > **Messages** > **Text messages** > **Delete messages**. Then choose from the following options:

All messages—to delete all messages from all folders. If there are unread messages, the phone prompts you to confirm you want to delete these also.

Inbox—to delete all messages in the Inbox.

Sent items—to delete all messages in the Sent folder.

Archive—to delete all messages in the Archive folder.

• E-MAIL MESSAGES

The e-mail features allow you to access your e-mail account using your phone. The compatible e-mail application that you use in the office or at home must use POP3 and IMAP4 e-mail servers.



Note: When sending e-mail, your phone may display the words **Message sent**. This is an indication that the e-mail has been sent by your phone to the e-mail server. This is not an indication that the e-mail has been received at the intended destination. For more details about e-mail services, check with your service provider.

Before you can send and retrieve e-mail, you may need to do the following:

- Obtain a compatible e-mail account. For details on compatibility, contact an e-mail service provider.
- For the settings required for e-mail, contact your service provider. For receiving the e-mail settings over the air, see "Over-the-air settings service" on page 18.
- To set the e-mail settings on your phone, select **Menu > Messages > Message settings > E-mail messages**. See "E-mail settings" on page 36.

Write and send e-mail

You can write your e-mail message before connecting to the e-mail service, or connect to the service first, and then write and send your e-mail.

- 1 Select **Menu > Messages > E-mail > Create e-mail**.
- 2 Key in the recipient's e-mail address. (To search for the e-mail address in contacts, select **Edit > Options > Find** and select the contact from the list. Select **OK** to return to the header details.)
- 3 Move to the **Subject** field and enter a subject line. Select **OK**.
- 4 Select **Options > Message editor** and key in your message.
- 5 To save the message in the Drafts folder, select **Options > Save draft msg**.
- 6 To send the message, select **Send**. Choose one of the following options:

Send now—sends the e-mail immediately. If you are not connected to the e-mail account, your phone establishes the connection and then sends the e-mail.

Send later—saves your e-mail in the **Outbox** folder to send later. When you are ready to send the e-mail, select **Menu > Messages > E-mail > Options** and select **Send now** or **Retrieve and send**.

Other options in the options list allow you to edit the e-mail or subject, add a copy recipient or a hidden copy recipient, exit the editor or use the dictionary.

Download e-mail from your e-mail account

If message memory is full, delete some of your older messages before you start to download new messages.

- 1 Do one of the following:
 - To download new messages, select **Menu > Messages > E-mail > Retrieve**.

- To send messages that are in your **Outbox** folder at the same time you download new messages, select **Menu > Messages > E-mail > Options > Retrieve and send**.
- 2 Select any messages you want to view in the **Inbox**, or press **Back** to view it later.
Unread text messages are indicated by .

Read and reply to an e-mail message

- 1 Select **Menu > Messages > E-mail > Inbox**.
- 2 Display the desired message and select **Options**.
- 3 Select **Reply** to reply to an e-mail. Select **Original text** to include the original message in the reply or select **Empty screen**.
When replying to an e-mail, first confirm or edit the e-mail address and subject; then write your reply.
- 4 Select **Options > Send > Send now** to send the message.

E-mail menu folders

Your phone has the following folders in the **E-mail** menu:

Inbox—for saving e-mail messages that you have downloaded from your e-mail account.

Outbox—for saving e-mail messages that have not been sent if you have selected **Send later** (see "Write and send e-mail" on page 33).

Deleted items—for e-mail messages that have been deleted.

Sent items—for saving e-mail messages that have been sent.

Drafts—for saving unfinished e-mail messages.

Archive—for organizing and saving your e-mail messages.

• VOICE MESSAGES

The voice mailbox is a network service. For more information, contact your service provider.

Select **Menu > Messages > Voice messages**, and select one of the following options:



Note: You can also press and hold the **1** key to call your mailbox. This shortcut is available with the keyboard open or closed.

- **Listen to voice messages** to call your voice mailbox at the phone number that you have saved in the **Voice mailbox number** menu. If you have two phone lines available through your network service, each phone line may have its own voice mailbox number. For more information, see "Call settings" on page 51.
- **Voice mailbox number** to key in, search for or edit your voice mailbox number and select **OK** to save it.

If supported by the network, the icon  indicates there are new voice messages. Select **Listen** to call your voice mailbox number.

• INFO MESSAGES

Info messages is a network service that provides informational messages from your service provider on various topics. For availability, topics and the relevant topic numbers, contact your service provider.

• MESSAGE SETTINGS

The message settings affect the sending, receiving and viewing of messages.

Settings for SMS text and e-mail messages

- 1 Select **Menu > Messages > Message settings > Text messages > Sending profile**.
- 2 If more than one message profile set is supported by your SIM card, select the set that you want to change.

Message center number—to save the phone number of the message center that is required for sending text messages. You will receive this number from your service provider.

Default recipient number (for message type **Text**)—to save a default number for sending messages for this message profile.

Use GPRS > Yes—to set GPRS as the preferred SMS bearer. Also set the GPRS connection setting to **Always online**. (See "EGPRS" on page 50.)

Reply via same center—to allow the message recipient to send you a reply by way of your message center (network service).

Overwrite settings

When the text message memory is full, the phone cannot receive or send any new messages. However, you can set the phone to automatically replace old text messages in the **Inbox** and **Sent items** folders with new ones.

Select **Menu > Messages > Message settings > Text messages**, and select either **Overwriting in inbox** or **Overwriting in sent items** and **Allowed**.

Settings for multimedia messages

You may receive the multimedia connection settings as an over-the-air message from the service provider. To receive the settings over the air, see "Over-the-air settings service" on page 18.

To key in the settings manually, select **Menu > Messages > Message settings > Multimedia msgs.**, and set up the following items:

Save sent messages > Yes—to set the phone to save sent multimedia messages in the **Sent items** folder. If you select **No**, the sent messages are not saved.

Delivery reports—to ask the network to send delivery reports about your messages (network service).

Scale image down—to define the image size when you insert the image to the multimedia message.

Default slide timing—to set the timing for slides in multimedia messages.

Allow multimedia reception > No, Yes, or In home network—to use the multimedia service. If you select **In home network**, you cannot receive multimedia messages outside your home network.

Incoming multimedia messages > Retrieve—to set the phone to automatically fetch newly received multimedia messages. Select **Reject** if you do not wish to receive multimedia messages.

Connection settings—to define connection settings for retrieving multimedia messages. First select **Active multimedia settings**, and activate the set in which you want to save the settings. Select **Edit active multimedia settings** and edit the active settings.

Select each of the settings one by one and key in all the required settings. Contact your service provider for the settings.

Allow adverts—to receive or reject advertisements. The setting is not shown if **Allow multimedia reception** is set to **No**.

● E-MAIL SETTINGS

You may receive the e-mail connection settings as an over-the-air message from the service provider. For receiving the settings over the air, see "Over-the-air settings service" on page 18. For keying in the settings manually, select **Menu > Messages > Message settings > E-mail messages > Active e-mail settings**.

You must first activate a mailbox. Select **Mailbox in use** and activate the mailbox for which you want to save the settings. Select **Activate > Edit active e-mail settings** and edit the settings.

Select each of the settings one by one and key in all that are required. Contact your or e-mail service provider for the settings.

Mailbox name—key in the name that you want to use for the mailbox.

E-mail address—key in your e-mail address.

My name—key in your name or nickname if you want the recipient to see it.

Outgoing (SMTP) server—key in the address of the e-mail server.

Outgoing (SMTP) port—key in the number of the e-mail server port for outgoing e-mail. The most common default value is 25.

Use SMTP authorization—if your e-mail service provider requires authentication for sending e-mails, set the setting to on. You must also define your **SMTP user name** and **SMTP password**.

SMTP user name—key in the user name for outgoing mails that you have obtained from your e-mail service provider.

SMTP password—key in the password that you want to use for outgoing mails. If you have not defined a password, you may be asked to define one when your phone connects to your e-mail account.

Include signature—confirm your selection if you want to add a predefined signature to your e-mail.

Incoming (POP3/IMAP) server—key in the e-mail server address for incoming e-mail (either **POP3** or **IMAP4**).

Incoming (POP3/IMAP) port—key in the port number that you have obtained from your e-mail service provider.

POP3/IMAP user name—key in the user name to access the mailbox. If you have not defined your **SMTP user name**, the e-mail server uses this user name instead.

POP3/IMAP password—key in the password to access the mailbox. If you have not defined your **SMTP password**, the e-mail server uses **POP3/IMAP password** instead.

Reply-to address—key in the e-mail address to which you want the replies to be sent, if it differs from your e-mail address.

Incoming server type > POP3 or IMAP4—if both types are supported, select **IMAP4**. Changing the server type also changes the incoming port number.

Secure login APOP > On—if your connection requires an encrypted login, set it to **On**. Otherwise leave it set to **Off**. Contact your service provider if in doubt. This option is only shown if you have selected **POP3** as your mailbox type. Using encrypted login enables increased security for user names and passwords. It does not increase security for the connection itself.

Retrieve e-mails—key in the number of e-mails that you want to retrieve at a time.

• FONT SIZE SETTING

To select the font size for reading and writing messages, select **Menu > Messages > Message settings > Other settings > Font size**.

• SERVICE COMMANDS

Select **Menu > Messages > Service commands**. Key in and send service requests (also known as USSD commands), such as activation commands for network services, to your service provider.

8 Call log



The phone records the phone numbers for missed, received and dialed calls, and the approximate length of the calls.

The phone records missed and received calls only if the network supports these functions. The phone must also be switched on and within the network service area.

When you select **Options** in the **Missed calls**, **Received calls**, and **Dialed numbers** menu, you can view the date and the time of the call, edit or delete the phone number from the list, save the number in **Contacts**, or send a message to the number.

• RECENT CALL LISTS

Select **Menu > Call log**, and one of the following options:

Missed calls—to view the list of the last 20 phone numbers from which somebody has tried to call you (network service). The number in front of the name or phone number indicates the number of call attempts from that caller.

When a note about missed calls is displayed, select **List** to access the list of phone numbers. Scroll to the number you would like to call back and press the **Send** key.

Received calls—to view the list of the last 20 phone numbers from which you have most recently accepted calls (network service).

Dialed numbers—to view the list of the last 20 phone numbers that you have most recently called or attempted to call. See also "Last number redial" on page 19.

Delete recent call lists—to delete the recent calls lists. Select whether you want to delete all the phone numbers in the recent calls lists, or only the numbers in the missed calls, received calls or dialed numbers lists. You cannot undo the operation.

• TIMERS AND COUNTERS

Timers and counters maintain useful information about phone activity.



Note: The actual invoice for calls and services from your service provider may vary, depending upon network features, rounding-off for billing, taxes and so forth.

Select **Menu > Call log > Timers and counters**, and one of the following options:

- **Call timers**—scroll to view the approximate duration of your incoming and outgoing calls in hours, minutes, and seconds. The security code is required to clear the timers.

If you have two phone lines available (network service), each phone line has its own call duration timers. The timers of the selected line are displayed.

- **GPRS data counter**—scroll to check the size of data that was sent or received in bytes, sent and received data in total, and to clear the counters. The security code is required to clear the counters.
- **GPRS connection timer**—scroll to check the duration of the last GPRS connection or the total GPRS connection time. You can also clear the timers. The security code is required to clear the timers.



Note: Timers and counters may be reset if you have your phone repaired.

9 Contacts



You can save names and phone numbers (contacts) in both the phone memory and in the SIM card memory.

You may save up to 500 names with numbers and text notes for each name in the phone memory. You can also save an image for a certain number of names. The number of names that can be saved depends on both the length of the names, and the number and length of the phone numbers and text items.

The phone supports SIM cards that can save up to 250 names and phone numbers. Names and numbers that are saved in the SIM card memory, are indicated by .

• CONTACTS SETTINGS

Select **Menu > Contacts > Settings**, and one of the following options:

Memory in use—to select the memory, either SIM card or phone, that you want to use for your contacts. To recall names and numbers from both memories for contacts, select **Phone and SIM**. In this case, the names and numbers will be saved in the phone memory.

Contacts view—to select how the names, numbers and images in contacts are displayed.

Memory status—to view how much free memory is available for both memories for contacts.

• ADD CONTACTS

Names and numbers will be saved in the memory in use.

- 1 Select **Menu > Contacts > Add contact**.
- 2 Key in the name and select **OK**.
- 3 Key in the phone number and select **OK**.
- 4 When the name and number have been saved, select **Done**.



Note: To quick save in the standby mode, key in the phone number and select **Save**. Key in the name, select **OK > Done**.

Save multiple numbers and text items per contact

You can save different types of phone numbers and short text items for each name in the phone memory that is allocated for contacts.

The first number saved is automatically set as the default number and it is indicated by a frame around the number type icon, for example . When you select a name from contacts the default number is used unless you select another number.

- 1 Make sure that the memory in use is either **Phone** or **Phone and SIM**.

- 2 To access the list of names and phone numbers, move the joystick down in the standby mode.
- 3 Select the desired name and select **Details > Options > Add number or Add detail**.
- 4 To add a number or detail, select one of the number types or text types, respectively.
 - For the **User ID**—select **Search** to search for an ID by a mobile phone number or an e-mail address in the server of the operator or service provider if you have connected to the presence service. If only one ID is found, it is automatically saved. Otherwise, to save an ID, select **Options > Save**.
 - To key in the ID, select **Enter ID manually**. Key in the ID and select **OK** to save it.
 - To change the number or text type, select **Change type** in the options list.
 - To set the selected number as the default number, select **Set as default**.
- 5 Key in the number or text item and select **OK** to save it.
- 6 Select **Back > Exit** to return to the standby mode.

Add an image to a name or number

You can add an image to a name or number saved in the phone memory. The image must be one of the supported formats (JPEG, GIF, WBMP, BMP, PNG, and OTA-BMP).

Move the joystick down in the standby mode, scroll to the name (and number), and select **Details > Options > Add image**. The phone opens the list of folders in the **Gallery**. Scroll to the desired image, and select **Options > Save to contacts**.

• SEARCH FOR A CONTACT

- 1 Select **Menu > Contacts > Find**, or move the joystick down in the standby mode.
- 2 Key in the first characters of the name that you are searching for in the pop-up window.
Move the joystick up or down to scroll through the names in the list, and right or left to move the cursor in the pop-up window.
- 3 Scroll to the desired contact, and select **Details**.
- 4 Scroll to view the details of the selected contact.
Depending on the **Contacts view** setting in "Contacts settings" on page 40, the subscribed contacts are shown differently. Either only the availability icon or the availability icon, personal logo and the status message are shown.
- 5 Select **Details** to view all dynamic information.

To view the status message in full, select **Details** and press and hold the * key at the dynamic contact while scrolling through the contact names.

• DELETE CONTACTS

Select **Menu > Contacts > Delete** to delete a contact and the details attached to it.

- To delete names and numbers one by one, select **One by one** and scroll to the name (and number) that you want to delete. Select **Delete > Yes**.
- To delete contacts all at once, select **Delete all**, scroll to one of the memory locations (**Phone** or **SIM card**), and select **Delete**. Select **Yes**. Confirm the deletion using the security code.

• EDIT OR DELETE DETAILS IN CONTACTS

Move the joystick down in the standby mode, scroll to the contact that you want to edit or delete and select **Details**. Scroll to the name, number, text item or image that you want to edit or delete, and select **Options**.

- To edit a name, number or text item or to change an image, select **Edit name**, **Edit number**, **Edit detail**, or **Change image**. (You cannot edit or delete an ID when it is on the **IM contacts** or in the **Subscribed names** list.)
- To delete a number or text item, select **Delete number** or **Delete detail**.
- To delete an image which is attached to the contact, select **Delete image**. Deleting an image from contacts does not delete it from **Gallery**.

• COPY CONTACTS

You can copy names and phone numbers from the phone memory to your SIM card memory and vice versa. Any text items saved in the phone memory, such as e-mail addresses, will not be copied to the SIM card.

- 1 Select **Menu > Contacts > Copy**.
- 2 Select the method, **From phone to SIM card** or **From SIM card to phone**.
- 3 Select **One by one**, **All** or **Primary numbers**.
Primary numbers is shown if you copy from the phone to the SIM card. Only the primary numbers will be copied.
- 4 To keep or delete the original names and numbers, select **Keep original** or **Move original**.

• SEND AND RECEIVE BUSINESS CARDS

You can send and receive a person's contact information from a compatible device as a business card.

When you have received a business card, select **Show > Save** to save the business card in the phone memory. To discard the business card, select **Exit > OK**.

To send a business card, search for the name and phone number you want to send from contacts, select **Details > Options > Send bus. card**. Select **Via infrared**, **Via text message** (network service), **Via Bluetooth** or **Via multimedia**.

• SPEED DIALING

To assign a number to a speed dialing key, use the following steps:

- 1 Select **Menu > Contacts > 1-touch dialing** and scroll to the desired speed dialing key number.
 - 2 Select **Assign**.
If a number has already been assigned to the key, select **Options > Change**.
 - 3 Select **Find**, and select first the name and then the number you want to assign.
If the **1-touch dialing** function is off, the phone gives you the option to activate it.
- To make a call using the speed dialing keys, see "Speed dial a phone number" on page 20.

• VOICE DIALING

You can make a phone call by saying a voice tag that has been added to a phone number. Any spoken word or words, such as a person's name, can be a voice tag. You can add up to 10 voice tags.



Note: Using voice tags may be difficult in a noisy environment or during an emergency, so you should not rely solely upon voice dialing in all circumstances.

Before using voice dialing, review the following information:

- Voice tags are not language dependent. They are dependent on the speaker's voice.
- Voice tags are sensitive to background noise. Record them and make calls in a quiet environment.
- When recording a voice tag or making a call by saying a voice tag, hold the phone in the normal position near to your ear.
- Very short names are not accepted. Use long names and avoid similar names for different numbers.



Note: You must say the name exactly as you said it when you recorded it. This may be difficult in, for example, a noisy environment or during an emergency, so you should not rely solely upon voice dialing in all circumstances.

Add and manage voice tags

Before you begin, make sure you have the contact names you intend to save with voice tags set up in the phone memory. You can also add voice tags to the names in the SIM card, but if you replace your SIM card with a new one, you first need to delete the old voice tags before you can add new ones. Voice tags use shared memory. For more information, see "Shared Memory" on page 6.

- 1 In the standby mode, select **Menu > Contacts**, scroll to the desired contact, and select **Details**.
- 2 Select **Options > Add voice tag**.

- 3 Select **Start**, and say clearly the words you want to record as a voice tag.
After recording, the phone plays the recorded tag.
- 4 When the voice tag has been successfully saved, **Voice tag saved** is displayed, a beep sounds and a symbol  appears after the phone number with a voice tag.

To check the voice tags, select **Menu > Contacts > Voice tags**. Scroll to the contact, select **Options**, and select the function you want.

Make a call using a voice tag

If the phone has an application using the GPRS connection that is sending or receiving data, first end the application to make a call by using voice dialing.

- 1 In the standby mode, press the **Right selection** key or press and hold **Names**.

A short tone is heard and **Speak now** is displayed.

- 2 Say the voice tag clearly.

The phone plays the recognized voice tag and dials the phone number of the voice tag after 1.5 seconds.

If you are using a compatible headset, press and hold the headset key to start the voice dialing.

Info numbers and service numbers

Your service provider may have included information numbers or service on your SIM card.

Select **Menu > Contacts > Info numbers** or **Service numbers**. Scroll through a category to an information number, or to a service number and press the **Send** key to call the number.

• SAVE NUMBERS ON THE SIM CARD

The phone numbers assigned to your SIM card are saved in **My numbers** if this is allowed by the card. To view the numbers select **Menu > Contacts > My numbers**. Scroll to the desired name or number, and select **View**.

• CALLER GROUPS

You can arrange the names and phone numbers saved in **Contacts** into caller groups. For each caller group, you can select a ringing tone and a logo that is shown on the display when you receive a call from a phone number in the group. To set the phone to ring only upon calls from phone numbers belonging to a selected caller group, see **Alert for** in "Tone settings" on page 45.

Select **Menu > Contacts > Caller groups** and select the desired caller group. You can select from the following functions: **Group name**, **Group ringing tone**, **Group logo**, and **Group members**.

If you select **Group members**, select **Add**, to add a name to the group, if there are no names in the group. Otherwise, select **Options > Add contact**.

To remove a name from a caller group, scroll to the desired name, and select **Remove**.

10 Settings



• PROFILES

Your phone has a group of profiles that allow you to personalize the tone settings of your phone and to activate a profile for different events and environments. Available profiles are **General**, **Silent**, **Meeting**, **Outdoor**, **My style 1** and **My style 2**.

Select **Menu > Settings > Profiles** and select a profile. Choose from the following options:

- To activate the selected profile, select **Activate**.
- To activate the profile for a certain amount of time up to 24 hours, select **Timed** and set the end time. When the timed profile expires, the previous profile that was not timed, becomes active.
- To personalize the profile, select **Customize**. Select the setting that you want to change and make the changes. The settings can also be changed in the **Tone settings** menu, see "Tone settings" on page 45.
- To rename a profile, select **Customize > Profile Name**. The **Normal** profile cannot be renamed.
- To quickly change the profile in the standby mode, press the **Power** key, scroll to the profile that you want to activate and press **Select**.

• TONE SETTINGS

You can find the same settings in the **Profiles** menu. The settings you choose also update the active profile.

Select **Menu > Settings > Tone settings**, and select from the following options:

Ringling options—to select how the phone notifies you of an incoming voice call.

Ringling tone—to select a tone for incoming voice calls. To select ringing tones that have been saved in the **Gallery**, select **Open gallery** from the ringing tone list.

Ringling volume—to set the tone level for incoming voice calls and incoming messages.



Note: If you download a ringing tone or receive one using OTA, you can save it in the **Gallery**.

Vibrating alert—to set the phone to vibrate for incoming voice calls and incoming messages. The vibrating alert does not work when the phone is connected to a charger, a desktop stand, or a car kit.

Message alert tone—to set the alert tone for incoming messages.

Keypad tones—to adjust the tone level of keypad.

Warning tones—to set the phone to sound tones, for example when the battery is running out of power.

Alert for—to set the phone to ring only on calls from phone numbers that belong to a selected caller group. Scroll to the caller group that you want or **All calls** and select **Mark**.

• DISPLAY SETTINGS

Select **Menu > Settings > Display settings**, and choose from the following options:

Wallpaper—to set the phone to display a background image, known as wallpaper, when the phone is in the standby mode. Some images are provided in the **Gallery** menu. You can also receive images, for example through a multimedia message, or use PC Suite to transfer them from your PC and then save them in **Gallery**. Your phone supports JPEG, GIF, WBMP, BMP, PNG, and OTA-BMP formats, but not necessarily all variations of these formats.

- **Select image** to open an image folder. Scroll to the desired image you want to set as wallpaper, select **Options > Set as wallpaper**.
- **On** or **Off** to activate/deactivate the wallpaper. (The wallpaper is not displayed when the phone activates the screen saver.)

Colour schemes—to change the colour of some display components, such as icons and signal bars.

Menu view—to select how the main menu items are displayed on the phone. Select **List** or **Grid**.

Operator logo—to set the phone to show or hide the operator logo. If you have not saved any operator logos, the **Operator logo** menu is dimmed. The operator logo is not displayed when the phone activates the screen saver.

Screen saver timeout—to select the timeout after which the screen saver will be activated. The length of the timeout can vary from 5 seconds to 60 minutes.

The digital clock screen saver is used for power saving in the standby mode. It activates when the phone has not been used for a certain length of time while the keyboard is closed. To deactivate the screen saver, press any key or open the keyboard. The screen saver is also deactivated when the phone is out of the network coverage area. The screen saver overrides graphics and text information shown on the display when the phone is in the standby mode.

Display contrast—to change the brightness level of the phone display. Move the joystick to the left to decrease and to the right to increase the brightness level, and select **OK** to accept it.

• TIME AND DATE SETTINGS

Select **Menu > Settings > Time and date settings**, and select one of the following options:

Clock > Show clock or **Hide clock**—to show or hide the time on the top right of the display in the standby mode. Select **Set the time** to adjust the clock to the correct time, and **Time format** to select 12-hour or 24-hour time format.

The clock is also used for functions such as **Messages**, **Call log**, **Alarm clock**, timed **Profiles**, **Calendar**, **Notes**, and screen saver.



Note: If the battery is removed from the phone for an extended time, you may need to reset the time.

Date > Show date or **Hide date**—to show or hide the date on the display in the standby mode. Select **Set the date** to adjust the date. You can also select the date format.

Auto-update of date & time (network service)—to set the phone to automatically update the time and date according to the current time zone, select **On**. To set the phone to ask for confirmation before the update, select **Confirm first**.

The automatic update of date and time does not change the time you have set for the alarm clock, calendar or the alarm notes. They are in local time. Updating may cause some alarms that you have set to expire.

• PERSONAL SHORTCUTS

You can select the function for the **Right selection** key displayed in the standby mode.

You have also a list of phone functions which can be activated by saying a voice tag. Up to five voice tags for the voice commands can be added.

Select **Menu > Settings > Personal shortcuts**, and select from the following options:

Right selection key—to view the list of available functions for the **Right selection** key. Scroll to the function that you want and select it.

Voice commands—to add a command. Select the command folder you want, scroll to the command to which you want to add a voice tag. Select **Options > Add command**. If the command already has a voice tag, the icon  is shown. For adding and activating a voice command, see "Voice dialing" on page 43.

During a call or when an application using the EGPRS connection is sending or receiving data, you cannot activate or add a voice command.

• CONNECTIVITY AND RELATED SETTINGS

You can connect the phone to a compatible device using an IR or Bluetooth connection. You can also define the settings for EGPRS dial-up connections. Bluetooth connections and IR connections cannot be active at the same time.

Bluetooth technology

The phone supports Bluetooth wireless technology which allows you to connect the phone to a compatible Bluetooth device within approximately 32 feet (10 meters). The Bluetooth connection can be subject to interference from obstructions such as walls or other electronic devices.



Note: There may be restrictions on using Bluetooth devices in some locations.

The Nokia 6820 phone is designed to be compliant with and adapt to Bluetooth Specification 1.1. Compatibility between the phone and other products with Bluetooth wireless technology depends also on the profiles and protocols used by the devices. The current profiles supported by the Nokia 6820 phone are:

- SAP (SIM access profile)
- OPP (object push profile) as a client and server

- FTP (file transfer profile) as a server
- DUN (dial-up networking profile) as a gateway
- HSP (headset profile)
- HFP (hands-free profile) as an audio gateway
- SDP (service discovery profile)
- GAP (generic access profile)
- SPP (serial port profile) with the PC connectivity software
- GOEP (generic access exchange profile)

When a profile is active, the profile is shown on the phone display, such as **Remote SIM**, to indicate that the phone is disconnected from the GSM network, thereby deactivating all phone functions.

For compatibility between your phone and another Bluetooth device, consult the manufacturer of the device. In some locations, there may be restrictions on using Bluetooth devices. Check with your local authorities.



Note: Using Bluetooth features, or allowing them to run in the background while using other features, increases the demand on battery power and reduces the battery life.

Set up a Bluetooth connection

When you activate the Bluetooth application for the first time, you are asked to provide a Bluetooth name for your phone. This is the name that will be seen by other Bluetooth users.

Use the following steps to activate your Bluetooth connection.

- 1 Select **Menu > Settings > Connectivity > Bluetooth**.
- 2 Select **Bluetooth > On**.

The active Bluetooth connection is indicated by  at the top of the display.



Note: If you do not plan to use the Bluetooth feature for an extended time period, deactivate it to save power.

- 3 Select **Search for audio enhancements** to search for compatible Bluetooth devices.
- 4 Select the device that you want to connect to the phone.
- 5 Enter the Bluetooth passcode of the device to associate (or *pair*) and connect the device. (You only need to give this passcode when you connect to the device for the first time.)

Set up Bluetooth name and visibility

Select **Menu > Settings > Connectivity > Bluetooth > Bluetooth settings** to define how your phone appears to other Bluetooth devices. Select from the following options:

My phone's visibility and **Shown to all**—to show the phone to all other Bluetooth devices.

Hidden—to show the phone only to the paired devices.

My phone's name—to change the Bluetooth device name for your phone.

Start a Bluetooth connection

Select **Menu > Settings > Connectivity > Bluetooth**, and select from the following options:

View active device—to check which Bluetooth connection is currently active. To close the connection to the selected device, select **Disconnect**.

View paired devices—to view a list of Bluetooth devices that are currently paired with the phone. Scroll to the desired device. To delete the pairing to the device, select **Delete**.

Select **Options**—to access some of the following functions. (This list may change depending on the status of the device and the Bluetooth connection.)

Connect—to connect to the selected device.

Assign short name—to give a nickname (visible to you only) to the selected device.

Request conn. authorization—to set up authorization. Select **No** to allow the phone to connect automatically. Select **Yes** if you want the phone to prompt you first.

Infrared

The phone has an IR (infrared) port that you can use for connecting your phone to another IrDA compliant device. You can send or receive data such as business cards and calendar notes to or from a compatible phone or data device, such as a computer.

Do not point the IR (infrared) beam at anyone's eye or allow it to interfere with other IR devices. This device is a Class 1 Laser product.

Send and receive data using IR

- Ensure that the IR ports of the sending and receiving devices are pointing at each other and that there are no obstructions between the devices.
- To activate the IR port of your phone, select **Menu > Settings > Connectivity > Infrared**.
- The user of the sending phone selects the desired IR function to start data transfer.

If the data transfer is not started within two minutes after the activation of the IR port, the connection is cancelled and has to be started again.

IR connection icon

- When  appears continuously, the IR connection has been activated and your phone is ready to send or receive data using its IR port.
- When  blinks, your phone is trying to connect to the other device or a connection has been lost.

The IR connection deactivates automatically.

EGPRS

GPRS (general packet radio service) is a network service that allows mobile phones to be used for sending and receiving data over an IP-based network. GPRS is a data bearer that enables wireless access to data networks, such as the Internet.

EGPRS (enhanced GPRS), also known as EDGE (enhanced data rates for GSM evolution) is similar to GPRS but the connection is faster. For more information on availability of EGPRS and data transfer speed, contact your service provider.



Note: The Nokia 6820 phone is 3GPP GSM Release 99 terminal supporting EGPRS service. It is also designed to support Release 97 GPRS networks. However, proper functionality in all Release 97 GPRS networks cannot be guaranteed. For more information, contact your service provider.

The applications that may use EGPRS are multimedia, IM and text messaging, browsing sessions, e-mail, remote SyncML, Java application downloading and the PC dial-up (such as Internet and e-mail).

To use EGPRS technology, you must first do the following:

- Contact your service provider for availability and subscription to the EGPRS service.
- Save the EGPRS settings for each of the applications used over EGPRS.

For information on pricing, contact your service provider.



Note: When you select GPRS as a data bearer, the phone uses EGPRS instead of GPRS, if it is available in the network. You cannot select between EGPRS and GPRS but for some applications you may be able to select either GPRS or GSM data (CSD).

EGPRS CONNECTION

Your phone supports three simultaneous EGPRS connections. You can browse XHTML pages, receive multimedia messages and maintain a PC dial-up connection, all at the same time.

Select **Menu > Settings > Connectivity > GPRS > GPRS connection**.

Select **Always online** to set the phone to automatically register to an EGPRS network when you switch the phone on. When the GPRS connection is established, the icon  appears on the top left of the display.

When you start an application using EGPRS, the connection between the phone and the network is established, and data transfer is possible. When you end the application, the EGPRS connection is ended but the registration with the EGPRS network remains.

If you receive a call or a text message, or make a call during a GPRS connection, the icon  appears on the top right of the display to indicate that the EGPRS connection has been suspended (on hold).

The GPRS and EGPRS connections are indicated by the same icons.

If you select **When needed**, the EGPRS registration and connection are established when required by an application using GPRS and closed when you end the application.

• EGPRS MODEM SETTINGS

You can connect the phone to a compatible PC using IR, Bluetooth or a data cable connection and use the phone as a modem to enable EGPRS connectivity from the PC.

Select **Menu > Settings > Connectivity > GPRS > GPRS modem settings**. Select **Active access point** to activate the desired access point. Select **Edit active access point** to change the access point settings.

- Select **Alias for access point**. Key in the name that you would like for the activated access point and select **OK**.
- Select **GPRS access point**. Key in the access point name (APN) to establish a connection to an EGPRS network. Contact your service provider for the APN.

You can also set the EGPRS dial-up service settings (APN) on your PC using the Nokia Modem Options software. See "PC Suite" on page 80. If you have set the settings on both your PC and on your phone, the settings for the PC are used.

• CALL SETTINGS

Select **Menu > Settings > More settings > Call settings**, and select from the following options:

Call forwarding (network service)—to direct your incoming calls to an alternate location, such as your voice mailbox number. Forwarding options that are not supported by your SIM card or your service provider may not be shown. Contact your service provider for details.

For example, select **Call forwarding** to forward your voice calls when your number is busy or when you reject an incoming call.

To turn on call forwarding, select **Call forwarding**, select a menu option, and choose **Activate**. To turn call forwarding off, select **Cancel**. To check whether call forwarding is activated or not, select **Check status**.

To see the call forwarding icons in the standby mode, see "Icons in the standby mode" on page 16.

Anykey answer > On—to answer an incoming call by briefly pressing any key, except the **Power** key, **Left selection** key, **Right selection** key, and **End** key.

Automatic redial > On—to set up your phone to make a maximum of ten attempts to connect a call after an unsuccessful call attempt.

1-touch dialing > On—to turn on speed dialing.

Call waiting > Activate—to set up the phone to notify you of an incoming call while you have a call in progress. See "Call waiting" on page 20. This feature requires supporting network services.

Summary after call > On—to set the phone up to briefly display the duration and cost of the call when it terminates. This feature requires supporting network services.

Send my caller identity > Yes—to set your phone up to display your phone number to the person you are calling. Select **Set by network** and the setting agreed upon with your service provider is used. This feature requires supporting network services.

Line for outgoing calls—to select the phone line 1 or 2 for making calls. For example, you can use line 1 for personal calls and line 2 for business calls. For more information on availability, contact your service provider.

If you select **Line 2** and have not subscribed to this network service, you will not be able to make calls. However, calls on both lines can be answered regardless of the selected line.

If supported by your SIM card, you can prevent the line selection by selecting the **Lock** option.



Note: In the standby mode, you can switch from one line to the other by pressing and holding the * key.

• PHONE SETTINGS

Select **Menu > Settings > More settings > Phone settings**, and select from the following options:

Phone language—to set the language for the display text. If **Automatic** is selected, the phone selects the language according to the information on the SIM card.

Memory status—to view the amount of free, used, and total amount of memory for each function. You may also find memory information in the menus of some functions, for example in the **Applications** menu.

Security keyguard—to lock the keypad of the phone with a security code. For more information, see "Security code" on page 54.

- Key in the security code and select **OK**.
- To set the security keyguard, select **On**. The keypad lock remains active if you open the keyboard.
- To activate the security keyguard, select **Menu** and the * key within 1.5 seconds (when the keyboard is closed). To deactivate the keyguard when the keyboard is open, select **Unlock > OK**; then key in the security code. If the keyboard is closed, select **Unlock** and press the * key within 1.5 seconds. Then key in the security code.
- When the keypad is locked,  appears on top of the display. If you have activated the security keyguard, it does not protect your phone data from PC Suite access.

Cell info display > On—to set the phone to indicate when it is used in a cellular network that is based on micro cellular network (MCN) technology.

Welcome note—to customize the welcome note. Key in the note that you would like to be shown briefly when the phone is switched on and select **Save**.

Operator selection > Automatic—to set up the phone to automatically select one of the cellular networks available in your area.

If you select **Manual**, you can select a network that has a roaming agreement with your service provider. If **No network access** is displayed, you must select another network. The phone stays in manual mode until the automatic mode is selected or another SIM card is inserted into the phone.

Confirm SIM service actions—to receive confirmation messages when SIM services are being used. For more information, see “SIM services” on page 79.

Help text activation—to set the phone to show the help topics.

Start-up tone—to set the phone to play a start-up tone when it is switched on.

• ENHANCEMENT SETTINGS

The enhancement settings menu is only shown if the phone is or has been connected to some mobile enhancements (accessories), such as a charger or hands-free unit.

Select **Menu > Settings > More Settings > Enhancement settings**. Then select an appropriate enhancement from a list, if the corresponding enhancement is or has been connected to the phone. You can select the following options:

Default profile—to automatically activate the desired profile when you connect to the selected enhancement. You can select another profile while the enhancement is connected.

Automatic answer—to set the phone to automatically answer an incoming call after five seconds. If the **Incoming call alert** is set to **Beep once** or **Off**, automatic answer will not be used.

Lights—to set the lights permanently to **On**. Select **Automatic** to set the lights on for 15 seconds after a keypress. The **Lights** option is available only when **Handsfree** is selected.

When the phone is connected to the full car kit, select **Ignition detector** and **On** to automatically switch off the phone approximately 20 seconds after you have switched off the ignition.

For the Loopset, select **Use Loopset**.

For **Text phone**, select **Use text phone** and select **Yes** to use the text phone settings instead of headset or loopset settings.

• SECURITY SETTINGS

To work with security settings, select **Menu > Settings > More settings > Security settings**, and select the setting you would like to modify.



Note: When security features that restrict calls are in use (call restricting, closed user group, and fixed dialing), calls may be possible to certain emergency numbers in some networks.

PIN code request

Select **PIN code request** to set the phone to ask for your PIN code every time the phone is switched on. Some SIM cards do not allow the PIN code request to be turned off.

Call restricting

Select **Call restrictions** to restrict incoming calls to, and outgoing calls from, your phone. Network service and a password are required.

Fixed dialing

Select **Fixed dialing** to restrict your outgoing calls and text messages to selected phone numbers if this function is supported by your SIM card. The PIN2 code is required.

When the fixed dialing is on, GPRS connections are not possible except while sending text messages over a GPRS connection. In this case, the recipient's phone number and the message center number must be included in the fixed dialing list.

Closed user group

Closed user group is a network service that specifies the group of people whom you can call and who can call you. For more information, contact your service provider.

Security level

Security level instructs the phone to ask for the security code whenever a new SIM card is inserted into the phone.

Memory

Select **Memory** to set the phone to request the security code when the SIM card memory is selected.

Access codes

Select **Access codes** to change the security code, PIN code, PIN2 code or restriction password. Codes can only include numbers from 0 to 9. Refer to the following items when changing access codes.

SECURITY CODE

The security code is 5 to 10 digits and protects your phone against unauthorized use. The preset code is 12345. When you have changed the code, keep the new code secret and in a safe place separate from your phone. To change the code, and to set the phone to request it, see "Security settings" on page 53.

If you key in an incorrect security code five times in succession, the phone may display **Code error**. Wait for five minutes and key in the code again.

PIN AND PIN2 CODES

The PIN (personal identification number) code is 4 to 8 digits and protects your SIM card against unauthorized use. The PIN code is usually supplied with the SIM card. To set the phone to request the PIN code each time the phone is switched on, see "Security settings" on page 53.

The PIN2 code may be supplied with the SIM card and is required to access some functions.

MODULE PIN

The module PIN code is 4 to 8 digits and is required to access the information in the security module. See "Security module" on page 78. The module PIN is supplied with the SIM card if the SIM card has a security module in it.

SIGNING PIN

The signing PIN is 4 to 8 digits and is required for the digital signature. See "Digital signature" on page 78. The signing PIN is supplied with the SIM card if the SIM card has a security module in it.

PUK AND PUK2 CODES (8 DIGITS)

The PUK (personal unblocking key) code is required to change a blocked PIN code. The PUK2 code is required to change a blocked PIN2 code.

If the codes are not supplied with the SIM card, contact your service provider.

If you key in an incorrect PIN code three times in succession, the phone may display **PIN blocked** or **PIN code blocked** and ask you to key in the PUK code.

RESTRICTION PASSWORD (4 DIGITS)

The restriction password is required when using the **Call restriction service**. You can obtain the password from your service provider.

WALLET CODE (4 TO 10 DIGITS)

The wallet code is required to access the wallet services. If you key in an incorrect wallet code several times, the wallet application is blocked for five minutes. For further information, see "Wallet" on page 63.

• RESTORE FACTORY SETTINGS

To reset the menu settings to their original values, select **Menu > Settings > Restore factory settings**. Key in the security code and select **OK**.



Note: The data you have keyed in or downloaded, for example the names and phone numbers saved in contacts, are not deleted.

11 Gallery



In the **Gallery** menu you can manage images, photos, recordings, tones and video clips.

Your phone supports usage rights system to protect acquired content. A piece of content, for example ringing tone, can be protected and associated with certain usage rules, for example number of usage times and a certain usage period. The rules are defined in the usage rights for the content which can be delivered either together with the content or independently depending on the service provider. You may be able to update these rights. Always check the delivery terms of any content and usage rights before acquiring them, as they may be subject to a fee.

The **Gallery** uses shared memory. For more information, see “Shared Memory” on page 6.

1 Select **Menu > Gallery**.

A list of folders is shown. **Graphics, Images, Video clips, Recordings** and **Tones**, are the original folders on the phone. You cannot delete, rename or move the original folders on the phone.

2 Scroll to the desired folder and select **Open** to view a list of files in the folder. You can select **Options** to access **Delete, Send, Edit image, Move, Rename, Set as wallpaper, Details, Type of view, Sort, Delete all, Open in sequence, Add folder, Memory status, Activation key list**. Other available options include the following:

Type of view—to select how the folders are displayed.

Gallery downloads—to download more images and tones. Select **Image downloads** or **Tone downloads**. The list of available browser bookmarks is shown. Select **More bookmarks** to access the list of bookmarks in the **Services** menu.

Select the appropriate bookmark to connect to the desired site. If the connection fails, you may not be able to access the page from the service whose connection settings are currently active. In this case, enter the **Services** menu and activate another set of service settings. Try again to connect to the site.

For availability of different services, pricing and tariffs, contact your service provider. Download content only from the sources you trust.

3 If you opened a folder in step 2, select the file you want to view and select **Open**.

Or, select **Options** to access **Edit image, Set contrast, Set as wallpaper, Set as ringtone, Details, Delete, Send, Move, Rename, Open in sequence, Mute audio (Unmute audio), Play, Zoom**. Choose from the following options:

Send—to send the selected file using MMS, a Bluetooth connection, or an IR connection.

Delete—to delete the file.

Edit image—to insert text, a frame or clip-art into the selected picture.

View in sequence—to view the files in the folder one by one.

Play—to listen to or to view a sound or image file that is contained in the message.

Zoom—to increase the size of the image that is contained in the message.

Mute audio (Unmute audio)—to mute (unmute) the sound file.

Set contrast—to adjust the contrast level of the image.

Update rights—to update the usage rights of the selected file. The option is only shown if the rights update is supported by the file.

Copyright protections may prevent some images, ringing tones, and other content from being copied, modified, transferred or forwarded.

12 Camera



You can take photos and record video clips with the built-in camera. The camera lens is on the back of the phone, and the display of the phone works as a viewfinder. The camera produces pictures in JPEG format and the video clips in H.263 (SubQCIF) format. You cannot use the camera when the keyboard is open.

The camera includes a self-timer if you want to be included in the photo. The timer allows you 10 seconds before the camera takes the photo.

If there is not enough memory to take a new photo or record a video clip, you need to free some by deleting old photos or other files from **Gallery**. The camera uses shared memory. For more information, see "Shared Memory" on page 6.



Note: Obey all local laws governing the taking of pictures.

• CAMERA SETTINGS

Use this procedure to choose your camera settings.

Select **Menu > Camera > Settings**. Choose settings for the following:

Image quality—to define how much the photo file will be compressed when saving the image. Select **High**, **Normal** or **Basic**. The **High** setting provides the best image quality but takes more memory.

Video clip length—to select the length for video clips recorded with the camera. Select **Default** if you intend to send the file as a multimedia message.

Camera sounds—to set the shutter sound and the self-timer tone to **On** or **Off**.

Default title—to define the prefix the camera should use to name the photo files.

If you select **Automatic**, the camera uses the prefix **Image** with an incremental number (such as **Image001**, **Image 002**).

If you select **My title**, you can key in a prefix for a series of photos and the camera numbers the photo files for you. For example (**PoolParty001**, **PoolParty002**).

• TAKE A PHOTO

1 Select **Menu > Camera** and choose from the following:

- **Standard photo**—to take a basic photo using landscape orientation.
- **Portrait photo**—to take a photo using portrait orientation.
- **Night mode**—to take a photo when the lightning is dim.



Note: To quickly access the camera in the standby mode (with standard photo view), move the joystick up.

The image appears on the display, and you can use the display as a viewfinder.

2 Select **Capture**.

The phone saves the photo in the **Photos** folder of the **Gallery** menu. The saved photo appears on the display.

3 Select **Back** to take another photo, or select **Options** and select from the following:

- **Zoom**—to enlarge the view. Use the joystick to reposition the picture in the viewfinder window.
- **Send**—to send the photo using MMS, IR or Bluetooth technology.
- **Rename**—to change the name of the photo.
- **Open Gallery**—to view the folders in the **Gallery** menu.
- **Set contrast**—to adjust the contrast for the photo.
- **Set as wallpaper**—to save the photo as background wallpaper on your phone.
- **Details**—to see the name, size, resolution, date created, format, and copyright information.

4 To use the viewfinder options, select **Options** and select from the following:

- **View Previous**—to view the previous photo.
- **Open Gallery**—to view the folders in the **Gallery** menu.
- **Change mode**—to change the type of photo or video.
- **Self-timer**—to take a photo using a delay.

To use the self-timer, select **Start** and, after the timeout period (approximately 10 seconds) the camera takes the photo and saves it in the **Gallery** menu. While the self-timer is running, a beeping sound is heard.

• RECORD A VIDEO CLIP

Select **Menu > Camera > Video > Record**. The recording icon  and the remaining recording time are shown at the top of the display.

To stop the recording, select **Stop** and the video clip is saved in the **Video clips** folder of the **Gallery** menu.

To pause the recording, select **Pause**. To resume the recording, select **Continue**.

Select **Options** to select, for example, an option to set the desired operation mode, mute or unmute the microphone, or access the **Gallery**.

13 Organizer



• ALARM CLOCK

The alarm clock uses the time format that has been set for the clock. The alarm clock works even when the phone is switched off.

Select **Menu > Organizer > Alarm clock**.

- Select **Alarm time**, key in the alarm time and select **OK**.
To change the alarm time, select **On**.
- Select **Alarm tone**, and you can select a default alarm tone, personalize your alarm tone by selecting one from the ringing tone list or from the **Gallery**.

When the alarm time expires, the phone sounds an alert tone, and flashes **Alarm!** along with the current time on the display. Select **Stop** to stop the alarm. If you let the alarm continue for a minute or if you select **Snooze**, the alarm stops for about ten minutes and then resumes.

If the alarm time is reached while the phone is switched off, the phone switches itself on and starts sounding the alarm tone. If you select **Stop**, the phone prompts you to activate the phone for calls by displaying **Switch the phone on?**. Select **No** to switch off the phone or **Yes** to make and receive calls.



Note: Do not select **Yes** when wireless phone use is prohibited or when it may cause interference or danger.

• CALENDAR

The calendar helps you to keep track of reminders, calls that you need to make, meetings, and birthdays.

The calendar uses shared memory. For more information, see “Shared Memory” on page 6.

- 1 Select **Menu > Organizer > Calendar**.



Note: To quickly view the current **Calendar** month, move the joystick to the right in the standby mode.

- 2 Scroll to the day that you want and select **View**.

The current day is indicated by a frame around the day. If there are any notes set for the day, the day is shown in bold type.

- 3 To view a single note, scroll to the desired note, and select **View**.

You can scroll to view the entire note.

- 4 To perform other tasks, select **Options** and choose from the following:

Make a note—to create a note.

Delete, Edit, or Move options—to erase, change, or move a note.

Go to date—to go directly to a new date.

Send note—to send the note to a compatible phone calendar using IR, calendar, text message, MMS, or Bluetooth technology.

Copy—to copy the note to another day.

Settings—to set the date, time, date or time format, or the first day of the week. In the **Auto-delete** option you can set the phone to automatically delete old notes after a specified time. However, the repeated notes, for example birthday notes, will not be deleted.

Go to to-do list—to take a shortcut to the to-do list.

Add a calendar note

For information on keying in letters and numbers, see “Tips for writing text” on page 24.

About the Alarm Feature

When you add a calendar note, you have the option to use an alarm. If you set the alarm, the phone will beep and display the note at the alarm time. When a call note icon  is shown on the display, you can call the displayed number by pressing the **Talk** key. To stop the alarm and view the note, select **View**. Select **Snooze** to phone returns to the standby mode. To stop the alarm without viewing the note, select **Exit**.

Select **Menu > Organizer > Calendar** or move the joystick to the right in the standby mode to go to the monthly view. Scroll to the date that you want, and select **View**. Select **Add Note** if there are no notes for the day, or select **Options > Make a note** and select from the following:

 **Meeting**—Key in the note and select **Save** (or select **Options** and search for the name in contacts and select **OK**). Key in the location of the meeting, select **Save**. Key in the start time for the meeting and select **OK**, and then key in the end time and select **OK**. To set the alarm for the note, select **With tone** or **Silent** (no alarm tone) and then set the alarm time.

 **Call**—Key in the phone number, and select **Save**. Key in the name, select **Save**. (Instead of keying in the phone number, search for the name and number in contacts). Key in the time for the call and select **OK**. To set the alarm for the note, select **With tone** or **Silent** (no alarm tone) and then set the alarm time.

 **Birthday**—Key in the name (or select **Options** and search for it in contacts) and select **Save**. Then key in the year of birth and select **OK**. To set the alarm for the note, select **With tone** or **Silent** (no alarm tone) and then set the alarm time.

 **Memo**—Key in the note, and select **Save**. Key in the end day for the note and select **OK**. To set the alarm for the note, select **With tone** or **Silent** (no alarm tone) and set the alarm time.

 **Reminder**—Key in the subject for the reminder, and select **Save**. To set the alarm for the note, select **Alarm on** and set the alarm time.

When you have set the alarm, the icon  is displayed when you view the notes.

• TO-DO LIST

In the to-do list, you can save notes for tasks that you have to do and manage the tasks in different ways.

The to-do list uses shared memory. For more information, see "Shared Memory" on page 6.

Select **Menu > Organizer > To-do list**.

- To add a new note when the task list is empty, select **Add note**, or select **Options** and select **Add** if you have saved tasks. Select **Save** and select the priority for the note **High**, **Medium**, or **Low**. The phone automatically sets the deadline without an alarm for the note. To change the deadline, view the note and select the option **Deadline**.
- In the task list, you can select **Options**, and select an option for, example to sort the tasks by priority or by deadline, send them to another phone, save them as a calendar note, or access the calendar.
- To view a task, scroll to the desired task on the list and select **View**. To edit the displayed task, select **Edit**.

• NOTES

You can use **Notes** for writing and sending notes using IR, SMS, or MMS. **Notes** uses shared memory. For more information, see "Shared Memory" on page 6.

- 1 Select **Menu > Organizer > Notes**, or type a character when the messaging keyboard is open.
The phone will ask you to set the date and time, if they have not already been set when you start to write a note.
- 2 To add a new note, select **Add note** (if the list of notes is empty) or select **Options > Make a note**.
- 3 To view a note, scroll to the desired note on the list and select **View**.
- 4 To edit the displayed note, select **Edit**.
- 5 Key in the note and select **Save**.

If you select **Options**, you can select **Insert time & date** to add the current time and date to the note. If there is not enough space for time and date, the phone will ask you to delete the appropriate number of characters from your note.

You can also send the note using IR, Bluetooth connection, MMS, or as a text message (SMS) to another compatible phone. If the note is too long to be sent as a text message, the phone prompts you to delete the appropriate number of characters from your note.

• WALLET

You can use the wallet to pay for your purchases made from the browser. You can save your personal information, such as credit card numbers and addresses in the wallet, and then use the data that are saved in the wallet during browsing. You can also save access codes to mobile services that request a user name and password.

The data in the wallet is protected with a wallet code that you can define when you access the wallet for the first time. At **Create wallet code**, key in the code and select **OK** to confirm it and at **Verify wallet code**, key in the code again and select **OK**.

To delete all the contents of the wallet and the wallet code, key in *#7370925538# (*#res wallet# in letters) in the standby mode. You also need the security code for the phone. See "Access codes" on page 54.

Access the wallet

Select **Menu > Organizer > Wallet**. Key in your wallet code, select **OK**. You then can choose from the following options:

Wallet profiles—to create card combinations, for example, for different services. A wallet profile is helpful if the service asks you to fill in many data items. You can select the appropriate wallet profile instead of selecting different cards separately.

Cards—to save personal card information. You can save payment card, loyalty card and access card information, including information such as user name and password combinations for different services.

Tickets—to save notifications of e-tickets that you have bought using your mobile service. To view the tickets, scroll to the desired ticket and select **View**.

Receipts—to save receipts for mobile purchases.

Personal notes—to save all kinds of personal information that you want to protect by the wallet PIN code.

Settings—to manage your wallet settings. For more information, see "Wallet settings" on page 65.

Save card details

- 1 Select **Menu > Organizer > Wallet > Cards**.
- 2 Select one of the following card types to save the details:

Payment cards—for credit and debit cards.

Loyalty cards—for membership cards.

Access cards—for personal user names and passwords to online services.

Address cards—for basic contact information for home or office.

User info cards—for customized personal preferences for online services.

- 3 If there are no cards in the folder, select **Add** to create a new card.
- 4 To view saved details of the card, scroll to the desired card and select **View**.
- 5 Fill in the fields for the details and select **Done**.

You can also receive card information to your phone over the air from a card issuer or service provider. You will be notified as to which category the card belongs to. Save or discard the received card. You can view, but not edit the saved card. To receive card information over the air, contact the card issuer or service provider.

Add personal notes

You can save personal notes, for example, account numbers, passwords, codes, or notations.

Access the wallet and select **Personal notes**. To create a new personal note, select **Add new**.

To view a note, scroll to the desired note on the list and select **View**. To edit the displayed note, select **Edit**.

When viewing a note, you can select the following options **Send via text msg**, **Copy to calendar**, **Use detail** or **Delete**.

Create a wallet profile

When you have saved your personal card details, you can combine them together to create a wallet profile. You can use the wallet profile to retrieve wallet data from different cards while browsing.

- 1 Select **Menu > Organizer > Wallet > Wallet profiles**.
- 2 To create a new wallet profile, select **Add new**.
- 3 Fill in the following fields and select **Done**.

Some of the fields contain data that are selected from the wallet. You must save the data before you can create a wallet profile.

Wallet profile name—enter a name for the profile.

Select payment card next—select a card from the payment card list.

Select loyalty card next—select a card from the loyalty card list.

Select access card next—select a card from the access card list.

Select user info card next—select a card from the user data card list.

Select billing address next—select an address from the address card list.

Select shipping address next—select an address from the address card list.

Select receipt delivery address next—select an address from the address card list.

Select receipt delivery method next—select the way to deliver the receipt; **Receipt to phone number** or **Receipt to e-mail address**.

Wallet settings

- 1 Select **Menu > Organizer > Wallet > Settings**.
- 2 Select **Change code** to change the wallet code.
- 3 Select **RFID** to set the RFID code.

Guidelines for wallet purchases

To do your shopping, access the desired service site that supports the wallet. The service needs to support the Electronic Commerce Modeling Language specification. See "Connect to a service" on page 74.

Choose the product that you want to buy and read carefully all provided information before your purchase.



Note: The text may not fit within a single screen. Therefore, make sure that you scroll through and read all of the text before your purchase.

- To pay for the items, the phone asks whether you want to use the wallet or not. The phone also asks for your wallet PIN code.
- Select the card you want to pay with from the **Payment cards** list. Provided that the data form you receive from the service provider supports the Electronic Commerce Modeling Language specification, the phone automatically fills in the credit card information or the wallet profile from the wallet.
- When you approve the purchase, the information is forwarded.
- You may receive an acknowledgement or a digital receipt of the purchase.
- To close the wallet, select **Close wallet**. If you do not use the wallet for 5 minutes, it will be automatically closed.



Note: If you have tried to access or have accessed confidential information requiring passwords (for example, your bank account), empty the cache of your phone after each use.

• SYNCHRONIZATION

Synchronization allows you to save your calendar and contacts data on a remote Internet server or on a compatible PC. If you have saved data on the remote Internet server, you can synchronize your phone by starting the synchronization from the phone. Synchronizing to the remote server is a network service. You can also synchronize your contact and calendar data to correspond with the data on your compatible PC by starting the synchronization from your PC. The contact data in your SIM card will not be synchronized.



Note: Answering an incoming call during synchronization will end the synchronization process and you will need to restart it.

Synchronize from your phone

Before synchronizing from your phone, you may need to do the following:

- Subscribe to a synchronization service. For more information on availability and the synchronization service settings, contact your service provider.
- Retrieve the synchronization settings from your service provider.
- Set the connection settings you need for synchronization. See "Phone setup" on page 73.

To start the synchronization from your phone, use the following steps:

- 1 Activate the connection settings that you need for synchronization. See "Phone setup" on page 73.
- 2 Select **Menu > Organizer > Synchronization > Settings > Active Internet sync. settings**.
- 3 Scroll to the set you wish to activate and select **Activate**.
- 4 Mark the data to be synchronized.
- 5 Select **Menu > Organizer > Synchronization > Synchronize**.

The marked data in the active set will be synchronized after confirmation.



Note: Synchronizing for the first time or after an interrupted synchronization may take up to 30 minutes to complete, if contacts or calendar are full.

Obtain synchronization settings

You may receive the synchronization settings as an OTA message from your service provider. To receive the settings over the air, see "Over-the-air settings service" on page 18.

To key in the settings manually, use the following steps:

- 1 Select **Menu > Organizer > Synchronization > Settings > Active Internet sync. settings**.
- 2 Scroll to the set you wish to activate, and select **Activate**.

You must activate the set where you want to save the synchronization settings. A set is a collection of settings required to make a connection to a service.

- 3 Select **Edit active Internet sync. settings**. Select each setting one by one and key in all the required settings.
 - **Settings' name**—to key in the name for the set.
 - **Data to be synchronized**—to mark the data you want to synchronize. Select **Contacts** and/or **Calendar**, and select **Done**.
 - **Database addresses**—to select **Contacts database** and/or **Calendar database**.
 - **User name**—to key in the user name.
 - **Password**—to key in the password.

- **Synchronization server**—to key in the name of the server.
- **Connection settings**—to define connection settings required for synchronization.
Select each of the settings one by one and key in all the required settings. Contact your service provider for the settings.

4 Select **PC sync. settings** to key in the settings for server alerted synchronization.

5 Select and key in **User name** and **Password**.

Synchronize from your PC

To synchronize contacts and the calendar from your PC, use an IR or Bluetooth connection, or a data cable. You also need the PC Suite software of your phone installed on your PC. Start the synchronization from your PC using PC suite.

14 Applications



- **GAMES**

The games use shared memory. For more information, see “Shared Memory” on page 6.

About photosensitive seizures

A very small percentage of people may experience a seizure when exposed to certain visual images, including flashing lights or patterns that may appear in video games. Even people who have no history of seizures or epilepsy may have an undiagnosed condition that can cause photosensitive epileptic seizures while watching video games. These seizures may have a variety of symptoms, including lightheadedness, altered vision, eye or face twitching, jerking or shaking of arms or legs, disorientation, confusion, or momentary loss of awareness. Seizures may also cause loss of consciousness or convulsions that can lead to injury from falling down or striking nearby objects.

Immediately stop playing and consult a doctor if you experience any of these symptoms. Adults who allow teenagers (or children) to play the games should watch for or ask their children about these symptoms as they are more likely than adults to experience these seizures. The risk of photosensitive epileptic seizures may be reduced by playing in a well-lit room and by not playing when you are drowsy or fatigued. If you or any of your relatives have a history of seizures or epilepsy, consult a doctor before playing.

Play safely. Take a break from playing games at least every half hour. Stop playing immediately if you begin to feel tired or if you experience an unpleasant sensation or pain in your hands or arms. If the condition persists, consult a doctor.

How to play games

Select **Menu > Applications > Games** and select from the following options:

Select game—to launch a game. Scroll to a game or a game set (the name depends on the game) and select **Open**. For functions that you can access by selecting **Options** in the game list, see “Other options for an application or application set” on page 69.

Memory—to view the amount of memory that is available for game and application installations.

Settings—to set sounds, lights and shakes for the game.



Note: Running some games may consume the battery faster (and you may need to connect the phone to the charger).

• COLLECTION

Collection menu allows you to manage and use applications downloaded to the phone. Collection uses shared memory. For more information, see "Shared Memory" on page 6.

Select **Menu > Applications > Collection** and select from the following options:

Select application—to launch an application. Scroll to an application or application set (the name depends on the application) and select **Open**. For functions that you can access by selecting **Options** in the applications list, see "Other options for an application or application set" on page 69.

Memory—to view the amount of memory that is available for game and application installations.



Note: Running some applications may consume the battery faster and you may need to connect the phone to the charger.

Other options for an application or application set

Delete—to delete the application or application set from your phone.

Web access—to restrict the application from accessing the network. Select **Ask first** and the phone will ask you for net access, **Allowed** to allow the net access, or **Not allowed** not to allow the net access.

Update version—to check if a new version of the application is available for download from the services (network service).

Web page—to provide further information or additional data for the application from an Internet page. This is a network service and the menu is shown only if an Internet address has been provided with the application.

Details—to give additional information about the application.

Download a game or an application

Your phone supports J2ME™ Java games and applications. Make sure that the application or a game is compatible with your phone before downloading it. You can download new Java applications in different ways:

- Select **Menu > Applications > App. downloads > Applications** or select **Menu > Applications > Games > Game downloads**.

The list of available browser bookmarks appears. Select **More bookmarks** to access the list of bookmarks in the **Services** menu.

Select the appropriate bookmark to connect to the desired site. If the connection fails, you may not be able to access the page from the service whose connection settings are currently active. In this case, enter the **Services** menu and activate another set of service settings. (See "Connect to a service" on page 74.) Try again to connect to the site.

For the availability of different services, pricing and tariffs, contact your service provider.

- Select **Menu > Services > Download links** to download an appropriate application or game.
- Use the Nokia Application installer from PC Suite to download the applications to your phone.

When downloading a game or an application, you have the option to save it to the **Games** menu instead of the **Applications** menu.



Note: Nokia does not warrant applications from other sites. If you choose to download Java applications from them, you should take the same precautions, for security or content, as you would with any site.

• EXTRAS

Voice recorder

The voice recorder allows you to record sounds and speech. You might find this useful for recording information you intend to write down later, such as a name and a phone number. The recorder cannot be used when a data call or connection is active.



Note: Obey all local laws governing recording of calls.

MAKE A RECORDING

- 1 Select **Menu > Applications > Extras > Voice recorder**.
- 2 To start the recording, select **Record**. To start the recording during a call, select **Options > Record**. While recording a call, all parties to the call will hear a faint beeping sound.
When recording, hold the phone in the normal position near to your ear.
- 3 To end the recording, select **Stop**.
The recording is saved in the **Recordings** folder of the **Gallery** menu.
- 4 To listen to the last recording, select **Play last recorded**. To send the recording as a multimedia message, select **Send**.

LIST OF RECORDINGS

Select **Menu > Applications > Extras > Voice recorder > Recordings list**. The list of folders in the **Gallery** appears. Scroll to **Recordings**, select **Open** and you can select some of the options for files in the **Gallery**.

Calculator

The calculator in your phone adds, subtracts, multiplies, divides, calculates the square and the square root, and converts currency values.

- 1 Select **Menu > Applications > Extras > Calculator**.

- 2 When "0" appears on the screen, key in the first number of the calculation, press the **#** key for a decimal point or the corresponding symbol on the keyboard, if the keyboard is open.
- 3 Select **Options > Add, Subtract, Multiply, Divide, Square, Square root or Change sign**.
If the keyboard is open, you can also use the corresponding calculation symbols of the keyboard, if available.
-  **Note:** If you are using the calculator with the keyboard closed, press the ***** key once to add, twice to subtract, three times to multiply, or four times to divide.
- 4 Key in the second number.
- 5 For the total, select **Equals**.
- 6 To start a new calculation, press and hold **Clear**.



Note: This calculator has a limited accuracy and is designed for simple calculations.

Currency conversion

- 1 Select **Menu > Applications > Extras > Calculator**.
- 2 To save the exchange rate, select **Options > Exchange rate**.
- 3 Select either of the displayed options.
- 4 Key in the exchange rate, press the **#** key for a decimal point, and select **OK**.
The exchange rate remains in the memory until you replace it with another one.
- 5 To perform the currency conversion, key in the amount to be converted, select **Options > To home or To foreign**.

You can also perform the currency conversion in the standby mode. Key in the amount to be converted, select **Options > To home or To foreign**.



Note: When you change base currency, you must key in the new rates because all previously set exchange rates are set to zero.

Countdown timer

Select **Menu > Applications > Extras > Countdown timer**. Key in the time in hours and minutes and select **OK**. If you wish, write a note that will be displayed when the time expires, and select **OK** to start the countdown timer.

To change the countdown time, select **Change time**, or to stop the timer, select **Stop timer**.

If the alarm time is reached when the phone is in the standby mode, the phone sounds a tone and shows the note, if available or **Countdown time up**. Stop the alarm by pressing any key. If no key is pressed, the alarm stops automatically within 30 seconds. To stop the alarm and to delete the note, select **OK**.

Stopwatch

You can measure time and take split or lap times using the stopwatch. During timing, the other functions of the phone can be used. To set the stopwatch to run in the background, press the **End** key.



Note: Using the stopwatch or allowing it to run in the background when using other features increases the demand on battery power and reduces the battery life.

TAKE SPLIT TIMES OR LAP TIMES

- 1 Select **Menu > Applications > Extras > Stopwatch > Split timing or Lap timing > Start**.
You can select **Continue** if you have set the stopwatch to run in the background.
- 2 Select **Split** to take a split time, **Lap** to take a lap time, or **Stop** to stop the timing. You can scroll through the split or lap times shown below the overall time.
- 3 Select **Save** to save the lap or split times as a set of times.
- 4 To reset the times or to continue timing, select **Options > Reset** or **Start**.

VIEW AND DELETE TIMES

Select **Menu > Applications > Extras > Stopwatch**.

If the stopwatch has not been reset, select **Show last** to view the most recent measured time. Select **View times** and a list of names or the final times of the time sets is shown. Select the time set that you want to view.

To delete the saved times, select **Delete times**. Select **Delete all > OK**, or select **One by one**, scroll to the times that you want to delete, and select **Delete > OK**.

15 Services



You can access various services with the multimode browser, such as weather reports, news, flight times, financial information and entertainment.

Check the availability of these services, pricing, and tariffs with the service provider you plan to use. Service providers will also give you instructions on how to use their services.

With the multimode browser you can view the services that use wireless mark-up language (WML) or extensible hypertext markup language (XHTML). Since the phone display area and the memory capacity are much smaller than in a computer, Internet content is displayed differently on the phone. You may not be able to view all details of the Internet pages.

The main steps for using services are listed below:

- 1 Save the service settings that are required to access the service that you want to use.
- 2 Make a connection to the selected service.
- 3 Start browsing the pages of the service.
- 4 When finished browsing, end the connection to the service.

• PHONE SETUP

You may receive the service settings as an over-the-air message from your service provider that offers the service that you want to use. You can also key in the settings manually or add and edit the settings using PC Suite.

For more information and for the appropriate settings, contact the service provider that offers the service that you want to use.

To receive the service settings over the air, see "Over-the-air settings service" on page 18.

Key in the service settings

- 1 Select **Menu > Services > Settings > Connection settings > Active service settings**.
- 2 Scroll to the connection set that you would like to activate and select **Activate**.
You need to activate the connection set where you want to save the service settings. A connection set is a collection of settings that are required to connect to a service.
- 3 Select **Edit active service settings**.
- 4 Select each of the settings one by one and key in all the required settings according to the information you have received from your service provider. Bearer-related settings are in the **Bearer settings** menu.

Connect to a service

Make sure that the service settings of the service that you want to use have been activated. To activate the settings:

- 1 Select **Menu > Services > Settings > Connection settings > Active service settings**.
- 2 Scroll to the set you want to activate and select **Activate**.
- 3 Connect to the service using one of the three following methods:
 - Open the start page of the service, such as the home page of the service provider. To use this method, select **Menu > Services > Home**, or in the standby mode, press and hold the **0** key. If the keyboard is open, press the corresponding number key.
 - Select the bookmark of the service. To use this method, select **Menu > Services > Bookmarks**, and select a bookmark. If the bookmark does not work with the current active service settings, activate another set of service settings and try again.
 - Key in the address of the service. To use this method, select **Menu > Services > Go to address**. Key in the address of the service, and select **OK**. It is not necessary to add the prefix `http://` in front of the address.

• BROWSE THE PAGES OF A SERVICE

After you have made a connection to the service, you can start browsing its pages. The function of the phone keys may vary in different services. Follow the text guides on the phone display. For more information, contact your service provider.

If EGPRS is selected as the data bearer, the  icon appears on the top left of the display during browsing. If you receive a call or a text message, or make a call during an EGPRS connection, the  icon appears on the top right of the display to indicate that the EGPRS connection has been suspended (on hold). After the call the phone tries to reconnect the EGPRS connection.

• USE THE PHONE KEYS WHILE BROWSING

- Move the joystick up or down to browse through the page.
- To select a highlighted item, press the joystick briefly or press the **Send** key.
- To enter letters and numbers, press the keys **0–9**. To enter special characters, press the ***** key. When the keyboard is open, you can key in letters and numbers normally.

• OPTIONS WHILE BROWSING

Select **Options** to view a list of options. The service provider may also offer other options. Choose from the following selections:

Home—to return to the home page.

Bookmarks—to view the list of bookmarks. (See "Bookmarks" on page 76.)

Download links—to show the list of bookmarks for downloading.

Add bookmark—to save the page as a bookmark.

Shortcuts—to open a new list of options that are, for example, specific to the page.

Other options—to show a list of other options, such as **Wallet** and some security options.

Reload—to reload and update the current page.

Quit—to disconnect. (See "Disconnect from a service" on page 75.)



Note: If you access confidential information requiring passwords, such as your bank account, empty the cache of your phone after each use. (See "Cache memory" on page 77.)

Direct calling

The multimode browser supports functions that you can access while browsing. You can make a voice call, send DTMF tones while a voice call is in progress, and save a name and a phone number from a page.

Disconnect from a service

To quit browsing and to end the connection, select **Options > Quit**. When **Quit browsing?** is shown, select **Yes**.

Alternatively, press the **End** key twice. The phone ends the connection to the service.

Appearance settings of the multimode browser

While browsing, select **Options > Other options > Appear. settings**, or in the standby mode, select **Menu > Services, Settings > Appearance settings**. Select from the following settings:

Text wrapping > On—to make the text continue on the next line or select **Off**, if you want it to be abbreviated when it is too long to be shown on one line.

Show images > No—to turn off the pictures while browsing. This can speed up the browsing of pages that contain a lot of pictures.

Font size—to choose a font size. Select **Small**, **Medium** or **Extra small font**.

Alerts > Alert for unsecure connection > Yes—to set the phone to alert when a secure connection changes to an unsecure one during browsing. Select **Alert for unsecure items** and **Yes** to set the phone to alert when a secure page contains an unsecure item.

Character encoding and select an option in **Content encoding**—to change the encoding for the Web page content. The default value is **Western**. Select **Unicode (UTF-8) web addresses > On**, if you want the phone to send a URL as a UTF-8 encoding.

Cookies

A cookie is data that a site saves in the browser cache memory of your phone. The data can be, for example, your user information or your browsing preferences. Cookies are saved until you clear the cache memory. See "Cache memory" on page 77.

- 1 While browsing, select **Options > Other options > Security > Cookie settings**, or in the standby mode, select **Menu > Services > Settings > Security settings > Cookies**.
- 2 Select **Allow** or **Reject** to allow or prevent the phone receiving cookies.

• BOOKMARKS

You can save addresses as bookmarks in the phone memory.

- 1 While browsing, select **Options > Bookmarks**, or in the standby mode, select **Menu > Services > Bookmarks**.
- 2 Select the desired bookmark or press the joystick briefly to make a connection to the page associated with the bookmark.
- 3 To manage bookmarks, select **Options > View, Edit, Delete, Send, or New bookmark**.

Your phone may be set up with some bookmarks for sites that are not affiliated with Nokia. Nokia does not guarantee or endorse these sites. If you choose to access them, you should take the same precautions for security and content as you would with any Internet site.

When you receive a bookmark as an OTA message, select **Save** to add it to the bookmark list, or select **Options > View or Discard**.

• DOWNLOADS

- 1 To download more tones, images, games or applications to your phone, select **Menu > Services > Download links**.
- 2 Select **Tone downloads, Image downloads, Game downloads or App. downloads** to download tones, images, games or applications, respectively.

Download content only from sources you trust.

• SERVICE INBOX

The phone is able to receive service messages (pushed messages) from your service provider.

To set the phone to receive service messages, select **Menu > Services > Settings > Service inbox settings > Service messages > On**.

- To view a received service message, select **View**. If you select **Exit**, the message is moved to the **Service inbox**. To view the service message later, select **Menu > Services > Service inbox**.
- While browsing, select **Options > Other options > Service inbox**. Scroll to the message that you want, and select **Retrieve** to download the marked content from the Web page, or select **Options > Details or Delete**.

• CACHE MEMORY

The information or services you have accessed are stored in the cache of your phone. A cache is a buffer memory that stores data temporarily.

To empty the cache while browsing, select **Options > Other options > Clear the cache**.

To empty the cache in the standby mode, select **Menu > Services > Clear the cache**.

• BROWSER SECURITY

Security features may be required for some services, such as banking services or shopping on a site. For such connections you need security certificates and possibly a security module, which may be available on your SIM card. For more information, contact your service provider.

CERTIFICATES

There are three kinds of certificates: server certificates, authority certificates, and user certificates.

The phone uses a server certificate to improve security in connection between the phone and the gateway. The phone receives the server certificate from the service provider before the connection is established and its validity is checked using the authority certificates that are saved on the phone. Server certificates are not saved.

The security icon  is displayed during a connection if the data transmission between the phone and the gateway (identified by the **IP address** in the **Edit active service settings**) is encrypted.

However, the security icon is not an indication that the data transmission between the gateway and the content server (place where the requested resource is saved) is secure. It is up to the service provider to secure the data transmission between the gateway and the content server.

Authority certificates are used by some services, such as banking, for checking the validity of other certificates. Authority certificates can be either saved in the security module by the service provider, or they can be downloaded from the network, if the service supports the use of authority certificates.

User certificates are issued to users by a Certifying Authority. User certificates are required, for example, to create a digital signature and they associate the user with a specific private key in a security module.

While the use of certificates makes the risks involved in remote connections and software installation considerably smaller, they must be used correctly in order to benefit from increased security. The existence of a certificate does not offer any protection by itself. The certificate manager must contain correct, authentic, or trusted certificates for increased security to be available.

Certificates have a restricted lifetime. If *Expired certificate* or *Certificate not valid yet* is shown (even if the certificate should be valid), check that the current date and time in your phone are correct.

Before changing these settings, make sure that you really trust the owner of the certificate and that the certificate really belongs to the listed owner.

SECURITY MODULE

The security module can contain certificates as well as private and public keys. The security module may improve the security services for applications requiring browser connection, and allows you to use a digital signature. The certificates are saved in the security module by the service provider.

Select **Menu > Services > Settings > Security settings > Security module settings**.

Select from the following module settings:

Security module details—to show the security module title, status, manufacturer and serial number.

Module PIN request—to set the phone to ask for the module PIN when using services that are provided by the security module. Key in the code and select **On**. To disable the module PIN request, select **Off**.

Change module PIN—to change the module PIN, if allowed by the security module. Key in the current module PIN code; then key in the new code twice.

Change signing PIN—to change a signing PIN. Select the signing PIN that you want to change. Key in the current PIN code; then key in the new code twice.

DIGITAL SIGNATURE

You can create digital signatures with your phone. The signature can be traced back to you through the private key in the security module and the user certificate that was used to create the signature. Using the digital signature may be considered to be equal to a normal signature on any legal document.

To create a digital signature, select a link on a page, for example, the title of the book you want to buy and its price. The text that needs to be signed (possibly including amount, date, etc.) will be shown.

Check that the header text is **Read** and that the digital signature  icon is shown.



Note: If the digital signature icon does not appear, there is a security breach and you should not enter any personal data such as your signing PIN.

To add the digital signature to the text, read all of the text before you select **Sign**. The text may not fit on a single screen. Therefore, make sure to scroll through and read all of the text before signing.

Select the user certificate that you want to use. Key in the signing PIN and select **OK**. The digital signature icon will disappear, and the service may display a confirmation of your purchase.

16 SIM services



In addition to the functions that are available on the phone, your SIM card may provide additional services that you can access in **Menu 10**.

Menu 10 is only shown if it is supported by your SIM card. The name and contents of the menu depend entirely on the service available.



Note: For availability, rates and information on using SIM services, contact your SIM card vendor.

You can set the phone to show you the confirmation messages that are sent between your phone and the network when you are using the SIM services by selecting the option **Yes Confirm SIM service actions** in **Phone settings**.



Note: Accessing these services may involve sending a text message (SMS) or making a phone call for which you may be charged.

17 PC connectivity

You can send and receive e-mail, and access the Internet when your phone is connected to a compatible PC using an IR or Bluetooth connection, or a data cable. You can use your phone with a variety of PC connectivity and data communications applications. With PC Suite you can, for example, synchronize contacts, calendar, to-do notes, and notes between your phone and the compatible PC.

You can find more information and downloadable files on the Nokia Web site:

www.nokia.ca.

• PC SUITE

PC Suite contains the following applications:

- Nokia Application Installer to install Java applications from the compatible PC to the phone.
- Nokia Image Converter to create images in supported formats for portrait images, multimedia messages, or wallpapers, and to transfer them to your phone.
- Nokia Sound Converter to edit polyphonic ringing tones in supported formats to be compatible with your phone and transfer them to your phone.
- Nokia Content Copier to copy data or back-up data from your phone to a compatible PC or to another compatible Nokia phone.
- Nokia Settings Manager to edit and send your browser bookmarks or update the connection sets to your phone.
- Nokia Phone Editor to send text messages (SMS) and edit the contacts in your phone.
- Nokia Phone Browser to view the contents of the Gallery folder of your phone on a compatible PC. You can browse picture and audio files in the phone memory and to transfer them between phone and PC.
- Nokia Multimedia Player to play multimedia (MMS) messages, and audio and video files. You can also create playlists of your favorite multimedia files.
- Nokia PC Sync to synchronize contacts, calendar, to-do notes and notes between your phone and your PC.
- Nokia 6820 data modem drivers to use your phone as a modem.
- Nokia Modem Options to obtain settings for HSCSD and GPRS connections.
- Nokia Connection Manager to select the connection type between the PC and the phone.

Copyright protections may prevent some images, ringing tones and other content from being copied, modified, transferred or forwarded.

EGPRS, HSCSD and CSD

You can use EGPRS, GPRS, HSCSD, and CSD data services. For availability and subscription to data services, contact your service provider.

The use of HSCSD service consumes the battery more quickly than normal voice or data calls. You may need to connect the phone to a charger for the duration of data transfer.

For more information, see “EGPRS modem settings” on page 51.

- **DATA COMMUNICATIONS APPLICATIONS**

For information on using a data communications application, refer to the documentation provided with it.



Note: Making or answering phone calls during a computer connection is not recommended as it might disrupt the operation.

For a better performance during data calls, place the phone on a stationary surface with the keypad facing downward. Do not move the phone or hold it in your hand during a data call.

18 Enhancements



This section provides information about the batteries, chargers, and accessories for your phone. Be aware that the information in this section is subject to change as the batteries, chargers, and accessories change.



Warning: Use only batteries, chargers and accessories approved by the phone manufacturer for use with this particular phone model. The use of any other types may invalidate any approval or warranty applying to the phone, and may be dangerous. For availability of approved accessories, please check with your dealer.

• SAFETY

- Keep all enhancements out of the reach of small children.
 - When you disconnect the power cord of any enhancement, grasp and pull the plug, not the cord.
 - Check regularly that any vehicle-installed enhancements are mounted and are operating properly.
 - Installation of any complex car enhancements must be made by qualified personnel only.
- Check the model number of any charger before use with this device. This device is intended for use when supplied with power from ACP-7U, ACP-12U, LCH-12, and AC-1U.

• ENHANCEMENTS FOR YOUR PHONE

For detailed information on accessories and enhancements, contact your authorized Nokia dealer or visit the Nokia Web site at www.nokia.ca.

Audio

- Wireless Headset (HDW-3)
- Wireless Clip-on Headset (HS-3W)
- Wireless Boom Headset (HS-4W)
- Boom Headset (HDB-4)
- Headset (HS-5)
- Retractable Headset (HS-10)
- HDA-10 Phone Adapter
- LPS-4 Inductive Loopset

Car

- Wireless Car Kit (CK-7W)

Imaging

- Nokia Observation Camera

Messaging

- Digital Pen

Data

- Data Cable (CA-42)
- Desktop Stand (DCV-14)

Power

- Battery, 900 mAh, Li-ion (BL-5C)
- Retractable Charger (AC-1U)
- Travel Charger (ACP-12U)

19 Reference Information

• BATTERY INFORMATION

Charging and discharging

Your device is powered by a rechargeable battery. The full performance of a new battery is achieved only after two or three complete charge and discharge cycles. The battery can be charged and discharged hundreds of times but it will eventually wear out. When the talk and standby times are noticeably shorter than normal, buy a new battery. Use only Nokia approved batteries, and recharge your battery only with Nokia approved chargers designated for this device.

Unplug the charger from the electrical plug and the device when not in use. Do not leave the battery connected to a charger. Overcharging may shorten its lifetime. If left unused, a fully charged battery will lose its charge over time. Temperature extremes can affect the ability of your battery to charge.

Use the battery only for its intended purpose. Never use any charger or battery that is damaged.

Do not short-circuit the battery. Accidental short-circuiting can occur when a metallic object such as a coin, clip, or pen causes direct connection of the positive (+) and negative (-) terminals of the battery. (These look like metal strips on the battery.) This might happen, for example, when you carry a spare battery in your pocket or purse. Short-circuiting the terminals may damage the battery or the connecting object.

Leaving the battery in hot or cold places, such as in a closed car in summer or winter conditions, will reduce the capacity and lifetime of the battery. Always try to keep the battery between 59°F and 77°F (15°C and 25°C). A device with a hot or cold battery may not work temporarily, even when the battery is fully charged. Battery performance is particularly limited in temperatures well below freezing.

Do not dispose of batteries in a fire! Dispose of batteries according to local regulations. Please recycle when possible. Do not dispose as household waste.

• ENHANCEMENTS, BATTERIES, AND CHARGERS

Check the model number of any charger before use with this device. This device is intended for use when supplied with power from ACP-12 travel charger.



Warning: Use only batteries, chargers, and enhancements approved by Nokia for use with this particular model. The use of any other types may invalidate any approval or warranty, and may be dangerous.

For availability of approved enhancements, please check with your dealer. When you disconnect the power cord of any enhancement, grasp and pull the plug, not the cord.

Your device and its enhancements may contain small parts. Keep them out of reach of small children.

• CARE AND MAINTENANCE

Your device is a product of superior design and craftsmanship and should be treated with care. The suggestions below will help you protect your warranty coverage and enjoy your device for many years.

- Keep the device dry. Precipitation, humidity, and all types of liquids or moisture can contain minerals that will corrode electronic circuits. If your device does get wet, remove the battery and allow the device to dry completely before replacing it.
- Do not use or store the device in dusty, dirty areas. Its moving parts and electronic components can be damaged.
- Do not store the device in hot areas. High temperatures can shorten the life of electronic devices, damage batteries, and warp or melt certain plastics.
- Do not store the device in cold areas. When the device returns to its normal temperature, moisture can form inside the device and damage electronic circuit boards.
- Do not attempt to open the device other than as instructed in this guide.
- Do not drop, knock, or shake the device. Rough handling can break internal circuit boards and fine mechanics.
- Do not use harsh chemicals, cleaning solvents, or strong detergents to clean the device.
- Do not paint the device. Paint can clog the moving parts and prevent proper operation.
- Use a soft, clean, dry cloth to clean any lenses (such as camera, proximity sensor, and light sensor lenses).
- Use only the supplied or an approved replacement antenna. Unauthorized antennas, modifications, or attachments could damage the device and may violate regulations governing radio devices.

All of the above suggestions apply equally to your device, battery, charger, or any enhancement. If any device is not working properly, take it to the nearest authorized service facility for service.

• ADDITIONAL SAFETY INFORMATION

Operating environment

Remember to follow any special regulations in force in any area and always switch off your device when its use is prohibited or when it may cause interference or danger. Use the device only in its normal operating positions. To maintain compliance with radio frequency exposure guidelines only use accessories approved by Nokia for use with this device. When the device is on and being worn on the body, always use an approved carrying case.

Medical devices

Operation of any radio transmitting equipment, including wireless phones, may interfere with the functionality of inadequately protected medical devices. Consult a physician or the manufacturer of the medical device to determine if they are adequately shielded from external RF energy or if you have any questions. Switch off your phone in health care facilities when any regulations posted in these areas instruct you to do so. Hospitals or health care facilities may be using equipment that could be sensitive to external RF energy.

PACEMAKERS

Pacemaker manufacturers recommend that a minimum separation of 6 in (15.3 cm) be maintained between a wireless phone and a pacemaker to avoid potential interference with the pacemaker. These recommendations are consistent with the independent research by and recommendations of Wireless Technology Research. To minimize the potential for interference, persons with pacemakers should

- Always keep the device more than 6 in (15.3 cm) from their pacemaker when the device is switched on
- Not carry the device in a breast pocket
- Hold the device to the ear opposite the pacemaker

If you have any reason to suspect that interference is taking place, switch off your device immediately.

HEARING AID

Some digital wireless devices may interfere with some hearing aids. If interference occurs, consult your service provider.

Vehicles

RF signals may affect improperly installed or inadequately shielded electronic systems in motor vehicles such as electronic fuel injection systems, electronic antiskid (antilock) braking systems, electronic speed control systems, air bag systems. For more information, check with the manufacturer or its representative of your vehicle or any equipment that has been added.

Only qualified personnel should service the device, or install the device in a vehicle. Faulty installation or service may be dangerous and may invalidate any warranty that may apply to the device. Check regularly that all wireless device equipment in your vehicle is mounted and operating properly. Do not store or carry flammable liquids, gases, or explosive materials in the same compartment as the device, its parts, or enhancements. For vehicles equipped with an air bag, remember that an air bags inflate with great force. Do not place objects, including installed or portable wireless equipment in the area over the air bag or in the air bag deployment area. If in-vehicle wireless equipment is improperly installed and the air bag inflates, serious injury could result.

Potentially explosive environments

Switch off your device when in any area with a potentially explosive atmosphere and obey all signs and instructions. Potentially explosive atmospheres include areas where you would normally be advised to turn off your vehicle engine. Sparks in such areas could cause an explosion or fire resulting in bodily injury or even death. Switch off the device at refuelling points such as near gas pumps at service stations. Observe restrictions on the use of radio equipment in fuel depots, storage, and distribution areas, chemical plants or where blasting operations are in progress. Areas with a potentially explosive atmosphere are often but not always clearly marked. They include below deck on boats, chemical transfer or storage facilities, vehicles using liquefied petroleum gas (such as propane or butane), and areas where the air contains chemicals or particles such as grain, dust or metal powders.

FCC regulations prohibit using your wireless device while in the air. The use of wireless telephones in an aircraft may be dangerous to the operation of the aircraft, disrupt the wireless telephone network, and may be illegal.

Failure to observe these instructions may lead to suspension or denial of telephone services to the offender, legal action, or both.

EMERGENCY CALLS



Important: Wireless phones, including this phone, operate using radio signals, wireless networks, landline networks, and user-programmed functions. Because of this, connections in all conditions cannot be guaranteed. You should never rely solely on any wireless phone for essential communications like medical emergencies.

To make an emergency call:

- 1 If the phone is not on, switch it on. Check for adequate signal strength. Some networks may require that a valid SIM card is properly inserted in the phone.
- 2 Press **End** key as many times as needed to clear the display and ready the phone for calls.
- 3 Key in the official emergency number for your present location. Emergency numbers vary by location.
- 4 Press the **Talk** key.

If certain features are in use, you may first need to turn those features off before you can make an emergency call. Consult this guide or your service provider. When making an emergency call, give all the necessary information as accurately as possible. Your wireless phone may be the only means of communication at the scene of an accident. Do not end the call until given permission to do so.

CERTIFICATION INFORMATION (SAR)

THIS MODEL PHONE MEETS THE GOVERNMENT'S REQUIREMENTS FOR EXPOSURE TO RADIO WAVES.

Your mobile phone is a radio transmitter and receiver. It is designed and manufactured not to exceed the limits for exposure to radio frequency (RF) energy set by Industry Canada. These limits are part of comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines are based on standards that were developed by independent scientific organisations through periodic and thorough evaluation of scientific studies. The guidelines include a substantial safety margin designed to assure the safety of all persons, regardless of age and health.

The exposure standard for mobile phones employs a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit set by the Industry Canada is 1.6 W/kg* Tests for SAR are conducted using standard operating positions with the phone transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR of the phone while operating can be well below the maximum value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a base station, the lower the power output of the phone.

Before a phone model is available for sale to the public, compliance with the Canadian Standard must be shown. The highest SAR value for the Nokia 6820a model phone as reported to the FCC when tested for use at the ear is 0.66 W/kg, and when worn on the body, as described in this user guide, is 1.20 W/kg. The highest SAR value for the Nokia 6820b model phone as reported to the FCC when tested for use at the ear is 0.78 W/kg, and when worn on the body, as described in this user guide, is 0.87 W/kg.

(Body-worn measurements differ among phone models, depending upon available enhancements and Industry Canada requirements).

While there may be differences between the SAR levels of various phones and at various positions, they all meet the government requirement for RF exposure.

* The SAR limit for mobile phones used by the public is 1.6 watts/kilogram (W/kg) averaged over one gram of body tissue. The standard incorporates a substantial margin of safety to give additional protection for the public and to account for any variations in measurements. SAR values may vary depending on national reporting requirements and the network band. For SAR information in other regions please look under product information at www.nokia.com.

• TECHNICAL INFORMATION

Weight	3.5 oz (100 g) with BL-5C 900-mAh semi-fixed Li-Ion Battery	
Size	Volume: 4.8 cubic inches (79 cc) Length: 4.2 in (106.1 mm) closed Width: 1.8 in (46.1 mm) at hinges, 1.5 in (38 mm) at bottom Thickness: .8 in (21.6 mm) at top, .7 in (17 mm) at bottom	
Frequency range	6820a GSM900 880.2–914.8 MHz (TX) 925.2–959.8 MHz (RX) GSM1800 1710.2–1784.8 MHz (TX) 1805.2–1879.8 MHz (RX) GSM1900 1850.2–1909.8 MHz (TX) 1930.2–1989.8 MHz (RX)	6820b GSM850 824.2–848.8 MHz (TX) 869.2–893.8 MHz (RX) GSM1800 1710.2–1784.8 MHz (TX) 1805.2–1879.8 MHz (RX) GSM1900 1850.2–1909.8 MHz (TX) 1930.2–1989.8 MHz (RX)
Transmitter output power	Up to 2 W	
Battery voltage	3.7 V	
Operating temperature	14°F to + 131°F (-10°C to +55°C)	
^aTalk time, standby time	Talk time: up to 7 hours Stand-by time: up to 10 days	

- a. Battery talk and standby times are estimates only and depend on signal strength, network conditions, features used, battery age and condition (including the effect of charging habits), temperatures to which battery is exposed, use in digital mode, and many other factors. Please note that the amount of time a phone is used for calls will affect its standby time. Likewise, the amount of time that the phone is turned on and in the standby mode will affect its talk time.

• NOKIA ONE-YEAR LIMITED WARRANTY

Nokia warrants that the Nokia wireless phone and enhancements are free from defects in material and workmanship. The warranty period for the Phone (Radio) units and all enhancements (excluding carry cases) is twelve (12) months from the date of purchase OR fourteen (14) months from date of wholesale shipment from Nokia, OR fifteen (15) months from the date of manufacture by Nokia. The warranty period for the Carry cases is three (3) months from the date of purchase or five (5) months from the date of wholesale shipment from Nokia.

During the warranty period, Nokia will, at its option, repair or replace the defective product free of charge. Replacement Product may be either new or remanufactured or refurbished.

However, if Nokia determines that the warranty conditions cannot be applied, the purchaser will be billed for the repair and shipping.

EXCEPTIONS

This warranty is subject to the following exceptions:

- 1 Mobile or fixed installation, which is not in accordance with the installation instructions, published by Nokia, will void the warranty. Damage caused by a repair or an attempt to repair by other than a service centre authorized by Nokia will void the warranty;
- 2 This warranty covers normal consumer use and does not cover defects or damage to any product which, in the sole opinion of Nokia, has been subject to: improper storage, exposure to moisture or dampness, exposure to fire, sand, dirt, windstorm, lightning, or earthquake; to theft, battery leakage, unauthorized modification, misuse, neglect, abuse, misapplication, accident, alteration, improper installation, maladjustment of consumer controls, or abnormal operating conditions, or which has been attributable to acts of God;
- 3 Fuses are not covered by the warranty;
- 4 This warranty does not cover defects or damages caused by a product which is not approved by Nokia to be connected to its wireless phone;
- 5 This warranty does not cover defects or damages caused by improper or defective function of the carrier system or by inadequate signal reception by the antenna;
- 6 Removal and reinstallation costs are not covered by this warranty;
- 7 This warranty is applicable only to products bought through Nokia Products Ltd. in Ajax, Ontario, Canada, and sold either in Canada or Bermuda.
- 8 Removal, alteration, or defacing of the Serial Number Plate, or the enhancement Date Code Labels will void the warranty.

In no event shall Nokia be liable for incidental, special, or consequential damages, direct or indirect, loss of anticipated benefits or profits, loss of use of its wireless telephone, resulting from the use of its wireless phone, or its enhancements, or arising from any breach of this warranty.

CLAIM PROCEDURE

In order to obtain warranty performance, return the defective unit to the Nokia Service Centre with transportation charges prepaid (Shipping of the repaired unit may be paid by Nokia, in which case Nokia shall have risk of loss or damage during this shipment).

The proof of date of purchase will be required before in-warranty service is rendered.

Maintenance and service may be obtained in any authorized service centre in Canada.

EXTENSION OF WARRANTY PERIOD

When a repair is made, an extra 90-day service warranty is given to the labour and parts of the repair concerned. If replacement of a faulty unit is applied, instead of repairing, this 90-day service warranty is applied to the replaced unit.

Besides this 90-day service warranty, the warranty repairs or replacements do not affect the original warranty conditions, which are determined by the date of purchase.

THE FOREGOING WARRANTY IS THE PURCHASER'S SOLE AND EXCLUSIVE REMEDY AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY IMPLIED WARRANTY OR MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE OR USE.

Some provinces do not allow limitations on how long an implied warranty lasts, so the above limitations may not apply to you.

FOR WARRANTY SERVICE LOCATIONS, CONTACT YOUR SERVICE PROVIDER/RETAILER/DEALER OR DIRECTLY TO:

NOKIA PRODUCTS LIMITED

601 Westney Road South

Ajax, Ontario L1S 4N7

Tel: 905-427-1373

1-888-226-6542

Website: www.nokia.ca

For products being returned to Nokia or its authorized service centres, the service provider/retailer/dealer shall prepay shipping charges, taxes, duties, insurance. Nokia shall have no risk for loss or damage during this shipment.

NOTE: As warranty is automatically registered, no further action is required by the consumer.

Appendix A

Message from the CTIA (Cellular Telecommunications & Internet Association) to all users of mobile phones.

© 2001 Cellular Telecommunications & Internet Association. All Rights Reserved. 1250 Connecticut Avenue, NW Suite 800, Washington, DC 20036. Phone: (202) 785-0081

Safety is the most important call you will ever make.

A Guide to Safe and Responsible Wireless Phone Use

Tens of millions of people in North America today take advantage of the unique combination of convenience, safety and value delivered by the wireless telephone. Quite simply, the wireless phone gives people the powerful ability to communicate by voice--almost anywhere, anytime--with the boss, with a client, with the kids, with emergency personnel or even with the police. Each year, Americans make billions of calls from their wireless phones, and the numbers are rapidly growing.

But an important responsibility accompanies those benefits, one that every wireless phone user must uphold. When driving a car, driving is your first responsibility. A wireless phone can be an invaluable tool, but good judgment must be exercised at all times while driving a motor vehicle--whether on the phone or not.

The basic lessons are ones we all learned as teenagers. Driving requires alertness, caution and courtesy. It requires a heavy dose of basic common sense--keep your head up, keep your eyes on the road, check your mirrors frequently and watch out for other drivers. It requires obeying all traffic signs and signals and staying within the speed limit. It means using seatbelts and requiring other passengers to do the same.

But with wireless phone use, driving safely means a little more. This brochure is a call to wireless phone users everywhere to make safety their first priority when behind the wheel of a car. Wireless telecommunications is keeping us in touch, simplifying our lives, protecting us in emergencies and providing opportunities to help others in need.

When it comes to the use of wireless phones, *safety is your most important call.*

Wireless Phone "Safety Tips"

Below are safety tips to follow while driving and using a wireless phone which should be easy to remember.

- 1 Get to know your wireless phone and its features such as speed dial and redial. Carefully read your instruction manual and learn to take advantage of valuable features most phones offer, including automatic redial and memory. Also, work to memorize the phone keypad so you can use the speed dial function without taking your attention off the road.
- 2 When available, use a hands free device. A number of hands free wireless phone accessories are readily available today. Whether you choose an installed mounted device for your wireless phone or a speaker phone accessory, take advantage of these devices if available to you.
- 3 Position your wireless phone within easy reach. Make sure you place your wireless phone within easy reach and where you can grab it without removing your eyes from the road. If you get an incoming call at an inconvenient time, if possible, let your voice mail answer it for you.
- 4 Suspend conversations during hazardous driving conditions or situations. Let the person you are speaking with know you are driving; if necessary, suspend the call in heavy traffic or hazardous weather conditions. Rain, sleet, snow and ice can be hazardous, but so is heavy traffic. As a driver, your first responsibility is to pay attention to the road.

- 5 Do not take notes or look up phone numbers while driving. If you are reading an address book or business card, or writing a "to do" list while driving a car, you are not watching where you are going. It's common sense. Don't get caught in a dangerous situation because you are reading or writing and not paying attention to the road or nearby vehicles.
- 6 Dial sensibly and assess the traffic; if possible, place calls when you are not moving or before pulling into traffic. Try to plan your calls before you begin your trip or attempt to coincide your calls with times you may be stopped at a stop sign, red light or otherwise stationary. But if you need to dial while driving, follow this simple tip--dial only a few numbers, check the road and your mirrors, then continue.
- 7 Do not engage in stressful or emotional conversations that may be distracting. Stressful or emotional conversations and driving do not mix--they are distracting and even dangerous when you are behind the wheel of a car. Make people you are talking with aware you are driving and if necessary, suspend conversations which have the potential to divert your attention from the road.
- 8 Use your wireless phone to call for help. Your wireless phone is one of the greatest tools you can own to protect yourself and your family in dangerous situations--with your phone at your side, help is only three numbers away. Dial 9-1-1 or other local emergency number in the case of fire, traffic accident, road hazard or medical emergency. Remember, it is a free call on your wireless phone!
- 9 Use your wireless phone to help others in emergencies. Your wireless phone provides you a perfect opportunity to be a "Good Samaritan" in your community. If you see an auto accident, crime in progress or other serious emergency where lives are in danger, call 9-1-1 or other local emergency number, as you would want others to do for you.
- 10 Call roadside assistance or a special wireless non-emergency assistance number when necessary. Certain situations you encounter while driving may require attention, but are not urgent enough to merit a call for emergency services. But you still can use your wireless phone to lend a hand. If you see a broken-down vehicle posing no serious hazard, a broken traffic signal, a minor traffic accident where no one appears injured or a vehicle you know to be stolen, call roadside assistance or other special non-emergency wireless number.

Careless, distracted individuals and people driving irresponsibly represent a hazard to everyone on the road. Since 1984, the Cellular Telecommunications Industry Association and the wireless industry have conducted educational outreach to inform wireless phone users of their responsibilities as safe drivers and good citizens. As we approach a new century, more and more of us will take advantage of the benefits of wireless telephones. And, as we take to the roads, we all have a responsibility to drive safely.

The wireless industry reminds you to use your phone safely when driving.

For more information, please call 1-888-901-SAFE.

For updates: <http://www.wow-com.com/consumer/issues/driving/articles.cfm?ID=85>

© 2001 Cellular Telecommunications & Internet Association. All Rights Reserved. 1250 Connecticut Avenue, NW Suite 800, Washington, DC 20036. Phone: (202) 785-0081

NOTES

Index

Numerics

1-touch dial 43

A

accented characters 22
access codes 54
accessibility 6
alarm clock 60
allow multimedia reception setting 36
answer a call 20
anykey answer 51
applications 69
archive folder 28

B

battery
 charger connector 7
 how to charge 9
 installation 7
birthday notes in calendar 61
Bluetooth connections 49
bookmarks 76
brightness setting for display 46
browser security 77
business cards 42

C

cache memory 77
calculator 71
calendar 28, 60
call forwarding 51
call restricting 54
call timers 38
call waiting 20, 51
caller groups 44
caller ID 20
camera 58
certificates 77
characters, typing 22

charge battery 9
clock 46
closed user group 54
codes 9
color schemes 46
conference calls 21
connectivity 47, 80
connectors 7
contacts
 add images 41
 caller groups 44
 edit details 42
 how to add 40
 searching 41
contrast setting for display 46
convert currency 71
cookies 76
countdown timer 71
counter
 for GPRS data 39
 for text messages 29
currency conversion 71
Customer Care Center 10

D

data cable connector 7
date setting 46
default slide timing setting 36
delete
 distribution lists 29
 text messages 32
dialed numbers 38
dictionary 23
digital signature 78
display contrast 46
distribution lists 29
downloaded applications 69
downloads 76
DTMF tone strings 21

E

EGPRS 50

- e-mail
 - how to reply 34
 - required setup 32
 - send later option 33
 - settings 36
 - write and send 33
- enhancement settings 53
- enhancements for phone 82
- enter text
 - keyboard closed 23
 - keyboard open 22
- environment profiles 45

F

- factory settings 55
- fixed dialing 54
- folders, create 28
- font size setting 37
- formats for multimedia messages 30
- free memory 40
- frequencies 5

G

- gallery menu 56
- games 68
- GPRS
 - connection timer 39
 - data counter 39
- group lists, see distribution lists

H

- hands-free option 21
- headset connector 7
- Help screens 53

I

- images
 - add to contacts 41
 - editing 56
 - in multimedia messages 30
- IMEI number 10
- information label 10

- infrared 49
- install SIM card and battery 7
- international mobile equipment identity, see IMEI

K

- keyboard
 - functions when closed 13
 - how to enter text 22, 23
 - how to open 11
 - key functions when open 14
- keypad
 - lock 52
 - tones 45

L

- language selection 52
- lap timer 72
- last number redial 19
- lock phone keypad 52
- loudspeaker 21

M

- memory
 - setting for phone or SIM 40
 - sharing 6
 - status 40, 52
- menu shortcuts 25
- message center number 35
- message counter 29
- messages
 - alert tone 45
 - font size setting 37
 - send business cards 42
 - tips for text messages 24
- microphone connector 7
- missed calls 38
- MMS, see multimedia messages 30
- model number 5
- module PIN 55, 78
- multimedia memory full message 32

- multimedia messages 30
 - folders 32
 - how to create 30
 - how to reply 31
 - supported formats 30

N

- Nokia 10
 - Customer Care Center 10

P

- PC Suite 80
- phone
 - how to hold 10
 - illustration 3
 - location of antenna 10
 - model number 5
 - network frequencies 5
- phone illustration 3
- pictures
 - in multimedia messages 30
- PIN code
 - message when phone is turned on 9
 - request 53
- power key 13
- predictive text 23
- profiles
 - Bluetooth technology 47
 - environment 45

Q

- quick guide 4

R

- received calls 38
- record
 - sounds and speech 70
 - video clips 59
- redial
 - automatically 51
 - number 19
- reminders in calendar 61
- restriction password 55
- right selection key options 47
- ringing options 45

S

- save contact numbers 44
- scale image down setting 36
- screen saver timeout 46
- search for a contact 41
- security
 - code 54
 - keyguard 52
 - level 54
 - module 78
 - settings 53
- send DTMF tone strings 21
- service
 - commands 37
 - inbox 76
- settings
 - Bluetooth connections 48
 - calls 51
 - camera 58
 - display contrast 46
 - EGPRS 51
 - for contacts 40
 - for display 46
 - for e-mail 36
 - for enhancements 53
 - for font size 37
 - for text and e-mail 35
 - security 53
 - synchronization 66
 - time and date 46
 - wallet 65
- shared memory 6
- shortcuts 47
- signing PIN 55
- silence feature 20
- SIM 44
- SIM card
 - error messages 9
 - how to insert 8
 - installation 7
 - select as memory in use 40
 - service confirmation messages 53

- SMS, see text messages
- sound files 30
- special characters 22
- speed dial 43
- split timer 72
- standby times and talk times 88
- start-up tone 53
- stopwatch 72
- swap option for calls on hold 21
- synchronization 65

T

- talk time 88
- templates 28
- text messages
 - add to calendar 28
 - counter 29
 - enter with keyboard closed 23
 - enter with keyboard open 22
 - how to reply 27
 - messages 26
 - send to a group 27
 - SMS messages 26
 - templates for 28
 - tips for writing 24
- time setting 46
- timers
 - countdown 71
 - for GPRS connection 39
 - for phone calls 38
 - lap times 72
 - split times 72

- to-do list 62
- tone setting profiles 45
- troubleshooting 10
 - contact Nokia 10
 - multimedia memory full 32
 - SIM card messages 9
- TTY information 10

U

- unlock phone keypad 52
- USSD commands 37

V

- vibrating alert 45
- video
 - add clips to messages 30
 - record a video clip 59
- voice dial 43
- voice mailbox 19
- voice messages 34
- voice recorder 70

W

- wallet
 - code 55
 - purchases 63
- wallpaper 46
- warning tones 45
- Web site for accessibility 6
- welcome note on display 52