

RS-1, RS-3, RS-3 SUPER, RS-1007, FS-3L Analog Clamp-on Multimeters



FS-3L

- Works in wide range of temperatures
- Does not need battery for measuring volts or amp
- Easy to use rotary scale
- Pointer lock
- Recessed magnifying window
- Drop Proof to 5 feet



RS-3

| FEATURES | RS-1 | RS-3 | RS-3 Super | FS-3L | RS-1007 | ACCURACY |
|-----------------------|--------------------|-------------------------|------------------|---------------|----------------------------|--------------------|
| AC Voltage | 0-150 / 600 V | 0-150 / 300 / 600 V | | | 0-150 / 300 / 750 V | ± 3% of Full Scale |
| AC Current | 0-6/ 15 /40 /100 A | 0-6/ 15 /40 /100 / 300A | | | 0-15 /40 /100 / 300 /1000A | ± 3% of Full Scale |
| Resistance | N/A | 25 Ω Midscale | 0-1000Ω/100 kΩ | 25 Ω Midscale | | ± 3% arc |
| Frequency | 60 Hz | 50-400Hz | 50/60Hz | 60Hz | | ± 3% of Full Scale |
| Temperature | | | -25° F to 225° F | | | |
| Jaw Opening | 1" | | | 2" | | |
| Meter Movement | Rotary Scale | | Flat/Taut Band | Rotary Scale | | |



RS-1007

| OPTIONAL ACCESSORIES | PART NUMBER |
|--|--------------|
| Line Splitter (Energizer) | A47L |
| 5000A Clamp-on Current Transformer (50 to 1) | CT50-1 |
| 3000A Clamp-on Current Transformer (50 to 1) | CT50-2 |
| 600A Clamp-on Current Transformer (10 to 1) - (RS-1, RS-3, RS-3Super) | A50-1 |
| Extendo test leads (RS-1, RS-3, RS-3Super) | VLK-411R |
| Extendo test leads, Wide Temperature range, -40°F to 120°F (RS-1, RS-3, RS-3Super) | VLK-411R-WTR |
| Replacement probe tips for test leads | VPT |
| Alligator Clips | VRC-320 |
| Soft vinyl zippered pouch (RS-1, RS-3, RS-3Super) | SV-U |

| REPLACEMENT PARTS <i>(supplied with product)</i> | PART NUMBER |
|---|--|
| Voltage test leads (RS-1, RS-3, RS-3Super) | VL11S |
| Soft nylon, zippered carrying case with belt loop (RS-1, RS-3, RS-3Super) | SV-U |
| Ohmmeter adapter (RS-3, RS-3Super, RS-1007) | OHB-3HE |
| Fuse for OHB-3HE, 1 Amp, 600 Volt, 8AG size, FAST Blow (RS-3, RS-3Super, RS-1007) | 8AG-360x023 |
| Fuse for FS-3L (0.5 Amp, 250V, 8 AG size) | 8AG-361.5 |
| Carrying Case (RS-1007) | E |
| Instruction Manual | www.AMPROBE.com |