

# FLUKE.

## Fluke i410 AC/DC Current Clamp

Large AC/DC Current Clamp

### i410 AC/DC Current Clamp

Fluke Current clamps are the ideal tools to extend the current ranges of Fluke tools.

- Battery-powered Hall-effect clamp-on probe measures AC/DC current from 1A to 400A
- The i410 is a single range ac/dc current clamp with mV output
- The i410 is compatible with most Fluke multimeters or any other current measurement device that accepts safety shrouded banana plugs
- One year warranty



## Technical Data

Specifications	
Measurement type	Hall sensor
Nominal current range	400 A, AC/DC
Continuous current range	1 A - 400 A AC/DC
Highest current	400 A
Lowest measurable current	0.5 A
Basic accuracy	3.5% + 0.5 A (% reading + floorspec)
Useable frequency	DC - 3 kHz
Output level(s)	1 mV/A
Zero error adjustment	Yes

Safety Specifications	
Safety	CAT III, 600 V
Maximum voltage	600 V

Mechanical & General Specifications	
Warranty	1 year
Battery life	9 V, 60 h
Maximum conductor diameter	30 mm 2 x 25 mm
Output cable length	1.6 m
Shrouded banana plugs	Yes