# Panasonic

**BUSINESS**

## Super Dynamic Full HD Vandal Resistant Dome Network Camera
# WV-SFR531



i-PRO SmartHD 5 Series NEW

Onvif | S G

| SD ENHANCED Super Dynamic | VIQS Variable Image Quality on Specified area | H.264 JPEG | FULL HD Full High Definition 1080/60p | day/night ICR | Vandal Resistant | HLC | Fog sand Compensation | Auto Back Focus | i-VMD (Optional) Type2 |

*i-VMD Type2 : Intruder Detection / Loitering Detection / Direction Detection / Scene Change Detection / Object Detection / Cross Line Detection

## Full HD / 1,920 x 1,080 60 fps H.264 Vandal Resistant Network Camera featuring *Super Dynamic*

### Key Features

- **1080p** Full HD images up to **60 fps**[*1]
- Approximate 1/3 inches, high sensitivity MOS image sensor
- Super high resolution at Full HD/1,920 x 1,080 created by high sensitivity MOS image sensor.
- **Multiple H.264 (High profile) streams (max. 4 streams)** and JPEG streams ensure simultaneous real time monitoring and high resolution recording by enhanced "UniPhier®", Panasonic's proprietary System LSI platform.
- Maximum Screen Size is 2,048 x 1,536* @30fps, H.264
  * Used by super resolution techniques
- *Enhanced Super Dynamic*[*1] and ABS (Adaptive Black Stretch) technologies deliver **133 dB** wider dynamic range compared to conventional cameras.
- **Multi process NR & 3D-DNR** ensures noise reduction in various conditions.
- High sensitivity with Day/Night (ICR*) function: 0.07 lx (Color), 0.01 lx (B/W) at F1.6
  *ICR: IR Cut filter Removal
- **ABF (Auto Back Focus)** ensures easy installation.
- **VIQS** (Variable Image Quality on Specified area) technology allows the designated **eight areas** to retain higher image quality while the excluded area will have a decreased image quality, which enables to use lower image file size and bit rate.
- Cropping function enables to provide whole image and the part image simultaneously. Up to 4 image capture areas can be specified, and it is also possible to control the sequence.
- *Face Super Dynamic* technology ensures clear face image.
- Lens distortion compensation for the distorted images can be adjusted 256 steps.
- Electronic sensitivity enhancement: Auto (Up to 16/30s) / OFF
- Selectable light control modes:
  **Outdoor scene,Indoor scene (50 Hz) / Indoor scene (60 Hz),Fix shutter** Indoor scene (50 Hz/60Hz): Flicker caused by fluorescent lightning will be automatically compensated.
- 3x extra optical zoom at 640 x 360 resolution
- 2x, 4x digital zoom controlled by browser
- VMD (Video Motion Detection) with 4 programmable detection areas, 15 steps sensitivity level and 10 steps detection size
- Privacy Zone can mask up to 8 private areas, such as house windows and entrances/exits.
- Camera title display: Up to 20 alphanumeric characters on the browser
- Alarm sources including 3 terminal input, VMD and Panasonic alarm command can trigger actions such as SDXC/SDHC/SD memory recording, FTP image transfer, E-mail notification, Indication on browser, Alarm terminal output, and Panasonic alarm protocol output.

- Full duplex bi-directional audio allows interactive communication between camera site and monitoring site.
- JPEG Image compression ratio can be changed by alarm so that higher quality image can be provided.
- Prioritized stream control: One of the video streams can be prioritized when multiple recorders or client PCs are accessing the camera so that the recorder or the client PC can maintain the frame rate.
- **SDXC/SDHC/SD Memory card slot** for manual recording (H.264 / JPEG), alarm recording (H.264 / JPEG) and backup upon network failure (H.264 / JPEG). Realize long-term recording and auto backup function.
- Face detection function detects the position of human face and the information is sent by XML or video stream.(Optional)
- Can be added new intelligent extension software (Optional) in addition to built-in VMD (Video Motion Detection), alarm function.
- **Fog compensation function** equipped as standard.
- **HLC (High Light Compensation)** technology reduces strong light sources such as vehicle headlights to prevent camera being blinded.
- **SCC (Super Chroma Compensation)** function realizes a better color reproducibility even in low illumination.
- H.264 max. bit rate/client and Total bit rate control allows flexible network traffic management. Frame rate priority mode controls bit rate and compression ratio to provide the specified frame rate.
- Internet mode: H.264 images can be transmitted over HTTP protocol.
- Multi-language: English / Italian / French / German / Spanish / Portuguese / Russian / Chinese / Japanese
- IPv4/IPv6 protocol supported
- Supports SSL, DDNS (viewnetcam, RFC2136)
- Still images (JPEG) can be viewed on mobile phones via Internet.
- Onvif compliant model
- Vandal resistant mechanism for high reliability

*1 Super Dynamic function is automatically set off on 60 fps mode

### Optional Accessories

| Ceiling Mount Bracket **WV-Q105A** | Ceiling Mount Bracket **WV-Q174B** | Smoke Dome Cover **WV-CR1S** |
| --- | --- | --- |
|  |  |  |

# Specifications

| Camera | | |
|---|---|---|
| Image Sensor | Approx. 1/3 type MOS image sensor | |
| Effective Pixels | Approx. 2.4 mega pixels | |
| Scanning Mode | Progressive scan | |
| Scanning Area | 5.28 mm (H) × 3.30 mm (V)  {7/32 inches(H) x 1/8 inches(V) } | |
| Minimum Illumination | Color: 0.07 lx, BW: 0.01 lx    (F1.6, Maximum shutter: Max. 1/30s, Gain: On(High)) Color: 0.005 lx, BW: 0.0007 lx (F1.6, Maximum shutter: Max. 16/30s, Gain: On(High) *1 | |
| White Balance | AWC (2,000 - 10,000 K), ATW1 (2,700 - 6,000 K), ATW2 (2,000 - 6,000 K) | |
| Light Control Mode | Outdoor scene : Automatic integration of ALC and ELC Indoor scene [50 Hz] : Automatic integration of ALC and ELC with flickerless Indoor scene [60 Hz] : Automatic integration of ALC and ELC with flickerless | |
| Shutter Speed | [2 mega pixel [16:9](60 fps mode)] Off(1/60), 1/100, 1/120, 1/250, 1/500, 1/1000, 1/2000, 1/4000, 1/10000 Other than [2 mega pixel [16:9](60 fps mode)] Off(1/30), 3/100, 3/120, 2/100, 2/120, 1/100, 1/120, 1/250,1/500, 1/1000, 1/2000, 1/4000, 1/10000 | |
| Super Dynamic*2 | On(High) / On(Normal) / Off | |
| Face Super Dynamic | On / Off (Only when Super Dynamic : On) | |
| Adaptive Black Stretch | On / Off (Only when Super Dynamic : Off) | |
| Fog compensation | On / Off (Only when Super Dynamic / Adaptive black stretch : Off) | |
| AGC | On (Low, Mid, High) / Off | |
| Electronic Sensitivity UP | max. 1/1000 s, max. 1/500 s, max. 1/250 s, max. 1/120 s, max. 1/100 s, max. 1/60 s, max. 1/30 s, max. 2/30 s, max. 2/120 s, max. 2/30 s, max. 4/30 s, max. 6/30 s, max. 10/30 s, max. 16/30 s | |
| Day/Night (ICR) | Off / On / Auto1(Normal) / Auto2(IR Light) / Auto3(SCC) | |
| Dynamic Range | 133 dB typ. (Super Dynamic: On, Light Control Mode : indoor) | |
| Digital Noise Reduction | High / Low | |
| Video Motion Detection | 4 areas, Sensitivity : 15 steps, Detection size : 10 steps | |
| Privacy Zone | Up to 8 zones | |
| VIQS | Up to 8 zones | |
| Camera Title (OSD) | Up to 20 characters (alphanumeric characters, marks) | |
| Focus Adjustment | ABF / MANUAL(Html only) | |
| Lens Distortion Compensation | 256 steps | |

| Lens | | |
|---|---|---|
| Vari Focal Length | 2.8 - 9.5 mm {1/8 inches – 13/32 inches} | |
| Angular Field of View | [16 : 9 mode]  Horizontal : 31° (TELE) – 109° (WIDE)  Vertical    : 18° (TELE) – 59°  (WIDE) [4 : 3 mode]  Horizontal : 26° (TELE) – 89°  (WIDE)  Vertical    : 20° (TELE) – 66°  (WIDE) | |
| Maximum Aperture Ratio | 1 : 1.6 (WIDE) - 1 : 3.3 (TELE) | |
| Focusing Range | 0.3 m - ∞ | |

| Adjusting Angle | Horizontal: +120°(right)  to –240°(left), Vertical: ±85°, Image tilt adjustment range: -100°(Left) to +100°(Right) | |
|---|---|---|

| Browser GUI | | |
|---|---|---|
| Cropping | H.264(1) / H.264(2) / H.264(3) / H.264(4) /  H.264(all) / JPEG(1) / JPEG(2) / JPEG(3) Up to 4 image capture areas can be specified | |
| Camera Control | Brightness, AUX On / Off | |
| Display Mode | Spot, Quad : Image from 16 cameras can be displayed in 4 different Quad screens or 16 split screen (JPEG only). 20 characters camera title available. | |
| Digital Zoom | 1x, 2x, 4x controlled by browser GUI | |
| Camera Title | Up to 20 alphanumeric characters | |
| Clock Display | Time : 12H/24H, Date : 5 formats on the browser, Summer time (Manual) | |
| Alarm Control | Reset | |
| One Shot Capture | A still picture will be displayed on a newly opened window. | |
| Audio | Mic (Line) Input : On / Off     Volume adjustment : Low / Middle / High Audio Output   : On / Off     Volume adjustment : Low / Middle / High | |
| SD Memory Data Download | Still or motion Images recorded in the SDXC/SDHC/SD memory card can be downloaded. | |
| GUI / Setup Menu Language | English, Italian, French, German, Spanish, Portuguese, Russian, Chinese, Japanese | |
| System Log | Up to 100 (Internal), Up to 4,000 (SDXC/SDHC/SD memory when the recording format is set to JPEG.) error logs | |
| Supported OS *3 | Microsoft® Windows® 8.1, Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® | |
| Supported Browser | Windows® Internet Explorer® 11 (32 bit), Windows® Internet Explorer® 10 (32 bit), Windows® Internet Explorer®  9 (32 bit), Windows® Internet Explorer®  8 (32 bit), Windows® Internet Explorer®  7 (32 bit) | |

| Network | | | |
|---|---|---|---|
| Network IF | 10Base-T / 100Base-TX, RJ45 connector | | |
| Image Resolution | • 2 mega pixel [16:9] (30/60 fps) 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 • 2 mega pixel [4:3] (30 fps) 1,600 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 • 3 mega pixel [4:3] (30 fps) 2,048 x 1,536* / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 *Used by super resolution techniques | | |
| H.264 *4 | Transmission Mode | Constant bitrate / Framerate priority / Best effort / Advanced VBR | |
| | Frame Rate | 1 / 3 / 5 / 7.5 / 10 / 12 / 15 / 20 / 30 / 60 fps | |
| | Bit Rate/Client | 64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 1,536 / 2,048 / 3,072 / 4,096 / 6,144 / 8,192 / 10,240 / 12,288 / 14,336 / 16,384 / 20,480 / 24,576 kbps | |
| | Image Quality | Low / Normal / Fine | |
| | Refresh interval | 0.2 / 0.25 / 0.33 / 0.5 / 1 / 2 / 3 / 4 / 5s | |
| | Transmission Type | Unicast / Multicast | |
| JPEG | Image Quality | 10 steps | |
| | Refresh interval | 0.1 fps - 30 fps (JPEG frame rate will be restricted when displaying both JPEG and H.264 images.) | |
| | Transmission Type | Pull / Push | |
| Audio Compression | G.726 (ADPCM) 32 kbps / 16 kbps, G.711 64 kbps / AAC-LC | | |
| Audio Mode | Off / Mic (Line) input / Audio output / Interactive (Half duplex) / Interactive (Full duplex) | | |
| Authentication for Audio | Level 1 only / Level 2 higher / All users | | |
| Total Bit Rate | 64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 2,048 / 4,096 / 8,192 kbps / Unlimited | | |
| Supported Protocol | IPv6: TCP/IP, UDP/IP, HTTP, HTTPS, FTP, SMTP, DNS, NTP, SNMP, DHCPv6, RTP, MLD, ICMP, ARP IPv4: TCP/IP, UDP/IP, HTTP, HTTPS, RTSP, RTP, RTP/RTCP,FTP, SMTP, DHCP, DNS, DDNS, NTP, SNMP, UPnP, IGMP, ICMP, ARP | | |
| FTP Client | Alarm image transmission, FTP periodic transmission (When the FTP transmission is failed, backup on an optional SDXC/SDHC/SD memory card is available.) | | |

| Network | | |
|---|---|---|
| No. of Simultaneous Users | Up to 14 users (Depends on network conditions) | |
| SDXC/SDHC/SD Memory Card (Option) * Use the SD memory card manufactured by Panasonic (SD speed class 4 or higher), and in the case of SD Speed Class 10, that complies with UHS-1(Ultra High Speed-1). | H.264 recording : Manual REC / Alarm REC (Pre/Post) / Schedule REC / Backup upon network failure JPEG recording : Manual REC / Alarm REC (Pre/Post) / Backup upon network failure Compatible SD (SDHC/SDXC) card: Panasonic 2 GB, 4 GB*, 8 GB*, 16 GB*, 32 GB*, 64GB** model *SDHC card, ** SDXC card  (except miniSD card and microSD card) | |
| Cellular Phone Compatibility | JPEG image, AUX control (by access level) | |
| Mobile Terminal Compatibility | iPad, iPhone, iPod touch (iOS 4.2.1 or later), Android™ mobile terminals | |

| Alarm | | |
|---|---|---|
| Alarm Source | 3 terminals input, VMD, Command alarm, Audio detection alarm | |
| Alarm Actions | SDXC/SDHC/SD memory recording, E-mail notification, HTTP alarm notification, Indication on browser, FTP image transfer, Panasonic protocol output | |
| Alarm Log | With SDXC/SDHC/SD memory card : Up to 50,000 logs for each SD memory card | |
| Schedule | Alarm / VMD / Access permission / H.264 recording / Scene file | |

| Input/ Output | | |
|---|---|---|
| Monitor Output (for adjustment) | VBS : 1.0 V [p-p]/75 Ω, NTSC / PAL composite, ø3.5mm  mini jack MONITOR OUT conversion plug included | |
| Microphone/Line Input | MIC IN and Line IN are selectable. ø3.5 mm monaural mini jack (monaural input) (Applicable microphone: Plug-in power type) Supply voltage: 2.5 V ±0.5 V Input impedance: Approx. 2 kΩ (unbalanced) | |
| Audio Output | ø3.5 mm stereo mini jack (monaural output) Output impedance: Approx. 600 Ω (unbalanced) | |
| External I/O Terminals | ALARM IN 1(DAY/NIGHT IN), ALARM IN 2(ALARM OUT), ALARM IN 3(AUX OUT) | |

| General | | |
|---|---|---|
| Safety | UL (UL60950-1), C-UL (CAN/CSA C22.2 No.60950-1), CE, IEC60950-1 | |
| EMS | FCC (Part15 ClassA), ICES003 ClassA, EN55022 ClassB, EN55024 | |
| Power Source and Power Consumption | DC power supply: DC12 V / 450 mA / Approx. 5.4 W PoE Device: DC48 V / 110 mA / Approx. 5.3 W (Class 2 device) * ONLY CONNECT DC12 V CLASS 2 POWER SUPPLY. | |
| Ambient Operating Temperature | -10 °C to +50 °C (14 °F to 122 °F) | |
| Ambient Operating Humidity | 10 to 90 % (no condensation) | |
| Shock Resistance | Compliant with 20J IEC60068-2-75/ IEC 62262 IK10 | |
| Dimensions | ø129.5 mm x 102.5 mm (H) {ø5-3/32 inches x 4-1/32 inches (H)} Dome radius 41.5 mm {1-5/8 inches} | |
| Mass (approx.) | Approx. 0.70 kg {1.54 lbs} | |
| Finish | Main body : Aluminum die cast, sail white Dome section : Clear polycarbonate resin | |
| Others | Tamper-resistant enclosure*5 | |

*1 Converted value
*2 Super Dynamic function is automatically set off on 60 fps mode.
*3 Refer to "Notes on Windows Vista® / Windows® 7 / Windows® 8 / Windows® 8.1" on the provided CD-ROM for further information about system requirements for a PC and precautions when using Microsoft® Windows® 8.1 or Microsoft® Windows® 8 or Microsoft® Windows® 7 or Microsoft® Windows Vista®.
*4 Transmission for 4 streams can be individually set.
*5 Component that has a structure on which the screws that are accessible after installation can not be screwed or unscrewed using an ordinary screwdriver.

## Part Names and Functions



Direction marker for installation(⇧TOP) • Points up when installing to a wall.
Screen display top (TOP)
Data Matrix: To our website(*1)
Auto focus (AF) button
SD memory card(*2) slot
LINK indicator
ACT indicator
SD ERROR/AF indicator
SD MOUNT indicator
SD ON/OFF button
INITIAL SET button (Initializing / NTSC ⇔PAL switch button)
Power cord plug (accessory) 12 V DC power supply terminal
Direction marker for installation (FRONT⇩). • FRONT must positioned in front of the camera (on the Panasoniclogo side).
MONITOR OUT terminal (factory shipment : NTSC monitor)
Panning lock screw

*1 Data Matrix: This is the two-dimensional bar code that stores the address to our website. Depending on the scanning application used, the Data Matrix may not be able to be read correctly. In this case, access the site by directly entering the following URL. http://security.panasonic.com/pss/security/support/qr_sp_select.html
*2 SDXC/SDHC/SD memory card is described as SD memory card.

## Appearance



ø129.5(ø5-3/32")
56(2-7/32")
102.5(4-1/32")
SR41.5(1-5/8")
Unit: mm (inches)

**Trademarks and registered trademarks**
– Microsoft, and Windows are registered trademarks of Microsoft Corporation in the U.S. and other countries.
– iPad, iPhone and iPod touch are registered trademarks of Apple Inc.
– Android is a trademark of Google Inc.
– UniPhier is a registered trademark of Panasonic Corporation.
– "i-PRO SmartHD" logo is trademark or registered trademark of Panasonic Corporation.
– ONVIF and the ONVIF logo are trademarks of ONVIF Inc.
**Important**
– Safety Precaution: Carefully read the Important Information, Installation Guide and operating instructions before using this product.
– Panasonic cannot be responsible for the performance of the network and/or other manufacturers' products used on the network.

• Masses and dimensions are approximate.  • Specifications are subject to change without notice.

DISTRIBUTED BY:

# Panasonic

http://security.panasonic.com
http://www.facebook.com/PanasonicNetworkCamera

(2A-143CL)