

# KEYWALKER IDF 68 wireless mechanical keyboard Manual

## Using manual and warranty card

Thanks very much for buying KEYWALKER mechanical keyboards.  
Please read the manual before using it

## Attention

After using keyboards for a long time. Your hands, arms, neck, shoulders and waist will be uncomfortable. When you feel uncomfortable, tired, please stop using keyboard immediately and have a rest. When you are not well, please don't use keyboard for a long time.

## Feature

All "KEYWALKER" mechanical keyboards use original MX switch.  
They have hard internal structure and good touch.  
The common colors for MX switch are black, blue, brown, red.  
Each keyboard uses switches of only one color. Switches of different color have different functions and touch. Please check before purchase.

## Device parameters and using

**Key quantity:** 68 keys

**Switch:** MX Switch

**Keycaps:** Cherry keycaps

**Keyboard specifications:** wired control: Aint-ghosting NKRO/wireless control: Aint-ghosting 6KRO)

**Keyboard dimension:** 316mm\*109mm\*28mm

**Keyboard weight:** 722g

**Cord length:** 1.5m

### Wireless device system and hardware requirement:

Hardware: Bluetooth V4.0 or above (built-in bluetooth v4.0 or bluetooth adapter v 4.0 or above), Support Device driver/Custom Operation

### System requirement: Wired control:

Microsoft: windows XP or above.

IOS: MAC OS.

Linux system.

### Wireless control:

Microsoft: windows 8/windows 10.

IOS: IOS 7.0 or above/MAC OS 10 system or above.

Android: Android 4.4 or above.

**This device is with lithium polymer battery 1200mAh. Has USB interface for recharging 5.0V recharge Voltage, plug in and charge.**

**The wireless transmission distance is 15m if no obstacles, when first connection with wireless device, it needs input dynamic pairing code.**

## Wireless Control

1. After switch in the keyboard, FN+Q/W/E (flash once every 3-5 seconds), the keyboard now is on pairing mode. Then please turn on the Bluetooth function on your mobile phones/computer, or other Bluetooth devices. Searching for new Bluetooth devices, you will find KEYWALKER. Click KEYWALKER, your device will pop up one window to input identifying code, please input the identifying code on KEYWALKER keyboard, and press "Enter" key, then the light of "Q/W/E" key keeps on, which means your Bluetooth device and the keyboard are connected.

2. Press and hold "FN"+Q/W/E key is to disconnect the present Bluetooth device, it will enter into new pairing mode.

3. Change between multiple devices:

At the same time open the phone and tablet PC Bluetooth, by pressing the FN+Q/W/E key.

## 4. Other function instruction

FN key function	Fn+ESC	ALL for light
4.	FN+(1)	F1
5.	FN+(2)	F2
6.	FN+(3)	F3

7.	FN+(4)	F4
8.	FN+(5)	F5
9.	FN+(6)	F6
10.	FN+(7)	F7
11.	FN+(8)	F8
12.	FN+(9)	F9
13.	FN+(10)	F10
14.	FN+(-)	F11
15.	FN+(+)	F12
16.	FN+Q/W/E	Wireless connect
17.	FN+(P)	Print
18.	FN+(I)	Home
19.	FN+(I)	End
20.	FN+(~)	7 lighting effects change
21.	FN+delete	Change recording light for Custom Operation
22.	FN+pgup	Long press two seconds, into the recording state, the recording is completed and then press the FN+pgup once again to save the state of light.
23.	FN+pgdn	Long press two seconds, into the recording state, the recording is completed and then press the FN+pgdn once again to save the state of light.

**Note:** This version provides timely updates of software programs can be directly updated online , refresh the new program, and will continue to update latter, please focus on Keywalker official website: [www.keywalker.com](http://www.keywalker.com)