

User manual

Product Parameters:

Bluetooth Version: V2.1

Support Profile: AVRCP1.3, A2DP1.0, HFP1.5, HSP1.0

Working Distance Range: 10m

Frequency Range: 2.402GHz-2.480GHz

Battery Specifications: 3.7V, 300mAh, Built-in rechargeable lithium battery

Charging Voltage: DC4.2 - 5.5V

Charging Time: about 2 hours

Talking/Music time: about 5 hours

Standby Time: about 10 hours

Items Included:

1. One foldable Multifunction Bluetooth headset "BT-006"
2. One charging cable
3. One Aux-in cable
4. One User's Manual

Button Description:

ON/OFF: ON/OFF Switch

M: three kinds of playback modes switch(TF Mode, Radio Mode, Bluetooth Mode)

▶||: Play or Pause Music/ Answer or Reject Calls

▶▶|/V+: long press for Next song or radio station/ short press increase volume

|◀◀/V-: long press for Previous song or radio station/ short press reduce volume

Bluetooth Function Description:

1) Pairing Operation:

a. For the first time pairing: start up the Bluetooth headset. It will boot into Bluetooth Mode automatically, voice prompts "Bluetooth Mode", LED indicator light rapidly alternating flashes with blue and red colors. Please open the smart device's Bluetooth searching function, and select the device "BT-006", no password required, after successful pairing, voice prompts "Connected", LED indicator light stays blue.

b. Re-pairing: turn off the attached smart device's Bluetooth function, voice prompts "Disconnected", if can't search and pair with the last connected smart device within 3 seconds, the headset will automatically re-enter pairing mode, voice prompts "Bluetooth Mode", LED indicator light rapidly alternating flashes with blue and red colors. Open another smart device's Bluetooth searching function, and select the device "BT-006", no password required, after successful pairing, voice prompts "Connected", LED indicator light stays blue.

c. Follow-up pairing: automatically pair the last connected device in 3 seconds after boot.

2) Answer Calls:

Short press ▶|| when calls' coming.

3) Hang up phone calls:

Short press ▶|| after calling.

4) Reject Calls:

Long press ▶||.

5) Redial the last outgoing number:

Double-click ▶||.

6) Music Play:

Short press ▶|| after connected with the smart device.

Micro SD Card playback Mode:

1) When the slot is empty, inserted the Micro SD Card, voice prompts "TF Mode". Then it plays media automatically.

2) When the Micro SD Card is inside, switch to TF Mode through **M**.

FM Radio Mode:

1) When the headset is on, switch to FM mode through **"M"**, voice prompts "Radio Mode".

2) Usage Tips: short press **"▶||"** to search and save stations automatically(it can be abort with another short press while searching). Once enter FM mode again, it will play the first saved radio station automatically. If you want to re-scan, short press **"▶||"** again in the Radio mode.

Line-in Mode:

When the headset is on, insert the Line-in cable, voice prompts "Line-in Mode". Then it plays smart device's media automatically.

1. Maximum volume warning voice prompts "du du".
2. Supports MP3, WAV, WMA format playback.
3. Battery indication on IOS.
4. Micro USB as common use charging port.

LED indicator light Status:

Charge Status	Steady red LED. When fully charged, the LED indicator light turns off.
Power on Status	Blue LED indicator light turns on.
Power off Status	LED indicator light turns off.
Pairing Status	Blue and Red LED indicator lights rapidly alternating flash.
Standby Status	Blue LED indicator light turns on.
Connected Status	Blue LED indicator light turns on.
Using Status	Bluetooth Mode, Blue LED indicator light flashes every two seconds.
	Radio Mode, Green LED indicator light turns on.
	TF Mode, Green LED indicator light flashes every three seconds.
	AUX-in Mode, the headset automatically turns off, LED light goes out.

Note:

If no pairing connection after the Bluetooth headset enters the pairing mode, please turn off the headset as for power saving. Do not perform other operations when searching Bluetooth to prevent the program error.

Please select the appropriate volume in use to prevent damage to your ears.

Please note that a good environment while using the Bluetooth headset can avoid damage to the headphone.

Please charging the headset after a long time none-use.

FCC Notices

The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules.

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorienting or relocating the receiving antenna
- Increasing the distance between the equipment and receiver
- Connecting the equipment to an outlet on a circuit which is different from the one the receiver is connected to
- Consult a qualified expert for help