


iHome

BC

## COLOR CHANGING SPLASHPROOF BOOMBOX




## Quick Start Guide

Questions? Visit [ihomeintl.com](http://ihomeintl.com)

## Front

### TOP PANEL



#### Volume Button

- Short press volume - button to decrease volume. When playing music, long press to play the previous song. When in FM mode, long press to select the previous radio station.
- Short press volume + button to increase volume. When playing music, long press to play the next song. When in FM mode, long press to select the next radio station.

#### Light Button

- Short press to turn on the light, long press to turn off the light.

#### Mode Button

- Short press to switch mode: Bluetooth, FM, AUX, U disk, TF card. Long press for TWS function.


#### Power On/Off

- Long press for 2 seconds to power on/off.

#### Play/Pause Button

- Short press to play/pause. When in FM mode, long press to automatically search for channels.

### BACK PANEL



### CHARGING THE SPEAKER



#### LED STATUS INDICATORS:

Color	Meaning
RED	Charging
GREEN	Fully charged

\*Charging indicator located at the rear of unit

#### WATER RESISTANT CAP

Before using near water, make sure the water resistant cap is completely covered.



#### BLUETOOTH

Flashing Blue	Pairing (flashing)
Solid Blue	Connected to Bluetooth

\*Bluetooth indicator located on the top of unit

#### LOW BATTERY STATUS

4 lit LEDs	Low battery
4 solid LEDs	Fully charged

\*Low Battery Prompt: Low Battery

#### BLUETOOTH CONNECTION OPERATION

- Turn on unit to BT mode, make sure your device switch on Bluetooth.
- Press & hold the Play button to enter pairing mode.
- Select 'iHome iBT920' on your device to pair.

#### RECORDING OPERATION

- Insert TF card or U disk, switch to Bluetooth mode.
- Play BT music.
- Insert in a wired microphone.
- Short press the record button (on the remote control) to start recording. To finish recording, short press the record button.
- To play a recorded file, long press the Play button.
- To delete the recorded file, playing the recorded file and long press the Play button to delete the file.


#### TRUE WIRELESS PAIRING (TWS)

(REQUIRES 2 SPEAKERS)

- Pair one iBT920 unit to your device via Bluetooth.
- Power on the second iBT920 unit.
- Press and hold the Mode button for 2 seconds on each unit.
- When both units are linked, will announce "Left Channel", "Right Channel" respectively.
- Both units will link TWS automatically next time when both units are powered on.
- If want to remove TrueWireless, reset BT pairing: press & hold Play button for 10 seconds on both units.

## Back

### REMOTE SCHEMATIC DIAGRAM AND OPERATION INSTRUCTIONS



- Under normal circumstances, the remote control should be used within the receiving range of about 6 meters and 30 degrees from the device receiving window.
- When operating the remote, please aim it at the receiving window of the device. There should be no obstacles between the remote and the device.
- If the receiving window of the device is placed under a strong light, the operation panel of the remote may malfunction. In this case, please move the device away to avoid direct exposure.
- When the remote has no battery, you can replace "AAA" x 2 batteries to avoid mixing old and new batteries. Please check the remote batteries regularly to see if they need to be replaced.

### IMPORTANT SAFETY INSTRUCTIONS

Please heed all warnings, read and follow all instructions and keep these instructions handy for future reference.

- Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
- Heat - This product should be situated away from heat sources such as radiators, heat registers, stoves or other appliances (including amplifiers) that produce heat.
- Only use attachments/accessories specified by the manufacturer.
- Unplug this product during lightning storms or when unused for long periods of time.
- Damage Requiring Service - This product should be serviced by qualified service personnel when:
  - Plug has been damaged.
  - Objects have fallen into or liquid has been spilled into the enclosure.
  - The unit has been exposed to rain. The unit has been dropped or the enclosure damaged.
  - The unit exhibits a marked change in performance or does not operate normally.
- No naked flame sources, such as lighted candles, should be placed on this product.
- Attention should be drawn to the environmental aspects of battery disposal.
- This product is suitable for use in tropical and/or moderate climates.
- Do not dispose of batteries in the household trash or fire.
- The mains plug of power adaptor is used as the disconnect device, it shall remain readily operable.
- Unplug unit and clean only with damp cloth. Stronger cleaning agents, such as Benzene, thinner or similar materials can damage the surface of the unit.
- CAUTION! Risk of explosion if the battery is replaced by an incorrect type.
- If the unit is to be unused for an extended period of time, such as a month or longer, charge the unit fully before storage. Always use a UL/ETL certified charging adapter (not included), and the supplied USB charging cable.

### FCC INFORMATION

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. This device complies with Part 15 of the FCC Rules, operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

### ISED Information

The device comply with ISED RF exposure requirement, users can obtain Canadian information on RF exposure and compliance.

This equipment complies with IC RSS-102 radiation exposure limits set forth for an uncontrolled environment.

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- (1) This device must not cause interference.
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

L'appareil est conforme aux exigences d'exposition RF ISED, les utilisateurs peuvent obtenir des informations canadiennes sur l'exposition aux RF et la conformité. Cet équipement est conforme aux limites d'exposition aux radiations IC CNR-102 établies pour un environnement non contrôlé.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

- (1) L'appareil ne doit pas produire de brouillage;
  - (2) L'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.
- Tout changement ou modification non expressément approuvé par la partie responsable de la conformité peut annuler l'autorité de l'utilisateur à utiliser l'équipement.

CAN ICES-3 (B) / NMB-3(B)

### ONE YEAR LIMITED WARRANTY

iHome Products, a division of SDI Technologies Inc. (hereafter referred to as SDI), warrants this product to be free from defects in workmanship and materials, under normal use and conditions, for a period of 90 days from the date of original purchase. Should this product fail to function in a satisfactory manner, it is best to first return it to the store where it was originally purchased. Should this fail to resolve the matter and service still be required by reason of any defect or malfunction during the warranty period, SDI will repair or, at its discretion, replace this product without charge. This decision is subject to verification of the defect or malfunction upon delivery of this product to the Factory Service Center authorized by Customer Service.

If service is required, please contact Customer Service at [ihomeaudio.com/support/contact](http://ihomeaudio.com/support/contact) to obtain a Return Authorization Number and shipping instructions. A copy of the sales receipt is required to validate in-warranty coverage. If proof of purchase cannot be produced, the product will be deemed out-of-warranty. The date of purchase, vendor, product model number, and purchase price must be legible and verifiable.

#### Disclaimer of Warranty

NOTE: This warranty is valid only if the product is used for the purpose for which it was designed. It does not cover (i) products which have been damaged by negligence or willful actions, misuse or accident, or which have been modified or repaired by unauthorized persons; (ii) cracked or broken cabinets, or units damaged by excessive heat; (iii) damage to digital media players, CD's or tape cassettes (if applicable); (iv) the cost of shipping this product to the Factory Service Center and its return to the owner. This warranty is valid only in the United States of America and does not extend to owners of the product other than the original purchaser. In no event will SDI or any of its affiliates, contractors, resellers, their officers, directors, shareholders, members or agents be liable to you or any third party for any consequential or incidental damages, any lost profits, actual, exemplary or punitive damages.

(Some states do not allow limitations on implied warranties or exclusion of consequential damages, so these restrictions may not apply to you.) This warranty gives you specific legal rights, and you may also have other rights which vary from state to state. Your acknowledgment and agreement to fully and completely abide by the above mentioned disclaimer of warranty is contractually binding to you upon your transfer of currency (money order, cashier's check, or credit card) for purchase of your SDI product.

© 2023 SDI Technologies, Inc. All rights reserved.  
 Questions? Visit [www.ihome.com](http://www.ihome.com)