



USER MANUAL M1

1 Precautions

- Liquids Do not expose your device to liquids or extreme humidity. Liquids can get into the product's circuits, leading to damage and corrosion. If it does get wet, don't try to accelerate drying with the use of an oven or dryer, as this may damage the device.
 - Extreme heat/cold Avoid placing your device near a heat source or in direct sunlight. Extreme temperatures can cause the battery to swell, leak or malfunction.
 - Cleaning Use a clean cotton cloth. Don't use alcohol or other cleaning solutions.
 - Never place the device over other electronic devices.
 - Do not attempt to repair or take apart the device by yourself. Contact 5LINX® customer service for assistance: 5linxpowerplay@5linx.com

2 Included Accesories

- A. 3.5mm Male to Male Stereo Audio Cable
- B. Micro USB to USB Cable
- C. US AC to USB Power Charger Adapter Plug



Pictures are for illustration purposes only. Actual items may slightly vary in appearance and design.

3 Device Overview

USB Charging output Jack & Light Red indicator light - Power indicator Green Indicator Light - Charger indicator

AUX Connector

Aux Plug in – Aux mode, remove AUX, Bluetooth mode

Blue Indicator Light Bluetooth Indicator



Device Power on/off switch



Device on ■ Device off ■ Device off



4 Battery Management

- Connect the Micro USB cable (included) to the Micro USB port on the 5LINX PowerPlay and connect the USB Cable to the Power Charger Adapter Plug.
- Plug the Adapter Plug into an electrical wall outlet to fully charge the battery (approx. 8 hours).
- Red indicator light is on while charging and will turn off when fully charged.

Do not charge additional devices while charging the 5LINX PowerPlay, this will damage the device.



5 Pairing your Bluetooth enabled device to your 5LINX PowerPlay

5LINX PowerPlay doesn't work with all apps.

- Go to your mobile device's Network Settings.
- Set your Bluetooth device to discover.
 Follow your device's instruction guide.
 This usually involves going into a "setup",
 "connect" or "Bluetooth" menu.

Step 1 iPhone



Step 1 Android

Settings>Wireless & nework settings> Bluetooth Settings>Bluetooth devices





Step 2 iPhone Settings>Bluetooth>Devices



Step 2 Android

Settings>Wireless & nework settings> BluetoothSettings>Bluetoothdevices



- 3. Turn your 5LINX PowerPlay device's speaker on.
- Locate the 5LINX PowerPlay on your Bluetooth device & select "5LINX" from the list.
- 5. Your 5LINX PowerPlay will beep when pairing is complete.

Step 4
iPhone
Settings>Bluetooth>Devices



Step 4 Android

Settings>Wireless & nework settings>
Bluetooth Settings>Bluetooth devices



Android



In case of unsuccessful pairing, repeat the steps on previous pages.

6 Charging Devices (not compatible with iPad 1, 2 & Motorola cell phones)

- Connect the USB end of the charging cable that came with your mobile device to the OUT port on the 5LINX PowerPlay.
- Connect the micro USB end to your mobile device.
- During charging, the green indicator light will stay on.



7 Hands-free calling

- Connect the 3.5mm Male to Male Stereo Audio Cable to the AUX connector on your 5LINX PowerPlay.
- Connect the other end of the 3.5mm Male to Male Stereo Audio Cable to your mobile device's headphone jack.
- Make, receive and end calls on your mobile device as you normally would.



8 Specs

- Weight<6 ounces
- Size:4.53inches (L)*2.4inches(W)*.905 inches(H)
- RechargeableBattery:Lithium-polymer 3.7V5000mAh
- PowerConsumption:DC5V/500mA~1A
- SuperHighCapacity Rechargeable Battery5000mAh,about300%ofiPhone 4batterylife
- SpeakerFrequency:90Hz~20KHZ
- FreqencyRange: 2402MHz-2480MHzInput/Outputvoltage:5V
- Signalandnoiseratio:≥80dB
- Powerofloudspeaker.3W
- Chargingtime— Approximately8 hoursPlayingtime— Approximately32hours
- (volumeat60%)Hands-freecalling— via3.5mmAUX
- connector
- LEDindicatorLightforBluetooth
- EffectiveDistance— upto33feet

9 Troubleshooting

No Sound

 Makesurethemobiledeviceisnoton muteandyourvolumeis turnedup.

Bluetooth Connection

- Ensurethatthespeakerandmobile devicearewithin33feetofeachother.
- Ensuremobiledeviceisstillpairedwith your5LINXPowerPlay.

No Power

 Deviceneedstobecharged.Connect thedevicetoaUSBportandthepower adaptor.

ECC STATEMENT

- 1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
- (1) This device may not cause harmful interference.
- (2) This device must accept any interferencereceived, including interferencethat may causeundesired operation.
- Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interferenceby one or more of the following measures:

Reorient or relocatethe receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which a receiver is connected.

Consult the dealer or an experiencedradio/TV technician for help.

RF warning statement:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.