



inteo SOLIRIS RTS sensor 24V

Installation Instructions



24V SOLIRIS RTS SENSOR KIT
CAT NO. 6301051
(Includes transmitter, not shown)

- The SOLIRIS RTS sensor is a radio sun & wind sensor for awnings.
- The wind and sun thresholds can be set directly on the SOLIRIS RTS sensor.
- The SOLIRIS RTS sensor is compatible with the LT RTS CMO and ALTUS RTS motors.

Power supply : 24V DC (min: 17V max: 40V)

24V AC (min: 17V max: 28V)

Rated Current : 20 mA at 24V DC

The SOLIRIS RTS sensor must be supplied by a class 2 transformer

Protection index : IP34 (protection against water project from all directions. Not submersible).

Operating temperature : -4°F to 122°F/-20°C to +50°C

1 Installation



Dimensions




2 Wiring

WARNING: For the SOLIRIS RTS SENSOR to function properly, the component which is mounted into the motor's receiver, must be configured correctly. The DOWN button **MUST** correspond to DOWN on the remote. In the case of an opening, it will open or extend the awning. If the UP button extends the awning, the wind sensor will also extend the awning during windy conditions. **This is DANGEROUS!** Damage and injury could occur. Do not proceed until proper operation of the transmitter is verified. Please refer to the installation instructions of the released motor to change the direction if necessary.

1. Power input to the sensor is not polarized, but turn off the power and fully discharge the transformer before making final connections.
2. The cable distance between the power supply and the sensor must not exceed 164 feet.

COLOR CODE


BROWN
WHITE



3. Connect the cable leads to the terminals.
- Terminal block is removable for easier connections




1. Remove Cover and unscrew plate over wiring compartment.



2. Loosen the strain relief plate and guide the power supply wires through the black grommets into terminal block.



4. Replace wire compartment cover



5. Attach the sensor to the wall. Replace front cover and secure with screws provided

SOMFY 2013050, INC. reserves the right to update, change or modify these instructions without prior notice.
REF ID: 162205A
COPYRIGHT © SOMFY SYSTEMS, INC. 10/01

SOMFY MEXICO S.A. De C.V.
Calle 3 No. 47, Local E-8
Fracc Ind. Alte Sierra
Nave 12do. Col. Mixco, C.P. 14090

SOMFY SYSTEMS, INC.
47 Commerce Drive
Chatsbury, NJ 07921

SOMFY CANADA
601 St. Blaisewood Drive, Unit 4F
Mississauga, Ontario L5T 1J6

CAUTION: Changes or modifications not expressly approved by the manufacturer responsible for compliance could void the user's authority to operate the equipment