SY-TWS1 正面 规格: 35 x 11 cm

对耳无线立体声

蓝牙耳机

使用指南

₹ (€ **% 6**

配 对

1. 右耳机与左耳机自动配对



将左右耳机同时从底座充电盒取出,双耳会自动开机互连,成功后,左耳机红蓝灯

2. 右耳机与左耳机手动配对

如左右耳自动配对失败,或出现双耳断连时,按左和右耳的多功能键重新开关机, *如果将双耳放回充电仓或手动配对依然不能配对,请长按多功能键10S,实现强制 性开关机 (部分方案支持这种方法)。

3. 耳机与手机配对 ①.参考配对1/2将左右耳机配对。 ②.激活手机蓝牙设置 ③.搜索 "SY-TWS1" ,点击连接。

4. 右耳机与手机单独配对 ①.长按右耳机多功能键。 ②.激活手机蓝牙设置。 ③.搜索 "SY-TWS1" ,点击连接。

5. 左耳机与手机单独配对 ①.长按左耳机多功能键。 ②.激活手机蓝牙设置。 ③.搜索 "SY-TWS1",点击连接。



1. 开关机



双耳配对:长按左和右耳的多功能键3秒,开关机 单耳配对:长按左或右耳的多功能键3秒开机,进入单耳配对,长按3秒关机。(开机时 红蓝灯交替闪烁,关机时红灯闪烁后熄灭。)

2. 接听/挂断电话

来电状态下,单击左或右耳的多功能键接通电话。 通话状态下,单击左或右耳的多功能键接通电话。

3. 拒接/回拔电话

来申状态下、长按左或右耳的多功能键拒接电话。 回拔电话,三击右耳的多功能键,回拔最后一个电话;三击左耳的多功能键,打开语音助手。



4. 播放/暂停音乐

在播放音乐状态下,单击左或右耳的多功能键播放/暂停音乐。


5. 上一曲/下一曲控制

在播放音乐状态下,双击左耳的多功能键实现上一曲功能;双击右耳的多功能键实现下

充电功能

1.给充电仓充电

用本产品包装盒内附带的充电线,连接电源适配器进行充电。



2.给耳机充电

在确保充电仓有充足电量的时候,将耳机放入对应的穴位进行充电。

3.充电仓指示灯显示状态

①充电仓充电时闪烁红灯;充满电时亮红灯.②按充电仓按键显蓝灯,表示有电量;若是蓝灯慢闪,表示电池低电量;若是不

本机需使用优质充电线进行充电,Micro USB线连接5V(1A-2A)电源适配器,5V (1A-2A)车载充电头,推荐使用2A以下的电源活配器给耳机进行充电,蓝牙耳机充满

•本机充电时请注意使用优质充电器或电脑端口充电,切不可使用廉价 劣质的充电器。 •蓝牙耳机均有使用环境以及连接距离的问题,请您勿在强电磁干扰和辐射的环境中

•请不要将蓝牙耳机置于水中或摔打,这些均会造成产品损害。

•如果您的蓝牙耳机长时间不使用,请约30天充电一次,以防止因缺电而造成的无法

•我们可能在未事先通知您的情况下,对于此产品进行一次软件或者硬件以及外观的 升级和改动,请您以实物为准。

常见问题

蓝牙耳机不开机? ①.检查蓝牙耳机是否没电,需进行充电;

②.需长按多功能键开机(具体时间请参考操作说明)。

蓝牙耳机信号不稳定? ②重新启动的证券 ②重新启动或于耳机; ②直看手机的兼容性及手机通话质量; ③确认是否距离过远或者周边环境有干扰; ④.不要停留在信号反射的环境中。

蓝牙耳机噪音过大? ① 查看手机抑噪控制: ②.确认蓝牙是否与耳机距离过远 ③.确认周边环境是否有电磁辐射。

蓝牙耳机听不到声音? 型の中が明不到20日: ①.检查耳机音量是否调为静音; ②.检查蓝牙耳机是否与手机连接 ③.检查蓝牙耳机是否与手机距离过远或周边有干扰体。

蓝牙怎么充电? ①.使用原装数据线充电,并根据要求选择合适的电压与电流适配器; ②.插入USB接口后,约2~3小时可以充满(不同机型充电时间略有差异)。

蓝牙耳机怎么连接电脑?

①.检查电脑是否有蓝牙功能,如没有需购买蓝牙适配器; ②.需安装蓝牙驱动软件即可连接。

蓝牙耳机是否可以升级? ①.蓝牙耳机产品芯片为ROM芯片,不能升级;

②.因操作不当,升级有可能造成产品故障。 蓝牙耳机怎么连接手机?

區才早机怎么连接手机。 ①,开机:进入红蓝灯交替闪烁配对状态; ②打开手机蓝牙,搜索蓝牙设备,点击配对; ③如有需要输入密码,请输入1234或0000。

包装明细

蓝牙耳机 (2 PCS) 耳机充电盒 USB充电线 使用说明书

备用硅胶套

产品规格

蓝牙版本: 5.0 电源输入: DC 5V 耳机工作时间: 2 小时左右 耳机充电时间: 1 小时左右 充电仓充电时间: 2~3 小时左右 耳机电池容量: 35mAh 充电仓电池容量: 400 mAh 支持协议: HSP/HFP/A2DP/AVRCP 灵敏度: 108+/-5dB 频率响应: 20-20000Hz 阳抗: 32 ohms

SY-TWS1 背面 规格: 35 X 11 cm

Bluetooth Earphone

True Wireless Stereo Earbuds

₹ € **₹ 6**

Pairing

1. Auto Pairing



Take out the left and right earphone form charging compartment, The earphones will be automatically on and paring. When pairing successfully, the left earphone will flash red and blue alternately and the right earphone light will go out.

2. Non-automatically earbuds pairing

When auto-pairing failed, or dual earphone disconnected. Press the power button on left and right earphone, to make the earbuds off and on again, the left and right earphone will be

connected manually.

If putting the earbuds back to the charging case or pairing the earbuds by buttons, neither way is ok to make the earbuds pairing, please long press the buttons for about 10 seconds, to force the earbuds off and on again. (some kinds of bluetooth solutions support this kind of operation)

3. Earphones and Mobile Phone Pairing


- Do above operation 1 or 2 to pair left and right earphone.
 Open Mobile Phone Bluetooth settings.
- 3.Search Bluetooth name "SY-TWS1", click it to connect
- 4. Right Earphone and Mobile Phone Pairing ①.Long press the button of the right earphone Search Bluetooth name "SY-TWS1", click it to connect.

5 Left Famhone and Mobile Phone Pairing (1).Long press the button of the left earphone

Open Mobile Phone Bluetooth settings.
 Search Bluetooth name "SY-TWS1", click it to connect

Button Function

1. On/Off Buttons



(When power on, the earphone will flash red and blue alternately. When power off, the light is off.)

2. Answer / Hang Up

3. Reject / Call Back

When coming call, long press left or right earphone to refuse the call.

Three-click the right earphone button to resume back to the last call, three-click the left earphone button to open the voice assistant.



4. Play / Pause Music

While playing music, click the button of left or right earphone to play or pause the music

5. Last / Next Song Control

When playing, double-click the left earphone button to switch to the Last song; double-click the right earphone button to switch to the next song.

Charging Function

1. Charge the Charging Box

There is an USB charging cable in the package, you can connect the power adapter for charging.



2. Charge for Earphones

Please double check and confirm the charging compartment has sufficient power, then put the earphones into the correct position for charging.

3. Charging Compartment Indicator State

(2)While charging, the charging compartment indicator flash red light. After fully charged, the light is keeping red.

(2)Press charging compartment button, when the indicator light blue, it means the charging case has sufficient power. If the blue light flashes slowly, it means the battery is low. When no power, the light will be off.

Precautions

The product needs to be charged with a premium charging cable, and the Micro USB cable is connected to a 5V(1A-2A) power adapter or a 5V (1A-2A) car charger. Recommending to use a power adapter below 2A. It needs about 1-2 hours to do the fully charge.

- Please pay attention to the use of high-quality charger or computer port charging for the
- rease pay attention to the use of impropany violage or computer port utaging for the product, must not use cheap and poor quality charger.

 Blueboth Earphones are affected by the environment and connection distance. Please do not use them in environments with strong electromagnetic interference and radiation.

 Please do not put the Bluetooth earphone in the water or beat it, which will cause damage
- If the Bluetooth Earphone is not used for a long time, please charge it monthly to prevent it from starting due to lack of powe
- We may upgrade the software, hardware or appearance of this product without notice, please refer to the actual product.

Frequently asked questions

- Why bluetooth earbuds can not turn on?
 ①. You can check if earbuds is with power or not ? if not, please fully charge it before turning it on.
 (2). Please long press the power on /off button.(the detailed operation , please refer to the manual.)

Why bluetooth earbuds signal is not unstable:

- Why bluetooth earbuds signal is not unstable?

 (i) Restart the bluetooth earbuds:

 (ii) Relater the bluetooth earbuds:

 (iii) Please kindly check the compatibility and calling communication quality of the mobile phone.

 (iii) Please confirm if the distance between earbuds and phone is too far or there are interference surrounded. If too far or there are interference, the signal will be unstable.

 (iii) Please don't stay in the signal reflective environment.

Why the bluetooth earbuds noise is so big?

- vmy the buelcone earbuse noise is so ong?

 (i) Please kindly check the mobile phone's noise suppression function.

 (i) Please kindly check if the bluetooth earbuds and mobiles phone's distance is too far. If too far, please shorten it and try it again.

 (ii) Please kindly confirm if there is an electromagnetic radiation surrounding environment.

- ...у высывающе чагошох сапт hear voice?

 (р.)Please kindly check if the bluetooth earbuds is on mute status.

 (р.)Please kindly check if bluetooth earbuds and phone are connected well.

 (в.)Then confirm if the distance between earbuds and phone is too far or there are interference surrounded.

How to charge?

①.Use the original USB charging cable, one side connect with earbuds, the other side connect with PC/Table/power bank.

(2).Usually it will takes about 2~3 hours to charge

Sirist check if the computer with bluetooth function or not?,if not ,please buy a bluetooth adaptor before connection.

 Install bluetooth driver into computer.

If the bluetooth earbuds can be upgraded? ①.Normally bluetooth can not be upgraded, as the bluetooth chipset is ROM chipset. ②.When upgraded, please operate follow the guideline, otherwise it may be failed

on upgrading.

How to connect earbuds with bluetooth devices(smart phones/tablet)?

①.1.Power on, the earbuds with enter into pairing mode.②.Turn on the bluetooth function on bluetooth device ,search the earbuds model name and click it to pairing.

(3).If need input the password, please input 1234 or 0000.

Bluetooth Earphone (2 PCS)
Earphone Charging Compartment
USB Charging Cable
User Manual
Beautiful Box
Spare Silicone Earpads

Packing details

Product **Specification**

Impedance: 32 ohms

Bluetooth Version: 5.0 Power Input: DC 5V Earphone Working Time: About 2 hours Earphone Charging Time: About 1 hours Charge Time: About 2 ~ 3h Earphone battery capacity: 35mAh Charging Case battery capacity: 400mAh Support Protocol: HSP/HFP/A2DP/AVRCP Sensitivity: 108+/-5dB Frequency response: 20-20000Hz

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- -Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.