

Phantom

Calls

**“Simply the Most Effective
Calls on the Market”**

Cover Photo



Extreme Dimension Wildlife Calls has quickly become the leader in game calling technology. We offer our customers quality calling systems which are simple to use at an affordable price, all this backed by the best customer service in the industry, how could things get any better?

Well we have just raised the bar again with our completely redesigned **Hunter** and **Pro- Series** of calls. We listened to our customers and have come up with solutions for every level of caller. **Electronic Calls aren't just for predators anymore!** I think you will agree the new line of Phantom Calls is the answer to all your game calling needs at an affordable price.

Sincerely,

Extreme Dimension Wildlife Calls

Hunter Series Calls

Pro-Series Calls Wired

Pro-Series Wireless

Sound Modules

Table of Contents

- 1. Common features of the family of Phantom Calls.**
- 2. Hunter Series**
- 3. Pro-Series – Wired Models**
- 4. Pro-Series Wireless Remote Models**
- 5. Trouble Shooting**
- 6. Warranty Information**
- 7. Trade Up Allowance**
- 8. Phantom Calls TV**
- 9. Phantom Calls Web Site**

Phantom Calls

Some of the Features that have made *Phantom Calls* the Choice for Serious Sportsman:

Digital Technology with Natural Sounds:

The ***Phantom Calls*** are compact touch pads that fit in the palm of your hand. All sounds are 100% natural digitally recorded.

Create a Series of Calls

The Phantom Calls are the only units available with the ***Patent Pending*** ability to play 2 sounds simultaneously. You can also overlap the same sound giving a dueling effect. The 12 sound units provide 144 different calling combinations.

Unlike conventional calls which only provide vocalizations the Phantom Calls simulate the sounds created by movement, enabling you to add realism and take your calling abilities and success to a successful new level.

Custom Mix 12 Lifelike Sounds

You control the sequence, variety, volume and frequency of vocalization and movement sounds. Now there is a single tool that enables you to respond to every stage of the season.

It's Light & Portable

The **Phantom** lightens your load while increasing your hunting efficiency. With its rugged, weather-resistant ABS construction, the entire unit weighs less than 28 ounces. You hold it all in the palm of your hand. This device is no bigger than your TV remote and even easier to use! No more hauling around multiple awkward and heavy calls.

Greater Stealth & Security

The Phantom transmits sound through a compact speaker attached to a 60-foot speaker wire (additional wire available to increase the distance) which is placed on the ground or attached to a tree away from you. Now you can remain motionless while distancing yourself from the sound. Safely distancing yourself from the origin of the sound decreases the risk of an unfortunate hazard.

Call like the Pro's

We have taken the guess work out of calling with our natural digitally recorded sounds coupled with a complete set of calling instructions (included with each call). You can now call like a pro!!!

Phantom **Calls**

HUNTER-SERIES

Family of Hunter Series Calls

PHANTOM *HUNTER-SERIES*

The ground breaking design of the original Phantom Calls have just been improved and expanded.

The economical non-wireless ***Phantom Hunter- Series*** now comes in seven different models. Predator, Whitetail, Turkey, Goose, Moose, Elk and Bear.
Electronic calls aren't just for Predators anymore!

NEW & IMPROVED:

The ***Phantom Hunter-Series*** also boast some major improvements at the same economical price.

Increased Sound Quality

New 16 bit sound IC and 16 bit processor the ***Phantom Hunter- Series*** now has twice the sound quality as before.

Longer Battery life

4 "AA" batteries for increased battery life up to 16 hours at max volume at an ear shattering 126 db.

Improved cold weather operation

All components are rated for -40 degrees.

Power & Low Battery Indicators

LED's for Power on and low battery.

POWER SOURCE

The Phantom Hunter-Series is powered by 4 "AA" batteries. We recommend using alkaline batteries for optimum performance. The Phantom is programmed to automatically shut down after remaining idle for 60 seconds to conserve battery life. With moderate use the average hunter could hunt a whole season on one set of batteries.

Phantom Hunter-Series

(Wired Model)

HUNTER SERIES CALLS

TO BEGIN CALLING

Be sure you have installed 4 “AA” batteries. Place the speaker at the desired location. Plug the 60- foot section of wire (more if desired) to the speaker tail and run the wire to your desired stand site. **FIRMLY** plug the speaker wire into the speaker jack at the top of the hand held unit. Turn the unit ON by pushing the ON button. The flashing LED signifies the unit is ON. The phantom has a short power-up time. As soon as the Green Power LED begins to flash the unit is completely powered up. Set the desired volume level and you are now ready to begin calling.

When the unit is turned OFF and then ON, the volume level automatically returns to the MID level setting.

The Phantom Hunter-Series features an 8-step volume control. To adjust volume, simply press the volume UP or DOWN button. You must press each time you wish to make an incremental volume level change.

For example: When the Phantom is on the lowest volume setting, you must press the volume UP button 7 separate times to reach the maximum volume level.

If you feel 60 feet of speaker wire is not enough for your calling situations; we also offer additional 60-foot sections of wire complete with connectors. We have used the Phantom with up to 300 feet of wire without any noticeable distortion or volume loss.

Many customers purchase additional speaker/wire combinations to leave at multiple stand locations.

STORAGE

At the end of the hunting season we recommend removing the batteries from the Phantom before storing.

Phantom

Calls

PRO-SERIES

Photo 1
Pro Series Wireless

Photo 2
Pro Series Wired

Photo 3
Sound Modules

Photo 4
Wireless Remote Upgrade Kit
Figure 6

The "***Leader of the Pack***" has done it again with the completely re-designed ***Phantom Pro-Series***. This new series of Digital Calls boast the same original features with some new exciting and innovative features:

The new ***Phantom Pro-Series*** can be purchased in seven different models. Predator, Whitetail, Turkey, Goose, Moose, Elk and Bear.

Electronic calls aren't just for Predators anymore! The Phantom Pro-Series calls can be upgraded to any additional calls by purchasing additional sound modules. The Phantom Pro-Series can also be upgraded to wireless remote operation by purchasing the optional ***Remote Transmitter Upgrade Kit***, or may be purchase as a wireless remote unit.

Completely Re-designed Features Include:

Interchangeable Sound Modules

84 sounds available on 7 different sound modules. With interchangeable **Sound Modules** and custom case covers you can now have as many **Phantom Calls** as you want with the same main unit. Each Sound Module includes 12 sounds geared toward exactly what you are hunting, and a custom labeled case cover.

Wireless Remote Capability

200 yard range, 16 functions Remote Transmitter, with 3 Channels of wireless capability. With 3 channels of wireless capability, you can hunt in close proximity to others on separate Channels or use multiple receiver/speaker set ups with one transmitter.

The **Phantom Pro-Series** can be purchased without the wireless remote and can be upgraded to wireless remote by purchasing the **Wireless Remote Upgrade Kit** which includes; 200 yard, 16 function, 3 channel transmitter, Receiver Module & 2 antenna's; making it the only 16 function 3 channel remote on the market.

Increased Sound Quality

New 16 bit sound IC's & 16 bit processor used in the **Phantom Pro- Series** provides twice the sound quality as before.

Raised Rubber Keypad

Tactile feel takes the guesswork out of call selection and provides positive indication of buttons being pushed

Longer Battery life

4 "AA" batteries for increased battery life up to 16 hours at max volume at an ear shattering 126 db.

Improved cold weather operation

All components are rated for -40 degrees.

Power & Low Battery Indicators

LED's for Power on and low battery

Detachable Belt Clip

Clip on your belt or clip on your speaker base to create a single fixed unit

Sealed Module Ports

Custom labeled covers are as easy to remove as a cell phone cover providing completely sealed module ports, for particle and weather resistance.

All this Along with the Same Original Features that have made *Phantom Calls* the Choice for Serious Sportsman:

Pro-Series Wired Call

Using the *PRO-SERIES* as a Wired Unit (Non-wireless remote)

TO BEGIN CALLING

Be sure you have installed 4 “AA” batteries. Place the speaker at the desired location. Plug the 60- foot section of wire (more if desired) to the speaker tail and run the wire to your desired stand site. **FIRMLY** plug the speaker wire into the speaker jack at the top of the hand held unit. Turn the unit ON by pushing the ON button. The flashing LED signifies the unit is ON. Set the desired volume level and you are now ready to begin calling.

When the unit is turned OFF and then ON, the volume level automatically returns to the MID level setting.

The **Phantom Pro-Series** features an 8-step volume control. To adjust volume, simply press the volume UP or DOWN button. You must press each time you wish to make an incremental volume level change. For example: When the Phantom is on the lowest volume setting, you must press the volume UP button 7 separate times to reach the maximum volume level.

If you feel 60 feet of speaker wire is not enough for your calling situations; we also offer additional 60-foot sections of wire complete with connectors. We have used the Phantom with up to 300 feet of wire without any noticeable distortion or volume loss.

CHANGING SOUND MODULES

The Phantom Pro-Series offers Interchangeable Sound Modules

84 sounds available on 7 different sound modules. With interchangeable **Sound Modules** and custom case covers you can now have as many **Phantom Calls** as you want with the same main unit. Each Sound Module includes 12 sounds geared toward exactly what you are hunting, and a custom labeled case cover.

TO CHANGE SOUND MODULES

Holding the unit upright with both hands simply depress the locking tab with your finger and pull the top and bottom covers apart.

Figure 1A

Figure 1B

Remove the sound module and firmly insert the desired Sound Module.

Figure 2A

Figure 2B

TO CHANGE FACE PLATE

Holding the top cover upside down peel the rubber key pad from the face plate and insert the rubber key pad into the custom labeled face plate provided with the corresponding sound module; making sure the 6 raised knobs are pushed firmly into the face plate holes.

Figure 3A

Figure 3B

Holding the main unit in one hand insert the dovetail section at the bottom of the face plate into the grooved base unit as shown.

Figure 4A

Figure 4B

Push the top pieces together making sure the sides line up. When the unit is pushed together at the top the latching tab will snap locking the face plate into place.

Figure 5

Wireless Remote Operation

The Phantom Pro-Series is also the most versatile electronic call ever designed. The Phantom Pro-Series can be upgraded to wireless remote by installing the **Wireless Remote Upgrade Kit (Figure 6)** which includes; 200 yard, 16 function, 3 channel transmitter, Receiver Module & 2 antenna's.

1. Simply remove the main unit cover refer to **Figure 1**
2. Insert the Remote receiver module into the Receiver module port opening. **Figure 6A**
3. Remove the antenna cap on the top of the main unit and screw in the antenna firmly. **Figure 6B**
4. Install the other antenna on to the wireless transmitter.
5. Making sure the transmitter and the main unit are on the same desired Channel (Channel 1, 2 or 3); replace the faceplates making sure the faceplate with the labeled sounds is on the transmitter. **Figure 6C & 6D**

Figure 6

Figure 6A

Figure 6B

Figure 6C

Figure 6D

FIRMLY plug the speaker tail wire into the speaker jack at the top of the main unit. Turn the unit ON by pushing the ON button. The flashing LED signifies the unit is ON.

Note: The main unit (unit with the sound module) must always have the speaker wire attached to the speaker to operate.

The detachable belt clip will clip on your speaker base to create a single fixed unit. Place the main unit and speaker at the desired remote location.

Figure 7A

Figure 7B

Figure 7C

Note: Installing the remote receiver module will over-ride the battery saving auto shut-down feature. The main unit is now required to be turned on while in operation and turned off after each use.

Simply turn on the transmitter and you now have wireless of unmatched capability of a 16 function, 3 channel remote out to 200 yards in ideal conditions. Range may be less depending on terrain or in brushy areas.

Note: The Phantom Pro-Series Wireless Remote range has been successfully tested at 200 yards. This is under ideal conditions with fresh and fully charged batteries. Your actual operating range will have to be determined by you in your normal operating conditions.

Note: The phantom **Pro-Series** has a mute function which will mute the sound and act as a reset.

STORAGE

At the end of the hunting season we recommend removing the batteries from the Phantom before storing.

WARRANTY INFORMATION

All Phantom Calls are fully warranted against factory defects for a period of one year from the date of purchase. Faulty parts will be replaced free of charge. All returns must be shipped prepaid to the factory and insured. This Warranty is only valid to the original purchaser and is not transferable.

We also pledge to our customers that our commitment to service and satisfaction does not end with your 1-year manufacturer's warranty. If at any time, for any reason, The Phantom Predator fails to mechanically operate, please notify us immediately. We will make every effort to take care of it promptly and with minimal cost to you.

TROUBLESHOOTING

Our Phantom Calls are very simple and easy to use below are some basic trouble shooting tips for you to try in the event your call isn't working properly before you call our customer service line for assistance

1. My call will not work?

Make sure you have properly inserted the 4 AA batteries and have firmly plugged the speaker wire into the main unit. Make sure the green power LED is flashing.

2. My unit turns on but no sound comes out of the speaker?

Again make sure the speaker wire is plugged in firmly. Even the wireless systems need to have the wire connected to the main unit to operate.

3. My unit works with the speaker wire and not with the 60' extension wire.

Check the wire for cuts and frayed ends near the connector.

Pro-Series Units Only

4. Both the green LED and the Red LED's flash at the same time!

This indicates that there is no sound module installed!

5. No sound comes out of the main unit when I press buttons on the Transmitter.

Make sure the speaker wire is firmly inserted into the main unit!

Make sure the Remote Receiver Module is installed into the Main unit!

Make sure the main unit is turned on! The main unit cannot be turned on and off by the Transmitter!

The Transmitter power LED needs to be flashing to indicate the transmitter is on!

Note: By inserting the Receiver Module into the main unit will override the battery saving Automatic Shutdown function. Therefore the main unit is required to be turned on when in use and turned off while not in use to save the battery life.

Note: The Transmitter will shutdown automatically after 60 seconds at idle to conserve battery life. The Transmitter is required to be powered up to transmit a signal to the main unit.

Note: When using as a wireless call the sound on the main unit will remain at the same level each time the transmitter is turned on.

6. My unit will not work at 200 yards?

The phantom pro-series has been successfully tested out to 270 yards in perfect conditions. The normal operating range will vary on your specific hunting conditions, terrain and battery power level!

PHANTOM CALLS TRADE UP POLICY

We at phantom calls want to make sure you have the unit you want! We realize some units may be purchased as gifts and or at some point you may want to have a wireless unit instead of a wired unit.

We would like to offer our customers a trade in allowance for the Hunter Series to trade up to a Pro-Series call. At the time of printing we haven't firmed up the trade up allowance. Please call toll free 1-866-862-2825 for details.

PHANTOM CALLS TV

Now you can watch the Phantom Calls Pro Staff using the complete line of Phantom Calls on "The Outdoor Channel". "Phantom Calls Chasing the Dream" TV will be airing 52 weeks a year starting July 2004. Be sure to catch all the actions as we successfully use the Phantom Products on Trophy class animals across North America and beyond.

PHANTOM CALLS WEBSITE

Be sure to log on to www.phantomcalls.com to keep up to date on new products as well as the new line of hunting video's coming soon.

- **The Phantom Calls** have been extensively field tested throughout the U.S. with Incredible results!
- **Extreme Dimension Wildlife Calls** advocates and promotes safe and ethical hunting. Please check your State and local regulations before using **The Phantom Calls** for hunting.
- **Extreme Dimension Wildlife Calls** welcomes your questions, comments, success stories and photos.
- **Warning:** Due to the high volume level, do not place the speaker next to the ears when the system is activated.

NOTE:

THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER AUTHORITY TO OPERATE THE EQUIPMENT.



P.O. Box 220 • Hampden, ME 04444-220

Customer Service: 1-866-862-2825
Phone: (207) 862-BUCK • Fax: (207) 862-3925
Web Site: www.phantomcalls.com