

Scale:1:1

S/N	Remarks
1	Die cut
Size	300*240mm
1	
3	
4	
5	
6	
7	
8	
9	
10	

Setting up the Transmitter

Connecting the Audio
The X31 transmitter is connected to the audio source by the included 3.5mm audio cable. The audio source can be a CD player, MP3 player, or any other audio source. The audio source should be connected to the transmitter's 3.5mm audio jack. The audio source should be turned on and set to play the audio file you want to use.

Setting up the Headset
Step 1: Insert the battery into the headset. The headset is powered on by the X31 transmitter. The headset is powered on by the X31 transmitter. The headset is powered on by the X31 transmitter.

Headset Effects Button
Pressing the effects button activates the headset's effects. The effects are: Ambient, Bass, and Treble. The effects are: Ambient, Bass, and Treble. The effects are: Ambient, Bass, and Treble.

Configuring the XBOX Settings
The X31 transmitter has a unique feature called XBOX. XBOX is a feature that allows you to use the transmitter with your XBOX console. XBOX is a feature that allows you to use the transmitter with your XBOX console.

Using the Chat Boost™ Feature
The Chat Boost™ feature is a unique feature that allows you to use the transmitter with your headset. The Chat Boost™ feature is a unique feature that allows you to use the transmitter with your headset.

Using the X31

Transmitter Range
The transmitter has a range of 100 feet. The transmitter has a range of 100 feet. The transmitter has a range of 100 feet.

Pairing the X31
The transmitter is paired with the headset by the X31 transmitter. The transmitter is paired with the headset by the X31 transmitter.

Troubleshooting Tips
If the transmitter is not working, check the battery. If the transmitter is not working, check the battery. If the transmitter is not working, check the battery.

Avoid Hearing Damage
The headset has a maximum volume of 100 dB. The headset has a maximum volume of 100 dB. The headset has a maximum volume of 100 dB.

Using the X31

Transmitter Range
The transmitter has a range of 100 feet. The transmitter has a range of 100 feet. The transmitter has a range of 100 feet.

Pairing the X31
The transmitter is paired with the headset by the X31 transmitter. The transmitter is paired with the headset by the X31 transmitter.

Troubleshooting Tips
If the transmitter is not working, check the battery. If the transmitter is not working, check the battery. If the transmitter is not working, check the battery.

Avoid Hearing Damage
The headset has a maximum volume of 100 dB. The headset has a maximum volume of 100 dB. The headset has a maximum volume of 100 dB.


Using the X31

Transmitter Range
The transmitter has a range of 100 feet. The transmitter has a range of 100 feet. The transmitter has a range of 100 feet.

Pairing the X31
The transmitter is paired with the headset by the X31 transmitter. The transmitter is paired with the headset by the X31 transmitter.

Troubleshooting Tips
If the transmitter is not working, check the battery. If the transmitter is not working, check the battery. If the transmitter is not working, check the battery.

Avoid Hearing Damage
The headset has a maximum volume of 100 dB. The headset has a maximum volume of 100 dB. The headset has a maximum volume of 100 dB.



U.S. Patent 7,812,345 B2
© 2011 Turtle Beach
www.turtlebeach.com



Package Contents
• X31 Transmitter
• X31 Headset
• 3.5mm Audio Cable
• User Manual



For more information, visit us at www.turtlebeach.com