



iCarte Wallet Installation and Authentication

Installation

The iCarte Wallet Application Installation process consists of the following two steps:

- 1. Determination of the iPhone Unique Device Identifier, UDID.
- 2. Installation of the Ad-Hoc.

Determination of the iPhone Unique Device Identifier, UDID.

- 1. Open iTunes and connect the iPhone.
- 2. Under **Devices**, click on iPhone.



3. The iPhone information is displayed as shown below:



4. Find the Unique Device Identifier by Clicking Serial Number:



5. Copy the Unique Device Identifier by selecting Edit and then Copy



6. Paste the Unique Device Identifier into an email addressed to your WDI representative by clicking **Edit** and then **Paste** on the email program.

Installation of the Ad-Hoc.

After WDI has received the UDID of the iPhone to be used, the following file and directory will be sent on a zip archive in order to install the iCarte Wallet Appplication:

- *.mobileprovision file
- *.app directory

Ensure that iTunes resides in the computer that is normally used to synchronise to the iPhone whose UDID was provided previously.

- 1. After receiving the zip file from WDI, unzip the contents to a convenient place such as the Desktop on the computer.
- 2. Open iTunes.
- 3. Drag the "*.mobileprovision" file into **Applications**, under **Library**. Also, drag the "*.app" directory into **Applications**.



4. Connect the iPhone to the computer. Please use the iPhone whose UDID was provided to WDI

5. Under **Devices**, click on your iPhone.

for provisioning.



6. Click on the Applications tab



7. Ensure there is a check mark beside **Sync applications** and beside the application:



WIRELESS DYNAMICS INC.

8. Sync the iPhone to iTunes.

Authentication

- 1. Launch the "iCarte Wallet" application by pressing the "iCarte Wallet" icon.
- 2. The iCarte Wallet will ask for a Passcode; enter "1234".
- 3. The iCarte Wallet will authenticate then verify with an "Authentication Complete" message.

NOTE: Authentication is only required once after the iCarte Wallet has been installed.

After completion of the steps above, please refer to "iCarte Wallet Quick Start Guide" for instructions on how to use the iCarte with the iCarte Wallet Application on the iPhone.

iCarte Wallet Quick Start Guide

Installation and Authentication

- 4. Install the application
- 5. Launch the "iCarte Wallet" application by pressing the "iCarte Wallet" icon.
- 6. The iCarte Wallet will ask for a Passcode; enter "1234".
- 7. The iCarte Wallet will authenticate then verify with an "Authentication Complete" message.

NOTE: Authentication is only required once after the iCarte Wallet has been installed.

Use

Insert the iCarte into the bottom connector of the iPhone and follow the instructions below:

Enter PIN

- 3. When iCarte Wallet is launched, the iCarte Wallet will ask for a PIN; enter "7905".
- 4. The iCarte Wallet will then go to the "Main Menu".

The iCarte Wallet supports the following features: Payment, Discovery and Quick Payment. These features require the iCarte to be connected to the iPhone via the 30-pin connector.

Payment

- 1. From the "Main Menu" press the "Make Payment" button.
- 2. Present the $iCarte^{TM}$ to a contactless point-of-sale terminal.
- 3. The terminal will beep when the transaction has taken place.
- 4. The iCarte Wallet will ask to save the eReceipt.
- 5. To save the eReceipt press "Yes"; to discard press "No."

Discovery

- 1. From the "Main Menu" press the "Discovery" button.
- 2. Present the *iCarte* to a *Smart Poster*.
- 3. When the *iCarte* has read a Smart Poster the iCarte Wallet will display the contents of the *Smart Poster*.

NOTE: Please ensure that 3G or WiFi connectivity is enabled in order to display the contents of the Smart Poster correctly.

This device complies with Part 15 of the FCC Rules.

Operation is subject to the following two conditions:

This device may not cause harmful interference, and This device must accept any interference received, including interference that may cause undesired operation.

Any change or modification not expressly approved by the manufacturer could void the user's authority to operate the equipment.











FCC ID: SHFICARTE110

Industry Canada Certification Number: 5998A-ICARTE110

This device is a Radio Frequency Identification Reader operating in the frequency of 13.56 MHz. This device has been approved by The Federal Communications Commission, FCC, and Industry Canada. This device also complies with European requirements.

European Declaration of Conformity

The CE mark confirms that the iCarte is in compliance with the legal requirements of the European Union as a prerequisite for the placing and free movement of the product within the European internal market.

Wireless Dynamics Inc. hereby declares that iCarte is in compliance with the essential requirements of:

- 1. The European Directive 1999/5/EC on radio equipment and telecommunications terminal equipment and the mutual recognition of their conformity (R&TTE),
- 2. The European Directive 1999/519/EC on the limitation of exposure of the general public to electromagnetic fields (0 Hz to 300 GHz), and
- 3. The European Directive 2002/95/EC on the restriction of the use of certain hazardous substances in electrical and electronic equipment (RoHS).

The Signed European Declaration of Conformity is maintained by the manufacturer and a copy can be obtained upon request.