

CE FCC UKCA PSE RoHS




7.0 Specification


7.0 Specification

*Please note that the phone's Bluetooth signal can not be transmitted underwater.

Not for swimming under water



Notes for signal transmission distance
(as show below)



 Warning!

1. Do not dismantle or refit the product to avoid malfunction or fire hazards.
2. Keep away from corrosive liquids.
3. Keep away from extreme ambient temperatures between -10°C or above 60°C.
4. Keep away from children and pets.
5. Do not touch the eardrums with sharp objects.
6. Do not use the product in thunderstorm weather.
7. If it has not been used for more than a month, please charge and maintain it in time to ensure that it is safe.
8. Since the Bluetooth signal cannot be transmitted underwater, swimming, diving will caused the signal disconnected or intermittent.

Wipe the hardware contacts of the headset and charging box when the headset is not charging.




Note.
If your problem is not answered above,
please contact us via email ,
we will respond within 24 hours.

Email: info@tozostore.com




Battery Warning!

This product has built-in lithium battery.
Do not expose the product to strong sunlight,
fire or throw it into the fire to avoid explosion.



T6

1.0 Product diagrammatic sketch



The diagram shows two earbuds side-by-side. The left earbud is labeled 'Left earbud' and the right earbud is labeled 'Right earbud'. Both earbuds have a circular 'MFB Touch Panel' on the top surface. The right earbud also features a 'Mic Hole' on its side, indicated by a blue line pointing to it.

NOTE: The M ear tips have been pre-attached on the earbuds.

Step 1: Ensure the earbud tip facing downwards, then place earbuds into ear.
Step 2: Rotate earbuds back to auricle side to fit snugly.

4.1 How to pair

1. Take out the two earbuds from charging case, they will turn on automatically and will connect each other within 10 seconds.
2. The two earbuds flash alternately in red and blue (pairing mode).
3. Search for pairing name [TOZO-T6] and select it in your mobile.

Turn on:
Tap and hold the Touch Control on both earbuds for over 3 seconds

- 1.Touch the Control button 5 seconds will turn off when earbuds in playless status.
- 2.The earbuds will turn off automatically after it is disconnected for more than 5 minutes.

4.3 Reset

4.3 Reset

If you accidentally get only one earbud work, or fails to pair each other, please reset it:

1. Delete all [TOZO-T6] Bluetooth records on the phone, then turn off the Bluetooth.
2. Pick up two earbuds from charging case, then holding both earbuds panel for 5 seconds until red lights on both earbuds turn off.
3. Pressing the both earbuds for another 5 seconds till red and blue light blinking alternately, and then clicking the both earbuds twice quickly.
4. The reset will be done when the blue light flashes rapidly, and then red and blue light blinking alternately.

NOTE: In case there is [Connection Unsuccessful] in your devices, please delete all historical records of [TOZO-T6] and try the pairing process again.

5.1 Charging the earbuds

1. Put the earbuds into the charging case, they will power off & be charged automatically. When the red LED lights up, it means that the earbuds are being charged from charging case.
2. The red light will turn off when the earbuds are fully charged.

Please use the 5V/1A adapter to charge the charging case which can be charged with a computer USB or other USB interface charger.

Designed for the modern life, never be strangled by headphone cables. Enjoy the convenience of wireless charging and free charging devices provided by airports, hotels, and cafe shops around the world.


NOTE: The battery indicator—white indicator light is above the wireless charger.

Don't tap the earbuds touch button while in charge, otherwise it will be fail to pair.
Then you should follow the reset to factory settings.

6.1 Earbuds LED indicator

Turn on	Blue light flash for one seconds
---------	----------------------------------

(Operation in wearing of double earbuds)



Tap L or R touch area to answer the call or it will answer the call automatically

Hold L or R 2S the sensing area to reject the call

NOTE: If you accidentally get only one earbud paired with phone, please make sure both earbuds have been turn on. (Tap and hold the unpaired earbud for 3 seconds to turn on). If necessary, please try "Reset" options to restore to factory settings.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

.....

- English:

This device complies with Industry Canada licence-exempt RSS standard(s).

Operation is subject to the following two conditions: (1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device.

.....

- French:

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:

- (1) l'appareil ne doit pas produire de brouillage, et
- (2) l'utilisateur de l'appareil doit accepter tout brouillage radio électrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.