

ZTE Corporation

ZTE C79 CDMA 1X Digital Mobile Phone
User Manual

Copyright © 2008 by ZTE Corporation

All rights reserved.

No part of this publication may be excerpted, reproduced, translated, or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without the prior written permission of ZTE Corporation.

ZTE Corporation operates a policy of continuous development. ZTE Corporation reserves the right to make changes and improvements to any of the products described in this document without prior notice.

Contents

1. For your safety 11

- General Care 11
- Aircraft Safety 13
- Hospital Safety 13
- General Guidelines 14
- Road Safety 15
- Vehicles Equipped With an Air Bag 16
- Third Party Equipment 16
- Efficient Use 16
- Radio Frequency (RF) Energy 16
- Emergency Services 18
- FCC Notice 18
- Using Your Phone With a Hearing Aid Device 19
- Turning on the HAC Setting 21
- Copyright Notice 22

2. Introduction 23

- Overview 23
- What's included 23
- C79 Technical Specifications 24

Phone at a glance	25
Key Definitions	26
User Interface.....	29
Indicators and Icons	29
3. Set up Your Phone.....	31
Battery.....	31
<i>Installing the Battery.....</i>	<i>31</i>
<i>Charging the Battery.....</i>	<i>32</i>
<i>Removing the Battery</i>	<i>33</i>
Memory Card.....	33
<i>Inserting the MicroSD Memory Card.....</i>	<i>34</i>
<i>Removing the MicroSD Memory Card.....</i>	<i>34</i>
Powering On/Off your Phone.....	34
Unlocking Your Phone.....	35
Connecting to the Network	35
Activating Your Phone.....	35
4. Basic Operations	36
Making Voice Calls	36
<i>Using the Keypad.....</i>	<i>36</i>
<i>Using the Contacts list</i>	<i>36</i>

<i>Using the last number dialed</i>	36
<i>Using a number from the Call History</i>	37
<i>Using Speed Dials</i>	37
<i>Answering Voice Calls</i>	38
In-Call Features	38
Three-Way Call	39
Call Waiting	39
5. Entering Text	40
Key Functions.....	40
Text Input Modes	41
6. Contacts.....	44
Contact List	45
New Contact	46
Groups	47
Speed Dials.....	47
7. Calls	48
All Calls.....	48
Missed Calls	48
Incoming Calls.....	49

Outgoing Calls	49
Call Timers.....	49
8. Messaging	50
Send New	50
<i>Insert</i>	51
<i>Slide</i>	52
<i>Preview</i>	52
<i>Erase Item</i>	52
<i>Cc/Bcc/Sub</i>	52
<i>Save To Drafts</i>	52
<i>Quick Text</i>	53
<i>Signature</i>	53
<i>Message Priority</i>	53
Inbox	53
<i>Reading a message</i>	53
<i>Replying to a message</i>	54
Outbox	54
Drafts	55
Sent	55
Saved.....	55
Voice Mail	55

Web Alerts.....	56
Settings	56
<i>Message Settings</i>	56
<i>Quick Text Settings</i>	57
Memory Info.....	57
9. Brew	58
10. Web Wireless	59
11. Music & Media	61
Music Player.....	61
<i>Create a play list</i>	61
<i>Manage a play list</i>	62
<i>Control the music player</i>	62
Camera.....	63
<i>Take pictures</i>	63
<i>Viewing your photos</i>	64
My Tunes.....	64
<i>Playing your tunes</i>	64
<i>Managing your Tunes</i>	65
My Images.....	66
<i>View your image</i>	66

<i>Managing your Images</i>	66
Preload Files.....	67
<i>Tunes</i>	67
<i>Images</i>	67
Memory Info.....	68
12. Games.....	69
13. Tools.....	70
Calculator.....	70
Alarm Clock.....	71
<i>Edit an alarm</i>	71
<i>Alarm options</i>	72
Calendar.....	72
<i>Adding an appointment</i>	72
<i>Viewing an appointment</i>	72
<i>Calendar Options</i>	73
Tip Calc.....	73
World Clock.....	74
Voice Memo.....	74
<i>Recording a Voice Memo</i>	74
<i>Listen to a Voice Memo</i>	75

14. Settings	76
Sound Settings	76
<i>Ringers</i>	76
<i>Keypad Tone</i>	77
<i>Volume</i>	77
<i>Power On/Off Tone</i>	78
<i>Alerts</i>	78
Display Settings	78
Language	79
Bluetooth	79
<i>Bluetooth Manager</i>	80
<i>Bluetooth Device</i>	80
<i>Pairing with a new Bluetooth device</i>	80
GPS	81
System	81
<i>Call Setup</i>	81
<i>Saving Options</i>	82
<i>Memory Info</i>	82
<i>Phone Info</i>	82
<i>System Settings</i>	82
<i>TTY Mode</i>	83
<i>Security</i>	84

Airplane Mode ON/OFF	84
15. Glossary	86

1. For your safety

General Care

Your handset contains delicate electronic circuitry, magnets and battery systems. You should treat it with care and give particular attention to the following points:

- Do not allow the handset, battery or accessories to come into contact with liquids or moisture at any time. Do not immerse it in any liquid.
- Do not place the handset alongside computer disks, credit cards, travel cards or other magnetic media. The information contained on the disks or cards may be affected by the handset.
- Do not place anything inside the folded handset.
- Do not paint the handset.
- Do not leave the handset or battery in places where the temperature could exceed 140°F, e.g. on a car dashboard or a windowsill, behind glass in direct sunlight, etc.
- Do not remove the handset battery while the handset is switched on.
- Take care not to allow metal objects, such as coins or key rings to contact or short circuit the battery terminals.
- Do not dispose of batteries in fire. The handset's Li-ION batteries may be safely disposed of at a Li-ION recycling point.
- Do not put the handset's battery in your mouth, as battery electrolytes may be toxic if swallowed.
- Only use the battery with a charging system that has been qualified with the system per this standard. Use of an unqualified battery or charger may present a risk of fire, explosion, leakage, or other hazard.
- Do not disassemble or open, crush, bend or deform, puncture, or shred.

- Do not short circuit a battery or allow metallic or conductive objects to contact the battery terminals.
- Promptly dispose of used batteries in accordance with local regulations.
- Improper battery use may result in a fire, explosion, or other hazard.
- Do not put a battery into a microwave oven, dryer or high-pressure container.
- Do not contact battery directly into an electric outlet or cigarette lighter charger. Use only authorized chargers.
- Do not puncture the battery with a sharp object such as a needle.
- When the battery is disposed, be sure it is non-conducting by applying vinyl tape to the (+) and (-) terminals.
- Do not drop, throw, or subject the handset to rough treatment.
- Stop using the battery if abnormal heat, odor, discoloration, deformation, or abnormal condition is detected during use, charge or storage.
- Do not use with a damaged or deformed battery.
- Do not solder the battery directly.
- Remove the battery whose life cycle has expired from equipment immediately.
- The earpiece may become warm during normal use. Also, the handset itself may become warm while the battery is being charged.
- When a handset is in vibration mode, the vibration may cause the handset to move.
- Be careful not to place the handset near heat sources (such as a heater).
- Use a damp or anti-static cloth to clean the handset. Do not use an ordinary dry cloth or electrostatic cloth. Do not use chemical or abrasive cleaners as these could damage the casing.
- Third party equipment: The use of third party equipment, cables, or accessories, not made or authorized by ZTE, may invalidate the warranty of your phone and also adversely affect the phone's safety and operation.
- Remember to make backup copies of all important data on your handset.

- Remember to recycle: The cardboard packing supplied with this handset is ideal for recycling.

Warnings: In the unlikely event of a battery leak, take care to keep the battery discharge away from your eyes and skin. If the leakage does come into contact with the eyes or skin, flush thoroughly with clean water and consult with a doctor.

Aircraft Safety

- Switch off your phone or activate the airplane mode when inside or near an aircraft. Use of handsets in an aircraft may be dangerous to the operation of the aircraft and may disrupt the cellular network. Failure to observe this instruction may lead to suspension or denial of phone service to the offender, or legal action, or both.
- Airplane mode allows you to use many of your phone's features, such as games, calculator, voice memos, and many others when you are in an airplane or other area where wireless signals may cause interference. In the airplane mode, you are prohibited from making or receiving voice/data calls, however you may still attempt calls to your local emergency number.

Hospital Safety

- Switch off your phone and remove its battery in areas where handset use is prohibited.
- Follow the instructions given by any respective medical facility regarding the use of cellular handsets on their premises.

General Guidelines

- Many jurisdictions have laws and regulations about taking pictures in public or private areas regarding the processing and further use of such pictures. ZTE encourages its customers to obey all laws and to honor the personal rights of others.
- Check the roaming agreement availability with your network operator.
- The use of mobile phones is not allowed in some radiation sensitive areas, such as hospitals, research centers, and airplanes. The user is responsible to power-off the device. If there is any uncertainty, the battery should be removed.
- Observe any signs that indicate to power off your handset, such as those near gas stations, or explosives and power off the handset/device upon them.
- If you have a heart condition, be careful with the setting of call vibration or tone volume.
- Do not allow children to play with the handset, charger or batteries.
- The operation of some medical electronic devices, such as hearing aids and pacemakers, may be affected if a handset is used next to them. Observe any Caution signs and the manufacturer's recommendations.
- Take care not to put your phone in the back pocket of your pants and then sit on the phone. Also, do not put your phone at the bottom of a bag where it may be subject to excessive weight or pressure as this may damage the LCD and camera lens and cause them to malfunction.
- Your phone contains metal, which may cause you to develop an itch, rash or eczema depending on your physical condition.
- Do not leave the phone discharged or without a battery for a long period of time. Otherwise some data may be erased.

Road Safety

- You must exercise proper control of your vehicle at all times. Give your full attention to driving.
- Observe all of the recommendations contained in your local traffic safety documentation.
- Pull off the road and park before making or answering a call, if driving conditions require so. Check if local laws and/or regulations restrict the use of cellular phones while driving.
- You must not stop on the hard shoulder of a motorway to answer or make a call, except in emergency situations.
- Switch off your handset at a refuelling point, such as a gas station, even if you are not refuelling your own car.
- Do not store or carry flammable or explosive materials in the same compartment as the handset.
- Electronic systems in vehicle, such as anti-lock brakes, speed control and fuel injection systems are not normally affected by radio transmissions. The manufacturer of such equipment may advise if it is adequately shielded from radio transmissions. If you suspect vehicle problems caused by the radio transmitter in handset, consult your dealer and do not switch on the handset until your handset has been checked by a qualified technician.

Vehicles Equipped With an Air Bag

An airbag inflates with great force. Do not place objects, including either installed or portable wireless equipment, in the area over the airbag or in the airbag deployment area. If in-vehicle wireless equipment is improperly installed and the airbag inflates, serious injury could result.

Third Party Equipment

The use of third party equipment, cables or accessories, not made or authorized by ZTE, may invalidate the warranty of the handset and also adversely affect the handset's operation. For example, use only the ZTE charger supplied with the handset.

Efficient Use

For optimum performance with minimum power consumption, do not cover the antenna area (It's on the bottom of your phone) with your hand. Covering the antenna affects the call quality, may cause the handset to operate at higher power levels than needed, and may shorten talk and standby times.

Radio Frequency (RF) Energy

Your handset is a low-power radio transmitter and receiver. When it is turned on, it intermittently receives and transmits Radio Frequency (RF) energy in radio waves to

handle and control the power level at which the handset transmits. Exposure to radio frequency energy:

- Radio wave exposure and Specific Absorption Rate (SAR) information. The handset is designed to comply with safety requirements for exposure to radio waves. This requirement is based on scientific guidelines that include safety margins designed to assure the safety of all persons, regardless of age and health.
- The radio wave exposure guidelines employ a unit of measurement known as the Specific Absorption Rate, or SAR. Tests for SAR are conducted using a standardized method with the phone transmitting at its highest certified power level in all used frequency bands.
- While there may be differences between the SAR levels of various ZTE phone models, they are all designed to meet the relevant guidelines for exposure to radio waves.
- The SAR limit recommended is 1.6w/kg averaged over one(1) gram of tissue. The highest SAR value for this model phone tested for use at the head is 0.869w/kg(1g)
- The highest SAR value for this model phone tested for use at the body is 0.364w/kg(1g) SAR compliance for body-worn operations is restricted to belt-clips, holsters, or similar accessories that have no metallic component in the assembly and which provide at least 1.5cm separation between the device, including its antenna, and the users body.

Emergency Services

To make an emergency call in any country:

1. Ensure your handset is **ON** and in service.
2. Press the **End** key as many times as needed to clear the display and ready the device for calls.
3. Enter a local emergency number.
4. Press the **Send** key to dial the number. Follow instructions received and do **not** end the call until told to do so.

When the dial lock function is on, press the Right soft key and then enter a local emergency number. Press the **Send** key or **OK** key to dial the number.

Note: Tell the operator which service you require: Police, Ambulance, Fire Engine, Coastguard or Mountain Rescue Service. Give your position, and if possible, remain stationary and maintain contact. Due to the nature of the cellular system, the connection of emergency calls cannot be guaranteed. You should never rely on any wireless device for essential communication like medical emergencies.

FCC Notice

This mobile phone complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this

device must accept any interference received, including interference that may cause undesired operation.

This mobile phone has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Using Your Phone With a Hearing Aid Device

Your C79 device is compliant with the FCC Hearing Aid Compatibility (HAC) requirements.

When some wireless phones are used near some hearing devices (hearing aids and cochlear implants), users may detect a buzzing, humming, or whining noise. Some hearing devices are more immune than others to this interference noise, and phones also vary in the amount of interference they generate. The wireless telephone industry has developed ratings for some of their mobile phones, to assist hearing-device users in finding phones that may be compatible with their hearing devices. Not all phones have been rated. Phones that have been rated have a label on the box. Your C79 has been tested for hearing aid device compatibility and has an M[4] and/or T[4] rating.

These ratings are not guarantees. Results will vary, depending on the level of immunity of your hearing device and the degree of your hearing loss. If your hearing device happens to be vulnerable to interference, you may not be able to use a rated phone successfully.

Trying out the phone with your hearing device is the best way to evaluate it for your personal needs.

M-Ratings: Phones rated M3 or M4 meet FCC requirements and are likely to generate less interference with hearing devices than phones that are not labeled. M4 is the better/higher of the two ratings. T-Ratings: Phones rated T3 or T4 meet FCC requirements and are likely to be more usable with a hearing device's telecoil ("T Switch" or "Telephone Switch") than unrated phones. T4 is the better/higher of the two ratings. (Note that not all hearing devices contain telecoils.) The more immune your hearing aid device is, the less likely you are to experience interference noise from your wireless phone. Hearing aid devices should have ratings similar to those of phones. Ask your hearing health-care professional for the rating of your hearing aid.

Hearing devices may also be measured for immunity to this type of interference. Your hearing device manufacturer or hearing health professional may help you find results for your hearing device. The more immune your hearing aid is, the less likely you are to experience interference noise from wireless devices.

For additional information about the FCC's actions with regard to hearing aid compatible wireless devices and other steps the FCC has taken to ensure that individuals with disabilities have access to telecommunications services, please go to www.fcc.gov/cgb/dro.

Turning on the HAC Setting

When the HAC setting is on, your C79 sends the audio from your phone calls to the telecoil rather than to the microphone of your hearing aid. You are likely to hear calls much better because volume is increased and background noise and feedback are diminished. The HAC setting improves only the calls you listen to through the earpiece. Turn off the [Bluetooth] function. It does not affect calls heard on the speakerphone or with or a headset. HAC requires extra battery power, so watch your battery consumption when it's turned on.

CAUTION

Do not turn on the HAC setting unless you use a hearing aid with a telecoil. Using this setting without a hearing aid or with a hearing aid without a telecoil may be harmful to your hearing.

- 1 Make sure your phone is turned on.
- 2 Press Menu.
- 3 Select Settings -> system->HAC Mode
- 4 Check ON box.
- 5 Select OK.

Copyright Notice

The video/audio recordings you make/download are protected by copyright laws. They are for personal use only and must not be otherwise used without the permission of the copyright owner.

2. Introduction

Overview

Thank you for purchasing the ZTE C79 Mobile Phone. The C79 is capable of making voice calls and data connections to CDMA 1x networks. This phone provides many functions which are practical for daily use, including a camera, wireless internet browser etc. It can be connected to Bluetooth wireless devices and accessories. Simultaneously, it can also be connected to the PC as a USB flash disk.

To guarantee this mobile phone is always in its best condition, read this manual carefully and keep it for future reference. To ensure your safety, read the section *For Your Safety* thoroughly before using this handset for the first time.

What's included

Your ZTE C79 Mobile Phone package contains the following components. Check the box carefully to ensure all items are present.

- C79 Handset
- Battery
- User Manual and literature pack
- AC Travel Charger


We, ZTE Corporation,

Declared that the product is installed with battery separately in the box. The FCC ID label is placed on the mobile phone clearly visible to all persons at the time of purchase.


C79 Technical Specifications

Handset Type	C79
Dimensions (Lx W x H)	100 x 49 x 18mm (3.94 x 1.93 x 0.71in)
Weight	Less than 100 g (including battery)
Continuous Standby Time	180 hours.(subject to the net work)
Continuous Talk Time	220 minutes(subject to the network)

Phone at a glance



- [1] Camera Lens
- [2] Outer Display
- [3] Player Control Key
- [4] Volume Key



- [5] Camera Key
- [6] T Flash
- [7] USB Charger Port
- [8] Battery Cover

Key Definitions



Left Soft Key – Execute prompts that appear in the lower-left corner of the screen, directly above the button. These prompts change according to the screen content.



Right Soft Key – Execute prompts that appear in the lower-right corner of the screen, directly above the button. These prompts change according to the screen content.



Send Key – Make and answer calls. This button is also a short cut key to “All Calls” from the idle screen.



End Key – End calls and close applications. Holding this key for a while in the idle screen, it will power off the handset.




Camera Key – Holding this key for a while will launch the camera function when flip open.

Vol. up / Vol. down – Adjusts the volume of calls and music play.



Player Control Keys – Control the music player for fast forward, play/pause, and back forward.



Navigation Keys – These keys (up, down, left and right) allow for navigation through menu options and quick accessing to some function menus.



OK Key – Confirm actions and make selections. This key also executes prompts that appear on the lower-middle button on the screen, above the key. These prompts change according to screen content.



0-9 Number/Alphabetic Keys – These keys are used for entering numbers and letters to a text, dialing a speed call, and selecting options while navigating menus. Press 1 key in standby mode to launch Voice Mail for shortcut.



and * Keys – These keys have different functions, depending on the mode or function menu. Hold the * key for a while in standby mode to switch between standard mode and vibration mode of your phone.




Back Key – Deletes characters during text entry. This key returns to the previous page during menu navigation and web browsing.



Speaker Key – Activates and de-activates the speakerphone function during voice calls.























User Interface

User Interface is constituted by three parts. They are icon area, text & graphic area, and soft key indicator area.



Indicators and Icons

	Signal Strength Indicator		No Service Available
	Call in Progress		Battery Status Indicator
	New Voice Mail Indicator		New SMS Indicator
	New MMS Message Indicator		New MMS and SMS Indicator

 New Web Message Indicator	 New Voice Mail and Web Message Indicator
 1x Data Service Indicator	 Missed Call
 SMS Priority	 MMS Priority
 Ringer Is On	 Silent Indicator
 Vibration Mode	 Alarm Indicator
 Vibration and Ringer Mode	 Bluetooth Service Indicator
 Roaming Indicator	 Bluetooth Headset Indicator
 E911 GPS	 GPS Service Available Icon
 Data Communication in Progress	 Data Communication Dormant
 Calendar Indicator	 SSL (Web Security)
 TTY	 Airplane Mode Is Active


3. Set up Your Phone

This chapter outlines the steps required to set up your phone, power-on and activate on your service provider's network. Follow the procedure below step-by-step to get started.

Battery

Please switch off your phone and disconnect the charger with it before remove the battery. Avoid touching electronic components on the battery and battery compartment of the phone.

Installing the Battery




1. Insert battery to the plastic retainer clip. Make sure the + and – terminals on the battery be lined up with the metallic points in the battery compartment.
2. Push down on the bottom section of the battery until it clicks into place. It should be aligned with the bottom of the phone.

3. Place the battery cover so that it covers the entire battery. Slide the cover until it locks into position. Make sure the battery cover is secure.

Charging the Battery

Your phone is powered by a rechargeable battery. The battery is not fully charged when you purchase your phone, but there may be enough power in the battery to turn the phone on. Charge the battery with the procedure indicated below.

Note: For maximum battery performance, it is recommended that you completely charge the battery before using the phone for the first time. A new battery's full performance is achieved only after three complete charge and discharge cycles.




1. Pull the rubber USB cover out of the USB port and rotate it 90 degrees.
2. Insert the charger's USB adapter into the USB port. Ensure that the adapter is inserted with the correct orientation. Do not force the connector into the USB port.

Note: Make sure plug the AC charger into a standard AC outlet box when you begin charging the battery

Removing the Battery

If you need to remove your phone's battery, please follow the procedure indicated below:



1. Slide the back cover toward the bottom of the phone and lift off the back cover.
2. Insert your fingernail into the finger grip the slot on the bottom of the battery. Lift the bottom of the battery away from the handset.
3. Remove the battery from the battery compartment.

Memory Card

Your phone allows you to use a MicroSD memory card to expand the phone's available memory space. This digital card allows you to easily exchange images, music and voice data quickly between SD compatible devices.

Inserting the MicroSD Memory Card

1. Open the rubber MicroSD access door located on the top of the phone and rotate it 90 degrees.
2. Firmly insert the MicroSD card into the slot until it clicks into place.
3. Close the rubber memory card access door.

Removing the MicroSD Memory Card

1. Open the rubber MicroSD access door located on the top of the phone and rotate it 90 degrees.
2. Push the memory card downwards to release it from the slot.
3. Pull the memory card completely out of the MicroSD slot on the handset.
4. Close the rubber memory card access door.

<p>Note: Do not remove the memory card while reading or writing to the card. Doing so may cause data corruption on the card or phone. If possible, insert and remove the memory card while the phone is powered off.</p>

Powering On/Off your Phone

To power on the phone, press and hold the **End** key for a while. If the handset lock code has been activated, the phone will prompt to enter the code. The default password is 1234.

To power off the phone, press and hold the **End** key for a while from the idle screen.

Warning: Do not power the phone on when wireless phone use is prohibited, or when it may cause interference or danger.

Unlocking Your Phone

By setting the handset lock code, you can protect your phone against unauthorized use. To unlock the phone, enter the handset lock code and then press the **OK** key.

Connecting to the Network

After your phone is unlocked, it will automatically search for the network.

Activating Your Phone

Before placing a call with your new phone, you must activate the phone on the network. To activate the phone, dial provisioning number from the idle screen and follow the step-by-step instructions. Once the display indicates that programming is successful, the handset will restart automatically. You may then place a call with your handset.

4. Basic Operations

Making Voice Calls

Using the Keypad

1. Enter a phone number including the full area code by using the numeric keypad. If an incorrect character is entered, use the **Back** key to delete the digit. Pressing the **Back** key for a while will erase all digits before the cursor.
2. Press the **Send** key to make the voice call.
3. Press the **End** key to end the call, or to cancel the call attempt.

Note: To make an emergency call, enter the emergency number and press the **Send** key. If possible, remain stationary and keep the line connected.

Using the Contacts list

You can also make a call by choosing a record from your Contacts. To place a call from the contact list:

1. Choose the **Contacts** menu to display your contact list.
2. Scroll to the desired entry and press the **Send** key to make a call.

Using the last number dialed

Your phone can re-dial the last number that was called. To dial the last number:

1. Press the **Send** key from the standby mode.
2. Press the **Send** key again to dial the first entry.

Using a number from the Call History

Generally, all calls you have made or received are saved in a list on the phone. All numbers are grouped into Outgoing Calls, Incoming Calls, and Missed Calls. To dial a number from your call history:

1. Select **Menu**→**Calls** from the standby mode.
2. Navigate through the menu and press **OK** to select Outgoing, Incoming or Missed calls.
3. Select the phone number you want to dial from the list and press the **Send** key to place the call.

Using Speed Dials

Your phone is capable of storing 9 Speed Dial numbers that can be quickly dialed from the standby mode. Among the nine digit buttons, the 1 is assigned to Voice Mail function. To use the Speed Dialing feature:

1. Press and hold the number key for the Speed Dial entry you would like to call.
2. The call will be connected automatically.
3. Press the **End** key to end the call, or to cancel the call attempt.

Note: If you have not already assigned a Speed Dial to the selected key, the phone will prompt that no Speed Dial has been assigned. You may click **Yes** to add a Speed Dial immediately. For more information on creating Speed Dials, Refer to section 6 in this manual.

Answering Voice Calls

When you receive a call, the ring tone, illumination or vibration function will be activated, depending on your current settings. If the Caller ID function has been activated by the caller, the caller's phone number will be displayed. If the calling party uses the service hiding their phone number, your phone will show that the phone number has been withheld.

To answer the call, open the flip and press the **Send** or **OK** key. You can disconnect the call by pressing the **End** key or closing the phone's flip.

Note: You can also enable the phone to answer calls automatically when the flip is opened, or by pressing any key on the keypad. The default setting can be changed in **Menu**→**Settings**→**System**→**Call Setup**→**Call Answer**.

If your phone is connected to a compatible Bluetooth headset, you can answer or end the call by pressing the **Send/End key**.

In-Call Features

Volume

During a call, you can adjust the earpiece volume by pressing the volume key on the side of the phone.

Mute

You can mute your voice during the call by pressing **Mute**, located on the right soft key. Pressing **Unmute** will allow the caller to hear your voice again.

Speakerphone

Your phone has a speakerphone function that allows you to talk hands-free with the use of the phone's external speakers. To talk with speakerphone, press the **Speaker key** on the keypad after the call has been connected. Press the **Speaker key** again to return to the standard call mode.

Note: The 3-way calling and call waiting feature requires network support and may result in additional charges. Contact your service provider for more information.

Three-Way Call






Your phone has a three-way calling feature, which enables you to have conference calls with two parties.





Call Waiting

Your phone can accept phone calls while another call is active.

5. Entering Text


Key Functions




Key	Function	Description
	Left soft key	Execute prompts that appear in the lower-left corner of the screen, directly above the button
	Right soft key	Execute prompts that appear in the lower-right corner of the screen, directly above the button
	OK key	Confirm actions and makes selections. This key also executes prompts that appear on the lower-middle button on the screen, above the key.
	Navigation Key	Move the cursor up and down, left and right during text editing.
	* key	Switch between Lowercase Alphabetic mode and Uppercase Alphabetic mode.

	# key	Insert a space for pressing once.
	End key	Exit
	0-9 keys	Enter characters 0-9 and the alphabets from a-z. In text input mode, use key 1 to enter punctuations and symbols.
	Back key	Delete the previous character during text editing. Long pressing the Back key erases all text.

Text Input Modes

During text entry, you can press the display symbol button on the right soft key to select the input mode. The current mode is indicated on the right soft key menu among the following display symbols:

Display Symbol	Text Entry Mode
	Lowercase Alphabetic mode

	Uppercase Alphabetic mode
	Word predictive text mode
	Number mode

Alphabetic Mode

In Alphabetic mode, the alphanumeric keys from 2 to 9 are used to enter letters and numbers. You can enter the letters among the letters displayed on the keypad by pressing the keypad once and once again, and wait for a while until the underline of the entering letter disappears, the letter will be entered successfully. Take the 2 key for example: There are letters "abc" on the keypad.

So press the 2 key once to enter the letter "a", twice to enter the letter "b", three times to letter "c" and four times to enter number "2", then continue pressing to start a new loop of "a" to "2".

Word Mode

Word mode allows you to input messages or text quickly by using your keypad and the built-in predictive dictionary. To write a desired word, begin entering letters with the keys "a" to "z". After part of the word has been entered, a list will be displayed on the menu bar with the most commonly used words containing the letters you have input.

As you enter more letters, the words in the predictive dictionary will be modified to reflect your current text. At any time, you may scroll down the list with the **Navigation Keys** or **0**

key and select a desired word by pressing **OK key**. The complete word will be displayed in the editing window.

Number Mode

In Number mode, use alphanumeric keys from 0 to 9 to enter the number. You can only enter the number directly shown on the keypad. The letters can't be entered in this mode.

6. Contacts

Your phone has an address book capable of storing 500 contacts containing phone numbers, E-mail addresses, URLs and many other fields. To enter the contact list from the standby mode, select **Menu**→**Contacts**.



This menu allows you to save and manage contact address information. In Contacts you can add a new address, or search saved contact addresses by name. You can also add a personal ringtone to a contact card.

Note: To quickly access the Contacts menu, press the left soft key named **Contacts** from the standby mode.

Contact List










Select **Contact List** to view the listing of all contacts stored on your phone. You may scroll up or down the list using the **Up/Down** key, and press **OK** to view the desired contact information. Pressing **Options** will display the following pop-up menu:

1. **New Contact:** Add a new contact.
2. **Send Message:** Send a message or E-mail to the contact.
3. **Send Bus. Card:** Send the name, number and e-mail address of the record via Bluetooth to another Bluetooth compatible mobile phone.
4. **Delete:** Delete the selected record.
5. **Groups:** Display the groups interface.
6. **Set Speed Dial:** Assign the current number to one of the Speed Dial dialing keys. Speed dialing allows you to press and hold a number key in standby mode to call the stored phone number.
7. **Delete All:** Delete all records.
8. **Memory Info:** View the amount of Used, Available and Total records information.

You may also search for a contact from the **Contact List** screen. Type the name of the desired contact. Your input will be displayed at the bottom of the contact list. The phone will automatically scroll to the name that most closely matches your input.

New Contact

The **New Contact** menu allows you to add a new contact record. The following information can be stored for each contact:

-  **Name:** Contact name.
-  **Mobile1:** Mobile phone number.
-  **Home:** Home phone number.
-  **Office:** Office phone number.
-  **Mobile2:** Mobile phone number.
-  **Email:** Email address.
-  **Group:** Contact group (ie. Family, Business, VIP, etc.)
-  **Ringtone:** Ringtone to be played when receiving calls from the contact.
-  **Notes:** Other information about the contact.

Press the **OK** key to save the contact information. Press the **Back** key to exit from the **New Contact** interface.

<p>Note: You may enter any of the contact information above; however, the name and a phone number or an E-mail address must be entered in order to save the contact.</p>

Groups

The **Groups** menu allows you to add contacts to any of the five caller groups. The following are available from the Groups menu:

1. **Edit:** Rename the selected group
2. **Msg:** Switch to the contacts list for the desired group. You can mark recipients from the group to whom you can send an MMS or SMS message.
3. **Select:** Switch to the contacts list of the current group


Speed Dials

The **Speed Dials** menu allows you to view the current list of speed dials and add new entries. Use the **UP/DOWN** key to navigate to a desired speed dial number.

For speed dial numbers that are already assigned, click **View** to see the contact name and phone number. You may also select **Dial** to call the contact, or **Clear** to remove the contact from the voice dialing list.

To add a new speed dial, navigate an empty speed dial number and press **List**. The contact list will be displayed. Navigate to the desired contact and press **Select** to add the contact to the speed dial list.

7. Calls



Your phone has a call history feature that automatically stores information about incoming, outgoing and missed calls.

You may navigate through the Calls interface with the **UP/DOWN key** and press **OK key** to view the information below:

All Calls

List of all incoming, outgoing and missed calls

Missed Calls

Displays calls received but not answered

Incoming Calls

Displays calls received by the phone

Outgoing Calls

Displays calls made from the phone

Call Timers


The **Call Timers** feature allows you to view the approximate duration of your calls, as well as data transferred and data connection time.

You can reset the information such as Last Call, Recent Calls, Data Transferred and Connection Time by selecting the **Reset** on the right soft key.

Note: The call timers are not intended for billing purposes. The actual invoice for calls and service provider may vary depending on network features, rounding off for billing, rates and so forth.

8. Messaging

Your phone has the functionalities of sending and receiving text messages (SMS), multimedia messages (MMS) and voice mail messages. To enter the messaging interface from standby mode, select **Menu**→**Messaging**.



Send New

The **Send New** selection is used to create and send a message with the composer. To create a message, enter a phone number or E-mail address in the **To** field. You may directly enter the recipient's number using the keypad. After entering one number or address, you may press the **OK** key to enter additional addresses.

You may also add recipients from your contact list by pressing the **Options**→**Contact**. Use the **UP/DOWN** keys to highlight the desired contact, and press the **Mark** and then press **Select** to select the contact. You may scroll down to select multiple recipients. After

the desired numbers have been selected, press the **OK** to add the recipients to the message.

Note: You may send an SMS to a maximum of 10 recipients, and an MMS to a maximum of 30 recipients, inclusive of the **To**, **Cc** and **Bcc** fields. These fields can each contain a maximum of 10 recipients.

When you have finished entering all recipients, press the **DOWN** key to move the cursor to the lower window for creating your message text. For more information about text entry, refer to Section 5 – Entering Text.

Press the **OK key** to send the message. You can also save your message at any time by selecting **Options**→**Save To Drafts**.

Note: The maximum size of an MMS message is 350kB, and it may contain a combination of text, audio, and photo.

Your phone allows you to perform a variety of other functions within the messaging window. Select **Options** to access the following features:

Insert

Your phone also allows you to add pictures and audio files to your message. From the messaging composition screen, select **Insert** to display the following options:

1. **MyImages:** Add an image from the folder lists.
2. **MyTunes:** Add an audio clip from the folder lists.
3. **New Image:** Start the camera to take a photo and insert it into the message.

4. **New Tune:** Start the sound recorder to create a new audio file, and insert it into the message.

Slide

Enter the slide interface

1. **Add Slide:** Switch to the slide interface.
2. **Delete Slide:** Delete the current slide.
3. **Previous Slide:** View the previous slide.
4. **Next Slide:** View the next slide, when more than one slide has been added.
5. **Slide Timing:** Set the duration (in seconds) for each slide.

Preview

Preview the message.

Erase Item

Erase the selected image and audio item from the message.

Cc/Bcc/Sub

View and enter the cc/bcc recipients and subject text. After inputting the desired information, press the **Done** to save.

Save To Drafts

Save the message to the Drafts folder.

Quick Text

Quick Text messages are used to enter common responses to questions from a pre-defined dictionary. Select Quick Text, locate a desired phrase and click **OK** to add the text to the current message. For more information about Quick Text, refer to Settings - Quick Text settings.

Signature

Input your pre-defined signature. See Settings – Signature for information on how to create a customized signature.

Message Priority

Set the priority for the message. If you set High priority to the message, it will be an exclamation mark displayed on the message icon when the message listed in the message box.

Inbox

The Inbox folder contains all of your received text and multimedia messages. From this folder you can review your received messages, reply or forward messages to another recipient. To access the inbox from standby mode, select **Menu**→**Messaging**→**Inbox**.

Reading a message

1. Use the **UP/DOWN** keys to select the desired message.

2. Press the **View**.
3. If the message is an SMS message, it will be displayed on the screen immediately.
4. If the message is an MMS message, an MMS notification will be displayed. Press the **Get** to download the message.
5. The message will download and you will be returned to the Inbox.
6. Highlight the downloaded message and press **View**. The message will be displayed on the screen.
7. You may press the **Reply** to respond to the original recipient.

Replying to a message

1. Highlight the desired message and press the **Reply** or **View→Reply**.
2. Compose your reply message. For more information about creating messages, refer to Send New.

Outbox

The Outbox folder contains all messages that are waiting to be sent, or were unsuccessfully sent during the last attempt. From this folder you can edit or re-send your message.

To edit a message before sending, press **Edit**. This will display the composer interface where you can edit your message. Select **Send** from this screen to send the message. You can also send a message directly from the Outbox by pressing the **Send**.

Drafts

The Drafts folder contains drafts and unfinished text and multimedia messages. From this folder you can complete and re-send your messages. Select the **Edit** to open the message, and press **Send** in the composer to send the message.

You may delete a highlighted message by pressing the **Delete** located on the right soft key.

Sent

The Sent folder contains messages that have been successfully sent by your phone.

Press **Edit** to open the composer interface to edit or re-send your message. You may also select **Delete** to delete selected message from the Sent box.

Saved

The Saved folder contains saved text and multimedia messages. From this folder you can edit and resend your messages. The messages that are saved in this folder will not be deleted automatically.

You can view a saved message by highlighting the desired message and selecting **View**.

You can also reply to messages by pressing **Reply**.

Voice Mail

When the Voice Mail function is available, all unanswered calls to your phone can be transferred to your voice mailbox, even if your phone is not being used or powered off.

You should set up your voice mailbox and personal greeting as soon as your phone is activated. For more information, contact your service provider.

To check your voice mailbox, select **Call** from the Voice Mail interface. The phone will automatically place a voice call to the Voice Mail center. You may clear the new Voice Mail indicator by pressing **Reset**.

Shortcut: To quickly access your voice mailbox from standby mode, press and hold the 1 key. Your phone will automatically place a voice call to the Voice Mail center.

Web Alerts

Your phone is capable of receiving Web Alerts from online providers. For more details, contact your service provider. To access your Web Alerts:

1. From standby mode, select **Menu**→**Messaging**→**Web Alerts**.
2. Follow the on-screen instructions.

Settings

This menu allows you to customize the options to fit your preferences. From the standby mode, select **Menu**→**Messaging**→**Settings** to access the settings menu.

Message Settings

1. **SaveTo Sent Box:** Set whether messages are saved to the Sent folder.

2. **Auto Delete Inbox:** If new message comes, it will automatically delete the oldest message when the inbox is full.
3. **Default Entry Mode:** Set the default entry mode.
4. **Auto Download:** Set the preference for downloading MMS messages.
5. **Delivery Report:** On and Off the delivery report.
6. **Read Report:** On and Off the read report.
7. **Picture Talk Alert:** On and off the picture talk alert.
8. **Callback:** Set the callback number that is sent along with SMS and MMS messages.
9. **Signature:** Allow you to input and save your message signature. The saved signature is appended to all outgoing messages.

Quick Text Settings

The Quick Text Settings is a list of phrases that are commonly used in short messaging. To view or edit the phrase, press the **Edit**. For more information on adding Quick Text to your message, refer to Send New.

Memory Info

The Memory Info menu displays the amount of memory available for text and multimedia messages. Press the **OK** key to exit from the menu.

9. Brew

Your phone has a shopping menu that allows you to purchase music, ringtones, images, games and a variety of applications.

Navigate the navigation keys to get into the menu you desired. Follow the on-screen instructions to download and manage the desired files. The Help menu gives more information about the mobile shop of buying applications.

10. Web Wireless

The browser feature on your phone allows you to view internet content. You can view specially designed versions of popular websites which include sports, weather, news, stock quotes and many others. As well, you can download ringtones, wallpaper, and games from your service provider.

Launching and Navigating the Browser

When you choose Web Wireless menu, you will be connected to the service provider's homepage automatically. You may press **Options** to access the browser submenu. The following selections are available:

Home: Go to the homepage

Forward: Go back and reload the web page.

Go To URL: Switch to the URL screen where web addresses can be input

Bookmarks: All previously accessed addresses can be saved as bookmarks on your phone.

History: Browse previously viewed web addresses

Screenshot: Allows you to manage your screenshots

View URL: Show the detail information of current URL and send the link as a message.

Search web: Search via the search engine defined by your service provider.

Advanced: View the advanced menu for the Browser

1. **Home:** Clear the cache memory and reload the browser


2. **Multimedia:** Allows setting preferences for display pictures and background music
3. **Clear Memory:** Allows clearing of the stored cookies, cache, etc
4. **Scroll Mode:** Settings for the scroll mode and scroll speed of web pages
5. **Send Referrer:** Enable or disable adding "referrer" field into HTTP request head
6. **Connection Timeout:** Set the duration of the connection timeout
7. **Key press Timeout:** Set the duration of the key press timeout
8. **Security:** Set the security options

Exit: Exit Web Wireless and return to standby screen.

About: Show the version of Web explore.

11. Music & Media

Your phone has the capability of playing multimedia content such as music, image and video. You can also record voice memo, capture images and view the videos on your phone. This functionality is all accessible through the Music & Media menu. To access Music & Media, select **Menu**→**Music & Media** from standby mode.



Music Player

Music player makes you can enjoy the music stored in your handset. Please create play lists of the music and tunes of your own before you enjoy.

Create a play list

Make sure there are songs, tunes and other music in the **My Tunes** folder.

1. Access the music player via the path **Menu**→**Music & Media**→**Music Player**.
2. Press **Option** to select the **PlayList** to get into PlayList interface.

3. Use **Option** and choose **Create** to get into music center, use **Mark** to choose the music you desired and press **Save**.
4. Enter the name of the play list. (The default name is PlayListX.)
5. Press **Confirm** the play list will be existed in the **PlayList** interface. Use the **ListPlay** to view the music items in the list, and **EditList** to edit the exit list.

Manage a play list

In PlayList interface you can manage the play list by the following operations:

1. Highlight a play list.
2. Use the **ListPlay** to view the music information in the list, and **EditList** to edit the exit list.
3. If you want to delete or rename the play list, please use **Option Delete** or **Option Rename**.

Control the music player

When you use the music player to enjoy music, the **Navigation Keys** (Up/Down, Left/Right keys), **Ok Key** and **back Key** are used to control the play, and you can change the play mode by pressing **Cycle** on the left soft key.

When close the keypad, the player can control the playing by **Control Player Keys** to play, pause, fast forward, fast backward, etc.

In music player interface, pressing **Option** and choose **Setting** to get into player setting interface. You can turn on/off the **Repeat** and **Shuffle** play mode here, and then press **Confirm** to save the setting.

Camera





The Camera function allows you to take pictures with your phone. To access your camera, select **Menu**→**Music & Media**→**Camera** from standby mode.

Shortcut: You can quickly access the Camera application by long pressing the **Camera** key on the left side of the phone in standby mode.

Take pictures

To take a photo, press the **Capture** to shoot an image as your desired. You also can press the **Camera** key on the left side of the phone to take a photo.

You can use the **Right** and **Left** navigation keys to view your image settings while shooting. Use the **Up** and **Down** navigation keys to adjust the level for each of the following settings:

-  **Brightness:** Adjust the brightness level of the image.
-  **Contrast:** Adjust the contrast of the image.
-  **Zoom:** Adjust the zoom level.
-  **Effect:** Change the effect of the image.

For more shooting options, select the **Options** to do the following operations:

1. **Self Timer:** Set the self timer to be Off, 5s, 10s, or 15s.
2. **Image Size:** Choose among image sizes of 1280×960, 1024×768, 640×480, etc.
3. **Image Quality:** Select Super Fine, Fine or Standard image quality.
4. **White Balance:** Choose Auto, Sunny, Cloudy, Incandescent, and Fluorescent white balances.
5. **Shutter Sound:** Select your desired shutter sound.

Viewing your photos

You can view your previously taken images and the download videos by selecting the **MyImages** located on the right soft key. For more information, see the MyImages sections.

My Tunes

The Tunes selection allows you to manage the tunes in the folder. To access your Tunes from standby mode, select **Menu**→**Music & Media**→**My Tunes**.

Playing your tunes

In the My Tune interface when you highlight a tune, press **Play** to get into music player interface to play the highlighted tune.

- Use **OK key** to start and pause the playing.
- Use **Back key** to stop the playing.

- Use **Right key** to play fast forward.
- Use **Left key** to play fast backward.
- Use **Up** and **Down key** to rewind.

Managing your Tunes

In the My Tune interface when you highlight a tune, you can send the tune via Message or Bluetooth, copy it, move it, etc.

After highlight a tune, press **Mark** to mark the tune and **Play** to play the tune by the music player. When press **Options**, you can do the followings:

1. **Send:** Send the tune via Message or Bluetooth.
2. **Set As:** Set the tune as the ringers of the phone.
3. **Copy to MicoSD/Phone:** Copy the tune to the MicoSD or Phone.
4. **Move to MicoSD/Phone:** Move the tune to the MicoSD or Phone.
5. **Rename:** Rename the tune.
6. **Delete:** Delete the tune.
7. **Mark All:** Mark all the tunes in the folder.
8. **File Info:** View the file property of the tune.
9. **Switch to MicoSD/Phone:** Switch the management between MicoSD card and phone.

My Images

Your phone is able to manage the images in the folder. To access the Images menu from standby mode, select **Menu**→**Music & Media**→**Images**.

View your image

When you highlight a file, press **View** to view it. In viewing interface you can view it with full screen by press **Full Scr** and send it via MMS or set it as the wallpaper by pressing **Options Send** or **Options Set As Wallpaper**.

Managing your Images

In the My Tune interface when you highlight an image, you can send the image via Message or Bluetooth, copy it, move it, etc.

After highlight an image, press **Mark** to mark the image and **View** to view the image.

When press **Options**, you can do the followings:

1. **Send:** Send the image via Message or Bluetooth.
2. **Set As Wallpaper:** Set the image as the wallpaper.
3. **Copy to MicoSD/Phone:** Copy the image to the MicoSD or Phone.
4. **Move to MicoSD/Phone:** Move the image to the MicoSD or Phone.
5. **Rename:** Rename the image.
6. **Delete:** Delete the image.
7. **Mark All:** Mark all the images in the folder.

8. **File Info:** View the file property of the image.
9. **Switch to MicoSD/Phone:** Switch the management between MicoSD card and phone.

Preload Files

The preload files folder is a convenient way to organize all the preload tunes, images of your handset. To access the preload files folder from standby mode, select **Menu→Music & Media→Preload Files**. In this folder you will be able to access the folders Tunes, Images.

Tunes

After you highlight a tune, you can play it by pressing **Play** and set the tunes as Caller ID Ringtone, Unknown Calls Ringtone, etc via **Set As**.

Images


When you highlight an image, you can view it by pressing **View** and set the image as the wallpaper via **Set As**.

Memory Info

The Memory Info selection allows you to view the details about the space used and available memory. To view the memory information from standby mode, select **Menu**→**Music & Media**→**Memory Info**.

12. Games


Your phone is capable of playing a variety of games that are available through your service provider. You can download games and store them on your phone for future use. To access the Games folder from standby mode, select **Menu**→**Games**.



Please follow the instructions on the screen to play the game.

13. Tools

The Tools menu provides helpful software applications to assist with daily tasks, such as a calculator, alarm clock, voice memo, world clock etc. To access the Tools folder, select **Menu**→**Tools** from standby mode.



Calculator

Your mobile phone comes with a built-in calculator capable of performing addition, subtraction, multiplication and division. To access the calculator from standby mode, select **Menu**→**Tools**→**Calculator**.

1. Enter a number with the keypad.
2. If necessary, press the right soft key to insert a decimal point.
3. Use the navigation keys to select a mathematical function.
 - a. **Up key:** add
 - b. **Down key:** subtract








- c. **Left key:** multiply
- d. **Right key:** divide
- 4. Enter the next number with the keypad.
- 5. Press **Equal** to view the result.

Alarm Clock

The alarm function allows you to set up multiple separate alarms. To access the alarm clock function, select **Menu**→**Tools**→**Alarm Clock** from standby mode.

Edit an alarm

To edit an alarm, highlight the desired alarm, select **Options**→**Set Alarm** to edit or create a new alarm by pressing **New**. You may set the alarm options described below:

-  **Type:** Set the alarm type.
-  **Date:** Select the date. This feature is only available for Once alarm type.
-  **Time:** Enter the time for the alarm format.
-  **Ring:** Set the alarm sound as on or off.
-  **Ringtone:** Select the Ringtone that will be played when the alarm sounds. This feature is hidden if the Ringtone is set to off.
-  **Status:** Enable or disable the alarm.
-  **Remark:** Enter a comment about the alarm.

You can save the alarm by pressing the **Save** key.

Alarm options

To access the alarm settings, press **Options**. The following options are available:

1. **Set Alarm:** Edit the highlighted alarm entry.
2. **Set Rest Days:** Set the days that the alarm is enabled.
3. **Delete All:** Delete all the alarms set.

If there are alarms existed, select **View** can view the alarm info. Press **Delete**, if you want to cancel. And press **Edit**, if you want to edit the viewing alarm.

Calendar

The Calendar allows you to conveniently access and modify your agenda. Simply store your appointment with a reminder and your phone will alert you on the time and date selected. You can access the Calendar by selecting **Menu**→**Tools**→**Calendar**.

Adding an appointment

To add an appointment to the Calendar, press **Add** on the right soft key. You may select to add a Meeting, Memo or Anniversary from the list.

Viewing an appointment

When you open your Calendar, it will automatically navigate to the current date. You may navigate the navigation keys to view appointments on a different date. To view the details of an appointment, highlight the desired appointment and press the **View**. This will display

various parameters such as the time, date, subject and location. You can manage the appointments in the view interface by **Edit**, and **Delete**.

Calendar Options

To access the Calendar settings, press the **Options** located on the left soft key. The following options are available:

1. **Go To Date:** Input a date and press **OK** to jump to the specified date.
2. **Delete Entries:** Delete the In This Day, Before Date, and All Entries appointments.
3. **Settings:** Set the alarm tone and default calendar view (Month or Day view).
4. **Memory Info:** Displays the number of used, available and total calendar entries.

Tip Calc

The tip calculator function allows you to quickly and easily calculate the tip amount based on the tip rate and bill. You can access the Tip Calculator from standby mode by selecting **Menu**→**Tools**→**Tip Calc**. To calculate a tip:

1. Enter the Bill amount. Press **Decimal** to enter a decimal point.
2. Enter the Tip percentage.
3. Press **OK**.
4. The Tip and Total will be displayed.

You may press **Reset** to clear the bill and tip amount.

World Clock

The world clock displays the time in twenty-four different time zones around the world, together with one or more cities, states, regions or countries in each time zone. To access the World Clock, select **Menu**→**Tools**→**World Clock** from standby mode. Press the left and right navigation keys to display different time zones.

You may press the **DST** to enable or disable daylight savings time. The **Cities** sets the default time zone for the phone.

Voice Memo

You can use your phone to record brief memos to remind yourself of important events, phone numbers or other information. To access the voice memo from standby mode, select **Menu**→**Tools**→**Voice Memo**.

Recording a Voice Memo

You may press the **Record** to record a memo. Once the recording has started, press the **Stop** to end the memo. After the recording is complete, you may press the **Discard** to delete, or **Save** to store the memo for future reference.

Press the **Options** to display the following features:


1. **Send**: Send the voice memo via MMS message.
2. **Play**: Play the voice memo.

Listen to a Voice Memo

To listen to a previously recorded voice memo, press **My Tunes** on the right soft key. A listing of audio clips will be displayed. Navigate to the desired entry and press **Play** to listen to the clip. For more information about managing a voice album, please reference to Section 11 Music & Media-> My Tunes.

14. Settings

The settings menu allows you to customize your phone's display, sound, and various other settings based on your preferences. In the standby mode, select **Menu**→**Settings** to access the settings menu.



Various phone settings are available within the **Settings** menu. Highlight the desired selection and press **OK key** to view or change the current settings.

Sound Settings

The sound setting menu allows you to change the sound properties of your phone.

Ringers

Many different ringers are available to help you identify incoming calls and messages. You can assign ringtones to individual contact entries and types of calls or messages.

1. **Voice Calls:**

Caller ID: Edit the ringtone for calls with caller ID tags.

Unknown Calls: Set the ringtone from blocked or restricted phone numbers.

2. **Messages:**

Voice Mail: Select the Voice Mail indicator sound.

Messaging: Set the tone for new text and multimedia messages.

Web Alerts: Choose the indicator for new web alerts.

Reminder: Set the reminder time for new messages.

Press **Default** to set the ringtones as initial ringer. Press **Edit** to edit the ringtone for types of ringtones. To save the settings of ringer, you can press **OK key**.

Keypad Tone

The keypad tone menu allows you set the volume of the keypad tone.

Volume

The Volume menu sets the mode and volume options for the ringer and earpiece.

1. **Silent Mode:** Enable or disable silent mode.
2. **Master Volume:** Change the master volume level among Off, Vibrate only, four steps of Volume Level, etc.
3. **Earpiece:** Set the volume level among three steps of volume level for the earpiece of the wired headset accessory.

Power On/Off Tone

The Power On/Off setting allows you to enable or disable the music played during power on/off of the handset.

Alerts

The alerts menu allows you to change the sound settings for various alerts on your phone. To access the alerts menu, select **Menu**→**Settings**→**Sound Settings**→**Alerts** from standby mode. The following settings are available:

1. **Minute Beep:** Enable or disable the beep played before the calling time is about to achieve one minute or multi-minutes.
2. **Call Connect:** Enable or disable the alert when a call is connected successfully.
3. **Call Lost:** Enable or disable the alert when a call is lost.
4. **Low Battery:** Enable or disable the low battery alert when the battery low.

Display Settings

The display settings allow you to customize your mobile phone's display screen. To access the display settings from the standby mode, select **Menu**→**Settings**→**Display Settings**. The following settings can be changed via the display settings menu:

1. **Banner:** Edit the banner name displayed on the standby mode.
2. **Wallpaper:** Select the background image from Images for the standby mode.

3. **Backlight:** Set the screen and keypad backlight to be Always Off, 3 Seconds, 10 Seconds or 20 Seconds.
4. **Clock Format:** Change the format of the clock between Digital and Large Digital.
5. **Menu Style:** Choose between Icon and List menu style.
6. **Dialing Font:** Change the size of dialing font between Normal and Large.

Language

Your phone can display text in English or Spanish. To change the language settings, select **Menu**→**Settings**→**Language** from the standby mode. Changing the language settings changes all menus and message settings. Use the **Up** and **Down** keys to select between English and Spanish. Press **OK** to select the highlighted language.

Bluetooth

Your phone is capable of connecting to a variety of Bluetooth wireless accessories. It makes you implement data transfer between Bluetooth devices, talk with a Bluetooth wireless earphone, remote control the handset, etc. You may create and store 20 pairings within the phone and connect to one device at a time. The approximate range for Bluetooth wireless technology is up to 30 feet (10 meters).

The Bluetooth menu allows you to search for Bluetooth wireless devices, and manage devices that have already been paired with your phone. To access the Bluetooth menu from standby mode, select **Menu**→**Settings**→**Bluetooth**.

Bluetooth Manager

Manage the Bluetooth settings below:

1. **Power:** Enable or disable the Bluetooth support.
2. **Discovery Mode:** Disable or enable discovery mode for 60 seconds. Turn discovery mode on for 60 seconds to allow other devices to find your handset.
3. **Device Name:** Set the Bluetooth device name for your phone. This name will appear on other Bluetooth devices when your phone is located.
4. **Address:** Identifies the address for your handset.
5. **Device Type:** Shows your Bluetooth device type.
6. **Support Profiles:** Allows you to view a listing of the Bluetooth profiles supported by the handset.

Bluetooth Device

This menu allows you to manage the Bluetooth devices that have been, or currently are paired to your handset.

Pairing with a new Bluetooth device

1. Access in the **Bluetooth Device** interface.
2. Press **Search** to find a new compatible device.

3. If Bluetooth power is set to off, you will be prompted to turn the power on. Select **OK** to enable Bluetooth.
4. The device will appear in the Bluetooth Devices menu once it has been located. Highlight the desired device and press **OK**.
5. The phone will prompt you for the pass key. Consult the Bluetooth accessory instruction manual for the correct pass key. Enter the pass key and press the **OK** key.
6. Once connected, you will see the device listed in the paired Devices menu, and the Bluetooth icon will appear on the status bar.

GPS

Your phone's GPS features enable service providers to locate your position in emergencies, or for other services to request your position. You may choose the **GPS Status** between Location On and E911 Only, and then set the **GPS Privacy** if necessary.

System

The System menu provides system settings.

Call Setup

The call setup menu allows you to change the answering features on your phone. To access the call setup menu from standby mode, select **Menu**→**Settings**→**System**→**Call Setup**. The following settings are available:

1. **Call Answer:** Set the way of answering a call.

2. **Auto Answer:** Set the auto-answer settings. This feature is intended for use when your phone is connected to an optional hands-free headset.
3. **Auto Redial:** Enable or disable the auto-redial feature. This feature automatically redials a call after an unsuccessful call.

Saving Options

You can choose files in the phone to save to SD card or Phone.

Memory Info

The Memory Info menu allows you to view information about the phone's and SD card's memory.

Phone Info

You can view the phone information such as the phone number, phone software version, etc.

System Settings

1. **Set Mode:** Select the mode of network.
2. **Set NAM:** Your phone has the capability of storing 2 different phone numbers. Use this setting to select the current Number Assignment Module (NAM). Contact your service provider for more information about the NAM.

Note: Additional fees may apply when roaming on another network.

TTY Mode

Your handset is a TTY compatible device. Simply connect the TTY equipment to the USB jack with the ZTE TTY-to-USB connector. To access the phone's TTY settings, select **Menu**→**Settings**→**System**→**TTY mode**. Use the Up and Down keys to choose between the following settings:

TTY Full: Users who cannot talk or hear may use this setting to send and receive text messages through TTY equipment.

TTY+Talk: Users who can talk, but cannot hear, may use this setting to speak through the phone and receive responses via text message.

TTY+Hear: Users who can hear, but cannot speak, may use this setting to listen to conversation of the other party, and respond via text message.

TTY Off: Users who can hear and speak may use this setting to disable TTY support.

Connecting to TTY Equipment

1. Connect the cable from the TTY device into the ZTE TTY-to-USB connector.
2. Plug the USB connector into the jack on the right side of the phone.
3. Enter the TTY Mode menu and select the desired TTY Mode (shown above).
4. After setting the TTY mode, check the LCD screen on the phone for the TTY icon.
5. Connect the TTY equipment to the power source and turn it on.
6. Make a phone connection to the desired number.
7. When a connection is made, use the TTY equipment to send a text message, or speak (for TTY+Talk mode).

8. The voice or text message from the other party will be heard or displayed on the TTY equipment, depending on the TTY mode selected.

Security

The security menu allows you to lock your phone electronically. To access the Security menu, select **Menu**→**Settings**→**Security** from the standby mode.

Note: You will need to enter the phone lock code to enter this menu. The default code is 0000.

The following options are available:

Lock Mode: Choose between Unlock, Lock and On Power Up. In Lock mode, the phone is only able to receive calls or make emergency calls. The On Power-Up setting will automatically lock your phone when it is powered on.

Change Code: This menu allows you to change the phone's lock pass code. To change your code:

1. Select **Menu**→**Settings**→**Security**→**Change Code** from the standby mode.
2. When prompted, enter your old lock code.
3. Input the new code (1 to 8 characters).
4. Input the new code again to confirm.

Reset Defaults: This selection restores the default security settings.

Airplane Mode ON/OFF

Airplane Mode allows you to use some features of your phone, such as games, calculator, voice memos, and many others when you are in an airplane or other area where RF signals

may cause interference. In airplane mode, you are prohibited from making or receiving voice/data calls, however you may still make calls to your local emergency number.

To enable Airplane Mode, select **Menu**→**Settings** from standby mode. Highlight **Airplane Mode: On/off** and press **Select**.

15. Glossary

Abbreviation	Description
AC	Alternating Current
CDMA	Code Division Multiple Access
DST	Daylight Saving Time
DTMF	Dual-Tone Multi-Frequency
HFP	Hands-Free Profile
HSP	Headset Profile
GPS	Global Positioning System
MMS	Multimedia Messaging Service
NAM	Number Assignment Module
OPP	Object Push Profile
RF	Radio Frequency
SD	Secure Digital
SID	System Identifier
SMS	Short Messaging Service
SW	Software
TTY	Teletype
URL	Uniform Resource Locator
USB	Universal Serial Bus
VIP	Very Important Person

