

## Turning the Headset On and Off

### Turning On the Headset

Press and hold the **MFB** for 2 seconds until you hear a short “beep” tone. The **LED** will flash green.

**IMPORTANT** Press the **MFB** again each time you turn on the headset to re-activate pairing so that the connection between the headset and the mobile handset is resumed. For pairing, please refer to “Pairing Your Headset” on page 6-7.

### Turning Off the Headset

Press and hold the **MFB** for 3 seconds until you hear a long “beep” tone. The **LED** flash stops.

## Adjusting the Volume

Press the **Volume Key** repeatedly until you reach the desired volume level.

## Resetting the Headset

You may want to reset the headset to its default settings. This also clears all current pairings.

1. Ensure the headset is OFF.
2. Press the **Volume Key** for 20 seconds.
3. The **LED** will alternately flash green and red rapidly.
4. Release the **Volume Key**.
5. Press and hold the **Volume Key** again for 2 seconds until you hear two “beep” tones.
6. Recharge the headset for a few seconds.
7. The headset is turned off and returns to the default setting. All current pairings are cleared.

## Troubleshooting

If you are unable to connect your headset and mobile handset, please try the following:

- Ensure your headset is turned on and is properly charged.
- Ensure the headset is paired with your mobile handset.
- Ensure your mobile handset's Bluetooth feature is activated. Please refer to your mobile handset user guide for specific instruction.
- Ensure the headset is within a maximum of 10 meters of your mobile handset(s) and there are no obstructions, such as walls or other electronic devices in between.
- Ensure your headset has not reached its 8 mobile handsets limit. If the headset has reached its pairing limit, please reset it to its original settings and recharge for a few seconds.
- If the above steps do not resolve your problem, please recharge the headset and remove your mobile handset battery pack for a while.

## Charging Your Headset

Connect the charger to an AC wall outlet and the charger plug to the headset's charging socket (fig 2). The **LED** will be red while charging.

**IMPORTANT** Charging indication will be delayed for a few minutes if the headset has not been used for a long time or the battery is drained.

### Nominal Charging Time

Charging the battery fully is normally within 3 hours. When the battery is fully charged, the **LED** will turn green. Disconnect the charger from AC wall outlet and the headset. Press and hold the **MFB** (fig 1) for 2 seconds to turn the headset on, please refer to "Turning the Headset On and Off" in the next page.

### Talk & Standby Time

The fully charged battery offers up to 4 hours talk time and up to 120 hours standby time. When no calls are in progress, the headset remains turned on in standby mode.

### Low Battery

When the headset is on and the battery becomes low, the **LED** flashes red and the headset emits a beep every 1 minute. Please recharge the battery as described above.