

# 2.0MP Smart HD PT Camera iB-HDP203SAM



User Manual


Please read the user manual carefully before using it.

iOS	Search "Guard_PTCAM" in App Store and install or scan the QR code.	
Android	Search "Guard PTCAM V2" in Play Store and install or scan the QR Code.	
		IOS Android

Step 1-: Connect power to the camera.

Step 2-: Wait for the Voice prompt "Access point established", to connect your mobile to Camera Wi-Fi (SSID named "MVxxxxx")

Step 2-: Follow the below instructions on iBall PTCAM app:





2) Open camera App



 Click on "+" and select "Add networked device"



1) Connect your

phone to camera

SSID

4) Input device ID or scan the QR code, click on "Add to the list"



5) Click on Set \* and go to Network Settings



6) Select Station mode (Router connection mode), Select required Wi-Fi, Enter router Wi-Fi password 7) Wait for the voice prompt "Wi-Fi Connected" to access the camera over Internet.

#### FAQs

- 1. If Wi-Fi SSID contains special symbols, then camera might fail to connect to Wi-Fi.
- 2. Camera prompt is stuck on "Connecting"
- (a) Check if your Wi-Fi is 2.4 GHz. Camera doesn't support 5 GHz.
- (b) Reset the camera and reconfigure it
- (c) DHCP should be ON
- 3. To reset the password of the camera, press the reset button for 5 seconds.

#### Video Playback



Search the record files



Select playback from time playback



Video playback interface



Device Setting

## 1) Network Settings:

- AP Mode: The Camera works as an independent Access Point (Hotspot).
- Station Mode: The camera is connected to the router.



Network Settings

## 2) Recording Settings:

- Auto Record: Continuous video recording (Note: Old videos will be overwritten, if memory card is FULL)
- Alarm video: Start video recording on motion detection
- Video & Audio: Audio will be recorded with video
- Video resolution: Set video recording quality (HD/SD)



**Recording Settings** 

### 3) Date & Time setting: Set date and time of the camera



Date & Time Settings

## 4) Alarm setting: Alarm ON/Alarm OFF: Switch various alarm

settings ON/OFF
Alarm Area: Set motion detection area
Alarm Sound: Buzzer on motion detection
Voice Prompt Language: Camera voice
prompt language
Save: Save the settings



Alarm Settings









 Warranty: All Ball products are governed by Ball Warranty Terms. Refer www.Ball.co.in - Product specifications are subject to change without knoice - All trademarks, loops, brands and product names are properties of their respective owners - Actual product/accessories may differ from the image shown - For any technical help on Ball products, phase contact apport/gibBall.co.in - This product falls under e-waste (Management & Handling) Rules, 2011. For proper disposal method, visit our weeksite (www.Ball.co.in e-waste).

www.iBall.co.in

1 year warranty

Ver.: 1.0.1