

SRH840A

User's Guide

The Shure professional studio headphones, SRH840A, user guide.

Version: 3.2 (2022-A)

Table of Contents

		Furnished Accessories	5
SRH840A User's Guide	3	Replacement Parts	5
Professional Reference Headphones	3	SAFETY PRECAUTIONS	5
General Description	3	CAUTION	5
Care and Maintenance	3	WARNING	6
		WARNING	6
Cable Lock	3		
		LIMITED WARRANTY	6
Storage	3	Service Centers	7
Accessories	5	Certifications	7

SRH840A User's Guide

Professional Reference Headphones

General Description

Building on 90 years of pro audio experience, the SRH840A Headphones from Shure deliver world-class audio performance, comfort, and durability to professional audio engineers and musicians. Reference-quality frequency response and 40 mm neodymium dynamic drivers combine with total comfort and durability to provide the ultimate listening experience. The replaceable cable and ear cushions ensure a long-lasting lifetime of use.


- · 40mm neodymium driver optimized for studio recording and critical listening
- · Closed-back, circumaural design for superior isolation in noisy environments
- · Adjustable, collapsible headband provides comfort and portability
- Replacement earcup pads included to ensure long product life
- 3 m (10 ft.) detachable cable provides plenty of length and easy storage and replacement
- · Carrying Bag protects headphones when on the go or not in use


Care and Maintenance


To clean the headphones, use a soft, damp cloth.

CAUTION: Do not use cleansers that contain solvents. Keep liquid and foreign objects out of the driver openings.

Cable Lock








Storage







Transducer Type
Dynamic, Neodymium magnet

Driver Size 40 mm

Frequency Response 5 to 25,000 Hz

Sensitivity @ 1 kHz

96 dB/mW

Impedance @ 1 kHz 38 Ω

Maximum Input Power 400 mW


Weight 273 g (9.63 oz.)

Connector

Gold-plated 3.5 mm (1/8") stereo mini jack plug with 6.35 mm (1/4") threaded adapter

Cable

3 m, (9.8 ft) straight, detachable, non-PVC, Oxygen-free copper (OFC)



Accessories

Furnished Accessories

Carrying Pouch for Professional Headphones	HPACP1
Replacement 3.5mm Bayonet Headphone Audio Cable	SRH-CABLE

Replacement Parts

Replacement Ear Cushions for SRH840A	SRH840A-PADS
Universal 3.5mm Bayonet Headphone Communication Cable	RMCH1-UNI
Replacement Coil Cable Assembly for SRH Headphones	SRH-CABLE-COILED

SAFETY PRECAUTIONS

The possible results of incorrect use are marked by one of the two symbols—"WARNING" and "CAUTION"—depending on the imminence of the danger and the severity of the damage.



WARNING: Ignoring these warnings may cause severe injury or death as a result of incorrect operation.



CAUTION: Ignoring these cautions may cause moderate injury or property damage as a result of incorrect operation.

CAUTION

- · Never disassemble or modify the device, as failures may result.
- Do not subject to extreme force and do not pull on the cable or failures may result.
- Keep the product dry and avoid exposure to extreme temperatures and humidity.

WARNING

- If water or other foreign objects enter the inside of the device, fire or electric shock may result.
- · Do not attempt to modify this product. Doing so could result in personal injury and/or product failure.

This device is able to produce sound volume higher than 85 dB SPL. Please check your maximum allowed continuous noise exposure level based on your national employment protection requirements.

WARNING

LISTENING TO AUDIO AT EXCESSIVE VOLUMES CAN CAUSE PERMANENT HEARING DAMAGE. USE AS LOW A VOL-UME AS POSSIBLE. Over exposure to excessive sound levels can damage your ears resulting in permanent noise-induced hearing loss (NIHL). Please use the following guidelines established by the Occupational Safety Health Administration (OSHA) on maximum time exposure to sound pressure levels before hearing damage occurs.

90 dB SPL	95 dB SPL	100 dB SPL	105 dB SPL
at 8 hours	at 4 hours	at 2 hours	at 1 hour
110 dB SPL	115 dB SPL	120 dB SPL	
at ½ hour	at 15 minutes	Avoid or damage may occur	

LIMITED WARRANTY

Shure Incorporated ("Shure") hereby warrants to the original consumer purchaser only that, except as otherwise specified below, this product will be free in normal use of any defects in materials and workmanship for a period of two (2) years from the consumer's original date of purchase directly from Shure or from a Shure-authorized reseller.

Any rechargeable batteries contained in or packaged with this product are so warranted for a period of one (1) year from the consumer's original date of purchase. However, rechargeable batteries are consumable and their capacity will be reduced over time based on temperature, amount of time in storage, charging cycles, and other factors; hence reduction in battery capacity does not constitute a defect in material or workmanship.

At its sole option, Shure will repair or replace the defective product and promptly return it to you. In order for this warranty to be valid, the consumer must, at the time the product is returned, provide proof of purchase in the form of the original purchase receipt directly from Shure or from a Shure-authorized reseller. If Shure elects to replace the defective product, then Shure reserves the right to replace the defective product with another product of the same model or a model of at least comparable quality and features in Shure's sole determination.

If you believe this product is defective within the warranty period, carefully repack the unit, insure it and return it with proof of purchase, postage prepaid, to Shure Incorporated, Attention: Service Department, at the address below.

Outside of the United States, return the product to your dealer or Authorized Service Center. Addresses are listed on www.Shure.com or can be obtained by contacting Shure at the address listed below.

This warranty is not transferable. This warranty does not apply in cases of abuse or misuse of the product, use contrary to Shure's instruction, ordinary wear and tear, an act of God, negligent use, purchase from a party other than Shure or a Shureauthorized reseller, unauthorized repair, or modification of the product.

ALL IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE ARE HEREBY DISCLAIMED TO THE EXTENT PERMITTED UNDER APPLICABLE LAWS AND, TO THE EXTENT NOT PERMITTED, ARE HEREBY LIMITED TO THE DURATION AND TERMS OF THIS WARRANTY. SHURE ALSO HEREBY DISCLAIMS ALL LIABILITY FOR INCIDENTAL, SPECIAL, OR CONSEQUENTIAL DAMAGES.

Some states do not allow limitations on how long an implied warranty lasts, or the exclusion or limitation of incidental or consequential damages, so the above limitation may not apply to you. This warranty gives you specific legal rights, and you may have other rights which vary from state to state.

This warranty does not restrict the rights of the consumer mandated under applicable laws.

THIS WARRANTY SUPERSEDES ALL OTHER WARRANTIES THAT ARE ASSOCIATED OR INCLUDED WITH THIS PROD-UCT, EXCEPT THAT ANY SOFTWARE CONTAINED IN OR PACKAGED WITH THIS PRODUCT IS EXCLUDED FROM THIS WARRANTY AND INSTEAD SHALL BE COVERED BY THE WARRANTY, IF ANY, PROVIDED IN SHURE'S END USER LI-CENSE AGREEMENT ACCOMPANYING SUCH SOFTWARE.

Service Centers

United States, Canada, Latin America, Caribbean

Shure Incorporated Attn: Service Department 945 Chaddick Dr. Wheeling, IL 60090-6449 U.S.A.

Europe, Middle East, and Africa

Shure Europe GmbH Attn: Service Jakob-Dieffenbacher-Str. 12, 75031 Eppingen, Germany

IndonesiaService Center Resmi:

Jakarta Hotline (021) 612 6388 Medan (061) 6612550 Surabaya (031) 5032219 Jogjakarta (0274) 371710 Denpasar (0361) 766788 Makasar (0411) 324652

Certifications

This product meets the Essential Requirements of all relevant European directives and is eligible for CE marking.

The CE Declaration of Conformity can be obtained from: www.shure.com/europe/compliance

Authorized European representative:

Shure Europe GmbH Global Compliance Jakob-Dieffenbacher-Str. 12 75031 Eppingen, Germany Phone: +49-7262-92 49 0

Email: info@shure.de www.shure.com